CHALLENGES OF SCANNING HALL MICROSCOPY USING BATCH FABRICATED PROBES

KODAI HATAKEYAMA

Graduation committee

Prof. dr. P.M.G. Apers	University of Twente (chairman and secretary)
Prof. dr. ir. L. Abelmann	University of Twente (promotor)
Prof. dr. ir. G.J.M. Krijnen	University of Twente (promotor)
Dr. ir. E. Sarajlic	SmartTip B.V. (referee)
Dr. ir. N.R. Tas	University of Twente
Prof. dr. ir. J.W.M. Hilgenkamp	University of Twente
Prof. dr. O. Paul	IMTEK, Germany
Prof. dr. ir. T.H. Oosterkamp	Leiden University, the Netherlands

Paranymphs

Maarten Groen
Rolf Vermeer

UNIVERSITY OF TWENTE.

This research is supported by the Dutch Technology Foundation STW, which is part of the Netherlands Organisation for Scientific Research (NWO).

Cover design by Kodai Hatakeyama

Printed by Gildeprint Drukkerijen, Enschede, the Netherlands.
© Kodai Hatakeyama, Enschede, the Netherlands, 2016.
Electronic mail address: k.hatakeyama@alumnus.utwente.nl
ISBN 978-90-365-4163-3
DOI [10.3990/1.9789036541633](https://doi.org/10.3990/1.9789036541633)

CHALLENGES OF SCANNING HALL
MICROSCOPY USING BATCH FABRICATED
PROBES

DISSERTATION

to obtain
the degree of doctor at the University of Twente,
on the authority of the rector magnificus,
prof. dr. H. Brinksma,
on account of the decision of the graduation committee,
to be publicly defended
on Friday, 2 September 2016 at 14:45

by

Kodai Hatakeyama

born on 28 March 1987
in Akita, Japan

This dissertation is approved by

Prof. dr. ir. L. Abelmann University of Twente (promotor)

Prof. dr. ir. G.J.M. Krijnen University of Twente (promotor)

Contents

Contents	i
1 Introduction	1
2 Topographic cross-talk	7
2.1 Introduction	7
2.2 Theory	9
2.3 Experimental	10
2.3.1 Fabrication	10
2.3.2 Measurement setup	11
2.4 Results and discussion	15
2.4.1 Topographic cross-talk in SHPM	15
2.4.2 Offset voltages due to cross asymmetries	15
2.4.3 Offset variations by temperature changes	17
2.4.4 Offset variations by probe-sample distance changes	19
2.4.5 Offset variations during contact AFM	20
2.5 Discussion	21
2.6 Conclusion	22
3 Compensation of temperature dependent offset	23
3.1 Introduction	23
3.2 Theory	25
3.2.1 Temperature dependent offset in Hall probe	25
3.2.2 Compensation of temperature dependent offset	25
3.2.3 Mixing rule for the temperature coefficient	28
3.3 Experimental	28
3.3.1 Fabrication	28
3.3.2 Measurement setup	28
3.4 Results and discussion	30
3.4.1 Temperature dependent offset	30
3.4.2 Compensation of temperature dependent offset	31
3.5 Conclusion	34
4 Batch fabricated scanning Hall probes	37

4.1	Introduction	37
4.2	Theory	38
4.3	Experimental	39
4.3.1	Fabrication of the Scanning Hall probe	39
4.3.2	Measurement setup	39
4.4	Results and Discussion	43
4.4.1	Scanning Hall imaging on a smooth surface	43
4.4.2	Topographic cross-talk	47
4.4.3	Compensation of topographic cross-talk	47
4.5	Conclusion	49
5	Discussion	53
5.1	Target applications	53
5.2	Probe optimization	54
5.2.1	Compensation of topographic cross-talk	54
5.2.2	Signal to noise ratio	54
6	Conclusion	57
6.1	Mechanical fragility	57
6.2	Magnetic sensitivity	57
6.3	Topographic cross-talk	58
	Appendices	59
A	Signal to noise ratio	61
	Bibliography	64
	Abstract	68
	Samenvatting	70
	Japanese Abstract	72
	Acknowledgments	74
	Publications	76
	Biography	78

Chapter 1

Introduction

Hall effect sensors (Osberger et al., 2016; Popović, 1991; Sander et al., 2016; Wouters et al., 2016) are used extensively for quantitative magnetic field analysis. To create magnetic field distribution images, Hall probes with an effective cross width of $50\text{ }\mu\text{m}$ have been mounted on a xy -positioning system driven by an electrical motor. By scanning in a raster fashion over the surface an image can be constructed. This is called scanning Hall probe microscopy (SHPM) (Honda et al., 2010).

The spatial resolution of SHPM has been improved down to the micro-meter scale, by means of Hall crosses fabricated by ion beam lithography on a millimeter sized microscope cover glass (Lustig et al., 1979) (figure 1.1). The probe was brought close to sample surface such that the cross-sample distance was in the order of micrometers. Scanning was performed by piezo-transducers.

To improve resolution even further, sub- μm Hall crosses have been fabricated by electron beam lithography on the corner of millimeter sized chips (Chang et al., 1992) (Figure 1.2). The cross-sample distance was controlled below $1\text{ }\mu\text{m}$ by a scanning tunneling microscopy (STM) tip located at the edge of the chip. With this type of probe, a large number of investigations have been reported by the research group of A. Oral (Mohammed and Bending, 2014; Oral et al., 1996; Sandhu et al., 2001, 2002a, 2004b, 2002b). The Hall crosses reported used mainly bismuth as sensitive layer, but also semiconductors such as two dimensional electron gas (2DEG) systems and indium antimonide have been used, because of their higher signal to noise ratio.

The disadvantage of STM distance control is that the choice of the samples is limited to electrically conductive materials. To expand the application of SHPM to insulating samples, Hall probes were mounted on quartz crystal resonators (Akram et al., 2008, 2009; Dede et al., 2008), analogue to atomic force microscopy (AFM) (Figure 1.3). Alternatively, the Hall cross was directly fabricated on the cantilever of an AFM probe (Bending, 2010; Brook et al., 2003) (Figure 1.4).

The cross dimensions were scaled further down to 50 nm by focused ion

FIGURE 1.1 – $2\mu\text{m} \times 2\mu\text{m}$ Hall cross fabricated by ion beam lithography from a InSb layer deposited on a microscope cover glass (Lustig *et al.*, 1979).

FIGURE 1.2 – Hall crosses on chips with STM feedback. These Hall crosses are made of GaAs/AlGaAs with a) 350 nm width, fabricated by electron beam lithography (Chang *et al.*, 1992) and b) 380 nm width, defined by optical lithography (Oral *et al.*, 1996) or made of Bi with c) 200 nm width defined by focused ion beam (Sandhu *et al.*, 2004b) and d) 100 nm width defined by electron beam lithography (Mohammed and Bending, 2014).

FIGURE 1.3 – Hall probes with STM feedback are mounted on quartz crystal oscillators to utilize AFM feedback for electrically insulated samples. These Hall crosses are made by a) Bi with 100 nm crosses defined by electron beam lithography (Dede *et al.*, 2008) and b) AlGaIn/GaN with 1 μm crosses defined by reactive ion etching (Akram *et al.*, 2008).

FIGURE 1.4 – GaAs/AlGaAs Hall cross with 1.5 μm width defined by optical lithography, located close to an AFM tip a) (Brook *et al.*, 2003), b) (Bending, 2010).

FIGURE 1.5 – Bi Hall cross with 50 nm width defined by focused ion beam a) (Sandhu et al., 2004a), b) (Petit et al., 2004).

FIGURE 1.6 – Bi Hall cross with 100 nm width defined on AFM tip by electron beam (Zhou et al., 1999).

beam lithography (Petit et al., 2004; Sandhu et al., 2004a) (Figure 1.5). A further decrease in the cross size did not lead to better spatial resolution. In the case of AFM or STM distance control, the minimum distance between the Hall cross and the sample is limited to the height of the AFM or STM tip. To increase resolution beyond this limitation, one needs to situate the Hall cross on the apex of a tip. The tip should preferably be an AFM tip rather than electrically driven STM tip, since STM signal can cause cross-talk in Hall signal, in the case Hall cross served both as a Hall sensor and a STM height sensor.

Hall crosses integrated on the tip apex were fabricated with a cross width of 100 nm by means of electron beam lithography (Zhou et al., 1999). However, this fabrication method is a rather expensive, elaborate technique, unsuitable for high-volume manufacturing and therefore not practical for day-to-day applications.

Next to fabrication issues, the choice for the Hall cross materials in these three-dimensional structures is limited to metal layers, as the fabrication of semiconductors in 3D is technologically too challenging. Therefore, if one at-

tempts SHPM with nanometer resolution, the Hall cross will probably have to be made from gold or bismuth.

The main issue with electron beam lithography on the tip apex is that it is extremely difficult to transfer it to a batch fabrication process. A very promising alternative, without losing resolution, is to apply corner lithography (Berenschot et al., 2008). This is a three-dimensional fabrication technique that allows sub-100 nm features using $2\text{ }\mu\text{m}$ optical lithography. The first prototype of such a probe is shown in figure 1.7 (Sarajlic et al., 2010). The Hall cross is realized at the end of the free standing silicon nitride wireframe pyramid, which is located at the end of the AFM type cantilever. The wireframe pyramid consists of wires with 300 nm width, which are coated with gold as the Hall sensing layer. The Hall cross is electrically addressable through the four leads on the cantilever.

To be able to utilize the wireframe probes in high resolution scanning Hall microscopy, we see three challenges: mechanical fragility, magnetic sensitivity and topographic cross-talk. These challenges are addressed in this thesis. At first glance, the wireframe seems very fragile compare to a bulk tip used in commercial probes. Is it robust enough to perform contact-mode AFM? We use a gold layer for simplicity. However the Hall coefficient is a factor of 1000 lower than commercially used materials. Is gold on the wireframe sensitive enough to measure any magnetic fields? To achieve a high spatial resolution, it is necessary to operate the probe in contact-mode scan. This however brings the wires on the probe close to a sample surface. Does that induce artifacts, such as topographic cross-talk?

This thesis is organized as follows. In chapter 2, imaging experiments with 300 nm Hall probes showed very strong topography cross-talk. It is shown by four different experiments that this cross-talk is due to thermal effects. In chapter 3 an electronic detection technique is presented that suppresses these thermal effects. The method is tested on millimeter sized crosses, and shown to suppress the thermal sensitivity of the probe by a factor of 30. In chapter 4, a successful imaging experiment is shown with a novel type of probe that has a $2\text{ }\mu\text{m}$ Hall cross. The resolution is not yet competitive to high resolution MFM. These initial result however give confidence that with a reduction in cross-size, and by replacing the sensitive layer to one with a higher Hall coefficient than gold, batch fabricated Hall probes for scanning probe microscopy can be made by corner lithography. In chapter 5, I position the work in this thesis in the context of a commercial application of scanning Hall probes fabricated by corner lithography. Conclusions and suggestions for further work are given in chapter 6.

FIGURE 1.7 – *Scanning Hall probe made by corner lithography*

Chapter 2

Topographic cross-talk in scanning Hall microscopy caused by probes with asymmetric crosses

Abstract

In this chapter, I discuss nanometer sized Hall crosses on cantilever probes, fabricated by means of corner lithography. Scanning attempts on a permanent magnet show a strong topographic cross-talk. As this cross-talk was three orders of magnitude larger than the expected Hall signal, magnetic imaging over such a rough surface was impossible. We investigated the origin of the cross-talk by four different methods. These measurements clearly show that the asymmetry in the Hall cross, caused by fabrication imperfections, leads to an extra series resistance between the voltage sensing leads, resulting in an offset voltage on top of the output signal. Since this additional resistance is temperature dependent, the offset voltage varies with probe temperature. As the probe is heated by Joule heating, its temperature varies with probe-sample distance. This distance is slightly modulated due to topography of the sample while scanning, resulting in the observed strong topographic cross-talk.

This work is a team effort by Edin Sarajlic, Martin Siekman and myself. My contribution is the theoretical model, the experiments and their analysis. The scanning Hall probes were fabricated by Edin Sarajlic. Martin Siekman assisted in construction of the measurement setup.

2.1 Introduction

Scanning probe imaging techniques have established themselves as an indispensable tool in research and development. In the after-wake of the STM and AFM inventions, many different techniques have been developed. The logical extension of these developments are probes that have electrical sensors at the tip apex, such as scanning SQUID ([Hilgenkamp et al., 2003](#)), thermal ([Dai et al.,](#)

FIGURE 2.1 – A network model for electrical resistances of the fabricated probe. The network consists of the resistances of four leads and the extra resistance R_a due to the ridge located at the apex of the pyramidal cavity.

2009) and Hall microscopy (Oral et al., 1996). Next to complex fabrication processes, these probes, which are electrically interrogated to obtain the sensor signals, suffer from the fact that the wiring over the cantilever heats up while relative high currents are passed to obtain the highest possible signal-to-noise ratios. In this study, we demonstrate that this heating effect may lead to topographic cross-talk. The demonstration is performed on scanning Hall probes, but the results are applicable to a large class of probes with electrically interrogated sensors. In essence the topographic cross-talk originates from the combination of the heating of the probe, its subsequent height-dependent heat loss to the substrate and the temperature dependence of the electrical resistivity of the probe electrodes. This combination causes a height dependent offset-voltage leading to topographic cross-talk in the probe signal.

The corner lithography enabled batch fabrication of sub- μm Hall probes, however the cross has a slight asymmetry (Figure 2.1), caused by imperfections in the mask, and its alignment relative to the crystallographic axes, which determines the template for the AFM pyramid. The asymmetry can be reduced by employing e-beam generated masks, but can never be entirely removed.

Due to this asymmetry, the resistance network of the Hall cross has an additional apex resistance R_a , next to the lead resistances R_{1-4} . This apex resistance causes an offset in the Hall voltage. If this offset were constant, it could simply be compensated by subtraction. However, the offset varies with the temperature of the Hall cross, which in turn varies with probe-sample distance. This distance varies due to the topography of the sample during contact scanning. This effect is so severe that it prohibits magnetic imaging. In this paper, we proof by four different measurements that the topographic cross-talk is temperature induced. This result is not only of importance to scanning Hall microscopy, but to all imaging techniques that employ advanced probes with electrical read-out.

2.2 Theory

Hall probes exploit the effect that moving charges in a magnetic field experience a Lorentz force perpendicular to their velocity, and perpendicular to the field. The force translates into a potential difference (Hall voltage) over the width of an electrode carrying a current, which can be picked up in a so called Hall cross geometry. In the case of corner lithography, the cross might have an additional intersection at the tip apex (Figure 2.1). Still we can obtain a Hall voltage if we apply the current for instance from lead 3 to 1, and measure the voltage between lead 2 and 4. Note that if we apply the current from lead 2 to 3, or 1 to 4, no Hall voltage can be measured. In practical Hall measurement, we drive the Hall cross by an alternating current to employ lock-in technique.

Due to the apex resistance R_a caused by cross asymmetry, the total voltage measured is a sum of the Hall voltage and the offset voltage

$$V_{\text{tot}} = \left(\frac{R_H}{d} B + R_a \right) I_0 \cos \omega t \quad (2.1)$$

where R_H is the Hall coefficient [m^3/C], d the thickness of the Hall cross [m], B the perpendicular magnetic field [T], I_0 amplitude of the driving current [A], ω the angular frequency [rad/s] and t the time [s].

It should be noted that the Hall voltage term in equation (2.1) is a crude approximation. In the case of a combination of uniform fields and non-uniform current distribution, the Hall sensitivity can be modified by means of geometric correction factors (Paul and Cornils, 2009) to accurately describe the sensitivity, as the Hall cross is fabricated on the pyramidal structure rather than on a planar surface. However, in the case of micro-magnetic structures, this method can not hold as magnetic fields have a large gradient in both perpendicular and parallel direction to sample surfaces. We neglected the factor, which is why equation (2.1) is considered a crude approximation.

R_a is determined by the length of the cross asymmetry and temperature dependent, according to

$$R_a = \rho_a \frac{L}{wd} = R_0 (1 + \alpha \Delta T) \quad (2.2)$$

where ρ_a is the resistivity [Ωm], L and w are the length and the width of the ridge respectively [m], R_0 is the apex resistance at an ambient temperature [Ω], α is the temperature coefficient of resistance [K^{-1}] and ΔT is the temperature change of the Hall cross [K].

It should be noted that this lumped resistance model is for the resistive offset voltage, not for the Hall signal.

The temperature is determined by a balance between Joule self-heating due to current passing through the probe and the heat loss to the ambient. Since the leads are thermally coupled with the cross, effective heating is not only caused by R_a but also the resistances of the current carrying leads R_l . By defining the ratio between the two resistances $b = R_l/R_a$, ΔT is given by

$$\Delta T = cP = c(1+b)R_a I_0^2 \cos^2 \omega t \quad (2.3)$$

where c is the heat resistance [K/W] and P is the electrical power dissipated on the Hall probe [W]. By combining equation (2.3) and equation (2.2), R_a can be rewritten as

$$R_a = \frac{R_0}{1 - \alpha c(1+b)R_0 I_0^2 \cos^2 \omega t} \quad (2.4)$$

Due to the quadratic relationship between current and temperature, the total voltage V_{tot} has higher order components in the drive frequency ω . Since the 2ω component is zero, we only consider the first and third harmonics:

$$V_{\text{tot}} = U_1 \cos \omega t + U_3 \cos 3\omega t \quad (2.5)$$

The components can be obtained from mathematical manipulation of equation (2.1), equation (2.4) and equation (2.5), leading to

$$\begin{aligned} U_1 &= \left(\frac{R_H}{d} B + \frac{4R_0}{4-3A} \right) I_0 \\ U_3 &= \frac{R_0 A}{(4-3A)(4-2A)} I_0 \\ A &= \alpha c(1+b)R_0 I_0^2 \end{aligned}$$

As expected, when the temperature coefficient α , heat resistance c and/or drive current I_0 is very small, A becomes negligible, the higher harmonic U_3 disappears and the expression for V_{tot} (2.5) simplifies to equation (2.1).

2.3 Experimental

2.3.1 Fabrication

The probe is realized in a wafer-scale fabrication process using only standard surface and bulk micromachining and conventional contact lithography. The basic fabrication steps are shown in figure 2.2. The fabrication process starts on a (100)-oriented standard silicon wafer. In the selected wafer a pyramidal cavity is formed by wet anisotropic etching of silicon in KOH (Step a). The pyramidal pit serves as mold for a probe tip. In order to achieve a sharper tip the mold is thermally oxidized at low temperature (Akamine and Quate, 1992). After the oxidation, a silicon-rich nitride layer is deposited by LPCVD (Step b). Platinum nanowires are formed in the concave corners of the pyramidal mold by corner lithography (Step c). After the nanowire formation, gold microelectrodes and contact pads are formed by a lift-off process (Step d). Subsequently, the cantilever outline is defined by patterning of the silicon nitride layer by RIE (Step

e). In the next fabrication step, which is not illustrated in figure 2.2, the patterned silicon wafer is anodically bonded to a pre-diced glass substrate. After the anodic bonding the silicon wafer is partially dissolved in a hot TMAH solution (Step f). The patterned silicon nitride layer serves as a mask guiding the etching process in such a way that silicon is almost completely removed from the backside leaving only a small part underneath the contact pads. The preserved silicon serves as a mechanical reinforcement. SEM micrographs of a successfully fabricated scanning thermal probe are shown in figure 2.3. The entire probe has a dimension of $3400\text{ }\mu\text{m}$ by $1600\text{ }\mu\text{m}$. The cantilever is $150\text{ }\mu\text{m}$ long, $36\text{ }\mu\text{m}$ wide and $0.5\text{ }\mu\text{m}$ thick. Platinum nanowires integrated at the inner edges of the pyramidal tip are 300 nm wide and 100 nm thick. The microelectrodes and contact pads are made of 100 nm thick gold layer. The nanometer-sized cross-junction formed by platinum nanowires is addressable through the gold microelectrodes.

2.3.2 Measurement setup

The probes were glued on a dedicated printed circuit board (PCB) and wires were drawn between electrodes on the PCB and contact pads on the probe base by a manual wirebonder.

To measure the resistance R_a , we performed 4-terminal sensing by applying a DC current from lead 1 to 3 and measured a voltage between leads 4 and 2 (Figure 2.3).

To measure the offset voltage as a function of temperature, we applied a 377 Hz AC current with a peak amplitude of $100\text{ }\mu\text{A}$ to the probe and amplified the detected voltage by a differential pre-amplifier (THS4130CD, Texas Instruments Incorporated). This amplified signal was detected by a lock-in amplifier (eLockIn204/2, Anfattec Instruments AG) using the drive current as the reference signal (Figure 2.4).

The Hall sensitivity of the probe used in the experiment was determined using the same lock-in technique, while applying a magnetic field perpendicular to the plane of the cantilever by means of a water cooled electromagnet. Figure 2.5 shows the calibration curve, from which we estimate a magnetic field sensitivity of $1.32(4)\text{ m}\Omega\text{ T}^{-1}$. The offset voltage for this particular probe was $1.73(3)\text{ }\mu\text{V}$. The fluctuations of the curve are most likely due to thermal drift.

To demonstrate the scanning Hall microscopy, we prepared magnetic domain structures on a NdFeB permanent magnet (S-08-01-N, supermagnete.de) by means of a thermal demagnetization. Subsequently, the surface of the magnet was polished. Before the demagnetization, the stray field above the surface was $0.292(2)\text{ T}$ confirmed by a Gaussmeter (Model 455 DSP Gaussmeter, Lake Shore Cryotronics, Inc.). The scanning setup (Figure 2.6) consists of a piezo scanner (P-527 Multi-Axis Piezo Scanner, Physik Instrumente (PI) GmbH & Co.) on which a sample can be placed, and a piezo step motor (ANSz100, attocube systems AG) with the PCB holder for a coarse probe height adjustment. The PCB is angled around 10° with respect to the scanner plane.

FIGURE 2.2 – A wafer-scale fabrication process based on standard micromachining and conventional optical lithography: (a) etching of a pyramidal pit followed by oxidation sharpening, (b) silicon nitride deposition, (c) formation of nanowires by corner lithography, (d) sputtering of electrodes, (e) etching of the probe layout and (f) anodic bonding (not shown) and probe release.

FIGURE 2.3 – SEM micrographs of top side view of the fabricated scanning Hall probe. Four conductive leads run over the cantilever from contact pads on the probe base to the nanowire Hall cross. The cross integrated at the concave corners of the pyramidal cavity has a ridge. This ridge is caused by the fact that the mask is not exactly square. The tip for contact scanning is facing downwards.

FIGURE 2.4 – Schematic of the measurement setup. The resistance network represents the nanowire Hall cross structure (Figure 2.3). A current source is applied to two leads, and the Hall voltage is detected on the other set of leads by means of lock-in technique.

FIGURE 2.5 – The Hall voltage as a function of applied magnetic flux density with an applied current of $100\mu\text{A}$ at 377 Hz . The offset of approximately $1.7\mu\text{V}$ is due to R_a (Figure 2.1). The sensitivity of this particular probe was $1.32\text{ m}\Omega\text{ T}^{-1}$.

FIGURE 2.6 – The picture of the scanning setup. The probe is glued on the dedicated PCB, then mounted on the piezo step motor for a course probe height adjustment. The sample can be placed on the piezo scanner located below the probe.

2.4 Results and discussion

2.4.1 Topographic cross-talk in SHPM

To illustrate the issue of topographic cross-talk in SHPM, we imaged a demagnetized NdFeB permanent magnet. Figure 2.7 shows the topography and magnetic domain structure of the magnet measured by simultaneous tapping mode AFM and MFM in DI3100 (Veeco Instruments Inc). The AFM image shows that the surface has height differences of approximately $1\text{ }\mu\text{m}$ and the MFM shows the well known maze domain structures of demagnetized permanent magnets (Neu et al., 2004), with a smallest feature size of approximately $1\text{ }\mu\text{m} \times 1\text{ }\mu\text{m}$. These domains should be large enough, both in size and field magnitude, to be imaged by our nanowire Hall cross, which is approximately $500\text{ nm} \times 500\text{ nm}$.

We attempted SHPM on the exact same sample in contact-mode, with an applied current of $300\text{ }\mu\text{A}$ at 3.77 kHz . The measurement (Figure 2.8) resembles the topography image of figure 2.7, rather than the magnetic domain structures measured by MFM. Since the signal is in the order of $350\text{ }\mu\text{V}$, which is considerably larger than the expected Hall voltage, we conclude that the magnetic information is hidden in topographic cross-talk.

2.4.2 Offset voltages due to cross asymmetries

Since we expected that the topographic cross-talk is due to variations in offset voltage, caused by the probe asymmetry, we characterized the offset resistance R_a , by taking voltage-current curves for various probes using a 4-point technique. Figure 2.9 shows the results for five probes with different asymmetry. For

FIGURE 2.7 – AFM (top) and MFM (bottom) images of a demagnetized NdFeB permanent magnet. The magnetic features are bigger than $1\mu\text{m}$, which should have been easy to image with our $500\text{ nm} \times 500\text{ nm}$ Hall cross.

all probes, the voltage varied linearly with current with either a positive or a negative slope, proving that the offset is due to a resistance effect. The polarity depends on which axis of the rectangle of the cross asymmetry is longer. Probe B showed the smallest resistance of the five probes, with a value of 0.5Ω . This resistance would correspond to a length of the ridge of 180 nm . Even this smallest resistance will lead to offsets of tens of μV , which is a factor of 1000 larger than the expected Hall voltage.

FIGURE 2.8 – Attempt to perform Scanning Hall microscopy on a demagnetized permanent magnet in contact-mode. The applied current to the probe was $300\mu\text{A}$ at 3.77 kHz . The measured image shows a topographic feature rather than the magnetic domain structures measured by MFM (Figure 2.7). Since the measured range of $350\mu\text{V}$ is much larger than the expected Hall voltage, the magnetic information is hidden in topographic cross-talk.

2.4.3 Offset variations by temperature changes

Since the offset voltage is proportional to the resistance of the ridge, it is temperature dependent. This is demonstrated by placing a doped-silicon resistive heater located underneath the probe. The probe-sample distance was in the order of $100\mu\text{m}$. Figure 2.10 shows the change in offset voltage as a function of time. From 0 to 20 s the heater is at room temperature. After 20 s, we intermittently turned on and off the heater by applying a DC current of 100 mA to the heater every 20 s. As the heater was on, the offset increased by 6.1 % with respect to room temperature. Assuming a bulk value for the temperature coefficient of platinum of $3.9 \times 10^{-3}\text{ K}^{-1}$, this relates to a temperature increase of approximately 16 K. Clearly, the offset voltage is very temperature dependent.

Even if the probe is not heated on purpose, it will still suffer from Joule self-heating due to the current passing through the wiring at frequency ω . Referring to the theory of section (2.2), since the heating power is proportional to the square of the applied current, the temperature of the probe will vary at a frequency 2ω , and so does the resistance. Because the voltage is the product of resistance and current, it will have a 3ω component, which only contains the temperature signal of the probe.

Figure 2.11 shows the thermal frequency response of the offset voltage, measured by lock-in at the third harmonic of the applied current frequency. In this measurement, the current was set at $300\mu\text{A}$. There is a strong third harmonic

Probe	A	B	C	D	E
R_a [Ω]	51.8	0.5	33.1	43.0	1.9
error [%]	0.3	18.1	0.3	0.3	3.3

FIGURE 2.9 – Offset voltage as a function of the applied DC current for probes with different asymmetry. The polarity depends on which axis of the rectangle is longer.

FIGURE 2.10 – Offset change due to a resistance change caused by a temperature change induced by a external heater. The applied current to the probe was $30\mu A$ at 377 Hz.

FIGURE 2.11 – *The offset voltage of the probe measured at the third harmonic as a function of frequency. The applied current was $300\text{ }\mu\text{A}$. The response is essentially flat until 100 Hz after which it falls off with approximately 8 dB per decade.*

component of $2\text{ }\mu\text{V}$ at low frequencies, which proves that self-heating is substantial. The estimated temperature variation due to self-heating at frequency 2ω is 4.1 K.

The third harmonic starts to fall off strongly above 100 Hz with approximately 8 dB per decade, reaching -3 dB at 300 Hz. The thermal response of the probe has a low-pass filter characteristic, but not as a simple first order filter (which should attenuate 10 dB per decade).

2.4.4 Offset variations by probe-sample distance changes

When the temperature increase due to self-heating is constant, it does not cause a problem since then it can be easily compensated for. However, the heat loss is dependent on probe-sample distance, so the probe temperature decreases if the probe is moved towards the substrate. Figure 2.12 shows the offset voltage measured at the third harmonic, as a function of the vertical distance between the tip and the silicon substrate. The probe-sample distance was changed by the z-piezo located under the sample. We again applied a current of $300\text{ }\mu\text{A}$ but this time at 70.7 Hz i.e., sufficiently below the thermal corner frequency. The measured offset voltage indeed decreases strongly with decreasing distance, the effect increasing as the probe approaches the sample and lands at a piezo displacement of about $2.5\text{ }\mu\text{m}$. At this point, the third harmonic response of the offset voltage is approximately $100\text{ nV}/\mu\text{m}$. The corresponding temperature change and the heat resistance change are approximately $0.2\text{ K}/\mu\text{m}$ and $3\text{ kW/K}/\mu\text{m}$, respectively.

FIGURE 2.12 – Offset voltage of the probe at the third harmonic as a function of tip-substrate distance. Close to contact, the voltage varies with approximately $100 \text{ nV}/\mu\text{m}$. The distance was varied by the z-piezo scanner. The applied current to the probe was $300 \mu\text{A}$ at 70.7 Hz .

2.4.5 Offset variations during contact AFM

While scanning in contact-mode, the average cantilever-probe distance varies due to sample topography. This leads to temperature variations of the wiring on the cantilever. Therefore, we scanned the probe in an AFM in contact mode over a silicon surface with steps of 180 nm height and $5 \mu\text{m}$ width.

Figure 2.13 shows the third harmonic of the offset voltage of the probe, again with a current of $300 \mu\text{A}$ at 70.7 Hz . The voltage difference between the top and bottom of the steps is around 15 nV . This value is reasonably close to 18 nV , which would result from multiplying the 180 nm step height with a sensitivity of $100 \text{ nV}/\mu\text{m}$, as obtained from figure 2.12. We confirmed by conventional AFM that the bright and dark areas of the scanned image indeed correspond to the high and low plateaus respectively. Therefore it is very likely that at least part of the observed topography is due to the temperature difference of the probe caused by variation in average cantilever-sample distance.

Next to the plateaus, however, we observe spikes of both positive and negative polarity at the boundary of the steps. We suspect that when the tip is close to the concave corners of the step (at $3, 8$ and $13 \mu\text{m}$), the probe temperature decreases as the sample provides more surface area closer to the tip. On the other hand, when the tip is at the convex corners of the step, there is less substrate surface close to the tip, and the temperature increases. This indicates that offset voltage variations with topography are due to both temperature variations of the leads on the cantilever, caused by variation in average cantilever-sample distance, as well as temperature changes of the nanowire cross itself. Judging

FIGURE 2.13 – Offset voltage of the probe at the third harmonic during contact-mode AFM on a 180 nm step height sample. The bottom graph shows the scan from a to a' , The signal clearly suffers from topographic cross-talk. The signal increases as the cantilever-sample distance increases. A dip in the voltage is observed when the tip ascends or descends the step (at 3, 8 and 13 μm respectively), indicating an additional tip cooling effect. The applied current to the probe was 300 μA at 70.7 Hz.

from the height of the spikes, both effects are about equally strong.

To confirm that the cross-talk is indeed due to temperature variation of the probe, we recorded the offset voltage during scanning at the third harmonic of the drive frequency. This 3ω signal only contains information on temperature changes, eliminating the offset voltage and Hall signal. The temperature sensitivity of the offset at 3ω is a factor of twelve smaller than the sensitivity at ω . The cross-talk in the Hall measurement, which has a Hall signal at ω , is therefore twelve times stronger.

2.5 Discussion

The experiments with the heated sample, approach curves and scans on a pre-patterned surface are consistent with our hypothesis that the topographic cross-talk is caused by temperature variations. So scanning Hall microscopy with probes fabricated with the current technology will only be possible on very smooth samples (height variations of less than 30 nm). Permanent magnets are therefore out of the question. Alternatively, one can measure at a constant height far from the sample surface, at the cost of spatial resolution and in-

strument complexity. Neither solution is satisfactory. We see four different approaches to circumvent the thermal cross-talk.

Since the origin of the problem lies in probe asymmetry, one could attempt to reduce the asymmetry by using higher quality masks to define the template for corner lithography, such as mask made by electron beam lithography. In that case the probe symmetry would be limited by the resolution of the photoresist, which in our process is in the order of 50 nm. Ideally, one would like to suppress the topographic cross-talk below the Johnson noise of the Hall cross. Assuming a 2 Hz bandwidth on a sample with height variations of 1 μm , with 50 nm asymmetry, the cross width has to remain above 500 nm. This is far away from the 26 nm that can be achieved by corner lithography (Sun et al., 2016). This implies that not only the photomask, but the entire lithography step has to be improved.

Secondly, one can attempt to improve the ratio between Hall voltage and cross-talk, by using a material which has a better ratio between Hall coefficient and temperature coefficient of resistance. Instead of Pt (with a ratio of $6.2 \times 10^{-9} \text{ m}^3 \text{ K/C}$), one could gain 5-7 orders of magnitude by using Carbon graphene ($1.8 \times 10^{-3} \text{ m}^3 \text{ K/C}$) or a 2D electron gas ($5.3 \times 10^{-2} \text{ m}^3 \text{ K/C}$) like commonly used in Hall sensors.

Third, one can try to keep the cross temperature constant by placing a thermal isolation layer between the cross and the remainder of the probe, possibly accompanied by integrating a resistive heater/sensor with a temperature feed back system.

Finally, one could measure simultaneously at ω and 3ω . After proper calibration of the thermal cross-talk at ω one could subtract the 3ω signal from the ω signal to recover the Hall component. However, since the thermal cross-talk is about 1000 times stronger than the Hall component of the signal, this is a challenging option.

These solutions all involve considerable modification of the fabrication process and/or scanning setup. A thorough analysis, supported by experiments, is required to select the most promising option.

2.6 Conclusion

We fabricated sub-micrometer sized Hall crosses on cantilever probes by means of corner lithography, to be used in Scanning Hall Microscopy. These crosses are asymmetric due to fabrication imperfections, which leads to an offset voltage on the Hall signal. This offset voltage is dependent on the temperature of the cantilever, which on its turn varies with cantilever-sample distance. Since this distance varies slightly during contact imaging, there is a very strong topographic contribution to the signal. This effect makes scanning Hall microscopy difficult on samples that are not perfectly smooth. We emphasize that this effect does not only take place in scanning Hall microscopy, but will be present in other AFM probes with current driven sensors.

Chapter 3

Compensation of temperature dependent offset for Hall effect devices with asymmetric crosses

Abstract

In chapter 2, I discussed how fabrication imperfections lead to strong topographic cross-talk, which makes scanning Hall probe microscopy on rough surfaces impossible. To circumvent this topographic cross-talk, we have designed a cross-talk compensation method. In contrast to a conventional Hall sensing scheme, this compensation method drives the Hall cross by applying current to two leads and draining current from the opposite two leads. The Hall voltage is taken between the two drain leads. The ratio between drain-currents is adjusted so that the offset voltage is eliminated. In this situation, the temperature sensitivity of the offset becomes negligible. To test the method, we fabricated planar Hall crosses of millimeter dimension so that the misalignment can be precisely adjusted. The test measurements show that the temperature dependence can be suppressed by at least a factor of 30, whereas at the same time the signal to noise ratio is improved by 11 dB.

The work in this chapter is a team effort by Martin Siekman, Thijs Bolhuis, Remco Sanders, Ke-Chun Ma and myself. I contributed with the theoretical analysis, the design of the Hall crosses, the experiments and final analysis. Thijs Bolhuis and Remco Sanders assisted me in the construction of the measurement setup. Martin Siekman assisted in the design and fabrication of the electronic circuit. The wafer with Hall crosses was fabricated by Ke-Chun Ma.

3.1 Introduction

Generally, the Hall effect sensors require a four terminal sensing method in which the sensing part has a cross-bar shaped electrode (Hall cross). Due to

FIGURE 3.1 – a) Asymmetry caused by process inaccuracies lead to an offset voltage in Hall cross devices. This offset voltage is proportional to the materials specific resistance, and therefore temperature dependent. When the Hall cross dimensions decrease, this becomes a serious issue. b) In this paper we propose an alternative detection scheme which cancels out the offset caused by asymmetry. The method uses a current balancing technique to compensate for resistance differences in the current leads towards the cross.

inevitable fabrication inaccuracies, the Hall cross geometry has an asymmetry. This asymmetry leads to an extra resistance between the voltage sensing electrodes (See figure 3.1), resulting in an offset voltage. Since the additional resistance is temperature dependent, the offset voltage is as well. As a result, the offset voltage drifts with changes in temperature. In millimeter sized sensors, the asymmetry is minimal and this effect does not cause a problem. When using Hall probes of below micrometer dimensions in scanning Hall microscopy, the asymmetry can become very considerable and prevent any meaningful measurement of the magnetic field (See chapter 2).

The temperature dependent offset can be suppressed by converting the offset polarity, by using multiple crosses in one sensor (Kordić, 1986). If the asymmetry of the crosses are the same, one could interconnect one cross to another cross by swapping the current leads and the voltage leads, so that their offsets are canceled out each others. However the fabrication error may not be the same for all crosses and it requires extensions in the Hall cross geometry. This method cannot be applied to scanning Hall probe microscopy, since spatial resolution would be lost.

Alternatively, one can convert the offset polarity by means of a connection-commutation method (Bilotti et al., 1997; Steiner et al., 1998). In this method, the current and voltage leads are swapped repeatedly, which enables separation of the offset voltage from the Hall voltage, resulting in an offset suppression by a factor of five. This method can induce voltage spikes due to the switchings, which can breaks nanoscale Hall crosses, or requires complex signal processing.

In this paper, we propose a new temperature compensation technique that does not rely on electrode switching, but rather uses a current balancing circuit to suppress the offset. The method is based on the fact that the current is

injected from two leads, and extracted from the two opposite leads, as shown in figure 3.1b. We demonstrate the method on lithographically defined Hall crosses with rather big (mm) dimensions, so that asymmetry could be accurately controlled.

We characterized the offset voltage, as well as its temperature sensitivity, with the conventional technique. Subsequently, we demonstrated the temperature sensitivity of the offset normalized to the Hall sensitivity, and the signal to noise ratio of both the compensation and the conventional technique.

3.2 Theory

3.2.1 Temperature dependent offset in Hall probe

As described in chapter 2, Hall sensors exploit the effect that moving charges in a magnetic field experience a Lorentz force perpendicular to their velocity, and perpendicular to the field. The force translates into a potential difference (Hall voltage) over the width of an electrode carrying a current, which can be picked up in a so-called Hall cross geometry.

In the case of nanoscale scanning probes, the cross might have an additional intersection at the tip apex, therefore the voltage electrodes of the cross can be misaligned with an offset. Still we can obtain a Hall voltage if we apply the current for instance from lead 4 to 2, and measure the voltage between lead 3 and 1.

Due to the voltage electrode offset caused by cross asymmetry, the total voltage measured is a sum of Hall voltage and the temperature dependent offset voltage,

$$V_{\text{tot}} = j \{ w R_H B + L \rho (1 + \alpha \Delta T) \}$$

where j is the current density [A/m^2], w the cross width [m], R_H the Hall coefficient [m^3/C], B the magnetic field perpendicular to the cross plane [T], L the voltage electrode offset [m], ρ the resistivity [Ωm], α the temperature coefficient of resistance [K^{-1}] and ΔT the temperature change [K].

3.2.2 Compensation of temperature dependent offset

We propose a new Hall cross operation scheme to compensate the shift in offset voltage caused by changes in temperature. The concept of the compensation method is in figure 3.3. To conveniently introduce the method, we assume four identical lead resistances R_L which are connected with R_a (figures a,b and c). To compensate the offset IR_a , we effectively use the fact that Hall voltage is orthogonal to the current flow. By means of the conventional scheme (a) ($V_3 - V_1$), both Hall voltage and the offset are detected. On the other hand, when the voltage is taken on the same side (b) ($V_3 - V_2$), only the offset is measured. Therefore, by combining those two situations, the offset can be subtracted. To

FIGURE 3.2 – Conventional Hall cross operation scheme. Driving current is applied from lead 4 to 2, and Hall voltage is measured across lead 3 and 1. In the case of nanoscale probes, the Hall measurement suffers from temperature dependent offset $IR_a(T)$.

do so, we apply current from lead 3, 4 and drain to lead 1, 2 (c). In this case, voltages $(V_3 - V_1)$ and $(V_3 - V_2)$ can be expressed as in equation (3.1) and equation (3.2) respectively. Therefore $(V_2 - V_1)$ measures only Hall voltage without the offset due to R_a (Equation (3.3)).

$$V_3 - V_1 = I \left(R_L + R_a + \frac{R_H}{2d} B \right) \quad (3.1)$$

$$V_3 - V_2 = I (R_L + R_a) \quad (3.2)$$

$$V_2 - V_1 = I \frac{R_H}{2d} B \quad (3.3)$$

It should be noted that the Hall voltage in this scheme is halved compared to the conventional method, as the Lorentz force is only integrated over half of the cross width w .

In case of non-identical leads (d), the compensation scheme still detects the offset $(I_2 R_2 - I_1 R_1)$. Including temperature dependence, we obtain

$$V_{\text{off}} = (I_2 R_2 - I_1 R_1) (1 + \alpha \Delta T)$$

where I is the current [A] and R_i the resistance [Ω] of the leads. The offset as well as its temperature sensitivity can be compensated by adjusting the ratio between I_1 and I_2 so that $(I_2 R_2 - I_1 R_1)$ equals zero.

FIGURE 3.3 – Concept of the compensation method. a) The conventional voltage detection ($V_3 - V_1$) detects both Hall voltage and the offset. b) When the voltage is taken from same side ($V_3 - V_2$), only the offset can be measured. c) By combining those two detections ($V_2 - V_1$), the offset due to R_a can be avoided. d) In case of non-identical leads, the current I_1 and I_2 are balanced to make the offset voltage zero.

This compensation method operates the Hall cross in a way similar to conventional split-drain method (Baltes and Popovic, 1986). However the method uses the Hall-induced imbalance in the split output currents as a measure for the magnetic field. Therefore the split-drain method differs from the compensation method where we force the current to be equal by means of a current-mirror circuit and measure the voltage difference resulting from the voltage drop over two (near-)identical measurement resistors. The compensation method serves two purposes. On the one hand it compensates the temperature dependent offset voltage due to the asymmetry of the apex of the Hall probe, whereas at the same time it helps to keep a symmetric temperature distribution in the leads of the probe, or at least the amount of dissipated power therein.

3.2.3 Mixing rule for the temperature coefficient

To compare the measured temperature dependence with theoretical values, an estimate of the temperature sensitivity of the Hall cross is required. Since the Hall cross is composed of a Au/Cr bi-layer, the temperature coefficient of the total resistance is a combination of the resistances and temperature coefficients of the individual layers. For small differences in resistance, we can assume the current distribution in both layers to be independent of temperature. In this case a simple parallel resistance circuit analysis leads to

$$\alpha_{\text{tot}} = \frac{\alpha_{\text{Au}} t_{\text{Au}} \rho_{\text{Cr}} + \alpha_{\text{Cr}} t_{\text{Cr}} \rho_{\text{Au}}}{\rho_{\text{Au}} t_{\text{Cr}} + \rho_{\text{Cr}} t_{\text{Au}}} \quad (3.4)$$

where α is the temperature coefficient [1/K], ρ the specific resistance [Ωm] and t the thickness of the layers [m].

3.3 Experimental

3.3.1 Fabrication

To demonstrate the compensation method, we designed Hall crosses with widths of 1, 1.5 and 2 mm and cross aspect ratios of 0, 0.5, 1.0 and 1.6 (Figure 3.4).

The Hall crosses are fabricated on a mempax (glass) wafer by standard lift-off lithography of a sputtered Au layer on top of a Cr adhesion layer. Total thickness of the Au/Cr layer was 28 nm, determined by AFM (DI3100, Veeco Instruments Inc.). The resolution of the lithography process is in the order of 2 μm , so the cross width and offset are very well defined. The wafer with Hall crosses is diced in separated chips before wirebonding (Figure 3.5).

3.3.2 Measurement setup

The chips with Hall crosses were glued on a dedicated printed circuit board (PCB) and wires were drawn between electrodes on the PCB and contact pads

FIGURE 3.4 – *Dimension of the Hall crosses. a is the width, L is the electrode offset.*

FIGURE 3.5 – *Fabricated cross with Au/Cr(28 nm) on a glass wafer. a is 2 mm, aspect ratio is $L/a = 0.5$ (left) and 0 (right).*

on the Hall cross by wirebonder. This PCB was inserted in an aluminum chamber with four integrated resistive heaters (BPC5200J, BI Technologies Co.) and a thermocouple (Z2-K, Labfacility Ltd.). The temperature of the chamber is controlled by a digital temperature controller (CAL3300, CAL Controls Ltd.) and a power supply. The Hall cross temperature is measured by a second thermocouple directly mounted on the PCB with thermally conductive grease. This chamber is placed in the gap of a water cooled electromagnet (Figure 3.6).

Hall crosses are operated by both the compensation and conventional techniques, whose circuit diagrams are shown in shown figure 3.7 and 3.8 respectively.

Compensation technique

In the compensation circuit the reference output V of a SR830DSP lock-in amplifier (Stanford Research Systems) drives a current at 1 kHz through a series resistor R_s into lead 3 and 4 of the Hall cross. The choice of the series resistor

may impact the thermal stability of the Hall sensor, but does not effect the functionality of the compensation method. The resulting currents into lead 1 and 2 are balanced by means of a feedback assisted current-mirror (Baker, 2010).

The current-mirror consists of two resistances, the value of which is close to the Hall cross impedance, an OP27GSZ low-noise precision operational amplifier (Analog Devices Inc.) and an AD8429 instrumentation pre-amplifier (Analog Devices Inc.). The ratio between I_1 and I_2 is adjusted by varying the variable resistance R_G which determines the amplification factor of the instrumentation pre-amplifier. From the current and the cross dimensions, we estimate the current density at $1.4 \times 10^8 \text{ A/m}^2$.

The Hall voltage is taken between lead 1 and 2, and fed into another instrumentation pre-amplifier. The signal is amplified by a factor of 600 and returned to the input of the lock-in amplifier with a bandwidth is 23 mHz.

Conventional technique

In contrast to the compensation circuit, the current in the conventional operation circuit is applied from lead 4 to 2 by a Model 6221 current source (Keithley). The drive frequency is 1 kHz, for currents of 4.560, 6.840 and 9.120 mA and cross widths of 1, 1.5 and 2 mm respectively, leading to a current density of $1.6 \times 10^8 \text{ A/m}^2$. The voltage between lead 3 and 1 is amplified and measured by the same instrumentation and lock-in amplifiers as used in the compensation circuit. In this case the reference signal however is the drive current from the current source. To obtain the change in the offset voltage at the highest possible sensitivity range of the lock-in, we subtract the initial offset $I_0 R_{a,0}$ by means of a 1:1 ratio transformer (OEP1200, Oxford Electrical Products Ltd.) connected to the reference out of the lock-in amplifier.

3.4 Results and discussion

3.4.1 Temperature dependent offset

To demonstrate that the offset voltage is due to asymmetry, we measured the offset voltage as a function of electrode offset L (Figure 3.9). The measurements were taken at a temperature of 333 K, for Hall cross widths a ranging from 1 to 2 mm. For all cross widths, the offset voltage is linear with electrode offset, with a slope of $15.2(2) \text{ V m}^{-1}$. From this slope, we can deduce a sheet resistance of $3.33(4) \Omega/\text{sq}$. This value is in agreement with literature values for the resistivity of Au and Cr (Belser and Hicklin, 1959), and deposited layer thicknesses of Au(2 nm)/Cr(26 nm).

The offset is caused by the resistance R_a , which is a result of the asymmetry. Since the specific resistance of the Au/Cr layer is temperature dependent, the offset voltage will be temperature dependent as well. To analyze this temperature dependence, we measured the offset at temperatures of 323, 333 and 343 K and calculated the temperature sensitivity. Figure 3.10 shows the temperature

FIGURE 3.6 – Picture of the temperature controlled chamber. The Hall cross is glued on a dedicated PCB, inserted in the temperature controlled chamber. The Hall cross temperature is measured by a thermocouple fixed on the PCB by a thermally conductive grease. The chamber can be closed and is placed between the gap of the electromagnet.

sensitivity of the offset voltage as a function of electrode offset L for three cross widths. The temperature sensitivity linearly increases with the electrode offset, with a slope of $14.7(4) \text{ mV K}^{-1} \text{ m}^{-1}$. From the slope we estimate that the temperature coefficient of resistance (TCR) of the Au/Cr films was $0.967(26) \times 10^{-3} \text{ K}^{-1}$. This value is close to the estimate of 1.3×10^{-3} using the mixing rule of equation (3.4) with thicknesses t of 2 and 26 nm for the gold and chromium layers, and literature values for specific resistance ρ of 22 and 173 nΩm and temperature coefficients α of 2.8×10^{-3} and $0.6 \times 10^{-3} \text{ K}^{-1}$ (Belser and Hicklin, 1959).

3.4.2 Compensation of temperature dependent offset

Our novel compensation method dramatically suppresses the temperature dependent offset. To demonstrate the effectiveness of the technique, we measured the temperature sensitivity of the offset voltage both with and without compensation. Figure 3.11 shows the offset normalized to the Hall sensor sensitivity as a function of cross aspect ratio. Without compensation, the temperature sensitivity increases linearly with aspect ratio, because the temperature sensitivity of the offset increases while the Hall sensitivity remains constant. In contrast, our compensation technique shows temperature sensitivity values scattered around zero. The average suppression factor was 30 at an aspect ratio $L/a = 1.6$, for various cross widths a .

In theory the temperature sensitivity could be tuned to zero by the compensa-

FIGURE 3.7 – Schematic of the compensation method. The resistance network R_1 - R_4 represents the Hall cross structure (figure 3.5). The drive current is applied to lead 3 as well as lead 4. The output current on lead 1 and 2 are balanced so that the offset voltage is zero. To balance the currents, we employed a feedback assisted current-mirror scheme. The voltage between lead 1 and 2 is amplified and measured by the lock-in amplifier, using the drive voltage V as reference.

ation technique. In practice however, imperfections in the current balancing circuit lead to under- or overcompensation. For instance, an analog potentiometer is used to set the current balancing point. Since potentiometers are temperature dependent, a temperature fluctuation in the potentiometer directly causes a fluctuation in the current balance, and therefore the output signal. Based on the manufacturers specification, a realistic 0.3 K temperature variation causes about a same order of scatter as found in figure 3.11. By changing to a digital potentiometer, the suppression factor can be further improved.

The compensation circuit is very effective in suppressing temperature sensitivity, but should not increase noise. We therefore determined the signal to noise ratio at room temperature, using a time varying magnetic field induced by a magnet rotating above the cross at about three revolutions per second. Figure 3.12 shows the effect of compensation on the power spectrum density (for cross width 2 mm and aspect ratio $L/a = 1.6$). The higher harmonics of the sig-

FIGURE 3.8 – Schematic of the conventional circuit. The drive current is applied from lead 4 to lead 2. The voltage between lead 3 and lead 1 is amplified and measured by lock-in amplifier. The offset is subtracted by a transformer and a reference out of the lock-in phase-locked to the current source, so that the input circuit of the lock-in amplifier can be set to the highest possible sensitivity.

FIGURE 3.9 – The Hall offset voltage is proportional to the distance between the voltage electrodes with a slope of $15.2(2) \text{ Vm}^{-1}$, for Hall cross widths a from 1 to 2 mm.

FIGURE 3.10 – *Temperature sensitivity of the Hall cross offset voltage as a function of the distance between the voltage electrodes, for different cross widths a . The temperature sensitivity increases linearly, with a slope of $14.7(4) \text{ mV K}^{-1} \text{ m}^{-1}$*

nal are due to the cross-magnet distance change caused by a misalignment of the magnet on the rotation axis. The compensation method leads to less noise, but also lower signal. The resulting signal to noise ratio however is improved by 11 dB within a 1 Hz bandwidth.

3.5 Conclusion

When the dimensions of a Hall cross are reduced, fabrication inaccuracies lead to asymmetry, which in turn leads to a temperature dependent offset voltage. To characterize this effect, we experimented with Hall crosses that had designed asymmetries. We conclude that the offset voltage, as well as its temperature dependence, is proportional to the offset distance between the voltage leads of the Hall cross.

To suppress the temperature dependent offset, we designed a new detection method that is insensitive to cross asymmetry. Our new method suppresses the temperature dependence by a factor of 30, with the increase in signal to noise ratio of 11 dB.

This new compensation technique will strongly reduce the effects of manufacturing inaccuracy in nanometer sized probes, enabling scanning Hall microscopy using mass fabricated probes.

FIGURE 3.11 – Temperature sensitivity of the offset voltage normalized to the sensor sensitivity, as a function of cross aspect ratio. The compensation technique suppresses the sensitivity by a factor of 30, for various cross widths a .

FIGURE 3.12 – Power spectrum density of the Hall voltage with an applied magnetic field of 105(29) mT oscillating at 0.3 Hz. The Hall cross width a in this case is 2 mm, its aspect ratio $L/a = 1.6$. Although the compensation technique (red curve) applied a lower current, the signal to noise ratio is improved by 11 dB. This signal to noise ratio can be improved further by applying larger current.

Chapter 4

Batch fabricated micro scanning Hall probes for quantitative imaging of magnetic stray fields

Abstract

Apart from the problem of topographic cross-talk, for which a solution was discussed in chapter 3, the initial imaging attempts with nanosized Hall crosses presented in chapter 2 suffered from mechanical as well as electrical fragility, caused by the extremely long and thin leads. To avoid this problem, we modified the probe design so that the leads can be wider than the Hall cross width. This could be achieved by fabricating the leads on the faces of the AFM pyramid instead of at the edges. With this probe, we investigated Hall signal as well as topographic cross-talk and the functionality of the compensation method under scanning conditions. We demonstrate scanning probe Hall imaging of a thermo-magnetically patterned sample with a $10\mu\text{m} \times 10\mu\text{m}$ checkerboard pattern.

This work is a team effort with Edin Sarajlic, Martin Siekman, Ke-Chun Ma, Thibaut Devillers, Svetlana Ponomareva, Henk van Wolferen and Carsten Brill. My contribution is the measurements and their analysis. The scanning Hall probes used in the chapter were designed and fabricated by Edin Sarajlic. The SEM images of the probes were taken by Henk van Wolferen and Carsten Brill. The patterned magnetic sample was fabricated by Thibaut devillers, and its MFM analysis was performed by Svetlana Ponomareva of the Néel institute in Grenoble, France. The step sample for topographic analysis was fabricated by Ke-Chun Ma.

4.1 Introduction

Corner lithography enabled batch fabrication of nanowire scanning Hall probes. A disadvantage of this type of nanowire probes is that they are mechanically and electrically fragile. The cross dimensions are determined by the wire width, so

FIGURE 4.1 – Probe design concept. The Hall cross is realized at the apex of a pyramidal AFM tip, defined by slits at corners of the pyramid. The bottom of the pyramid is supported by four electrodes on four individual cantilevers, enabling a four terminal sensing on the cross.

an increase in resolution necessarily requires thinner wires. Next to mechanical fragility, this results in higher electrical resistance, so an increase in noise. To compensate the decrease in signal-to-noise ratio, higher current densities are required, leading to electromigration (Pierce and Brusius, 1997) and electrical over-stress(EOS) (Stojadinovic and Ristic, 1983).

To circumvent the problem, we modified the probe design with leads that can have a larger dimension than the cross. To realize this concept, we utilized the faces of the pyramid as leads, by using nanowires realized by corner lithography as an outline of the cross, see figure 4.1. The cross width is determined by the length of the slits made by the nanowire outline, and therefore it is fundamentally possible to reduce the cross width without a significant increase in the lead resistance. We demonstrate the Hall sensitivity of this novel type of probes, imaging on a patterned permanent magnet and the influence of topography on the magnetic signal.

4.2 Theory

As described in chapter 2, The total voltage measured is the sum of the Hall voltage and an offset voltage

$$V_{\text{tot}} = \left(\frac{R_H}{d} B + R_a \right) I_0 \cos \omega t$$

where R_H is the Hall coefficient [m^3/C], d the thickness of the Hall cross [m], B the perpendicular magnetic field [T], I_0 the driving current [A], ω the angular frequency [rad/s] and t the time [s].

R_a is determined by the cross asymmetry

$$R_a = \rho_a \frac{L}{wd}$$

where ρ_a is the resistivity [Ωm], L and w are the length and the width of the cross respectively [m].

4.3 Experimental

4.3.1 Fabrication of the Scanning Hall probe

We batch fabricated our novel Hall probes by means of the corner lithography technique (Berenschot et al., 2008). The Hall cross geometry is realized at the apex of an AFM tip by forming slits on the corners of a pyramid composed of silicon nitride. The entire structure is subsequently coated by a Au(50 nm)/Ti(5 nm) layer. Since the silicon-nitride structure is disconnected, the electrodes of the Hall cross are addressable via four individual cantilevers connected to contact pads located on a glass chip. Figure 4.2 shows a SEM image of the cantilevers and the probe. In this particular realization the cross width is approximately 1.8 μm . The process allows for much smaller cross-widths however.

Figure 4.3 shows SEM images of the crosses used in the experiments (row A), as well as examples of production failures (row B). These failures range from minor short-cuts close to the tip apex, which do probably not influence the resolution too much (B1), to shortcuts near the base (B2) and even fully closed (B3) crosses, which increases the cross-width up to 10 μm . When counting only fully successful probes, like in row A, the production yield is 15 %. Since this is only the first realization of this type probe, this value can certainly be improved.

On careful inspection, one can observe that also the successful probes have a slight asymmetry caused by irregularity of the slits.

4.3.2 Measurement setup

Similar to chapter 2, the Hall probes were glued on a dedicated printed circuit board (PCB) and wires were drawn between electrodes on the PCB and contact pads on the Hall cross by a manual wirebonder. The scanning setup is also same as described in chapter 2.

Conventional read-out

We used two ways to operate the Hall cross. The first method is straightforward, and commonly used for Hall sensor readout. As described in chapter 3, We apply a driving current from lead 4 to 2 in figure 4.2. The detected voltage between lead 3 and 1 is amplified by an instrumentation amplifier and measured by a lock-in amplifier. We subtracted the initial offset voltage $I_0 R_{a,0}$ to obtain the

FIGURE 4.2 – SEM micrographs of the fabricated scanning Hall probe. Four leads run over the four separated cantilevers to the Hall cross from contact pads on the probe base. Four triangle plates form AFM pyramidal tip, connected at the apex to realize Hall cross.

Hall voltage at a highest possible sensitivity of the lock-in amplifier. After measurements, this subtracted value is numerically added back to measured values (Figure 4.4).

To determine the Hall sensitivity of the probe, we applied a magnetic field perpendicular to the cantilever plane by means of a water cooled electromagnet. The probe driving current is 4.000 mA at 777.000 Hz. Figure 4.5 shows the Hall voltage of probe A2 as a function of the magnetic field, from which we determine a magnetic field sensitivity of $7.63(8) \mu\text{V/T}$, with a corresponding Hall coefficient is $0.95 \times 10^{-10} \text{ m}^3/\text{C}$. This value is in a good agreement with literature values for the Hall coefficient of gold (Chopra and Bahl, 1967). The offset voltage for this particular probe was $340.77(2) \mu\text{V}$, from which we estimate a cross asymmetry of 20%.

FIGURE 4.3 – SEM micrographs of the Hall crosses. While the probes in row A showed successfully fabricated crosses, which have been used in the experiments. Also shown are the probes with fabrication failures (row B), ranging from short cuts between faces of the pyramid (B1, B2), to fully closed probes (B3). While these probes are still functional, they suffer from a loss in resolution.

FIGURE 4.4 – Schematic of the measurement circuit for the conventional read-out method. The resistance network represents the Hall cross structure. The network consists of the resistances of four leads R_{1-4} and the extra resistance R_a due to the cross asymmetry. The driving current is applied from lead 4 to 2, and the voltage between lead 3 and 1 is amplified by a preamplifier, then measured by a lock-in technique. As the total voltage is a sum of the offset $I_0 R_a$ and the Hall voltage, we apply the offset subtraction scheme by means of a transformer and a function generator to employ the lock-in technique at a highest possible sensitivity.

FIGURE 4.5 – The Hall voltage as a function of applied magnetic field with an applied current of 4.000 mA at 777.000 Hz. The probe used in this measurement was A2 in figure 4.3. The offset of 340.77(2) μV is due to R_a . The sensitivity of this particular probe was 7.63(8) $\mu\text{V/T}$.

Read-out with offset compensation

Next to the conventional technique, we employed the compensation method described in chapter 3 to avoid measuring the offset resistance caused by probe asymmetry. In this chapter, the drive current is applied to lead 1 as well as lead 4 and the Hall voltage is taken between lead 2 and 3. The bandwidth of the lock-in amplifier is set at 5 Hz (Figure 4.6).

The magnetic sensitivity of probe A2 detected with this compensation method is shown in Figure 4.7. The driving voltage was 2.0194 V at 777.00 Hz, from which we estimate the probe current to be approximately 4 mA. The sensitivity was 3.64(1) $\mu\text{V/T}$ with a small offset of $-0.219(8)$ μV , caused by a residual imbalance in the current-mirror. Indeed, the sensitivity is smaller by approximately a factor of two, compared to the conventional technique.

Thermo-magnetically patterned sample

To demonstrate scanning Hall microscopy, we imaged perpendicular magnetic domains arranged in a checkerboard pattern on a flat NdFeB film by means of thermomagnetic patterning (TMP) (Dumas-Bouchiat et al., 2010). Figure 4.8 shows AFM and MFM images of this sample. The magnetic domains are magnetized with opposite polarity with 10 μm by 10 μm periodicity. The AFM image shows a surface roughness of approximately 30 nm on average.

FIGURE 4.6 – Schematic of the compensation technique. The resistance network R_1 - R_4 represents the Hall cross structure. In contrast to the conventional technique, the drive current is applied for instance to lead 1 as well as lead 4. The output currents on lead 2 and 3 are balanced so that the offset voltage is zero. To balance the currents, we employed a feedback assisted current-mirror scheme. The voltage between lead 1 and 2 is amplified and measured by the lock-in amplifier, using the drive voltage V as reference.

Topographic cross-talk test sample

To investigate in a systematic manner the effect of topographic cross-talk, we prepared a test sample with well determined topography. Arrays of square pits of several micrometer in size were etched into a silicon wafer by deep reactive ion etching, with a depth of approximately 550 nm. Figure 4.9 shows an AFM image and scan line of these holes.

4.4 Results and Discussion

4.4.1 Scanning Hall imaging on a smooth surface

To demonstrate the imaging functionality of the probes, we scanned over a thermomagnetically patterned sample (Figure 4.8) in contact-mode. In this

FIGURE 4.7 – The Hall voltage as a function of applied magnetic field with drive voltage of 2.0194 V at 777.00 Hz, operated by the compensation method. The probe used is the same as in figure 4.5. The offset of $-0.219(8) \mu\text{V}$ is due to the imperfection of the current balancing. The sensitivity of this particular probe was $3.64(1) \mu\text{V/T}$, which is by a factor of two lower than operated by the conventional technique, as predicted by theory.

FIGURE 4.8 – AFM (top) and MFM (bottom) images of a thermo-magnetically patterned NdFeB permanent magnet. The AFM shows approximately 30 nm surface roughness and the MFM shows a $10 \mu\text{m}$ by $10 \mu\text{m}$ checkerboard domain pattern. Note that the signal plotted in the MFM image is proportional to field derivatives, not the field itself.

FIGURE 4.9 – AFM image of the topographic cross-talk sample, showing a square pit of $20\mu\text{m}$ by $20\mu\text{m}$ with 550 nm depth. These pits are arranged with a periodicity of $20\mu\text{m}$ periodicity in both x and y directions.

FIGURE 4.10 – Demonstration of scanning Hall microscopy on the thermomagnetically patterned permanent magnet of figure 4.8. The probe driving current was 2.000 mA at 777.000 Hz. the magnetic sensitivity of this specific probe was $4.12(2) \mu\text{V/T}$. The bottom graph shows the scan from a to a' in the top image, averaged over three adjacent lines. The offset is removed from the measured signal. The signal shows $20 \mu\text{m}$ period in an agreement with the written pattern. The peak-to-peak voltage is $90(20) \text{ nV}$, which corresponds to a $22(6) \text{ mT}$ field change.

experiment, the probe driving current was 2.000 mA at 777.000 Hz, leading to the calibrated magnetic sensitivity of $4.12(2) \mu\text{V/T}$ for this specific probe. Figure 4.10, shows the checkerboard stray field pattern with $20 \mu\text{m}$ periodicity and a scanline. The measurements are in agreement with the MFM image (Figure 4.8), but the resolution is considerably lower. This is partially caused by the fact that the MFM measures the derivative of the field in z -direction, whereas the scanning Hall image displays the field itself. In the upper right corner of the image an artifact can be observed, with a negative signal twice the average Hall voltage. This artifact is most likely due to topographic cross-talk, induced by a probe-sample distance change caused by an imperfection in the sample.

From the measured signal amplitude of $90(20) \text{ nV}$, we can estimate the magnetic field amplitude to be $22(6) \text{ mT}$ using the calibration of figure 4.5.

4.4.2 Topographic cross-talk

The thermomagnetically patterned sample used in the SHPM demonstration is extremely smooth. Rougher samples, like polished permanent magnets led to unacceptably high topographic cross-talk (see chapter 2).

To characterize the topographic cross-talk, and the effect of the novel compensation detection method, we measured the height sensitivity of the offset voltage by scanning over the silicon test sample (figure 4.9) in contact mode. In this experiment we applied probe A3 (figure 4.3), with a drive current of 4.000 mA at 777.000 Hz.

Since the sample is non-magnetic, we expect no signal. Still figure 4.11 shows offset changes of around 700 nV between bright and dark area, corresponding to an array of square pits with a height difference of 550 nm in this sample. This topographic signal is caused by temperature changes of the cantilever, caused by variations in the average cantilever to sample distance, that change the offset voltage. From this experiment we conclude that the topographic cross-talk is 1.3 V/m. Combined with a magnetic sensitivity of approximately $3.6 \mu\text{V/T}$, we estimate that for 10 mT stray fields, the sample needs to be much smoother than 30 nm.

4.4.3 Compensation of topographic cross-talk

To circumvent the offset change due to the probe-sample distance change, we utilized the compensation method. To demonstrate the suppression ratio, we measured the offset change as a function of the probe-sample distance by means of both the conventional and compensation technique. We used the probe A2 in figure 4.3 with a drive current of 4.0000 mA at 777.000 Hz for the conventional technique, and a voltage of 2.0194 V which leads to around 4 mA at 777.00 Hz for the compensation technique.

Figure 4.12 shows the offset change normalized by Hall sensitivity when the probe-sample distance is changed by the z piezo. The conventional technique shows a distinct offset dependency on probe-sample distance, with a typical tip snap-in to the sample at around $2 \mu\text{m}$. On the other hand, the compensation technique barely shows any height sensitivity. Tip snap-in is hardly visible. From the graph we estimate that the compensation technique suppressed the height sensitivity by at least a factor of 10.

To demonstrate the functionality of the compensation technique under scanning conditions, we employed the technique while scanning over the silicon test sample. The probe used is A3 in figure 4.3, driven again by 2.0194 V at 777.00 Hz. We investigated the effect of scanning direction, as well as connection geometry. Figure 4.13 shows the offset signal for trace (a,c) and retrace scans (b,d), while measuring the voltage over the center two leads (a,b) or outer two leads (c,d). The scanning images as well as scan lines are shown for the four combinations.

FIGURE 4.11 – Offset voltage of the probe during contact-mode AFM on the silicon test sample. The bottom graph shows the scan from a to a' . The probe used in this measurement number A3 of figure 4.3. The drive current is 4.000 mA at 777.000 Hz. The offset change of approximately 700 nV is due to the probe temperature change caused by the variations in the average cantilever-sample distance. The bright/dark area correspond to high/low steps of the sample 4.9.

The measurement still shows a strong topographic signal, even though the compensation method suppresses topographic cross-talk caused by cantilever-sample distance variation by at least a factor of ten. The compensation method was designed to suppress the change in offset caused by temperature differences of the entire probe. As a result of the current-mirror scheme however, the compensation method amplifies the difference in temperature between the leads. We suggest that the topographic cross-talk that is still visible is caused by these temperature differences.

In the first place we observe a triangular signal instead of the square signal of figure 4.11. This is unexpected, since the signal corresponds to square steps in the test sample. It is not unlikely that there is a periodic change in the temperature difference between the leads when scanning transverse to the cantilever long direction, as the test sample has periodicity similar to the distance between the leads on the cantilever.

Next to the triangular signal, measurements a) and b) show voltage spikes at the edges of the steps with both positive and negative polarity. On the trace

FIGURE 4.12 – *The offset normalized to Hall sensitivity as a function of probe-sample distance varied by z-piezo displacement. The conventional technique shows a tip snap around 2 μm . The height sensitivity is suppressed by at least a factor of 10 by means of the compensation method.*

a), the amplitude of the positive spikes is larger than that of the negative spikes. On the retract b), the behaviors is opposite. The fact that the amplitude of the spikes is higher when the tip meets a rising edge suggest that the spikes are caused by torsion of the cantilever, which will cause temperature differences between the inner and outer lead due to a change in distance to the sample. Indeed, if the inner leads are used for detection, case c) and d), the signal is much lower and the profile shows similar spike amplitudes in both scan directions, which is in agreement with the fact that the distance changes between leads and sample are less prominent.

4.5 Conclusion

We introduce a novel way to batch fabricate integrated probes for scanning Hall probe microscopy. These novel probes are mechanically and electrically robust, and easy to operate. The current implementation has a cross dimension of around $2\mu\text{m} \times 2\mu\text{m}$, with 55 nm film thickness, leading to a sensitivity of $4.12(2)\mu\text{V/T}$. The production yield of the first batch is 15%, mainly caused by shortcuts between leads on the tip.

With these initial probes, we demonstrate $10\mu\text{m}$ spatial magnetic resolution on a smooth thermomagnetically written sample with a $10\mu\text{m} \times 10\mu\text{m}$ checker-board pattern.

For rougher samples, the probes suffer from topographic cross-talk. From artificially patterned silicon samples with 550 nm step height, we determine

FIGURE 4.13 – Offset voltage during contact-mode scan on the silicon step height sample, with the compensation technique by using lead 2,3 as the voltage sensing for the a) trace and b) retrace scan, and lead 3,4 as the voltage sensing for d) trace and c) retrace scan. Even though the offset compensation technique is applied, there is a topographic signal. The offset change is induced by temperature differences between leads.

the cross-talk to be 1.3 V/m. This topographic cross-talk is caused by probe temperature variation during scanning. There are three main contributions to this temperature variation.

In the first place, the cantilever temperature varies with average probe-sample distance. This effect can be suppressed by at least a factor of 10 by using a feedback assisted current-mirror scheme. This method however reduces the magnetic sensitivity by a factor of two.

Secondly, the temperature between leads on the cantilever varies due to cantilever torsion during scanning, especially on step edges. This leads to peaks in the detected signal, which only show up if the current-mirror scheme is used. The effect of cantilever torsion is much larger when the output voltage is taken from the outer two leads (in the order of 4 μ V), compared to when the voltage is taken from the center two leads (only 0.4 μ V).

Finally, we expect that the leads on the probe tip differ in temperature when the tip approaches a step edge. From the fact that the trace and re-trace signals look very similar if the center two leads are used for voltage detection, we conclude that this indeed could be the case.

Since our test pattern has a periodicity similar to the distance between the leads on the cantilever, we observe a triangular topographic background signal when scanning transverse to the cantilever long direction. This signal does not vary between trace and re-trace, nor does it depend on where the voltage leads are connected.

The main advantage of these probes is that one obtains calibrated, quantitative information on the magnetic field strength. Resolution can be improved, especially since the probe dimensions can be further reduced. This opens up the way to scanning Hall microscopy using batch fabricated probes based on corner lithography.

Chapter 5

Discussion

In this thesis, we investigated challenges of high spatial resolution scanning Hall probes by means of corner lithography. Despite improved probe designs over three generations, magnetic imaging is still limited to artificially patterned magnetic structures that are very smooth and have a relatively strong magnetic stray field. Realistic samples have not been imaged due to low sensitivity and topographic cross-talk. To proceed towards a commercially relevant probe, further investigation on those two points is required.

5.1 Target applications

To define what resolution and sensitivity a commercially relevant probe should aim for, we need to define the market. As the current implementation suffers from low sensitivity and cross-talk, a straightforward application that can be addressed without probe improvement are strong magnets with smooth surfaces. The typical example is hard disk recording heads. These are usually well polished, with a surface roughness of below 1 nm, so that they can fly over media at nanometer height. Currently, these heads are imaged by magnetic force microscopy. Since MFM detects field gradients, a quantitative measurement of the field strength is complex and inaccurate. Scanning Hall microscopy would be a valuable imaging technique for hard disk head development.

The state of the art head (Xu et al., 2015) generates 1 T magnetic fields with a resolution of $50 \text{ nm} \times 50 \text{ nm}$. For imaging this type of heads, the required spatial resolution should be in the order of 10 nm, which is at the very limit of our current implementation of corner lithography. The recording area per bit will be further reduced year by year. If corner lithography can not catch up with the increasing recording density, there will be no chance for a commercial application of scanning Hall probes in this field.

Alternatively, larger domains are present in permanent magnets for electrical motors, such as applied in both e-car industry and wind power generator industry. The magnetic stray fields of permanent magnets are high, but the sur-

face roughness is considerable. Widely used NdFeB (Sepehri-Amin et al., 2011) magnets for instance have fields above 0.5 T. As the grain size is typically $1\text{ }\mu\text{m}$, the expected topography is in the order of 500 nm and the domains will have a size of about $3\text{ }\mu\text{m}$. This would require 600 nm spatial resolution, for which the wireframe probes presented in chapter 2 are sufficiently small. The roughness however would lead to unacceptable topographic cross-talk.

Next to NdFeB, FeN (Ogawa et al., 2013) is considered as a future permanent magnet, mainly because of lower costs. The field can be 1 T and the grain size is 100 nm, therefore the topography and domain size are 50 nm and 300 nm respectively, resulting the required resolution of 60 nm, which is beyond the capability of the probes of chapter 2, but still within the reach of corner lithography.

5.2 Probe optimization

If scanning Hall probes are to be successfully applied in development of permanent magnets, two points need to be considered: topographic cross-talk and signal-to-noise ratio.

5.2.1 Compensation of topographic cross-talk

Since permanent magnets have rough surfaces, elimination of the cross-talk problem is necessary. However, topographic cross-talk will increase when the cross width is reduced to reach higher resolution. This is because with size reduction the probe asymmetry caused by fabrication imperfections will become relatively large. Furthermore, in the case of our compensation method, the temperature gradient within the probe becomes larger. Elimination of the heating effect itself might therefore become more effective than performing intelligent signal readout. To do so, we could start by replacing the probe material SiN (43 W/Km), used in the current implementation, to Si with a factor of four higher thermal conductivity (168 W/Km). For a coarse estimate of the effectiveness of this approach, we suppose the cantilever has a length of $150\text{ }\mu\text{m}$, width of $60\text{ }\mu\text{m}$ and thickness of 300 nm. One side connected to the probe base at ambient temperature (300 K), and the other side is heated by a driving current of 4 mA passing through a $100\text{ }\Omega$ Hall cross. By neglecting all of the heat loss to the ambient, the resulting temperature of the heated side reduces from 631 K to 380 K when replacing SiN with Si respectively. This simple estimate gives an upper limit, but indicates that improvement of probe cooling should be considered as a means to reduce topographic cross-talk.

5.2.2 Signal to noise ratio

Miniaturisation of Hall crosses leads to lower sensitivity. The gold cross with a width of $2\text{ }\mu\text{m}$, described in chapter 4 had just enough signal to noise ratio to measure the thermo-magnetically patterned smooth sample. Downscaling

the Hall cross to sub- μm dimensions seems out of the question. The way forward is therefore towards higher Hall coefficients. I believe a realistic candidate is bismuth, which has a Hall coefficient that is a factor of thousand higher than gold. The cross width could theoretically be reduced down to 2 nm. Bismuth suffers however from high roughness when evaporated or sputtered. This roughness does not have to be a problem if one uses a template-stripping method ([Kokorian et al., 2014](#)), which is perfectly compatible with corner lithography.

The maximum current density of bismuth is a factor of two higher than that of gold. Since the Hall sensitivity is linear to the driving current, one might expect that higher driving current density automatically leads to higher signal-to-noise ratio. At increasing current the temperature of the probe also increases, so not only the signal, but also the Johnson noise and temperature dependent offset will increase. In [appendix A](#) a detailed analysis of this effect is given. Therefore, to operate probes at the highest possible SNR, both Hall sensitivity and noise contributions should be determined to reach the optimum current density.

Chapter 6

Conclusions and recommendations

The corner lithography technique enables batch fabrication of Hall sensors on the apex of AFM tips. The Hall probes fabricated by this technique feature a free standing silicon nitride pyramidal wireframe, coated by a gold layer, located at the edge of an AFM-type cantilever. The cross junction at the apex of the pyramid serves both as the AFM tip and as a Hall sensor.

When investigating the possibility to utilize these probes in high resolution scanning Hall microscopy, we have encountered three challenges.

6.1 Mechanical fragility

The wireframe is mechanically fragile compared to commercial scanning probes, which have a bulk pyramidal tip. Initial AFM experiments indicated that the wireframe breaks quite often when the probe is approaching the sample surface. Therefore novel, mechanically more robust probes were designed and fabricated. Rather than an open wireframe, we fabricated conductive nanowires on the inside of a thin silicon-nitride pyramidal membrane. This closed membrane was mechanically robust enough to support sensing wires under contact scanning conditions, thus enabling scanning Hall microscopy.

A second advantage of this new design is that electrical contact between the Hall sensor and the sample surface is avoided. Of course, the increased distance between Hall sensor and sample will ultimately limit the resolution, and other solutions will have to be found.

6.2 Magnetic sensitivity

For reasons of simplicity, we used gold as the sensing layer in the first realisation of our scanning Hall probes. The Hall coefficient of gold is however over a factor thousand lower than materials used in commercial sensors, as for instance bismuth thin films or 2D electron gas (2DEG) systems. Therefore, the magnetic

sensitivity of the probe is relatively low, which limits its use to high magnetic fields.

For future work, I advise to replace the gold layer by better materials. However, these alternatives are not trivial to integrate. The surface roughness of bismuth is for instance in the same order as the Hall cross dimension, and 2DEG layers are technically challenging to fabricate on a 3D structure.

Next to the materials issue, the wireframe geometry itself also limits sensitivity. The long, thin electrodes on the wireframe legs easily fail under high currents, long before electromigration takes place. This limits the current density to values far below theoretically achievable values, and therefore sensitivity.

We addressed this challenge by altering the probe design so that thin current leads are avoided. By utilizing the faces of the pyramid to address the Hall cross, rather than the edges, the current density could be increased by a factor of five, leading to a proportionally higher signal. Using this design, we were able to image the stray field of magnetic domains in a thermomagnetically patterned permanent magnet.

6.3 Topographic cross-talk

To obtain the highest possible spatial resolution, the Hall probe has to be operated in contact-mode AFM. In this mode, the tip of the probe is continuously in contact with the sample surface. The height of the pyramid that forms the Hall probe is in the order of $10\text{ }\mu\text{m}$. As a result, the cantilever, on which the tip is mounted, is quite close to the sample surface. Any surface roughness therefore leads to changes in the average distance between the cantilever and the sample surface. Consequently, this leads to noticeable changes thermal conductance during scanning.

This effect can be seen as topographic cross-talk in the magnetic signal, especially on rough surfaces. Scanning Hall measurements for instance on a demagnetized permanent magnet showed topographic cross-talk that was a factor of 1000 larger than the estimated Hall voltage. As a result, magnetic imaging was impossible. Detailed investigation into this effect led to the conclusion that the cross-talk is mainly due to a combination of the cross asymmetry and the changes in probe temperature during scanning. Indeed scanning on a very smooth sputtered permanent magnet did not result in problematic topographic cross talk.

To circumvent the topographic cross-talk, we developed a differential detection scheme that reduces thermal sensitivity caused by probe asymmetry by a factor of at least 10. However this scheme suffers from topographic cross-talk due to temperature difference in leads, for instance caused by asymmetric thermal conductance at step edges.

Appendices

Appendix A

Signal to noise ratio

In the case of scanning Hall probes fabricated by corner lithography, the main contributions to the noise are Johnson noise and temperature drift of the offset signal. Both are dependent on temperature and resistance of the probe.

From equation (2.4) in chapter 2 and the ratio between apex resistance and lead resistance $b = R_l / R_a$, the total resistance of the probe is

$$R_{\text{tot}} = \frac{(1 + b) R_0}{1 - \alpha c_{\text{tot}} (1 + b) R_0 I^2} \quad (\text{A.1})$$

$$c_{\text{tot}} = c_0 + \Delta c \quad (\text{A.2})$$

where R_0 is the apex resistance at an ambient temperature $[\Omega]$, α the temperature coefficient of resistance $[\text{K}^{-1}]$, c_0 the average heat resistance $[\text{K}/\text{W}]$, Δc the heat resistance change $[\text{K}/\text{W}]$ and I the probe driving current $[\text{A}]$.

By combining equation (2.4) in chapter 2 and equation (A.1), the temperature of the probe can be derived:

$$T_{\text{tot}} = T_0 + \Delta T$$
$$\Delta T = \frac{\Delta c (1 + b) R_0 I^2}{1 - \alpha c_{\text{tot}} (1 + b) R_0 I^2}$$

where T_0 is the ambient temperature $[\text{K}]$, ΔT the temperature increase caused by the power dissipated in the probe and/or change due to heat resistance change $[\text{K}]$.

Therefore, Johnson noise and temperature dependent offset are

$$V_{\text{N}} = \sqrt{4kT_{\text{tot}}R_{\text{tot}}f}$$
$$V_{\text{T}} = R_{\text{tot}}I$$

where k is the Boltzman constant and f the measurement frequency bandwidth $[\text{Hz}]$.

An approximation of these equation can be obtained by taking the first two terms of their Taylor series expansion

$$V_N = \sqrt{4kT_0(1+b)R_0f} \left\{ 1 + \frac{c_{\text{tot}}(1+b)R_0}{2T_0} (1+\alpha T_0) I^2 \right\} \quad (\text{A.3})$$

$$V_T = R_0 I + \alpha c_{\text{tot}}(1+b)R_0^2 I^3 \quad (\text{A.4})$$

The first term of equation (A.3) is the Johnson noise at ambient temperature, the second term is the contribution from the probe heating, which is proportional to I^2 . Similarly, the first term of equation (A.4) is the offset due to the resistance at an ambient temperature, the second term is the offset increase and change due to the heating and heat resistance change respectively. If the heat resistance c_{tot} is constant ($\Delta c = 0$ in equation (A.2)), the offset could be simply compensated. However in the case c_{tot} is modulated by variation in probe-sample distance ($\Delta c \neq 0$), the offset can not be compensated easily. Therefore the contribution of the temperature dependent offset as a noise is only the second term with Δc .

Therefore, the signal to noise ratio of the Hall sensor is determined by Johnson noise and temperature dependent offset, which can be expressed as

$$\frac{V_H}{V_N} = \frac{R_H I}{d \sqrt{4kT_0(1+b)R_0} \left\{ 1 + \frac{c_{\text{tot}}(1+b)R_0}{2T_0} (1+\alpha T_0) I^2 \right\}} \frac{B}{\sqrt{f}}$$

$$\frac{V_H}{\Delta V_T} = \frac{R_H}{d \alpha (1+b) R_0^2 I^3} \frac{B}{\Delta c}$$

where R_H the Hall coefficient [m^3/C], B the magnetic field [T], d the thickness of Hall cross [m]. To be able to determine the minimum detectable field, we assume f to be equal to 1 Hz and Δc to be equal to 1 K/W. The sensitivity limited at $\text{SNR} = 1$ can than be expressed as

$$B_{\text{min}, N} = \frac{d \sqrt{4kT_0(1+b)R_0}}{R_H I} \left\{ 1 + \frac{c_{\text{tot}}(1+b)R_0}{2T_0} (1+\alpha T_0) I^2 \right\} \quad (\text{A.5})$$

$$B_{\text{min}, T} = \frac{d \alpha (1+b) R_0^2 I^3}{R_H} \quad (\text{A.6})$$

The field sensitivity has an optimum value (equation (A.5)). In first order, the field sensitivity increases with increasing current (first term), but when the current is increased the probe heats up and the Johnson noise becomes dominant. Therefore, there is an optimum drive current which increases if probe cooling is improved. Increased probe cooling will also be beneficial for topographic cross-talk, since probe heating quadratically increases with increasing current (equation (A.6)).

Bibliography

Akamine S, Quate C F, 1992

“Low temperature thermal oxidation sharpening of microcast tips”
J Vac Sci Technol B **10**, pp. 2307–2310

Akram R, Dede M, Oral A, 2008

“Variable temperature-scanning Hall probe microscopy with GaN/AlGaIn two-dimensional electron gas (2DEG) micro Hall sensors in 4.2–425 K range using novel quartz tuning fork AFM feedback”
IEEE Trans. Magn. **44**, pp. 3255–3260, doi: [10.1109/TMAG.2008.2001622](https://doi.org/10.1109/TMAG.2008.2001622)

Akram R, Dede M, Oral A, 2009

“Imaging capability of pseudomorphic high electron mobility transistors, AlGaIn/GaN, and Si micro-hall probes for scanning Hall probe microscopy between 25 and 125 °C”
Journal of Vacuum Science and Technology B: Microelectronics and Nanometer Structures **27**, pp. 1006–1010, doi: [10.1116/1.3056172](https://doi.org/10.1116/1.3056172)

Baker R J, 2010

CMOS Circuit Design, Layout, and Simulation,
Wiley-IEEE Press, 3rd edition
ISBN 0470881321, 9780470881323

Baltes H, Popovic R, 1986

“Integrated semiconductor magnetic field sensors”
Proceedings of the IEEE **74**, pp. 1107–1132, doi: [10.1109/PROC.1986.13597](https://doi.org/10.1109/PROC.1986.13597)

Belser R B, Hicklin W H, 1959

“Temperature coefficients of resistance of metallic films in the temperature range 25° to 600° C”
J. Appl. Phys. **30**, pp. 313–322, doi: <http://dx.doi.org/10.1063/1.1735158>

Bending S J, 2010

“Scanning Hall probe microscopy of vortex matter”
Physica C: Superconductivity and its Applications **470**, pp. 754–757, doi: [10.1016/j.physc.2010.02.027](https://doi.org/10.1016/j.physc.2010.02.027)

Berenschot E, Tas N R, Jansen H V, Elwenspoek M, 2008

“3D-nanomachining using corner lithography”
In: *3rd IEEE Int. Conf. on Nano/Micro Engineered and Molecular Systems (NEMS 2008)*, pp. 729–732, Sanya, doi: [10.1109/NEMS.2008.4484432](https://doi.org/10.1109/NEMS.2008.4484432)

Bilotti A, Monreal G, Vig R, 1997

“Monolithic magnetic hall sensor using dynamic quadrature offset cancellation”
IEEE Journal of Solid-State Circuits **32**, pp. 829–835, doi: [10.1109/4.585275](https://doi.org/10.1109/4.585275)

- Brook A, Bending S, Pinto J, Oral A, Ritchie D, Beere H, Henini M, Springthorpe A, 2003
“Integrated piezoresistive sensors for atomic force-guided scanning Hall probe microscopy”
Applied Physics Letters **82**, pp. 3538–3540, doi: [10.1063/1.1576914](https://doi.org/10.1063/1.1576914)
- Chang A, Hallen H, Harriott L, Hess H, Kao H, Kwo J, Miller R, Wolfe R, Van Der Ziel J, Chang T, 1992
“Scanning hall probe microscopy”
Applied Physics Letters **61**, pp. 1974–1976, doi: [10.1063/1.108334](https://doi.org/10.1063/1.108334)
- Chopra K L, Bahl S K, 1967
“Hall effect in thin metal films”
J. Appl. Phys. **38**, p. 3607–3610, doi: <http://dx.doi.org/10.1063/1.1710180>
- Dai Z, King W, Park K, 2009
“A 100 nanometer scale resistive heater-thermometer on a silicon cantilever”
Nanotechnology **20**, p. 095301, doi: [10.1088/0957-4484/20/9/095301](https://doi.org/10.1088/0957-4484/20/9/095301)
- Dede M, Ürkmen K, Girişen O, Atabak M, Oral A, Farrer I, Ritchie D, 2008
“Scanning Hall probe microscopy (SHPM) using quartz crystal AFM feedback”
Journal of Nanoscience and Nanotechnology **8**, pp. 619–622, doi: [10.1166/jnn.2008.A265](https://doi.org/10.1166/jnn.2008.A265)
- Dumas-Bouchiat F, Zanini L F, Kustov M, Dempsey N M, Grechishkin R, Hasselbach K, Orlanges J C, Champeaux C, Catherinot A, Givord D, 2010
“Thermomagnetically patterned micromagnets”
Appl. Phys. Lett. **96**, p. 102511, doi: [10.1063/1.3341190](https://doi.org/10.1063/1.3341190)
- Hilgenkamp H, Ariando, Smilde H J, Blank D, Rijnders G, Rogalla H, Kirtley J, Tsuei C, 2003
“Ordering and manipulation of the magnetic moments in large-scale superconducting pi-loop arrays”
Nature **422**, pp. 50–53, doi: [10.1038/nature01442](https://doi.org/10.1038/nature01442)
- Honda Y, Higashikawa K, Inoue M, Kiss T, Ayai N, Kikuchi M, Hayashi K, Sato K, 2010
“Study on critical current distribution in CT-OP Bi-2223 tape based on the scanning Hall probe magnetic microscopy”
Physica C: Superconductivity and its Applications **470**, pp. 1377–1379, doi: [10.1016/j.physc.2010.05.117](https://doi.org/10.1016/j.physc.2010.05.117)
- Kokorian J, Engelen J B C, de Vries J, Nazeer H, Woltering L A, Abelman L, 2014
“Ultra-flat bismuth films for diamagnetic levitation by template-stripping”
Thin Solid Films **550**, pp. 298–304, doi: <http://dx.doi.org/10.1016/j.tsf.2013.11.074>
- Kordić S, 1986
“Integrated silicon magnetic-field sensors”
Sens. Actuators **10**, pp. 347–378, doi: [http://dx.doi.org/10.1016/0250-6874\(86\)80054-3](http://dx.doi.org/10.1016/0250-6874(86)80054-3)
- Lustig C D, Baird A W, Chaurette W F, Minden H, Maloney W T, Kurtzig A J, 1979
“High-resolution magnetic field measurement system for recording heads and disks”
Review of Scientific Instruments **50**, pp. 321–325, doi: [10.1063/1.1135813](https://doi.org/10.1063/1.1135813)
- Mohammed H A, Bending S J, 2014
“Fabrication of nanoscale Bi hall sensors by lift-off techniques for applications in scanning probe microscopy”
Semiconductor Science and Technology **29**, doi: [10.1088/0268-1242/29/8/085007](https://doi.org/10.1088/0268-1242/29/8/085007)
- Neu V, Melcher S, Hannemann U, Fähler S, Schultz L, 2004
“Growth, microstructure, and magnetic properties of highly textured and highly coercive Nd-Fe-B films”
Physical Review B - Condensed Matter and Materials Physics **70**, pp. 144418–1–144418–8, doi: [10.1103/PhysRevB.70.144418](https://doi.org/10.1103/PhysRevB.70.144418)

- Ogawa T, Ogata Y, Gallage R, Kobayashi N, Hayashi N, Kusano Y, Yamamoto S, Kohara K, Doi M, Takano M, Takahashi M, 2013
 “Challenge to the synthesis of α - Fe_{16}N_2 compound nanoparticle with high saturation magnetization for rare earth free new permanent magnetic material”
Applied Physics Express **6**, p. 073007
- Oral A, Bending S J, Henini M, 1996
 “Real-time scanning hall probe microscopy”
Appl. Phys. Lett. **69**, pp. 1324–1326
- Osberger L, Frick V, Hébrard L, 2016
 “High resolution shallow vertical Hall sensor operated with four-phase bi-current spinning current”
Sensors and Actuators A: Physical **244**, pp. 270 – 276, doi: <http://dx.doi.org/10.1016/j.sna.2016.04.036>
- Paul O, Cornils M, 2009
 “Explicit connection between sample geometry and Hall response”
Appl. Phys. Lett. **95**, doi: [10.1063/1.3272267](https://doi.org/10.1063/1.3272267)
- Petit D, Atkinson D, Johnston S, Wood D, Cowburn R P, 2004
 “Room temperature performance of submicron bismuth hall probes”
IEE Proc.: Science, Measurement and Technology **151**, pp. 127–130, doi: [10.1049/ip-smt:20040167](https://doi.org/10.1049/ip-smt:20040167)
- Pierce D G, Brusius P G, 1997
 “Electromigration: A review”
Microelectron. Reliab. **37**, pp. 1053–1072, doi: [10.1016/S0026-2714\(96\)00268-5](https://doi.org/10.1016/S0026-2714(96)00268-5)
- Popović R S, 1991
Hall effect devices: magnetic sensors and characterization of semiconductors,
 Adam Hilger
- Sander C, Leube C, Aftab T, Ruther P, Paul O, 2016
 “Monolithic isotropic 3D silicon Hall sensor”
Sensors and Actuators A: Physical pp. –, doi: <http://dx.doi.org/10.1016/j.sna.2016.06.038>
- Sandhu A, Masuda H, Kurosawa K, Oral A, Bending S, 2001
 “Bismuth nano-Hall probes fabricated by focused ion beam milling for direct magnetic imaging by room temperature scanning hall probe microscopy”
Electronics Letters **37**, pp. 1335–1336, doi: [10.1049/el:20010908](https://doi.org/10.1049/el:20010908)
- Sandhu A, Masuda H, Oral A, Bending S J, Inushima T, 2002a
 “Magnetic imaging of ferromagnetic domains by room temperature scanning hall probe microscopy using GaAs/AlGaAs and bismuth micro-hall probes”
 volume 4746 II, pp. 950–955, Delhi
- Sandhu A, Kurosawa K, Dede M, Oral A, 2004a
 “50 nm Hall sensors for room temperature scanning Hall probe microscopy”
Japanese Journal of Applied Physics, Part 1: Regular Papers and Short Notes and Review Papers **43**, pp. 777–778
- Sandhu A, Okamoto A, Shibasaki I, Oral A, 2004b
 “Nano and micro Hall-effect sensors for room-temperature scanning hall probe microscopy”
Microelectronic Engineering **73-74**, pp. 524–528, doi: [10.1016/j.mee.2004.03.029](https://doi.org/10.1016/j.mee.2004.03.029)
- Sandhu A f, Masuda H, Oral A, Bending S J, Yamada A, Konagai M, 2002b
 “Room temperature scanning Hall probe microscopy using GaAs/AlGaAs and Bi micro-hall probes”
Ultramicroscopy **91**, pp. 97–101, doi: [10.1016/S0304-3991\(02\)00087-6](https://doi.org/10.1016/S0304-3991(02)00087-6)

- Sarajlic E, Vermeer R, Delalande M Y, Siekman M H, Huijink R, Fujita H, Abelmann L, 2010
“Batch fabrication of scanning microscopy probes for thermal and magnetic imaging using standard micromachining”
In: *Proc. 23rd Int. Conf. on Micro Electro Mechanical Systems (MEMS 2006)*, pp. 328–331, Hong Kong, doi: [10.1109/MEMSYS.2010.5442498](https://doi.org/10.1109/MEMSYS.2010.5442498)
- Sepehri-Amin H, Une Y, Ohkubo T, Hono K, Sagawa M, 2011
“Microstructure of fine-grained Nd-Fe-B sintered magnets with high coercivity”
Scripta Materialia **65**, pp. 396–399, doi: [10.1016/j.scriptamat.2011.05.006](https://doi.org/10.1016/j.scriptamat.2011.05.006)
- Steiner R, Maier Ch, Häberli A, Steiner F P, Baltes H, 1998
“Offset reduction in Hall devices by continuous spinning current method”
Sens. Actuators A **66**, pp. 167–172
- Stojadinovic N, Ristic S, 1983
“Failure physics of integrated circuits and relationship to reliability”
Phys. Status Solidi A **75**, pp. 11–48
- Sun X, Veltkamp H W, Berenschot E J, Gardeniers H J, Tas N R, 2016
“Nano-pyramid arrays for nano-particle trapping”
In: *Proceedings of the IEEE International Conference on Micro Electromechanical Systems (MEMS)*,
- Wouters C, Vranković V, Rössler C, Sidorov S, Ensslin K, Wegscheider W, Hierold C, 2016
“Design and fabrication of an innovative three-axis Hall sensor”
Sensors and Actuators A: Physical **237**, pp. 62–71, doi: <http://dx.doi.org/10.1016/j.sna.2015.11.022>
- Xu S, Sinha S, Rismaniyazdi E, Wolf C, Dorsey P, Knigge B, 2015
“Effect of carbon overcoat on heat-assisted magnetic recording performance”
IEEE Transactions on Magnetics **51**, doi: [10.1109/TMAG.2015.2445871](https://doi.org/10.1109/TMAG.2015.2445871)
- Zhou H, Mills G, Chong B K, Midha A, Donaldson L, Weaver J M R, 1999
“Recent progress in the functionalization of atomic force microscope probes using electron-beam nanolithography”
Journal of Vacuum Science and Technology A: Vacuum, Surfaces and Films **17**, pp. 2233–2239, doi: [10.1116/1.581753](https://doi.org/10.1116/1.581753)

Abstract

Scanning Hall probe microscopy is a widely used technique for quantitative high resolution imaging of magnetic stray fields. Up to now probes with nanometer spatial resolution have only been realized by electron beam lithography, which is a slow and expensive fabrication technique. In this thesis, we employ corner lithography to enable batch fabrication of high resolution scanning Hall probes.

The initial design consisted of a sub- μm Hall cross supported by four free standing wires in a pyramidal configuration, located at the end of an AFM type cantilever. This implementation was mechanically and electrically too fragile to operate. Therefore the design was improved by supporting the wires with a robust silicon-nitride membrane. These robust probes allowed for scanning operation, but we discovered that the output signals suffered from large topographic crosstalk. We determined that this crosstalk was caused by the combination of cross asymmetry, resulting from fabrication imperfections, and topography induced probe-sample distance modulation, leading to temperature variation.

To circumvent the crosstalk, we introduced an electronic compensation method to suppress the effect of temperature variation on the detected Hall signal. The method suppresses the temperature effect by at least a factor of ten, provided that the probe temperature varies uniformly over the entire structure. However, the method is not capable of compensating temperature changes within the probe structure itself, for instance caused by asymmetric probe cooling at step edges on the sample, or cantilever torsion.

To increase the signal-to-noise ratio and improve the electrical robustness of the probes even more, we improved the probe design further by widening the leads to the Hall cross and increasing its dimensions. Using this final design, we successfully demonstrated imaging on a thermo-magnetically patterned magnetic sample with domains of $10\mu\text{m} \times 10\mu\text{m}$, at a sensitivity of 4.12 V/T .

Samenvatting

Scanning Hall probe microscopie is een veel gebruikte techniek om hoge resolutie afbeeldingen te maken van magnetische strooivelden boven oppervlakken. Het voordeel van deze techniek ten opzichte van magnetische kracht microscopie is dat we kwantitatieve informatie over de sterkte van het veld kunnen krijgen. Voor nanometer resolutie konden deze probes tot nu toe alleen worden gemaakt met elektronenbundel-lithografie. Deze techniek is erg langzaam en duur. In dit proefschrift wordt de onlangs ontwikkelde *corner lithography* gebruikt, waarmee we in staat zijn honderden hoge resolutie Hall probes tegelijkertijd te produceren.

Het eerste ontwerp bestond uit een Hall kruis met een afmeting kleiner dan een micrometer, dat werd ondersteund door vier vrijstaande draden in een pyramide vorm. Dit ontwerp bleek mechanisch en elektrisch te fragiel om te kunnen gebruiken in een scanning probe microscoop. Daarom hebben we het ontwerp verbeterd door de gehele pyramide te omgeven met een silicium-nitride membraan. Deze tweede generatie probes konden worden gebruikt in de scanning probe microscoop, maar de magnetische informatie werd overschaduwd door een sterk topografisch signaal.

We ontdekten dat deze topografische overspraak wordt veroorzaakt door een combinatie van twee effecten. In de eerste plaats is het Hall kruisje asymmetrisch, wat wordt veroorzaakt door onnauwkeurigheden in de fabricage. Daardoor hebben de probes een offset spanning, wat op zich geen probleem hoeft te zijn. In de tweede plaats varieert de temperatuur van de probe tijdens het scannen, omdat de topografie van het monster leidt tot modulatie van de afstand tussen de probe en het oppervlak van het monster. Deze topografie geïnduceerde variatie in temperatuur resulteert echter in een variatie in de offset-spanning die niet te onderscheiden is van een magnetisch signaal.

We hebben een elektronisch circuit ontworpen dat deze topografische overspraak onderdrukt met minstens een factor tien. De techniek werkt uitstekend wanneer de temperatuur over de probe uniform varieert. Deze method is echter niet in staat temperatuurvariaties over de probe te compenseren, zoals die bijvoorbeeld worden veroorzaakt door het asymmetrisch afkoelen van het Hall kruisje op stappen in het monster, of torsie van de cantilever tijdens het scannen.

Om de signaal-ruis verhouding te vergroten en de probes elektrisch nog

robuuster te maken, hebben we het ontwerp nog eens verbeterd met bredere draden en een iets groter Hall kruisje. Met deze probes is een demonstratie uitgevoerd op magnetische film met thermomagnetisch geschreven domeinen van $10\mu\text{m} \times 10\mu\text{m}$, bij een gevoeligheid van 4.12 V/T .

要旨

走査型ホール素子顕微鏡は、磁場の定量的な高空間分解能イメージング法として広く用いられている。既存の探針でナノサイズの空間分解能を有するものは、高価かつ遅緩な電子線描画装置を使用して作製される。本学位論文では、高空間分解能を有する走査型ホール効果顕微鏡用探針の複数一括作製を可能にするために、コーナーリソグラフィー技術を用いた。

初めに作製を試みた探針のデザインは、原子間力顕微鏡用探針を模したカンチレバーの端に、四角錐型に自立した四本の細線によってマイクロメートル以下のホール素子を支えたものである。この探針は、機械的かつ電氣的に脆弱であり、操作が困難であったため窒化ケイ素の強硬な膜で支持して強化した。探針を強固にすることで試料表面の走査測定が可能になったが、測定信号が試料表面形状に起因する高強度の混信を被った。我々は、この混信は探針作製の不完全性によるホール素子の非対称性と、試料表面形状がもたらす探針試料間距離の変化に起因した探針の温度変化が原因であると断定した。

この混信を回避するために、我々は測定信号の温度依存性を抑える電氣的な補正法を提案した。この方法は探針全体で均一に温度が変化する場合に、温度依存性を十分の一以下に抑えた。しかしながら、試料表面凹凸の角または走査中のカンチレバーの捻れになどによる非対称冷却に起因した、探針構造内での温度変化には有効ではなかった。

信号対雑音比の向上かつ探針の電氣的強靱性のさらなる向上のために、ホール素子の寸法を僅かに増大させ、かつ導線の幅を素子よりも広げることで探針のデザインを改善した。この最終的なデザインを有した探針を用いることで、平坦な表面に熱磁気描画された $10\mu\text{m} \times 10\mu\text{m}$ の磁区構造のイメージングを 4.12V/T の磁場感度で達成した。

Acknowledgments

It is hard to thank everyone and especially not to forget someone, but I will do my best. If I accidentally forgot to acknowledge you here and you would like to be, please do not hesitate to come and blame me. I am willing to write down my sincere gratitude on the blank space of this chapter you have.

Leon, when you were in Akita university for sabbatical, I believe we both were very brave to make the plan "Kodai joins to TST". This bravery is based on my decision to dive into an unfamiliar country (even my first time abroad), and your decision to accept this weird Japanese speaking poor English as the PhD candidate of your precious project. I was not sure if I could survive as a PhD in the Netherlands, and probably you also felt the same, so there is no doubt we were trying to play quite a difficult gamble. I believe we won the game, right? Thank you for playing it with me so long with great patience, knowledge and motivation. I also would like to thank you for correcting my writing in Yoda-English all the time.

Gijs, I could not succeed without your supervision. It was always nice to talk with you by looking at equations and to approach problems theoretically, which I tend to forget. I liked a lot the way we made the model of the current balancing circuit together, and SNR of the Hall sensors by taking into account Joule heating. Thank you for encouraging me with your optimistic comments.

Edin, Niels, Hans Hilgenkamp, Oliver Paul and Tjerk Oosterkamp, thank you for being committee members of my promotion and accepting my thesis. Niels, occasional meetings with you helped a lot to ease the pressure caused by my struggle. Edin, nothing would have happened in this project if you did not fabricate those Hall probes presented in this thesis. I admire your nanofabrication technique. Oliver, thank you for your critical remarks, which improved my thesis dramatically.

Maarten and Rolf, it is my honor to have my defense with you. The time I spend as a room mate with Maarten and as an office mate with Rolf is priceless.

Martin, if you did not ask "Would you like to be a PhD in the Netherlands?" back in 2009, I would have never thought about studying abroad. Your question changed my life. I learned a lot from you, not only technical matters but also a way of thinking, living, etc. All your contributions dramatically boosted this research project. I can not thank you enough.

Thijs, Remco (S), the experimental results in chapter 3 would never have

been realized without your help on building the setup. Thank you for helping me to approach problems together.

Ke-Chun, thank you for helping me on fabricating the planar Hall crosses (chapter 3) and the Si steps (chapter 4). Your fabrication led to important paragraphs.

Henk, I enjoyed a lot to imaging Hall probes with the SEM together with you. Your contribution on SEM measurements and designing the optical path for AFM detections helped a lot. Also thank you for polishing magnets for the scanning demonstrations.

Carsten Brill, thank you for your quick SEM measurements (32 probes in less than an hour!).

Theo, thank you for helping me to solder.

Yoshimura-sensei, thank you for providing information of state of the art HDD recording heads and permanent magnets.

Mark Lantz and Johan Engelen, thank you for nice discussions and measurements. Silvia Derks, thank you for your hospitality at IBM.

Thibaut Devillers, Svetlana Ponomareva, Andre Dias and Nora Dempsey, thank you for providing us with the checkerboard magnet. We would have never succeed on scanning Hall measurement without them.

Susan, Karen, Brigitte and Jolanda, thank you very much for occasional chat and your kindness.

Joël and Laurens, thank you for choosing me as a paranymph for your defense.

Jeroen, Hans, Frieda, Maaïke, Olga, Haye, Erik, Dian, Vincent, Mourad, Françoise and Esther, thank you for sharing office with me.

Antoine, Auke, Bojian, Dilu, Dennis, Derya, Elmer, Erwin, Frank, Hadi, Hammad, Jaap, Janine, Jarno, Joost, Léon, Mark, Matthias, Meint, Narges, Olti, Ozlem, Pele, Per, Pieter, Rabindra, Remco (W), Robert, Samantha, Tijmen, Vitaly, Wesley and Yiyuan, occasional chats, discussions and conference attendance with you made unforgettable memories. Thank you for being nice fellows.

吉田泰夫様、私のオランダへの渡航を後押ししていただき感謝致します。田中智様、日本で精進する友がおり励みになりました。多謝致します。両親と達貴、長男である私を遠い異国に快く送り出してくれたことに拝謝致します。また、義両親のお二方、麻祐を遠い異国に快く送り出してくれたことに深謝致します。麻祐と佳には、今後の私の人生すべての時間を掛けても返せない位の大きな借りができました。常に後ろ盾していただいたことに万謝致します。皆様のお陰で博士と名乗る権利を得ることができました。ありがとうございました。

Last but not least, Kodai, I would like to thank you as well.

Publications

Journal articles

Hatakeyama K, Siekman M, Sarajlic E, Bolhuis T, Sanders R, Krijnen G, Tas N, Abelman L, 2016
“Batch fabricated scanning Hall probes for quantitative imaging of magnetic stray fields”
To be submitted

Conference contributions

Hatakeyama K, Sarajlic E, Siekman M, Huijink R, Abelman L, September 2012
“Full silicon-nitride probes with corner lithography wireframes for scanning Hall probe microscopy”
In: *23rd Micromechanics and Microsystems Europe Workshop, MME 2012*, p. A13, Ilmenau
University of Technology, Ilmenau, Germany

Hatakeyama K, Sarajlic E, Siekman M, Huijink R, Abelman L, 2013
“Batch fabricated scanning Hall probes”
In: *Int. Conf. on Materials Engineering for Resources, ICMR 2013*,

Hatakeyama K, Sarajlic E, Siekman M, Jalabert L, Fujita H, Tas N, Abelman L, 2014a
“Wafer-scale fabrication of scanning thermal probes with integrated metal nanowire resistive elements for sensing and heating”
In: *Conference of 27th IEEE International Conference on Micro Electro Mechanical Systems, MEMS 2014*, pp. 1111–1114, Institute of Electrical and Electronics Engineers Inc., San Francisco, CA
ISBN 9781479935086, doi: [10.1109/MEMSYS.2014.6765840](https://doi.org/10.1109/MEMSYS.2014.6765840)

Hatakeyama K, Vermeer R, Siekman M, Sarajlic E, Tas N, Abelman L, May 2014b
“Batch fabricated scanning Hall probes for quantitative imaging of magnetic stray fields”
In: *IEEE International Magnetism Conference, INTERMAG 2014*, pp. 1741–1742, IEEE Magnetism Society, Los Alamitos, CA, USA

Biography

Kodai Hatakeyama was born on the 28th of March 1987 in Noshiro, Akita, Japan. He attended Hamaguchi primary school and went to Hachiryu junior high School in Mitane. In 2005, he graduated from Noshiro senior high school in Noshiro, thereafter he moved to Akita city to study materials science and engineering at Akita university. In 2011, he received the master degree on Materials science and engineering on his thesis with the title 'Development of frequency-modulated magnetic force microscopy' at the group of Prof. Hitoshi Saito. He continued his research at the same group as a researcher. In 2012, he started his PhD research at the Transducers Science and Technology group at the University of Twente in Enschede, the Netherlands, led by Leon Abelmann and Gijs Krijnen, on the assignment presented in this thesis. During his PhD research he attended the CERAN language school in Spa, Belgium, and visited IBM in Zürich, Switzerland to demonstrate the devices presented in this thesis.

一括化された探針を用いた
走査型ホール効果顕微鏡の課題

島山 広大

ISBN 978-90-365-4163-3