VASILEIOS A. PAPADIMITRIOU ION CONCENTRATION POLARIZATION

VASILEIOS A. PAPADIMITRIOU

ION CONCENTRATION POLARIZATION

FOCUSING, SEPARATION
EXTRACTION AND PARTICLE POROSITY
DIFFERENTIATION

ION CONCENTRATION POLARIZATION

FOCUSING, SEPARATION, EXTRACTION AND PARTICLE
POROSITY DIFFERENTIATION

VASILEIOS PAPADIMITRIOU

ION CONCENTRATION POLARIZATION

**FOCUSING, SEPARATION, EXTRACTION AND PARTICLE
POROSITY DIFFERENTIATION**

DISSERTATION

to obtain
the degree of doctor at the University of Twente,
on the authority of the rector magnificus,
Prof. dr. T. T. M. Palstra,
on account of the decision of the Doctorate Board,
to be publicly defended
on Friday the 25th of October 2019 at 16:45

by

Vasileios Papadimitriou
born on the 11th of July 1988
in Athens, Greece

This dissertation has been approved by:

Prof. dr. Jan C. T. Eijkel
Prof. dr. ir. Loes I. Segerink

Promotor
Co-promotor

Cover design: Katerina Tzanetea

Printed by: Ipskamp print

ISBN: 978-90-365-4843-4

DOI: 10.3990/1.9789036548434

URL: <https://doi.org/10.3990/1.9789036548434>

© 2019 Enschede, The Netherlands. All rights reserved. No parts of this thesis may be reproduced, stored in a retrieval system or transmitted in any form or by any means without permission of the author. Alle rechten voorbehouden. Niets uit deze uitgave mag worden vermenigvuldigd, in enige vorm of op enige wijze, zonder voorafgaande schriftelijke toestemming van de auteur.

Graduation Committee:

Chairman:

Prof. dr. J.N. Kok

University of Twente

Promotor:

Prof. dr. J. C. T. Eijkel

University of Twente

Co-promotor:

Prof. dr. ir. L. I. Segerink

University of Twente

Committee Members:

Prof. dr. J. Han

Massachusetts Institute of Technology

Prof. dr. E. M. J. Verpoorte

University of Groningen

Prof. dr. ir. A. van den Berg

University of Twente

Prof. dr. S. G. Lemay

University of Twente

Prof. dr. Ir. R. G. H. Lammertink

University of Twente

Dr. H. T. M. van den Ende

University of Twente

The research described in this thesis was conducted at the BIOS Lab on a Chip Group of the MESA+ Institute for Nanotechnology, Max Planck Center for Complex Fluid Dynamics, University of Twente, Enschede, the Netherlands. The research was supported by the Horizon 2020 Framework Programme of the European Union under the project H2020-PHC-634013 (PHOCNOSIS).

UNIVERSITY
OF TWENTE.

MESA+
INSTITUTE

... from chaos to order and back again ...

I was planning to have a more inspirational quote from someone famous here but I read this somewhere and it felt quite fitting. Maybe because during the ion concentration polarization focusing the mixed analytes temporarily separate and they order themselves till the device is turned off and diffusion returns the system to its chaotic mixed state. Or maybe because of the chaos I was creating at my setup just so I can make a nice ordered graph and then one more chip ends up in the chaos of the trashcan. No matter what I thank you for picking up this book and I hope you find something useful in it.

Table of Contents

CHAPTER 1 INTRODUCTION	11
1.1 CARDIOVASCULAR DISEASES	13
1.2 THE PHOCNOSIS PROJECT	13
1.3 THE BIOMARKER	14
1.4 MICROFLUIDIC SEPARATION AND CONCENTRATION OF CHARGED SPECIES	15
1.4.1 MICROFLUIDICS	15
1.4.2 ELECTROKINETIC SEPARATIONS	16
1.4.3 ION CONCENTRATION POLARIZATION FOCUSING	17
1.5 THESIS OUTLINE	21
1.6 REFERENCES	22
CHAPTER 2 ION CONCENTRATION POLARIZATION FOR MICROPARTICLE MESOPOROSITY DIFFERENTIATION.....	27
2.1 INTRODUCTION	29
2.2 THEORY	30
2.2.1 NERNST PLANCK	31
2.2.2 TRANSPORT NUMBERS τ	32
2.2.3 CURRENT DENSITY J	35
2.3 EXPERIMENTAL.....	38
2.4 RESULTS AND DISCUSSION	40
2.5 CONCLUSIONS AND OUTLOOK.....	43
2.6 REFERENCES	44
CHAPTER 3 3D CAPILLARY STOP VALVES FOR VERSATILE PATTERNING INSIDE MICROFLUIDIC CHIPS.....	47
3.1 INTRODUCTION	49
3.2 THEORY	49
3.2.1 CAPILLARY FILLING	52
3.2.2 CAPILLARY STOP VALVE	52
3.2.3 OPEN MICROFLUIDICS	53
3.3 EXPERIMENTAL.....	54
3.4 RESULTS AND DISCUSSION	56
3.4.1 CHARACTERIZATION OF DEVICE OPERATION USING ETHANOL/WATER MIXTURES.....	56
3.4.2 METHOD FLEXIBILITY	58
3.4.3 ANTIBODY PATTERNING WITH AN AQUEOUS SOLUTION	59
3.5 CONCLUSIONS AND OUTLOOK.....	61
3.6 REFERENCES	62
CHAPTER 4 CONTINUOUS FOCUSING, FRACTIONATION AND EXTRACTION OF ANIONIC ANALYTES IN A MICROFLUIDIC CHIP.....	65
4.1 INTRODUCTION	67
4.2 THEORY	69
4.2.1 CONCENTRATION POLARIZATION AND ESTABLISHMENT OF A DEPLETION ZONE	69
4.2.2 ELECTRIC MODEL (FIGURE 4.2)	70

4.2.3 FLUIDIC MODEL (FIGURE 4.2)	71
4.2.4 SEPARATION AND EXTRACTION RESOLUTION	74
4.3 EXPERIMENTAL	77
4.4 RESULTS AND DISCUSSION	78
4.4.1 ANALYTE POSITION CONTROL	78
4.4.2 ANALYTE SELECTION CONTROL	79
4.4.3 HIGHER CONCENTRATION FACTORS	82
4.4.4 COMPARISON TO THE THEORETICAL MODEL	83
4.5 CONCLUSIONS AND OUTLOOK	85
4.6 REFERENCES	85
CHAPTER 5 FREE FLOW ION CONCENTRATION POLARIZATION FOCUSING (FF-ICPF)	89
5.1 INTRODUCTION	91
5.2 THEORY	91
5.2.1 CONVECTION	93
5.2.2 ANALYTE ELECTROPHORESIS	94
5.2.3 ANALYTE FOCUSING	94
5.2.4 OPERATION MODES	94
5.3.5 THROUGHPUT	96
5.3 EXPERIMENTAL	97
5.4 RESULTS AND DISCUSSION	99
5.4.1 PEAK MODE	99
5.4.2 PLATEAU MODE	99
5.4.3 ELECTROPHORETIC SPACERS	101
5.4.4 CONCENTRATION RATE AND EXTRACTION POSITION	102
5.5 CONCLUSIONS AND OUTLOOK	104
5.6 REFERENCES	104
CHAPTER 6 CONTINUOUS OR ON-DEMAND DROPLET GENERATOR FOR EXTRACTION OF ELECTROKINETICALLY FOCUSED ANIONIC ANALYTES ON CHIP	107
6.1 INTRODUCTION	109
6.2 THEORY	110
6.2.1 ION CONCENTRATION POLARIZATION FOCUSING	110
6.2.2 DROPLET GENERATOR	112
6.3 EXPERIMENTAL	116
6.4 RESULTS AND DISCUSSION	118
6.4.1 EQUILIBRIUM STATE	118
6.4.2 DROPLET ON DEMAND	118
6.4.3 DROPLET SIZE	120
6.4.4 INTEGRATION OF DoD AND ICPF	121
6.6 CONCLUSION AND OUTLOOK	125
6.6 REFERENCES	126
CHAPTER 7 CURRENT MONITORING FOR FLUORESCENCE-FREE ANALYTE EXTRACTION CONTROL IN ION CONCENTRATION POLARIZATION FOCUSING	131

7.1 INTRODUCTION	133
7.2 THEORY	133
7.3 EXPERIMENTAL	135
7.4 RESULTS AND DISCUSSION	136
7.5 CONCLUSIONS AND OUTLOOK	140
7.6 REFERENCES	141
CHAPTER 8 SUMMARY AND RECOMMENDATIONS FOR FURTHER WORK.....	143
8.1 SUMMARY AND RECOMMENDATIONS	145
APPENDIX A SUPPLEMENTARY INFORMATION FOR CHAPTER 3.....	149
A.1 CAPILLARY STOP VALVES	151
A.2 FLOW VELOCITY CALCULATION	151
A.2.1 CAPILLARY FILLING	151
A.2.2 OPEN MICROFLUIDICS	152
A.3 REFERENCES	153
APPENDIX B SUPPLEMENTARY INFORMATION FOR CHAPTER 4.....	155
B.1 ION CONCENTRATION POLARIZATION FOCUSING (ICPF) MODEL	157
B.2 DERIVATION OF FOCUSED ANALYTE PEAK SIZE AND DISTRIBUTION	161
B.3 REFERENCES	164
APPENDIX C SUPPLEMENTARY INFORMATION FOR CHAPTER 5.....	166
C.1 EFFECT OF HIGH ELECTRIC POWER TO THE STABILITY OF THE SYSTEM	168
C.1.1 HEAT ANALYSIS	168
C.1.2 ELECTROCHEMICAL REACTIONS	169
C.2 ORIGINAL MICROSCOPY IMAGES	169
APPENDIX D SUPPLEMENTARY INFORMATION FOR CHAPTER 6	171
D.1 CHIP DESIGNS AND DIMENSIONS	173
D.2 EQUILIBRIUM PRESSURE CALCULATIONS AND OBSERVATIONS	173
APPENDIX E CONVOLUTION IN MICROFLUIDICS.....	175
E.1 INTRODUCTION	177
E.2 CONVOLUTION	178
E.3 APPLICATION OF CONVOLUTION	179
E.4 APPLICATIONS OF DECONVOLUTION	182
E.5 CONCLUSION AND OUTLOOK	186
E.6 REFERENCES	186
PUBLICATION LIST.....	187
PEER - REVIEWED JOURNAL PUBLICATIONS	187
CONFERENCE CONTRIBUTIONS	187
SAMENVATTING	189

FUNDING AND CONTRIBUTIONS..... 193

 FUNDING 193

 CONTRIBUTIONS 193

ACKNOWLEDGEMENTS..... 195

Chapter 1

Introduction

1.1| Cardiovascular diseases

Cardiovascular diseases (CVD) remain the number **one** cause of death worldwide, accounting approximately for one out of three deaths (31.8%)¹. In developed countries there is a constant decrease in the death rate that can be accounted to CVD; *e.g.* in Europe the CVD death rates dropped from 42% in 1990 to 32% in 2017¹. In addition, there is a significant difference between males and females (figure 1.1), where since 2007 the number one cause of death for males in Europe is cancer instead of CVD. Despite the decrease in mortality over the years, on average CVD remains the leading cause of death in Europe and accounts annually for 1.9 million deaths with an estimated cost of almost €196 billion². Despite these numbers, CVD can be successfully treated when detected early and managed according to best practices. Therefore, having efficient detection tools for the implementation of preventive testing and early diagnosis is a key factor for reducing CVD mortality rates.

Figure 1.1 - Cause of death in European Union in 2017 (left – male, right – female)¹

1.2| The Phocnosis project

This thesis work took place in the context of the EU Horizon 2020 Phocnosis project. “The Phocnosis project aims at developing an ultra-sensitive, compact and low-cost point-of-care-testing (POCT) device based on nanophotonic and micro-/nanofluidic technology for its application to minimally invasive early diagnosis of CVD. The success of such a POCT device will significantly help to reduce the actual costs designated for early diagnosis and to implement mass screening programs, allowing a significant contribution to the improvement of the citizens’ health status and to the sustainability of healthcare systems” (<https://phocnosis.eu/>).

The device will consist of a disposable cartridge and a reusable read-out control device. The disposable cartridge operates based on two principles:

- i) An antibody-coated nanophotonic sensor that will provide a high sensitivity label-free detection of very low concentrations of targeted biomarkers. The aimed detection limit of these sensors is below $1 \mu\text{g L}^{-1}$. Despite the high sensitivity of the photonic sensor the concentration of the biomarkers of interest will still be below the limit of detection, namely in the ng L^{-1} range.

- ii) A microfluidic system responsible for concentrating the targeted biomarkers approximately 1000-fold and separating them out of their complex environment. This part is the goal of this thesis.

1.3| The biomarker

The Phocnosis analysis device will determine the diagnosis based on the concentration of specific biomarkers present in whole blood. The biomarkers that were chosen are cardiac troponin I (cTn-I) and cardiac troponin T (cTn-T) which are the golden standard for current diagnosis for many CVDs.

Cardiac troponins (cTn) regulate the contractibility of the cardiac muscles. cTn come in a complex of cTn-I, cTn-C and cTn-T. A simplified schematic of the role of troponin is shown in figure 1.2. In short, the muscle contractibility regulation by cTn is as follows^{3,4}. The cardiac muscle (*i.e.* myosin fibers) is covered by an actin filament made from actin fibers. cTn-I is bound to actin and cTn-C, while cTn-T is bound to tropomyosin and cTn-C. Due to various activation biomolecules, with calcium binding on cTn-C being recognized as the most dominant mechanism, cTn-I is detached from actin, opening up binding sites on actin. The myosin head of the myosin fiber can now bind on these free actin sites. The interaction between myosin and actin results in the motion of the muscle³. The more actin binding sites are attached to cTn-I, the less available binding sites for myosin are present making the muscle less contractible. In the case of a CVD, for example an acute myocardial infraction (heart attack), the cardiac muscle is getting damaged thereby releasing a mixture of free, complex and post translationally modified forms of troponins in the blood stream resulting in elevated concentrations of cardiac troponins⁵. This increased concentration of troponins (mainly cTn-I and cTn-T) is therefore a widely-used biomarker for CVDs. A table of some important physiochemical properties of the troponins is shown in table 1.

Figure 1.2 – Schematic of cTn regulation of the muscle contractibility mechanism. (left) cTn-I is bound to an actin binding site prohibiting myosin to attach to it. (right) cTn-C reacts with 4 calcium molecules and “unlocks” the cTn-I detaches from actin allowing myosin to anchor to the actins binding site and the muscle motion can take place. Schematic not in scale.

Table 1.1 - Physiochemical properties of cardiac Troponins

Protein	Charge [e] (at pH 7)	Molecular Weight	Isoelectric point
Troponin I	8.9 ⁶	23.9 kDa	9.5 ⁷ 5.5, 6.3 ⁸ >7 ⁹
Troponin I phosphorylated	p- 6.9 pp- 4.9 *	p-23.997 kDa pp-24.077 kDa ¹⁰	5.4 and 7-8 ⁸
Troponin T	-21.9 ⁶	36 kDa	4.8 ¹¹
Troponin C or complexes	-29.1 ⁶	18.4 kDa 161 amino acids	4.17 ⁶

*Phosphate pKa (2.2, 7.2 (5.8 as an ester) and 12.4)

p- single phosphorylation

pp- double phosphorylation

After protein biosynthesis, proteins can undergo various covalent and enzymatic modifications known as post-translational modifications (PTMs). There is a wide variety of PTMs that range from modifying existing functional groups or introducing new ones, to cleavage of peptide bonds or creation of disulfide bonds. A wide variety of isoforms and PMTs of troponins have been reported (*e.g.* for cTn-I more than 20 isoforms have been identified¹⁰).

The introduction of a phosphate group known as phosphorylation, is one of the most common PTMs¹². PTMs of troponin are found both on physiological and pathological conditions¹³. Phosphorylation of troponins (I and T) also contributes to the regulation of cardiac muscle contractility¹⁰. In healthy human cardiac tissue approximately 56% of all the cTn-I exists in a phosphorylated form (mono- or biphenylated). For a pathological condition such as chronic heart failure, the percentage of phosphorylated cTn-I drops to 1% making specific PTMs appealing biomarkers¹⁰.

In clinical devices that only depend on an immunoreaction to determine the cardiac troponin cTn-I and cTn-T concentrations, the existence of PTMs of both proteins affects their immunoreactivity but is of less importance¹⁴. When preconcentration by an electrophoretic method (like our approach) is used however, a change in the shape, charge and isoelectric point may have serious implications.

1.4| Microfluidic separation and concentration of charged species

1.4.1| Microfluidics

The current cTn quantification methods require highly sensitive assays such as Enzyme-Linked Immunosorbent Assay (ELISA), that require a large volume of sample (typically 5mL of blood is extracted from the patient). Also, the time between extracting the sample to answer is 1-2 hours which in the case of acute

myocardial infraction could be too long for the treatment of the patient. In addition, ELISA is a labor-intensive process with multiple washing steps which either requires trained personnel (low volume of tests) or highly sophisticated expensive bulky central devices (big volume of tests). Both cases result in an increased price per test. Microfluidics offer several advantages over typical lab-oriented approaches.

- i) **Low sample volume.** In most microfluidics-based devices only one or two droplets of sample is needed which can be extracted with a finger prick. A typical example usually given is the commercially available glucose meter for diabetics.
- ii) **Inexpensive.** Medical diagnosis devices that involve human blood must be disposable to avoid cross contamination between samples. In the early days of microfluidics, these devices were made of glass with cleanroom microfabrication techniques. Therefore, the price per chip was relatively high, limiting the use of microfluidics. Recent advances in material science has provided us with inexpensive, high quality and mass producible polymers (such as Cyclic olefin copolymer (COC)) reducing the price per chip to a few cents.
- iii) **“Fast”.** Due to the small channel size in microfluidics, the surface to volume ratio is high resulting in fast analyte transport towards the surface. This is a critical aspect when it comes to immunoassays where the antigen must reach the antibody on the surface. In the case of bulk assays (*e.g.* in a well plate) the antibody antigen reaction is limited by mass transport; in microfluidics the assay can be operated in the reaction-limiting regime when the right conditions are applied¹⁵⁻¹⁷. The fast mass transport to the surface results in short sample-to-answer times.
- iv) **Highly controllable.** Due to the small size in microfluidics, the liquid velocity, electric field, chemical gradients and temperature can be controlled on the nano- to microscale, opening ways for new analysis methods.
- v) **Lab-on-a-chip.** Microfluidics have a small footprint making them ideal for POTC devices with no need for centralized diagnosis. Using the glucose meter example again, the diabetic can measure his glucose levels and regulate his medicine intake by himself, where in past regular visits to the physician were required.

1.4.2| Electrokinetic separations

Electrophoresis is the motion of charged particles or molecules relative to a fluid due to an applied electric field. The electrokinetic motion of particles was first reported by the Russians Strakhov and Reuss in 1807 more than two centuries ago¹⁸. Since then, countless research and applications have used electrophoresis. A google scholar search on “electrophoresis” returns more than 3.1 million scientific articles, abstracts and patents. Later capillary electrophoresis and gel electrophoresis proved to be powerful analytical tools. These techniques find wide applications in chemistry, biology and medicine. With the development of Lab-on-

a-chip systems (μ TAS^{19–21}), a vast amount of capillary and column electrokinetic separation methods were adapted to microfluidics, taking advantage of better heat dissipation and microscale control of flows and fields^{22–35}. Later techniques that combine concentration and separation were also adapted to microfluidics chips, such as isoelectric focusing, isotachopheresis, temperature-gradient focusing and field-amplified sample stacking^{36–41}.

In 2005 Wang *et al.*⁴² introduced a new focusing method and demonstrated concentration factors in the order of millions. The method was using the differential migration of charged species in an electric field gradient established via the phenomenon of ion concentration polarization (ICP). They named the method ion concentration polarization focusing (ICPF). Later Quist *et al.*⁴³ demonstrated also separation in a similar system. Focusing techniques such as isotachopheresis and isoelectric focusing require the application of specific electrolytes whose preparation can be a tedious process. In contrast in ICPF, the only electrolyte needed is the sample itself making the process very appealing for integration in medical devices. Hence ICPF was chosen for the concentration and separation of cardiac biomarkers for the Phocnosis project.

1.4.3| Ion concentration polarization focusing

For the mechanism of ICPF the reader is referred to Chapter 4 and to the recent work of Ouyang *et al.*⁴⁴. In this section the design choices for the ICPF devices will be discussed. The microfluidic chip was designed for integration in the Phocnosis project; hence specific requirements should be met:

- i) **Inexpensive.** A limit to the price of the cartridge was set to €2. The cartridge will include a photonic sensor and the antibodies for the assay, hence the price of the microfluidic system should be as low as possible. Polycarbonate and COC were chosen as materials and the chip design should be suitable for fabrication with hot embossing in which one of the consortium members is specialized.
- ii) **Suitable for operation with human serum.** The ICP phenomenon is strongly dependent on the salt concentration of the electrolyte. The ion perm-selective material/region needed for ICP should be selective in salt concentrations present in human serum.
- iii) **Tunable focusing position.** The biomarkers will be separated and concentrated via ICPF. The focusing location of the analytes should be tunable so that the analytes are concentrated on top of the photonic sensor.

Since its introduction, there are multiple designs for ICPF. The first type of design variation is in the ion perm-selective region required for the ICPF, where either nanochannels (microfabricated^{42,43,45} or via electrical breakdown of small junctions⁴⁶) or an ion perm-selective polymer (Nafion) is used. There are two disadvantages to the nanochannel approach. First, the microfabrication process is an expensive and non-trivial process. It is not applicable to polymers and not suitable for mass production. Second, the ion permselectivity of nanochannels in

high concentration electrolytes is limited. The permselectivity in nanochannels arises from the cationic species that are accumulated in the electric double layer due to the negative charge on the walls of the nanochannel (often SiO₂ walls). A typical measure of selectivity is the dimensionless Dukhin⁴⁷ number (Du) which is the ratio between surface ($G_S[S]$) and bulk ($G_B[S]$) conductance:

$$Du = \frac{G_S}{G_B} \quad (1.1)$$

Strong ion concentration polarization (ICP) effects have been reported for $Du > 1$ ^{48,49} despite the non-overlapping electric double layers of the nanochannel walls. Nevertheless, in order to achieve a $Du > 1$, a nanochannel with characteristic length of 2-5nm is required depending on the surface charge of the material. The fabrication of any feature at this scale is extremely challenging. For these two reasons we decided to work with ion selective polymers (Nafion) instead of microfabricated nanochannels⁵⁰. The polymer chains in Nafion form a complex network of nanopores. In addition, a high number of functional charged groups are typical present in the polymer. In Nafion there is one sulfonate group for every 21 water molecules^{51,52} making the molecule highly negatively charged in physiological pH (Figure 1.3). Many application of ICPF has been demonstrated using Nafion in high electrolyte concentration^{53,54}.

Figure 1.3 – Schematic of structure of Nafion. Nafion forms nanochannels out of hydrophobic tetrafluoroethylene (TFE) backbone. The hydrophobic tails are pointing towards the center of the channel and terminated by hydrophilic sulfonate groups. Figure adapted by⁵²

The second variation between the ICPF devices is in the way Nafion is introduced in the microfluidic device. Nafion resin is typically used in microfluidics which after evaporation of the resin solvents results in a solid Nafion membrane. One approach reported by Kim *et al.*⁵⁵ is to make a small cut between two channels in a poly(dimethylsiloxane) (PDMS) device and use the Nafion resin to seal the cut and create a vertical membrane between the channels (Figure 1.4). Although this approach results in high throughput through the Nafion membrane due to its large cross-sectional area, it is only applicable for soft polymers such as PDMS.

Figure 1.4 - Schematic of the self-sealing Nafion membrane. Figure adapted by ⁵⁵

Another approach is the fabrication of a planar Nafion membrane, where Nafion resin is either stamped or patterned on a glass substrate and the PDMS chip is bonded on top⁵⁰ (figure 1.5). This is the most popular approach found in research^{53,56,57} because of its simplicity and ease of use. Nevertheless, the planar Nafion membrane has a sub-micrometer thickness limiting the throughput of the applications. The determining reason for not using this method in the Phocnosis project is the requirement for an addition alignment step since the Nafion membrane, the fluidic chip and the photonic sensor must in the final production be aligned. The addition of an extra alignment step will make the process cumbersome and the intra-chip variation will be increased.

(a) Micro-stamping **(b) Micro-flow patterning**

Figure 1.5 – Fabrication methods of planar Nafion membrane. Figure adapted by ⁵⁰

The last method for fabrication of the Nafion membrane, which is the method we chose, is the patterning and pinning of the Nafion resin with capillary forces (Figure 1.6)⁵⁸. This method creates Nafion membranes with high cross-sectional area and with no need for an alignment step since the capillary valve location is integrated in the microfluidic design. In addition, the method is applicable to a wide variety of materials. A disadvantage of the method is that Nafion resin experiences significant shrinkage during the solvent evaporation, occasionally forming open microgaps between the separation channel and the buffer channels. In order to prevent hydrodynamic bulk flow through these gaps between the separation and buffer channels, we demonstrated that the buffer channels can be filled with agarose gel.

The last type of variation between ICPF devices is the electric actuation scheme. Either two or three electric potentials are used. In the case of the two point actuation (at the two reservoirs of the separation channel), the focusing location is determined by the electric resistance of the channel, unless an external pressure driven flow is applied through the system⁵³. Despite the simplicity of the operation scheme of this method, the tunability of the focusing locations is very limited. In the three point actuation (at the two reservoirs of the separation channel and at the reservoir of the buffer channels) the focusing location⁴³ and the analyte electrophoretic mobility window that ICPF can focus⁴⁵ is regulated by the three actuation potentials. The enhanced tunability of ICPF in the three-point actuation method was the decisive factor to choose for this method in the Phocnosis project.

Figure 1.6 - Schematic of capillary based patterning of Nafion. Figure adapted from ⁵⁸

1.5| Thesis outline

In **chapter 2** the phenomenon of ICP is investigated as single particle porosity differentiation tool. Mesoporous particles under an electric field can induce ICP due to their ion permselectivity. As described earlier, the selectivity is strongly dependent on the electrolyte concentration. A different particle with different porosity will have a different ICP response with respect to the electrolyte concentration. Hence the ICP can be used for differentiation of particle porosity.

As mentioned above, in our devices the Nafion resin is introduced and patterned via capillary forces. In **chapter 3** we propose a novel 3D capillary stop valve for patterning liquids in microfluidics chips. The proposed geometry is a combination of capillary stop valves and open microfluidics^{59,60}. To demonstrate its capabilities, we use the method for patterning of antibodies. A similar setup can be used for patterning phase change materials such as Nafion resin and hydrogels.

During the initial experiments for integration of the different technologies used by the various partners in the Phocnosis project two main challenges arose. First, while the functionality of antibodies was validated and quantified in controlled background (1x Phosphate buffer saline with 1% human blood serum), the results could not be replicated when the experiments were repeated in full human blood serum and even high concentrations (in the range mgL^{-1}) of cTn-I and cTn-T could not be detected. The second challenge was the effect of ICPF on the photonic sensor. The photonic sensor is fabricated in silicon and operates in the infrared range (1650nm). The electric field changes the optical properties (absorption and refractive index) of silicon due to the optoelectrical effect⁶¹ reducing the sensitivity of the sensor. Both challenges could in the future possibly be overcome by first concentrating and separating the analytes and then extract them and place them

on top of the antibody coated sensor. Several techniques to enable this are presented in this thesis.

In **chapters 4, 5, and 6** three different methods for extracting analytes in ICPF are proposed. In **chapter 4** two extraction channels are introduced in a typical ICPF setup and selective extraction of concentrated anionic analytes was demonstrated. The extracted analytes were concentrated 300 times but the throughput of sample was low (in the nL min^{-1} range).

In **chapter 5** we aim for a high-throughput ICPF variant in a free-flow format. In free-flow separation the analyte separation is perpendicular to the flow of the sample. We report a throughput in the $\mu\text{L min}^{-1}$ range while separating and concentrating the analytes up to 17 times in human blood serum.

In the approaches presented in chapters 4 and 5 the extracted analytes are prone to diffusion which will reduce the achieved concentration factors. In **chapter 6** we propose the integration of a droplet generator which is able to package analytes in highly concentrated droplets (up to 100 times concentration is demonstrated). The droplet generator is able to operate as a droplet-on-demand or continuous generator without the need for active elements such as valves and without interfering with the ICPF process.

In all our experiments and most of the reported work in literature the ICPF process is monitored by fluorescent analytes. This approach is not feasible in the Phocnosis project where a POCT device will be used for automating the ICPF process. In **chapter 7** we propose a method to control and predict the focusing location of analytes in the chip by monitoring the electric current through the microfluidic system. Current monitoring has been used in other electrokinetic methods and is highly integrable and suitable for automation of the ICPF process.

Finally, in **chapter 8** we summarize the work that was done in this thesis and we give recommendations for future work.

1.6| References

1. World Health Data Exchange. Available at: <http://ghdx.healthdata.org/gbd-results-tool>.
2. European Heart Network / European Society of Cardiology. *European Cardiovascular Disease Statistics*. (2012).
3. Gaze, D. C. & Collinson, P. O. Cardiac troponin I but not cardiac troponin T adheres to polysulfone dialyser membranes in an in vitro haemodialysis model: Explanation for lower serum cTnI concentrations following dialysis. *Open Hear.* **1**, (2014).
4. Kerr, G., Ray, G., Wu, O., Stott, D. J. & Langhorne, P. Elevated troponin after stroke: A systematic review. *Cerebrovascular Diseases* (2009). doi:10.1159/000226773
5. Sheng, J. J. & Jin, J. P. Gene regulation, alternative splicing, and posttranslational modification of troponin subunits in cardiac development and adaptation: A focused review. *Frontiers in Physiology* **5 APR**, (2014).
6. Protein Calculator v3.4. Available at: <http://protcalc.sourceforge.net/>.
7. Kobayashi, T., Yang, X., Walker, L. A., Van Breemen, R. B. & Solaro, R. J. A

- non-equilibrium isoelectric focusing method to determine states of phosphorylation of cardiac troponin I: Identification of Ser-23 and Ser-24 as significant sites of phosphorylation by protein kinase C. *J. Mol. Cell. Cardiol.* **38**, 213–218 (2005).
8. Peronnet, E., Becquart, L., Martinez, J., Charrier, J. P. & Jolivet-Reynaud, C. Isoelectric point determination of cardiac troponin I forms present in plasma from patients with myocardial infarction. *Clin. Chim. Acta* **377**, 243–247 (2007).
 9. Jacroux, T., Bottenus, D., Rieck, B., Ivory, C. F. & Dong, W. J. I. Cationic isotachopheresis separation of the biomarker cardiac troponin I from a high-abundance contaminant, serum albumin. *Electrophoresis* **35**, 2029–2038 (2014).
 10. Zhang, J. *et al.* Top-down quantitative proteomics identified phosphorylation of cardiac troponin i as a candidate biomarker for chronic heart failure. *J. Proteome Res.* **10**, 4054–4065 (2011).
 11. Perry, S. V. Troponin T: Genetics, properties and function. *Journal of Muscle Research and Cell Motility* **19**, 575–602 (1998).
 12. Khoury, G. A., Baliban, R. C. & Floudas, C. A. Proteome-wide post-translational modification statistics: Frequency analysis and curation of the swiss-prot database. *Sci. Rep.* **1**, (2014).
 13. Solaro, R. J., Rosevear, P. & Kobayashi, T. The unique functions of cardiac troponin I in the control of cardiac muscle contraction and relaxation. *Biochem. Biophys. Res. Commun.* **369**, 82–87 (2008).
 14. Apple, F. S. Standardization of cardiac troponin i assays will not occur in my lifetime. *Clinical Chemistry* **58**, 169–171 (2012).
 15. Squires, T. M., Messinger, R. J. & Manalis, S. R. Making it stick: convection, reaction and diffusion in surface-based biosensors. *Nat. Biotechnol.* **26**, 417–426 (2008).
 16. Delamarche, E., Juncker, D. & Schmid, H. Microfluidics for processing surfaces and miniaturizing biological assays. *Advanced Materials* **17**, 2911–2933 (2005).
 17. Gervais, T. & Jensen, K. F. Mass transport and surface reactions in microfluidic systems. *Chem. Eng. Sci.* (2006). doi:10.1016/j.ces.2005.06.024
 18. Reuss, F. F. Sur un Nouvel Effet de l'electricite Galvanique. *Mem. Soc. Imp. Natur. Moscou* **2**, 327–337 (1809).
 19. Manz, A., Graber, N. & Widmer, H. M. Miniaturized total chemical analysis systems: A novel concept for chemical sensing. *Sensors Actuators B. Chem.* (1990). doi:10.1016/0925-4005(90)80209-I
 20. *Microsystem Technology in Chemistry and Life Science.* (1998). Ed. A.Manz and H. Becker, doi:10.1007/3-540-69544-3
 21. Verpoorte, E. *et al.* A silicon flow cell for optical detection in miniaturized total chemical analysis systems. *Sensors Actuators B. Chem.* (1992). doi:10.1016/0925-4005(92)80032-S
 22. Manz, A. & Becker, H. Parallel capillaries for high throughput in electrophoretic separations and electroosmotic drug discovery systems. in (2002). doi:10.1109/sensor.1997.635251

23. Manz, A. *et al.* Planar chips technology for miniaturization and integration of separation techniques into monitoring systems. Capillary electrophoresis on a chip. *J. Chromatogr. A* (1992). doi:10.1016/0021-9673(92)80293-4
24. Giddings, J. C. *Unified Separation Science*. (John Wiley & Sons, 1991).
25. Harrison, D. J., Manz, A., Lüdi, H., Widmer, H. M. & Fan, Z. Capillary Electrophoresis and Sample Injection Systems Integrated on a Planar Glass Chip. *Anal. Chem.* (1992). doi:10.1021/ac00041a030
26. Burggraf, N., Manz, A., de Rooij, N. F. & Widmer, H. M. Synchronized cyclic capillary electrophoresis: a novel concept for high-performance separations using low voltages. *Anal. methods & Instrum.* (1993).
27. Lichtenberg, J., de Rooij, N. F. & Verpoorte, E. A microchip electrophoresis system with integrated in-plane electrodes for contactless conductivity detection. *Electrophoresis* (2002). doi:10.1002/1522-2683(200211)23:21<3769::AID-ELPS3769>3.0.CO;2-E
28. Khandurina, J., Jacobson, S. C., Waters, L. C., Foote, R. S. & Ramsey, J. M. Microfabricated porous membrane structure for sample concentration and electrophoretic analysis. *Anal. Chem.* **71**, 1815–1819 (1999).
29. Ramsey, J. D., Jacobson, S. C., Culbertson, C. T. & Ramsey, J. M. High-efficiency, two-dimensional separations of protein digests on microfluidic devices. *Anal. Chem.* (2003). doi:10.1021/ac0264574
30. Shadpour, H. *et al.* Multichannel microchip electrophoresis device fabricated in polycarbonate with an integrated contact conductivity sensor array. *Anal. Chem.* (2007). doi:10.1021/ac0612168
31. Paegel, B. M., Hutt, L. D., Simpson, P. C. & Mathies, R. A. Turn geometry for minimizing band broadening in microfabricated capillary electrophoresis channels. *Anal. Chem.* (2000). doi:10.1021/ac000054r
32. Fiechtner, G. J. & Cummings, E. B. Faceted design of channels for low-dispersion electrokinetic flows in microfluidic systems. *Anal. Chem.* (2003). doi:10.1021/ac0207776
33. Shackman, J. G., Munson, M. S. & Ross, D. Gradient elution moving boundary electrophoresis for high-throughput multiplexed microfluidic devices. *Anal. Chem.* (2007). doi:10.1021/ac061759h
34. Kirby, B. J. & Hasselbrink, E. F. Zeta potential of microfluidic substrates: 1. Theory, experimental techniques, and effects on separations. *Electrophoresis* **25**, 187–202 (2004).
35. Hanlan, J., Skoog, D. A. & West, D. M. Principles of Instrumental Analysis. *Stud. Conserv.* (2006). doi:10.2307/1505543
36. Osbourn, D. M., Weiss, D. J. & Lunte, C. E. On-line preconcentration methods for capillary electrophoresis. in *Electrophoresis* (2000). doi:10.1002/1522-2683(20000801)21:14<2768::AID-ELPS2768>3.0.CO;2-P
37. Shihabi, Z. K. Field amplified injection in the presence of salts for capillary electrophoresis. in *Journal of Chromatography A* (1999). doi:10.1016/S0021-9673(99)00316-7
38. Herr, A. E. *et al.* On-chip coupling of isoelectric focusing and free solution electrophoresis for multidimensional separations. *Anal. Chem.* (2003). doi:10.1021/ac026239a

39. Jung, B., Bharadwaj, R. & Santiago, J. G. Thousandfold signal increase using field-amplified sample stacking for on-chip electrophoresis. *Electrophoresis* (2003). doi:10.1002/elps.200305611
40. Rickwood, D. Isoelectric Focusing: Theory, Methodology and Applications. *FEBS Lett.* (1983). doi:10.1016/0014-5793(83)80998-3
41. Chen, L. *et al.* Miniaturised isotachopheresis analysis. *Lab on a Chip* (2006). doi:10.1039/b515551g
42. Wang, Y. C., Stevens, A. L. & Han, J. Million-fold preconcentration of proteins and peptides by nanofluidic filter. *Anal. Chem.* (2005). doi:10.1021/ac050321z
43. Quist, J., Janssen, K. G. H., Vulto, P., Hankemeier, T. & Van Der Linden, H. J. Single-electrolyte isotachopheresis using a nanochannel-induced depletion zone. *Anal. Chem.* **83**, 7910–7915 (2011).
44. Ouyang, W., Ye, X., Li, Z. & Han, J. Deciphering ion concentration polarization-based electrokinetic molecular concentration at the micro-nanofluidic interface: theoretical limits and scaling laws. *Nanoscale* (2018). doi:10.1039/c8nr02170h
45. Quist, J., Vulto, P., Van Der Linden, H. & Hankemeier, T. Tunable ionic mobility filter for depletion zone isotachopheresis. *Anal. Chem.* **84**, 9065–9071 (2012).
46. Jeong, H. L., Chung, S., Sung, J. K. & Han, J. Poly(dimethylsiloxane)-based protein preconcentration using a nanogap generated by junction gap breakdown. *Anal. Chem.* (2007). doi:10.1021/ac071162h
47. Dukhin, S. S. & Shilov, V. N. *Kolloidn. Zh.* 706–713 (1969).
48. Goosen, M. F. A. *et al.* Fouling of reverse osmosis and ultrafiltration membranes: A critical review. *Separation Science and Technology* (2004). doi:10.1081/SS-120039343
49. Zangle, T. A., Mani, A. & Santiago, J. G. On the propagation of concentration polarization from microchannel-nanochannel interfaces. Part II: Numerical and experimental study. *Langmuir* **25**, 3909–3916 (2009).
50. Lee, J. H., Song, Y. A. & Han, J. Multiplexed proteomic sample preconcentration device using surface-patterned ion-selective membrane. *Lab Chip* (2008). doi:10.1039/b717900f
51. Mauritz, K. A. & Moore, R. B. State of Understanding of Nafion. *Chem. Rev.* (2004). doi:10.1021/cr0207123
52. Schmidt-Rohr, K. & Chen, Q. Parallel cylindrical water nanochannels in Nafion fuel-cell membranes. *Nat. Mater.* (2008). doi:10.1038/nmat2074
53. Ko, S. H. *et al.* Nanofluidic preconcentration device in a straight microchannel using ion concentration polarization. *Lab Chip* **12**, 4472 (2012).
54. Kim, M., Wu, L., Kim, B., Hung, D. T. & Han, J. Continuous and High-Throughput Electromechanical Lysis of Bacterial Pathogens Using Ion Concentration Polarization. *Anal. Chem.* (2018). doi:10.1021/acs.analchem.7b03746
55. Sung, J. K. & Han, J. Self-sealed vertical polymeric nanoporous-junctions for high-throughput nanofluidic applications. *Anal. Chem.* **80**, 3507–3511 (2008).

56. Kim, S. J., Ko, S. H., Kang, K. H. & Han, J. Direct seawater desalination by ion concentration polarization. *Nat. Nanotechnol.* (2010). doi:10.1038/nnano.2010.34
57. Chen, Y. Y., Chiu, P. H., Weng, C. H. & Yang, R. J. Preconcentration of diluted mixed-species samples following separation and collection in a micro-nanofluidic device. *Biomicrofluidics* **10**, (2016).
58. Liu, V., Song, Y.-A. & Han, J. Capillary-valve-based fabrication of ion-selective membrane junction for electrokinetic sample preconcentration in PDMS chip. *Lab Chip* **10**, 1485 (2010).
59. Berthier, J., Brakke, K. A. & Berthier, E. *Open Microfluidics*. (Scrivener Publishing, 2016).
60. Casavant, B. P. *et al.* Suspended microfluidics. *Proc. Natl. Acad. Sci.* **110**, 10111–10116 (2013).
61. Soref, R. A. & Bennett, B. R. Electrooptical effects in silicon. *IEEE Journal of Quantum Electronics* (1987). doi:10.1109/JQE.1987.1073206

Chapter 2

Ion Concentration Polarization for MicroParticle Mesoporosity Differentiation

Microparticle porosity is normally determined in a bulk manner providing an ensemble average that hinders establishing the individual role of each microparticle. On the other hand, single particle characterization implies expensive technology. We propose to use ion concentration polarization to measure differences in mesoporosity at single particle level. Ion concentration polarization occurs at the interface between an electrolyte and a porous particle when an electric field is applied. The extent of ion concentration polarization depends, amongst others, on the mesopore size and density. By using a fluorescence marker we could measure differences in concentration polarization between particles with 3 nm and 13 nm average mesopore diameters. A qualitative model was developed in order to understand and interpret the phenomena. We believe that this inexpensive method could be used to measure differences in mesoporous particle materials such as catalysts.

This chapter is based on the publication: Miguel Solsona⁺, Vasileios A. Papadimitriou⁺, Wouter Olthuis, Albert v.d. Berg and Jan C. T. Eijkel. "Ion Concentration Polarization for MicroParticle Mesoporosity Differentiation " *Langmuir* 2019, + Both authors contributed equally. <https://doi.org/10.1021/acs.langmuir.9b00802>.

2.1| Introduction

Porous materials are key components in many fields that rely on their void volume, network distribution, and pore size and shape.¹⁻³ They are particularly interesting in applications such as: catalysis, supercapacitors, fuel cells and batteries, due to their unique interaction with atoms, ions and molecules at the nanometer and sub-nanometer scale. In chemistry, in particular heterogeneous catalysis, the porosity of solid materials is normally used to enhance the available area in contact with reagents and products, thus increasing the activity per unit volume.⁴ In practice a porous catalyst is used or a catalyst support with immobilized nanoparticles. However, small differences in the porosity of these materials can cause large variations in mass transport of reagents through the pores which can result in a reduction or even loss of catalyst activity.⁵⁻⁷ Normally, these catalysts or catalyst supports are fabricated in batch reactors in a non-controlled but reproducible manner, resulting in large inter- and intra-particle heterogeneities.

Nanopores are generally subdivided into three groups depending on the pore dimensions: micro (<2nm), meso (2-50nm) and macropores (>50nm). There are many techniques available to measure the pore size distribution of nanoporous materials, where the most popular ones are based on gas adsorption, fluid intrusion, microscopy and spectroscopy^{5,8-12}. The Brunauer-Emmett-Teller (BET) method uses the adsorption of chemically inert gases on the porous material walls to determine the available surface area in the volume measured.¹³ The pore size distribution can also be derived from the pressure needed to drive flow of fluids such as Hg into the porous media.¹⁴ Both methods are widely used but the volumes of porous material needed are large, providing an ensemble averaged porosity instead of the porosity of single microparticles. For the latter, amongst others, Scanning Electron Microscopy (SEM) and X-Ray diffraction are used to determine meso- and macroporosity at single microparticle level. These methods, however, imply the use of expensive technology and can study only very small quantities.^{7,15,16} Therefore, new ways to measure the porosity of particles at the single-particle level are needed in order to understand and increase the efficiency of porous systems. In this study, Ion Concentration Polarization (ICP) is used to measure the mesoporosity at single particle level. ICP occurs at the interfaces of an ion-permselective material and free solution on application of an electrical field.¹⁷⁻²⁰ It results in the formation of ion accumulation and depletion zones at the opposite sides of the material due to the ion flux imbalance between free solution and inside the particle, see Figure 2.1a. Porous materials become ion-permselective when their pore dimensions are of the order of the electrical double layer thickness at the pore walls (typically nanometer scale).

Here, we propose to use ICP in a microfluidic system to analyze the mesoporosity of two types of porous polystyrene particles with different mesoporosities. We first present an approximative theory describing ICP at single particle level. Then, we show measurements and analysis of the ICP experimental fluorescent response of both types of particles at different electrolyte concentrations using a fluorescent dye marker with constant concentration.

Figure 2.1 - (a) Schematic of ICP at a cation-selective porous particle. The depletion and accumulation zones are indicated. (b) Schematic of the porous particle under an electric field. ICP occurs as a result of the ion flux imbalance at the particle /solution interfaces as shown by the flux vectors and the electrical transport numbers τ in the particle and solution. At the anodic side, a depletion zone is formed close to the interface of the particle while an enrichment zone is formed at the cathodic side. For simplicity a solution is assumed with a 1:1 electrolyte.

2.2| Theory

Figure 2.1b shows the mechanism of ICP, occurring when a uniform electric field is applied across a porous ion-permselective particle. ICP occurs when a difference exists in the fraction of the current that is carried by the different ionic species in particle and bulk solution, and involves gradients in the migration and diffusion fluxes. The ion permselectivity of the particles is caused by the difference in ionic concentration composition in the mesopores and the bulk. Assuming negative surface charge on the pore walls, more cations are present in the solution in the pores due to electroneutrality, and therefore more current will be carried by the cations in the pores than by the anions when compared to the bulk solution. A depletion zone, where the concentrations of all ionic species will be lower than in

the bulk, will then form at the anodic side of the particle (left side on Figure 2.1b). An accumulation zone, where the concentration of all ionic species will be higher than in the bulk, will form on the cathodic side (right side on Figure 2.1b). In the depletion and accumulation zones additional diffusion fluxes maintain a steady-state constant flux of cations and anions. In order to quantify the extent of ICP we use a fluorescent reporter ion and measure the difference of its fluorescent intensity in the depletion and accumulation zones during 4 sec over several alternating potential cycles assuming a linear relation between fluorescent intensity and concentration of the reporter. NaCl is used as bulk electrolyte salt (diffusion coefficients of $1.374 \cdot 10^{-5} [\text{cm}^2\text{s}^{-1}]$ and $1.957 \cdot 10^{-5} [\text{cm}^2\text{s}^{-1}]$ ²¹ for Na and Cl respectively and electrophoretic mobilities calculated with Einstein's relation). We will first theoretically derive the concentration profile of our fluorescent reporter bodipy disulfonate (BDP^{2-}) in the solution as a function of time and distance from the particle surface ($C_{\text{BDP}}(x, t)$), in an approach similar to Bergveld et al.²²

As our theoretical model is designed only to estimate a qualitative behavior of our system, a series of strong assumptions are made: i) The model is one-dimensional, ii) the convective flux (electroosmotic flow) can be neglected, iii) the particle pores are assumed to be perfectly cylindrical running the whole length of the particle, iv) the particle is assumed to be rectangular with a length equal to the diameter of the real particle, v) the particle is assumed to be a square part of a continuous membrane, with uniform non-crossing cylindrical mesopores passing through it, vi) the concentration distribution at the enrichment and depletion zone does not affect the local electric field, and vii) the diffusive flux inside the particle is neglected.

2.2.1| Nernst Planck

To calculate the concentrations of BDP^{2-} ($C_{\text{BDP}}(x, t)$), we will use the *one-dimensional* Nernst-Planck flux equations. The current density ($j[\text{Am}^{-2}]$), the local conductivity ($\kappa[\text{Sm}^{-1}]$) and the local electric field ($E[\text{Vm}^{-1}]$) are related by

$$\kappa(x, t)E(x, t) = j(2.1).$$

We will first consider the transport of BDP^{2-} in the electrolyte bordering the particle. Ignoring the convective flux contribution to the Nernst-Planck equation (hereby included electroosmotic flow), we can write the flux J^e of BDP^{2-} in the electrolyte as composed of a migration and a diffusion term,

$$J_{\text{BDP}}^e(x, t) = -\frac{\tau_{\text{BDP}}^e j}{F} - D \frac{\partial C_{\text{BDP}}^e(x, t)}{\partial x} (2.2),$$

where τ_{BDP}^e is the dimensionless transport number of BDP^{2-} in the electrolyte, F the faraday constant and $D[\text{m}^2\text{s}^{-1}]$ the diffusion coefficient of BDP^{2-} . By applying the continuity equation

$$\frac{\partial C_{\text{BDP}}^e(x, t)}{\partial t} = -\frac{J_{\text{BDP}}^e(x, t)}{dx} (2.3)$$

and realizing that the migration term in the electrolyte is constant in x , we arrive at

$$\frac{\partial C_{BDP}^e(x, t)}{\partial t} = D \frac{\partial^2 C_{BDP}^e(x, t)}{\partial x^2} \quad (2.4).$$

We then consider the transport of BDP^{2-} in the particle. Assuming no concentration gradient inside the particle, therefore only a migration contribution, the BDP^{2-} flux in the particle equals

$$J_{BDP}^p(0, t) = -\frac{\tau_{BDP}^p j}{F} \quad (2.5),$$

We solve Equation 2.4 using the following boundary conditions

- At $x = \infty$, at any t , $C_{BDP}^e(\infty, t) = C_{BDP}^B$ (2.6)
- At $t = 0$, at any x , $C_{BDP}^e(x, 0) = C_{BDP}^B$ (2.7)
- At $x = 0$, at $t \neq 0$, $\frac{\partial C_{BDP}^e(0, t)}{\partial x} = -\frac{j(\tau_{BDP}^p - \tau_{BDP}^e)}{FD}$ (2.8).

Here $x = 0$ is the location of the particle/solution interface at the cathodic side of the particle and $x = \infty$ is a sufficient distance away from this point where there is no effect of the particle hence the BDP^{2-} concentration retains its initial bulk value (C_{BDP}^B). Equation 2.8 simply expresses the conservation of mass for the fluxes crossing the plane at $x = 0$. The result is ²³,

$$C_{BDP}^e(x, t) = C_{BDP}^B - \frac{j(\tau_{BDP}^p - \tau_{BDP}^e)}{FD} \left\{ 2 \left(\frac{Dt}{\pi} \right)^{\frac{1}{2}} \exp \left(-\frac{x^2}{4Dt} \right) - x \operatorname{erfc} \left(\frac{x}{2(Dt)^{\frac{1}{2}}} \right) \right\} \quad (2.9),$$

where erfc is the complementary error function. In equation 2.9 the variables,

- Current density (j)
- Transport numbers ($\tau_{BDP}^e, \tau_{BDP}^p$),

depend on the electrolyte bulk salt concentration and the particle pore size, and we will investigate them separately in the following subsections.

2.2.2| Transport numbers τ

The difference of BDP^{2-} transport numbers between electrolyte and particle ($\tau_{BDP}^p - \tau_{BDP}^e$) indicates the ion permselectivity of the particle towards BDP^{2-} . We thus will derive the transport numbers of BDP^{2-} in the electrolyte and in the particle. The ion transport number (τ_i) of a species i is defined as the fraction of the total electric current density (j) carried by this species. In the electrolyte the transport number for BDP^{2-} equals

$$\tau_{BDP}^e = \frac{2c_{BDP}^e D_{BDP}}{\sum |z_i| c_i^e D_i} (2.10).$$

In the particle we use the same equation but now with the area-averaged concentration of BDP⁻² in the mesopore

$$\tau_{BDP}^p = \frac{2c_{BDP}^p D_{BDP}}{\sum |z_i| c_i^p D_i} (2.11).$$

In order to calculate the concentration in the pore we must account for the concentration distribution of the species in the electric double layer. We will follow the approach of Rice and Whitehead²⁴ who solved the Poisson-Boltzmann equations for a circular mesopore. Starting from the 1D Poisson equation for radial coordinates,

$$\nabla^2 \psi = -\frac{\rho(r)}{\epsilon_0 \epsilon_r} (2.12),$$

where $\psi[V]$ is the local electric potential, $r[m]$ is the distance from the pore center, ϵ_0 and ϵ_r are the vacuum and medium permittivity and $\rho[C/m^3]$ is the local electric space charge density which is defined as,

$$\rho(r) = \sum e z_i c_i(r) (2.13).$$

The concentration of the ions follows the Boltzmann distribution,

$$c_i(r) = c_i^p \exp\left(-\frac{z_i e \psi(r)}{k_B T}\right) (2.14),$$

where $c_i^p [mol/m^3]$ is the pore electrolyte concentration of species i , $e[C]$ the electron charge, K_B the Boltzmann constant and $T[K]$ the absolute temperature. It is worth mentioning that for c_i^p the bulk concentration of the species is used which doesn't hold for overlapping double layers. Hence, at low concentrations the results should be taken tentatively.

For $\psi \leq k_B T/e$,

$$\frac{1}{r} \frac{\partial}{\partial r} \left(r \frac{\partial \psi}{\partial r} \right) = \frac{\psi(r)}{\lambda_D} (2.15),$$

where λ_D is the Debye length^{25,26}.

$$\lambda_D = \sqrt{\frac{\epsilon_0 \epsilon_r R T}{2 F^2 c^e}} (2.16).$$

We use an approach similar to Taghipoor et al.²⁷ for the determination of the surface charge density ($\sigma [C/m^2]$). We then use the Grahame equation (Equation 2.17) for the determination of surface potential ($\psi_0 [V]$) and equation 2.18 for the relation between the surface potential and zeta potential, the potential at the slipping plane.

$$\sigma = \sqrt{8c_i^p N_A \epsilon \epsilon_0 k_b T} \sinh\left(\frac{ze\psi_0}{2k_B T}\right) \quad (2.17),$$

$$\psi_0 - \zeta = \frac{\sigma}{C_{stern}} \quad (2.18),$$

where $N_A [mol^{-1}]$ is the Avogadro number and $C_{stern} [F/m^2]$ is the specific Stern layer capacitance. Equation 2.15 is then analytically solved for the potential distribution in the diffuse double layer²⁸,

$$\psi(r) = \zeta \frac{I_0\left(\frac{r}{\lambda_D}\right)}{I_0\left(\frac{r_0}{\lambda_D}\right)} \quad (2.19),$$

where I_0 is the zero-order modified Bessel function of the first kind.

From equations 2.14 and 2.19 we can estimate the average BDP²⁻ concentration inside the mesopore. We subsequently calculate the BDP²⁻ transport number in the mesopore (Equation 2.11) by integrating $C_{BDP}^p(r)$ over the pore cross-sectional area. Figure 2.2 shows the transport numbers of BDP²⁻ in the electrolyte and particle as a function of bulk electrolyte concentration using the average mesopore size determined by BET measurements (Table 2.1). At low electrolyte concentrations, the concentration of BDP²⁻ in the particle is extremely low compared to the total ion concentration (especially cation concentration) since the electric double layers overlap and BDP²⁻ is almost completely excluded from both small and large mesopores. At high electrolyte concentrations the electric double layer is extremely thin and the average species concentration is almost the same as the bulk concentration. The larger diameter pores approach this state at much lower electrolyte concentrations than the smaller pores.

Figure 2.2 - Transport number of BDP²⁻ in the particle vs electrolyte concentration. Black - transport number in the electrolyte, blue - in the larger pores and red - in the smaller pores.

2.2.3| Current density j

To determine the magnitude of this E-field, we need to consider our experimental system. In the CP model of sections 2.2.1 and 2.2.2, the porous particle was modeled as part of a continuous membrane. During the experiments however, separate particles are placed at the bottom of a microfluidic channel and a constant potential is applied at the two reservoirs connected to this channel. The E-field across the particle will then depend on the conductance ratio between particle and its surrounding electrolyte. Now when we vary the electrolyte concentration, the particle conductance scales differently from the electrolyte conductance, creating a dependency of the E-field across the particle on the electrolyte concentration. An equivalent 1D macroscopic electrical circuit is therefore needed to calculate the E-field as a function of concentration, and is shown in Figure 2.4a. From the total system conductance, the separated conductance of the electrolyte and the particle, and the applied voltage we can then calculate the potential drop over and hence the E-field across the particle.

We assume that a constant and uniform electric field (E) exists inside the particle, i.e. the concentration distribution of the ions in the electrolyte close to the particle surface does not affect the local electric field inside the particle. The current density (j) through the particle then equals

$$j = E\kappa(2.20),$$

where κ is the area-averaged conductivity of the particle. The area-averaged conductivity of a single mesopore (κ_c) equals²⁷

$$\kappa_c = \frac{N_A e}{r_0} \sum_i \int_0^{r_0} \mu_i c_i(r) dr \quad (2.19),$$

where $c_i(r)$ was calculated as in the previous section. The electric conductance ($G_c[S]$) of a single mesopore then is

$$G_c = \frac{A \kappa_c}{d} \quad (2.20),$$

where $d[m]$ is the diameter of the particle (mesopore length) and $A[m^2]$ is the cross-sectional area of the mesopore. Figure 2.3 shows the conductivity of a single mesopore of the two kinds of particles, using the average mesopore size determined by BET measurements (Table 2.1). As expected, the smaller mesopore shows a higher conductivity.

We calculate the total conductance of a particle (G_p) from the total number of mesopores (N) per particle, treating them as parallel conductors

$$G_p = N G_c \quad (2.21).$$

For the calculation of N we use the specific pore volume ($V_s[m^3/g]$) or specific pore surface area ($A_s[m^2/g]$) and the density ($\rho[g/m^3]$) values found via BET and pycnometer methods, as will be explained in the experimental section,

$$N = \frac{\rho V_{particle} V_s}{V_{pore}} \quad (2.22),$$

or

$$N = \frac{\rho V_{particle} A_s}{A_{pore}} \quad (2.25),$$

where $V_{particle}[m^3]$ is the volume of the particle and $V_{pore}[m^3]$ and $A_{pore}[m^2]$ are the volume and surface area of a single mesopore.

Figure 2.3 - Single mesopore conductivity vs salt concentration – Eq. 2.20-22. The surface charge density dependence to the concentration was taken from M. Taghipoor et al²⁷. For high concentration where the double layer thickness is small compared to the mesopore width, the mesopore conductivity follows the bulk conductivity. In contrast at low concentrations the electric double layer thickness is similar to the channel diameter and the surface conductivity provides the dominant contribution. The negative slope in the conductivity is an effect of a combination of the surface charge density dependency on concentration and the EDL size and overlap in respect to concentration. A similar trend was seen at M. Taghipoor et al²⁷.

Figure 2.4b shows that the E-field remains relatively constant when the particle/pore conductivity is equal to the bulk conductivity. Once the bulk electrolyte concentration drops and the surface conductivity becomes the dominant conductivity contribution in the mesopore, the particle resistance increases slower than the resistance of the surrounding electrolyte resulting in a lower voltage drop and E-field across it. Now knowing the conductivity and the E-field as a function of bulk concentration and mesopore size we can calculate the current density via Equation 2.20.

Once the current density and transports numbers ($\tau_{BDP}^p - \tau_{BDP}^e$) are determined, Equation 2.9 can be used to describe the temporal concentration profile of the fluorescent reporter, BDP²⁻, as a function of distance from the surface of the particle ($C_{BDP}(x, t)$) in the enrichment zone. Figure 2.5a shows the calculated average BDP²⁻ concentration of both particles over a distance of 25 μm in the bulk electrolyte over 4 seconds and at the edge of the particle (see Figure 2.5b). The shape of the graph is dominated by the value of the product $j(\tau_{BDP}^p - \tau_{BDP}^e)$ in Equation 2.9, representing the particle ion-permselectivity. At low concentrations, the cation permselectivity is maximal, hence the accumulation is governed by the conductance of the mesopores, with the larger pores being more conductive because of the larger pore volume. However, these pores lose their selectivity

faster compared to the smaller pores as the bulk salt concentration increases. The two lines therefore cross, in the model at a bulk electrolyte concentration of 14mM. In addition, at low concentrations the resistance of the particle is approximately two orders of magnitude lower than the resistance of the channel. Hence the resistance of the microchannel (Figure 2.4a) regulates the current through the system and particle resulting in the flattening of the BDP concentration at low concentration at Figure 2.5a.

Figure 2.4 - (a) Equivalent circuit to calculate the electric field across the particle with varying electrolyte concentration. (b) At high concentrations the particle resistance is high compared to the electrolyte resulting in an E-field across the particle that is weakly dependent of the concentration. At low concentration the particle resistance will increase slower compared to the bulk resistance resulting in a lower E-field in the particle.

Figure 2.5 - (a) Averaged BDP²⁻ concentration at different electrolyte concentrations on the enrichment side of the particle over 4 sec over 25 μm from the particle/electrolyte interface (as shown in b).

2.3| Experimental

A PDMS microfluidic chip was fabricated by standard photolithographic techniques. First, a 200 μm SU8 layer was spun and baked on a 4-inch silicon wafer. Next, the photoresist was exposed for 50 seconds to UV light and developed. The chip design consisted of a straight channel 200 μm height, 1 mm wide and 2 cm

long, connecting two reservoirs. Polystyrene particles 50 μm in diameter with two meso-pore sizes (10 and 50 nm) were purchased at Chromospheres.com. Particles were submerged in ethanol and, with a pipette, they were deposited one by one on the PDMS channel. Thereafter, the PDMS with the particles were plasma treated for 40 seconds and bonded to a glass slide. The polystyrene particles were therefore stuck to the PDMS and sufficiently spaced between them in order to avoid interaction of the fluorescent reporter. A microscope Olympus IX51 and camera Grasshopper 3 were used with a Hg lamp for the fluorescent microscopy. Two platinum wires were used to connect the power supply (Keithley 2410) to the electrolyte solution at the reservoirs. BODIPYTM 492/515 Disulfonate (BDP²⁻) (ThermoFisher) and phosphate buffered saline solution (PBS)(Sigma-Aldrich) were used as a fluorescent molecule and background electrolyte respectively. The PBS concentrations used were 10^{-4} , 10^{-3} , 10^{-2} , $2.5 \cdot 10^{-2}$, $5.0 \cdot 10^{-2}$, $7.5 \cdot 10^{-2}$ and 10^{-1} M while the concentration of BDP²⁻ was 750 nM in all experiments. Matlab and ImageJ were used to analyze the experimental data. Matlab was used to simulate the model. The power supply was operated via LabView software. BET and density measurements were performed in a Gemini VII from Micromeritics and AccuPyc II 1340 Micromeritics pycnometer, respectively. The ICP was measured by applying a step function of ± 100 V across the channel, and performing 4 cycles of 4 seconds each. During the experimental data analysis, a linear drop of fluorescence intensity in the bulk, which we assumed to be caused by the marker photobleaching, was observed and compensated for.

Figure 2.6 - SEM images of both types of polystyrene particles.

2.4| Results and discussion

Figure 2.6 shows SEM images of both types of polystyrene particles showing a clear difference in pore size distribution. To measure the average pore size as well as the pore volume, surface area and density, BET and pycnometer measurements were performed, with the results summarized in Table 2.1. A clear difference between both types of particles can be observed, with both having pores in the mesoporosity size range. Also, the similar pore volume indicates that the particles with smaller pores have more pores per unit volume.

Figure 2.7a shows an image of a typical concentration polarization measurement of a particle with an accumulation zone on the cathodic side and a depletion zone on the anodic side. The area- and time-averaged fluorescence intensity at both sides of a particle was measured as illustrated in Figure 2.7a. Equation 2.9 describes the spatiotemporal concentration profile of Bodipy, assuming a 1-dimensional system. At any moment in time the magnitude of the concentration depletion and accumulation of Bodipy depends on the difference in Bodipy flux in the particle and in the solution, and hence on the particle properties that determine the Bodipy transport numbers in both. As this is true for all times and all locations adjacent to the particle, averaging the concentration difference over time and space keeps the essence of this information intact. The data thus validate the model in a qualitative In future a 3D simulation model could be constructed that is expected to provide more quantitative information. Figure 2.7b shows a typical experimental fluorescent intensity obtained in one positive and negative pulse.

Table 2.2. - Average pore radius, pore volume, surface area and density of both types of polystyrene particles.

Property	Method	Larger pores	Smaller pores
Average pore radius (r)	BET	13 nm	3.5 nm
Total pore volume (Vs)	BET	$1.9 \cdot 10^{-6} \text{ m}^3/\text{g}$	$1.5 \cdot 10^{-6} \text{ m}^3/\text{g}$
Surface area (As)	BET	$39.8 \text{ m}^2/\text{g}$	$158.59 \text{ m}^2/\text{g}$
Density (ρ)	Pycnometer	$1.100 \text{ g}/\text{cm}^3$	$1.100 \text{ g}/\text{cm}^3$

Figure 2.7 - (a) Image of a typical measurement showing an accumulation zone on the right and the areas that were measured and averaged over 4 seconds. (b) a typical fluorescent intensity profile (along the yellow line) for a positive and negative potential pulse.)

The experimentally determined difference in fluorescence intensity between depletion and enrichment zones is plotted against the electrolyte concentration in Figure 2.8. It was found that the particles with larger pores have a higher fluorescence intensity at low salt concentrations. This was indeed predicted by our model, where it results from the larger pore volume. The fluorescence intensity values of both particles cross at a higher salt concentration, which was also predicted in the model, where it follows from the earlier drop in the ion permselectivity of the particles with larger pores. This confirms that ICP can be used to differentiate between particles with different mesoporosity. The error bars in Figure 2.8 correspond to 95% confidence intervals and are a result of various factors. The particle size varied significantly ($106,7 \mu\text{m} \pm 16,8 \mu\text{m}$), resulting in strong variations in pore conductance. Furthermore, the average pore size, pore volume and surface area were measured in a sample with a large number of particles and the variation between particles is unknown. The differences between the model results and the experimental can furthermore result from the various assumptions made in the model. Specifically, the electroosmotic flow is neglected and the pores are assumed to be straight and cylindrical, while in reality a network of connected pores spaces exists as can be expected from the SEM images in Figure 2.6.

As some experimental verification of the model is now obtained, we will investigate its feasibility for future applications by modeling the effects of the following properties on the ICP: pore diameter, surface charge density, and total particle surface area. Figure 2.9a shows that an increase in pore size causes a faster decrease in fluorescent intensity with increasing electrolyte concentration which can be explained by the fact that smaller pores will be more permselective than larger pores at higher electrolyte concentrations, causing a higher transport number difference with the bulk electrolyte. It is worth noting that the total particle cross-sectional area was kept constant hence a constant current density is assumed on Figure 2.9a. In the case of varying surface charge, see Figure 2.9b, at

low electrolyte concentration no difference is observed, that is caused by the limitation of the current due high resistance of the bulk compared to the particle as commented earlier . In contrast a difference is seen when the electrolyte concentration increases, the pores with high surface charge lose their permselectivity at higher electrolyte concentrations due to higher concentration in the double layer. Figure 2.9c shows the effect of total particle surface area on the reporter concentration. As can be seen, a lower surface area causes an increase in fluorescent intensity. The total surface area is linearly (for a constant pore size) related to the number of pores. Since the total current through the particle is regulated by bulk resistance (microchannel) it is almost constant between particles. A decrease in the surface area translates in lower number of pores which results in a higher current density through the particle.

Figure 2.8 - Experimental results of ion concentration polarization vs electrolyte concentration. The points on y-axis were found by subtracting the lower fluorescent intensity value (in the depletion zone) from the high intensity value (in the enrichment zone). Similar to the theoretical graph, the ICP at low electrolyte concentration is larger for the large pore diameter particles, while the ICP at high salt concentration is larger for the small pore diameter particles. The lines cross in both the model and the experiments at a concentration where the selectivity is lost for the larger pores. The error bars correspond to 95% confidence intervals.

The conclusion is that differences in pore size and pore charge density lead to different concentration polarization behavior. In addition to a qualitative description of our system, also more specific information can be extracted from our model. As can be seen in Figure 2.9a, the cut-off point in the electrolyte concentration (intercept of red lines) where the concentration polarization effect starts to drop when increasing the electrolyte concentration is strongly correlated to the pore size as well as the surface area, with the effect of pore size being larger. On the other hand, the concentration polarization at very low electrolyte concentrations is dominated just by the specific surface area of the particle (Figure 2.9c), hence by measuring the ICP at low electrolyte concentrations (10^{-4} [M]) the

particles can be differentiated based on their specific surface area. As can be seen in the experimental data of Figure 2.8, the fluorescent intensity at low concentrations is slightly lower for the particle with smaller pores, indicating that their specific surface area is slightly larger. However, when evaluating the concentration at which the fluorescent intensity drops, a parameter that is largely dependent on the pore size, the ICP of the particles with larger pores drops at lower concentrations as predicted by our model.

Figure 2.9 - Simulations of the model when changing (a) the mesopore size, (b) surface charge density and (c) specific surface area. In each simulation, all the other parameters not simulated are taken from the smaller pores particles. In (a) the total cross-sectional area (# of pores * pore size) is kept constant. σ corresponds to the surface charge density calculated for silicon dioxide as described previously.

2.5| Conclusions and outlook

In conclusion, we demonstrated that ICP can be used to differentiate between particles with different mesopore dimensions. A model was developed demonstrating that both pore density and ion permselectivity play a role in the magnitude of ICP. Subsequently, the ICP of two types of particles with experimentally determined porosity and pore density was measured at different bulk electrolyte concentrations. Experimental and simulated results show similar trends. We conclude that the ICP method can be used to track differences in pore size between mesoporous particles such as catalysts or catalysts supports. Our

model is currently a 1-D model that provides qualitative results and allows understanding of the main factors affecting ICP. In the future it can be used as a foundation for numerical simulations in order to create a 3D (semi-)quantitative model. Such a numerical approach can also include phenomena that are currently neglected in our analytical model such as the electroosmotic flow.

2.6| References

1. Kitagawa, S. Porous Materials and the Age of Gas. *Angew. Chemie - Int. Ed.* **54**, 10686–10687 (2015).
2. Zaworotko, M. J. Designer pores made easy. *Nature* **451**, 410–411 (2008).
3. Davis, M. E. Ordered Porous Materials for Emerging Applications. *Nature* **10**, 813–821 (2015).
4. Parlett, C. M. A., Wilson, K. & Lee, A. F. Hierarchical porous materials: Catalytic applications. *Chem. Soc. Rev.* **42**, 3876–3893 (2013).
5. De Winter, D. A. M., Meirer, F. & Weckhuysen, B. M. FIB-SEM Tomography Probes the Mesoscale Pore Space of an Individual Catalytic Cracking Particle. *ACS Catal.* **6**, 3158–3167 (2016).
6. Wise, A. M. *et al.* Nanoscale Chemical Imaging of an Individual Catalyst Particle with Soft X-ray Ptychography. *ACS Catal.* **6**, 2178–2181 (2016).
7. Meirer, F. *et al.* Life and death of a single catalytic cracking particle. *Sci. Adv.* **1**, e1400199 (2015).
8. Cychosz, K. A., Guillet-Nicolas, R., García-Martínez, J. & Thommes, M. Recent advances in the textural characterization of hierarchically structured nanoporous materials. *Chem. Soc. Rev.* **46**, 389–414 (2017).
9. Meirer, F. & Weckhuysen, B. M. Spatial and temporal exploration of heterogeneous catalysts with synchrotron radiation. *Nat. Rev. Mater.* 324–340 (2018).
10. Ning, G., Wei, F., Luo, G. & Jin, Y. Online BET analysis of single-wall carbon nanotube growth and its effect on catalyst reactivation. *Carbon N. Y.* **43**, 1439–1444 (2005).
11. Leofanti, G., Padovan, M., Tozzola, G. & Venturelli, B. Surface area and pore texture of catalysts. *Catal. Today* **41**, 207–219 (1998).
12. Ihli, J. *et al.* A three-dimensional view of structural changes caused by deactivation of fluid catalytic cracking catalysts. *Nat. Commun.* **8:809**, (2017).
13. Gregg, S. J. & Sing, K. S. W. *Gregg_1982_adsorption_surface_area_and_porosity.pdf*. (Academic Press, 1982). doi:10.1149/1.2426447
14. Rouquerol, J. *et al.* Liquid intrusion and alternative methods for the characterization of macroporous materials (IUPAC Technical Report). *Pure Appl. Chem.* **84**, 107–136 (2011).
15. Liu, Y., Meirer, F., Krest, C. M., Webb, S. & Weckhuysen, B. M. Relating structure and composition with accessibility of a single catalyst particle using correlative 3-dimensional micro-spectroscopy. *Nat. Commun.* **7:12634**, (2016).
16. Whiting, G. T., Nikolopoulos, N., Nikolopoulos, I., Chowdhury, A. D. &

- Weckhuysen, B. M. Visualizing pore architecture and molecular transport boundaries in catalyst bodies with fluorescent nanoprobes. *Nat. Chem.* **11**, 23–31 (2019).
17. Kim, S. J., Li, L. D. & Han, J. Amplified electrokinetic response by concentration polarization near nanofluidic channel. *Langmuir* **25**, 7759–7765 (2009).
 18. Plecis, A., Nanteuil, C. & Chen, Y. Electropreconcentration with Charge-Selective Nanochannels. *Society* **80**, 9542–9550 (2008).
 19. Pu, Q., Yun, J., Temkin, H. & Liu, S. Ion-Enrichment and Ion-Depletion Effect of Nanochannel Structures. *Nano Lett.* **4**, 1099–1103 (2004).
 20. Leinweber, F. C. & Tallarek, U. Nonequilibrium electrokinetic effects in beds of ion-permselective particles. *Langmuir* (2004). doi:10.1021/la048408n
 21. Petr Vanysek. *Ionic conductivity and diffusion at infinite dilution. CRC Handbook of Chemistry and Physics, 91th Editio* (1991). doi:10.1111/j.1540-5834.2011.00596.x
 22. Bergveld, P., Eijkel, J. C. T. & Olthuis, W. Detection of protein concentrations with chronopotentiometry. *Biosens. Bioelectron.* (1997). doi:10.1016/S0956-5663(97)00023-7
 23. Bard, A. J. *et al. ELECTROCHEMICAL METHODS Fundamentals and Applications. Faulkner, L.R. Bard A.J.* (1944). doi:10.1016/B978-0-12-381373-2.00056-9
 24. Rice, C. L. & Whitehead, R. Electrokinetic flow in a narrow cylindrical capillary. *J. Phys. Chem.* (1965). doi:10.1021/j100895a062
 25. El-Gholabzouri, O., Cabrerizo-Vílchez, M. Á. & Hidalgo-Álvarez, R. Zeta-potential of polystyrene latex determined using different electrokinetic techniques in binary liquid mixtures. *Colloids Surfaces A Physicochem. Eng. Asp.* (2006). doi:10.1016/j.colsurfa.2006.05.017
 26. Plecis, A., Schoch, R. B. & Renaud, P. Ionic transport phenomena in nanofluidics: Experimental and theoretical study of the exclusion-enrichment effect on a chip. *Nano Lett.* (2005). doi:10.1021/nl050265h
 27. Taghipoor, M., Bertsch, A. & Renaud, P. An improved model for predicting electrical conductance in nanochannels. *Phys. Chem. Chem. Phys.* **17**, 4160–4167 (2015).
 28. Hunter, R. J. *Zeta Potential in Colloid Science. Microscopy* (1981). doi:10.2460/ajvr.70.2.167; 10.2460/ajvr.70.2.167

Chapter 3

3D Capillary Stop Valves for Versatile Patterning Inside Microfluidic Chips

The patterning of antibodies in microfluidics chips is always a delicate process that is usually done in an open chip before bonding. Typical bonding techniques such as plasma treatment can harm the antibodies with as result that these techniques are removed from our fabrication toolbox. Here we propose a method, based on capillary phenomena using 3D capillary valves, that autonomously and conveniently allows us to pattern liquids inside closed chips. We theoretically analyse the system and demonstrate how our analysis can be used as a design tool for various applications. Chips patterned with the method were used for simple immunodetection of a cardiac biomarker which demonstrates its suitability for antibody patterning.

This chapter is based on the publication: Vasileios A. Papadimitriou, Loes I. Segerink, Albert v.d. Berg and Jan C. T. Eijkel. "3D capillary stop valves for versatile patterning inside microfluidic chips" *Analytica Chimica Acta* 2018 1000, pp 232-238, <https://doi.org/10.1016/j.aca.2017.11.055>

3.1| Introduction

Proteomic studies by specific protein-antibody binding have a wide range of applications, from early diagnosis of diseases to fundamental medical and biological studies. Microfluidic chips offer an attractive platform for these studies for various reasons such as the use of extremely low volumes of expensive samples, chemicals and reagents used in immunodetection. For such studies it is necessary to coat a section of the chip with the protein-binding molecules, often an antibody¹. Typically, first one part of the device is coated with the antibody and then bonded to create the microfluidic chip². There are several methods for patterning antibodies prior to bonding with the most widely used ones being bioprinting³ and light assisted immobilization⁴. However, when the antibody coating is performed before the final chip is bonded (open-chip), any fabrication process that can harm the antibody coating (e.g. high temperature, plasma and ultraviolet(UV) treatment) is prohibited. Use of less stable materials (such as polydimethylsiloxane (PDMS)) or more delicate bonding methods then becomes necessary. Such bonding methods could be gluing, use of pressure sensitive adhesive (PSA) tapes⁵ and use of chemical functionalized surfaces⁶. As also these methods have their limitations, there exists a need for an antibody immobilization method that can be used after chip bonding. Trapping of antibody labelled beads for immunodetection in closed chip has been previously reported⁷ but bead trapping lacks the flexibility of patterning shapes. Capillary filling methods are an excellent candidate for this. The use of capillary effects has always been popular in microfluidic systems⁸. Specifically, the passive handling of fluids provided by the capillary phenomena simplifies the device operation and minimizes the need of external actuation devices (e.g. pumps) which makes the resulting devices inherently simple to use without any training⁹. Devices based on capillary system have found applications such as diagnostics in 'autonomous' systems with sequential transport of minute amounts of liquids¹⁰, capillary pinning of hydrogels¹¹ and phase-guides for passive routing of liquids¹². Here we develop a method based on capillarity to passively pattern antibodies in a closed, bonded chip. This method solves the bonding issue mentioned above, and consequently puts all the reliable but "harsh" fabrication processes back into our fabrication toolbox, allowing the use of stable microfluidic devices.

3.2| Theory

The configuration we propose for capillary patterning uses a series of capillary stop valves¹³ in 3D configuration. The first stop valve is formed when a deep channel intercepts another shallower channel (Figure 3.1a). A liquid is applied to the deep channel and fills it via capillary forces. Subsequently, when it reaches the intersection, the part of the liquid that meets the abrupt opening will become pinned, similar to the traditional 2D capillary stop valves. However, the part of the liquid that contacts the shallow channel in a ditch on the bottom of the intersecting channel can flow freely across this channel. The liquid is now pinned in the perpendicular direction as it crosses the channel and fills the ditch (Figure 3.1c). When the liquid has crossed the entire shallow channel, it will fully wet the deep

channel on the opposite side, being pinned again in the perpendicular direction to the shallow ditch as on the other side (Figure 3.1d).

Figure 3.1 - a) Schematic of the 3D capillary valve. The top part has been removed for easier visualization of the process. b) Typical dimensions of the valve. Part of the chip (marked with black lines) has been removed. c) Partial filling of the valve. The top part of the liquid is pinned in the vertical direction (1st pinning direction) and the lower part flows in the ditch while it is getting pinned in the horizontal direction (2nd pinning direction). d) Completely filled valve, the pinned edges are shown with dashed lines. The shape of the meniscus shifts from concave to convex due to pressure.

The 3D capillary valve pattern we use has three distinct regions where three different capillary phenomena take place: a) capillary filling, b) capillary pinning (stop valve), c) open microfluidics (Figure 3.2)¹⁴. Each of them will be investigated independently.

All three different capillary phenomena are governed by the liquid pressure that is generated during the filling process of the chip. Following the analysis by Man et al.¹³, the liquid pressure at the meniscus during filling can be derived as the change of total interfacial energy on an increase of the filling liquid volume,

$$P = \frac{dU_t}{dV} \quad (3.1)$$

Here P [Pa] is the pressure across the liquid/air interface, U_t is the total interfacial energy [J], and V [m³] is the volume of the liquid in the chip. The total interfacial energy is given by equation 3.2,

$$U_t = A_{sl}\gamma_{sl} + A_{sg}\gamma_{sg} + A_{lg}\gamma_{lg} \quad (3.2)$$

where A is surface area of each interface and γ is the energy per unit area of that interface (interfacial tension). The subscripts s, l, g stand for solid, liquid and gas,

e.g. A_{sl} is the surface area between solid and liquid phase, i.e. the wetted area of the channel. Equation 3.2 simply describes the sum of all interfacial energies. Depending on the balance of those energies either a negative or positive total energy change at a liquid volume can occur. A negative energy change results in a negative pressure which leads to capillary filling, and a positive energy change results in a positive pressure which leads to liquid pinning. We can rewrite equation 3.2 by using Young's equation (3.3) that relates interfacial tensions by the advancing liquid/air contact angle θ ,

$$\gamma_{sl} = \gamma_{sg} - \gamma_{lg} \cos \theta \quad (3.3)$$

By combining equations 3.2 and 3.3 we obtain

$$U_t = (A_{sl} + A_{sg})\gamma_{sg} - A_{sl} \gamma_{lg} \cos \theta + A_{lg} \gamma_{lg} \quad (3.4)$$

$$U_t = U_0 - \gamma_{lg} (A_{sl} \cos \theta - A_{lg}) \quad (3.5)$$

where $U_0 = (A_{sl} + A_{sg})\gamma_{sg}$ is constant because the total area of solid is constant. Substituting equation 3.5 in equation 3.1 we obtain the general expression for the meniscus pressure,

$$P = \frac{dU_t}{dV} = -\gamma_{lg} \left(\cos \theta \frac{dA_{sl}}{dV} - \frac{dA_{lg}}{dV} \right) \quad (3.6)$$

Equation 3.6 will be used to calculate the meniscus pressure in the three distinct regions of the device. This pressure is the driving force which will either pin the liquid or passively fill the device.

Figure 3.2 - Three different capillary phenomena that are exploited by the 3D valves. Capillary filling moves the liquid towards the valve. Capillary stop valves pin the liquid in two directions marked with red arrows (the pinned liquid air interface is shaded with red color) and the liquid advances via an open microfluidic structure.

3.2.1| Capillary filling

At the start of the filling process the liquid fills a rectangular channel of constant cross-sectional area. In that case $A_{lg} = wh$ in equation 3.6 will be constant when the liquid invades (assuming a flat meniscus), so that $dA_{lg}/dV = 0$. Furthermore $dA_{sl} = 2(w + h)dL$ and $dV = wh dL$, where w , h , L are the width, height and length of the wetted channel. As a result equation 3.6 for the meniscus pressure reduces to

$$P = -\gamma_{lg} \left(2\cos\theta \frac{h + w}{wh} \right) \quad (3.7)$$

The pressure at the reservoir is equal to atmospheric pressure but we will arbitrarily define it as zero for a more intelligible analysis; hence a negative constant pressure at the front of the meniscus is pulling the liquid through the channel. As the liquid advances and wets a bigger part of the channel, the hydraulic resistance increases linearly with filled channel length (assuming a constant channel cross-section area) and since the filling is driven by constant pressure the flow rate will decrease with the square root of time. In typical cases filling will eventually stop when the liquid becomes pinned at a small asperity. In our device during the entire filling process the pressure is sufficiently negative and the hydraulic resistance small enough for the liquid to move very rapidly (flow velocity in the range of millimeters per second, see ESI). After filling the rectangular channel, the liquid reaches the next region of the device, where the top part of the liquid meets a capillary valve and the bottom part an open microfluidic channel (Figure 3.2).

3.2.2| Capillary stop valve

The top part of the liquid meets an abrupt expansion of the channel, i.e. a geometrical capillary stop valve¹³ (indicated in red in figure 3.2). Capillary stop valves have been extensively studied and a first 2D model was made by Man et al¹³ where the pressure barrier and the energy of such system was calculated with the use of equations 3.6 and 3.2 and the geometrical change of the meniscus curvature. They showed that the pressure barrier in such a valve equals to:

$$\Delta P = \frac{2\gamma_{la}}{w} \left(\frac{\cos\theta - \frac{\alpha}{\sin\alpha}}{\frac{1}{\sin\alpha} \left(\frac{\alpha}{\sin\alpha} - \cos\alpha \right)} \right)$$

Where α is the meniscus arc angle (see figure 3.3).

Figure 3.3 - Typical layout of a 2D capillary stop valve.

For a pressure barrier of zero the critical expansion angle (β_c), i.e. the minimum expansion angle needed to achieve pinning, can be calculated and it is given by:

$$\beta_c = \frac{\pi}{2} - \theta \quad (3.8)$$

Later more sophisticated 3D models were proposed^{15,16} where the pressure barrier is given by:

$$\Delta P = - \frac{2\gamma l a \left[\left(\frac{\cos \theta w}{\cos \beta} \right) + h + h \left(\frac{\tan \beta}{\sin \alpha_h} \right) \left(\frac{\alpha_h}{\sin \alpha_h} - \cos \alpha_h \right) - \left(\alpha_h \alpha_v w \frac{\tan \beta}{\sin \alpha_h \sin \alpha_v} \right) \right]}{w \left[h - \left(h \frac{\tan \beta}{\sin \alpha_h} \right) \left(\frac{\alpha_h}{\sin \alpha_h} - \cos \alpha_h \right) - \left(\frac{w \tan \beta \alpha_h}{2 \sin \alpha_h \sin \alpha_v} \right) \left(\frac{\alpha_v}{\sin \alpha_v} - \cos \alpha_v \right) \right]} \quad (3.9)_{16}$$

Here α_h and α_v is the horizontal and vertical arc angle of the meniscus respectively, w is the width of the valve before the expansion, h its height, and finally β is the expansion angle (figure 3.3).

3.2.3| Open microfluidics

After the stop valve, the liquid now will proceed by filling an open channel, crossing the bottom of a wider channel (indicated in green in figure 3.2). This geometry is known as open microfluidics, a concept introduced by the Beebe group¹⁴. Also in this case, the condition for passive filling is a negative pressure at the meniscus relative to the reservoir pressure (defined as 0 bar). From equation 3.6 a negative pressure condition translates to:

$$\cos \theta > \frac{dA_{lg}}{dA_{sl}} \quad (3.10)$$

Equation 3.10 gives the general condition for passive filling of an open microfluidic feature of arbitrary shape. When we assume liquid interfaces with no curvature, equation 3.10 is simplified to:

$$\cos \theta > \frac{p_{lg}}{p_{sl}} \quad (3.11)$$

where p_{sl} is the perimeter of the cross section of the channel that is wetted, and p_{lg} is the non-wetted one. For the simple case of a rectangular channel with three walls we can calculate the meniscus pressure in a similar fashion as in equation 3.7 as

$$P = -\gamma_{lg} \left(\cos \theta \frac{2h + w}{wh} - \frac{1}{h} \right) \quad (3.12)$$

Once again, the flow in this simple open channel geometry is caused by a constant negative pressure at the proceeding liquid front. Similar to the capillary filling the flow rate will reduce as the liquid proceeds because of the pressure drop arising from the increasing hydraulic resistance. In open microfluidics as in closed-channel microfluidics the distance travelled by the invading liquid scales with the square root of time¹⁷. In our system the resistance of the open microfluidic channels is low as they are short (up to 100µm straight channel) and the meniscus pressure low, resulting in a capillary filling velocity in the range of millimeters per second which ensures the successful filling of the open microfluidic structure. Following the open microfluidics section, the liquid will proceed filling the closed microfluidic channel at the other side of the channel it just crossed.

3.3| Experimental

In order to test the geometry proposed in Figure 3.2, chips were fabricated out of PDMS with standard soft lithography methods¹⁸. Specifically, a silicon wafer was dehydrated on a hotplate 120°C for 5min and a layer of Microchem SU-8 2050 negative photoresist was spin-coated with a thickness of 35µm. Soft bake, UV exposure (photolithography with the blue pattern of figure 3.4 as mask), hard bake and resist development were performed according to the fabrication parameters suggested by the photoresist manufacturer. The same process was repeated for a second layer of SU-8 with a thickness of 75µm, using the green pattern of figure 3.4 as a photolithography mask. The silicon wafer with the patterned SU-8 was then used as a template for the soft lithography of PDMS. The obtained PDMS chips were bonded on standard microscope glass slides after O₂ plasma treatment and left in the oven at 60°C for varying amounts of time depending on the application, in order to reduce their hydrophilicity. Specifically for the characterization device with water/water mixtures the PDMS chips were annealed for 5 hours. For the immunodetection application where aqueous solutions are used, the chips were annealed for 90 minutes. PDMS was chosen because its surface properties are well investigated^{19,20} and can be trivially tuned via O₂ plasma treatment. In addition to

the simple straight channel geometry that is shown in figure 3.4, various other channel geometries shown in figure 3.5 were tested in order to test the capabilities of the capillary patterning procedure.

For the immunodetection experiments, chips were fabricated out of PDMS as described before and bonded to standard microscopy slides. A droplet of an aqueous antibody coating solution ($5\mu\text{g}/\text{ml}$ Anti-Cardiac Troponin I antibody (Abcam) in carbonate/bicarbonate buffer pH 9.2) was introduced in the antibody designated inlet channel after which via capillary forces the bottom of the sample channel was patterned. The antibody coating solution was allowed to bind for 15min and then the chip was flushed with 1xPBS (Sigma-Aldrich) + 0.1% Tween 20 (Sigma-Aldrich) solution and subsequently with DI water and dried overnight. To demonstrate proper functioning of the device as a protein sensor, fluorescently labelled Cardiac troponin-I (Abcam, $2.2\mu\text{g}/\text{ml}$) in 1xPBS + 1% BSA (Sigma-Aldrich) was introduced in the sample channel and allowed to incubate for 15min, after which the channel was flushed with 1xPBS+ 0.1% Tween and the fluorescence emission recorded. Cardiac troponin-I was chosen as the target protein because it is a key biomarker for cardiac disease.

Figure 3.4 - Example of a lithography mask for a device with a simple straight open microfluidic geometry. The green features have a depth of $75\mu\text{m}$ and the blue features of $35\mu\text{m}$, creating an open microfluidic channel of $40\mu\text{m}$ in depth at the bottom of the channel indicated in blue. The reservoirs are 1mm in radius. The channels start as $500\mu\text{m}$ and tapers down to $50\mu\text{m}$ and down to $10\mu\text{m}$ close to the open microfluidic structure. The tapering of the channel increases the capillary pressure and assists in the successful capillary filling.

Figure 3.5 - A few examples of more complicated shapes of the open microfluidics structures. Multiple channels (a,b), dead-end channels (c,d) patches (e,f) and closed loops/shapes(g,h,i) were investigated. Scale bar 100 μm .

3.4| Results and discussion

3.4.1| Characterization of device operation using ethanol/water mixtures

As shown in the theoretical section, the liquid/air interfacial tension (γ_{sg}) and the solid/liquid contact angle (θ) are the critical parameters that need to be controlled. On the one hand the liquid should be sufficiently wetting so that the condition for capillary filling and open microfluidics is met. On the other hand, the more wetting the liquid is (i.e. the lower the contact angle) and the lower the liquid/air interfacial tension, the lower the pressure barrier of the capillary valve. A low-pressure barrier easily results in valve-breakthrough and flooding of the device. Contact angle and interfacial tension can be controlled by both surface and liquid properties. For the initial experiments to characterize the device operation we chose to vary the latter. Droplets of different mixtures of ethanol (EtOH) and water (H_2O) were introduced to the inlet reservoir of two different devices with a straight open microfluidic channel geometry (Figure 3.4). The open microfluidic channels had a depth of 40 μm , a width of 10 μm and a length respectively of 50 μm and 100 μm . The capillary valves had a width of 10 μm and a height of 35 μm . Figure 3.6 shows the theoretically predicted capillary valve pressure barrier (equation 3.9) and the capillary pressure driving the filling of the open microfluidic feature for different H_2O and EtOH mixtures (equation 3.12). The points on the graph were derived using the experimentally obtained values for contact angle and surface tension for different H_2O and EtOH mixtures reported in ^{19,20}. Dotted lines were

added as a guide for the eye. Both pressures should be negative for a proper functionality of the device. If the pressure barrier has a positive value, then the device will flood and if the capillary pressure is positive then the open microfluidic feature will not fill. As shown in figure 3.6, according to the calculations both pressures are negative for solutions with a H₂O:EtOH ratio between 8:2 and 7:3(indicated by a green triangle) and with the optimum point with the lowest pressure (at the apex of the grey triangle) at a H₂O:EtOH ratio of 7.25:2.75. In figure 3.7 the experimental results are shown. For each H₂O:EtOH ratio ten devices were tested and the success rate for filling (i.e. successful capillary pinning at the valve and successful filling of the open microfluidic feature) was recorded. If the device failed in the grey area, it means that the open feature did not fill (as shown in the microscopy image(a) of the inset) and if it failed in the white area it means that the liquid front was not pinned at the capillary valve and the device flooded (also see inset(b)). As theoretically predicted, the highest success rate was obtained for solutions with a H₂O:EtOH ratio between 8:2 and 7:3. Theoretically, the device should only work in this volume ratio range, but experimentally some devices were found to function outside this range. This can be explained by differences between devices due to fabrication. For example, we assume that the expansion angle of the capillary valve is 90°, while in reality a perfect right angle cannot be fabricated in PDMS and on the nanoscale corners will be rounded. In addition, it is known that the thickness of the SU-8 that is used for PDMS soft lithography can slightly vary depending on the position on the wafer²¹. Also, equation 3.9 that was used for the calculation of the pressure barrier is valid for a simple capillary stop valve with four liquid-solid interfaces, continuous bottom and top and an abrupt expansion on the side walls. In contrast, in our design the capillary valve has no solid bottom wall and hence has one less liquid-solid interface. This will alter the geometry of the meniscus, and hence the pressure barrier will be slightly different from the predicted one.

Figure 3.6 - Theoretical model of pressures. Blue shows the pressure barrier of the capillary valve and red shows the capillary pressure driving the filling of the open microfluidic

feature, for different H₂O and EtOH mixtures. The operating range is shown with green colour.

As was expected, the length of the open microfluidic structure did not affect the success rate of the device: when the filling condition is met (equation 3.11) and the pressure at the meniscus is negative, then the open microfluidic structure will be passively filled independently of its length (see figure 3.7). As mentioned earlier the constant pressure at the liquid front results in a time-dependant flow velocity as the open microfluidic feature is filled, nevertheless the length of our features is small enough to neglect this phenomenon.

Figure 3.7 - Experimental results. For each water ethanol solution ten devices with a straight open microfluidic feature of 50µm (blue color) and ten with a 100µm (red color) open microfluidic were tested and the success rate for filling was recorded. If the device failed in the grey area it means that the open feature did not fill (a) and if it failed in the white area it means that the liquid front was not pinned at the capillary valve and the device flooded (b) as shown at the indent microscopy images. Once again the highest success rate is for solutions with H₂O:EtOH ratio between 8:2 and 7:3 that fits the theoretical model.

3.4.2| Method flexibility

The requirements for the capillary valve and the open microfluidic features are independent of each other, hence one can design various shapes of open microfluidics as long as the passive filling condition is met. Several different open microfluidics were tested in order to show the versatility of the proposed system in capillary patterning, and a few results are shown in figure 3.8. Bubble formation is a significant problem in filling microfluidic systems, but open microfluidics, where the air can simply escape, and which hence is insensitive to bubble formation, gives the opportunity for patterning dead end channels and loops which otherwise is impossible.

In practical applications it will not be easily possible to change the surface tension and contact angle by using solvent mixtures. However, surfactants can be used to

control the surface tension and contact angle. Also, the contact angle can be controlled by changing the surface properties. For research purposes where PDMS is used, the contact angle can be controlled by plasma treatment and annealing at low temperature. By adjusting the plasma treatment time, we tuned the water contact angle of the PDMS to make the device suitable for filling with an aqueous solution, as we will show in the next section.

Figure 3.8 - Experimental results of various capillary patterns in the bottom channel wall prior to filling (left) and after filling with 7.5:2.5 H₂O:EtOH (right).

The most convenient way to obtain functioning devices for a wide variety of materials and solutions is by controlling the feature size and specifically the depth of the features, i.e. the height of the capillary valves and the depth of the open microfluidic channel. To illustrate the potential of this method, in figure 3.9 calculations for the capillary pressure in the open microfluidic structure and the pressure barrier of the capillary valve are plotted against the depth of each feature for two different solutions, that vary in contact angle and surface tension. The width of both features is set to 10 μm. Once again both pressures are required to be negative, so that the necessary depths of the features can be obtained from the graphs. Similar graphs can for example be made for different feature widths. With such analyses, one can tailor the device for any specific material, solution and application.

3.4.3| Antibody patterning with an aqueous solution

We demonstrate the practical usefulness of our method by applying it for capillary patterning of antibodies for immunodetection. As mentioned earlier we tuned the contact angle of the PDMS chips, via O₂ plasma treatment and low temperature annealing, so the proper functionality of the device was ensured for aqueous solutions. We show that it is possible to pattern after bonding, hence in a closed chip,

which otherwise is cumbersome. A schematic representation of the application is showed in figure 3.10.

Figure 3.9 - Capillary barrier pressure and capillary filling pressure vs feature depth for two different solutions. Both pressures are required to be negative.

Figure 3.10 - Schematic of the antibody coating and subsequent immunodetection in the chip. a) Capillary filling of the 3D valve with antibody solution. b) incubation of the antibody solution, flushing and drying of chip. c) Capillary filling of the main channel with the fluorescent antigen-containing solution and incubation. d) Flushing and fluorescent microscopy detection.

In figure 3.11 the results are shown. After the capillary patterning we demonstrated the intact functionality of the antibodies by flushing the channels with fluorescent antigen. The results prove that the simple technique based on capillary phenomena enables patterning of antibodies in closed chips, with subsequent antigen immunodetection. The patterning freedom offered by the method is evidenced by successful coating of simple straight channels (Figure 3.11a-c), to more complex shapes (Figure 3.11d-i).

Our examples use PDMS only to demonstrate the method. As mentioned in the introduction, in future this technique is meant for use in closed glass or plastic chips that are suitable for diagnostic devices. One further point that needs consideration in the final devices is closing the 3D capillary valve channel exits, since the sample solution will leak out via these channels. An easy solution to this problem is the blocking of the 3D valve reservoirs prior to the introduction of antigen e.g. by glue. The trapped air in the channels will then allow only minute volumes to enter the capillary valve channels.

Figure 3.11 – Microscopy images of antibody antigen reactions after antibody patterning. Channel walls are marked with yellow dashed lines a) Bright field image of a chip with two straight channels for antibody coating. b,c) Fluorescent imaging of the chip with two(b) and one(c) channels coated with antibody and incubated with fluorescent antigen. d,f,h) Bright field images of more complex patterns. e,g,i) Fluorescent images after antibody coating and fluorescent antigen incubation.

3.5| Conclusions and outlook

The use of 3D capillary valves has been investigated for capillary patterning in closed microchips. We theoretically described the functionality of the system for selective filling of parts of a closed microfluidic structure and the experimental results adequately fit the proposed theoretical model. The model can be used as a design tool for tailoring 3D valves for various applications, solutions and materials as long as the contact angle and surface tension are known. In addition, we demonstrate that the method can be used to create a simple immunodetection device by demonstrating a passive antibody patterning of various shapes in a closed chip followed by antigen binding. The technique can find various applications such as capillary patterning of phase change materials e.g. hydrogels and local surface functionalization in closed chips.

3.6| References

1. Squires, T. M., Messinger, R. J. & Manalis, S. R. Making it stick: convection, reaction and diffusion in surface-based biosensors. *Nat. Biotechnol.* **26**, 417–426 (2008).
2. Cesaro-Tadic, S. *et al.* High-sensitivity miniaturized immunoassays for tumor necrosis factor alpha using microfluidic systems. *Lab Chip* **4**, 563–569 (2004).
3. Bernard, a, Renault, J. P., Michel, B., Bosshard, H. R. & Delamarche, E. Microcontact printing of proteins. *Adv. Mater.* **12**, 1067–1070 (2000).
4. Snabe, T., R??der, G. A., Neves-Petersen, M. T., Buus, S. & Petersen, S. B. Oriented coupling of major histocompatibility complex (MHC) to sensor surfaces using light assisted immobilisation technology. *Biosens. Bioelectron.* **21**, 1553–1559 (2006).
5. Kim, J., Kim, J., Shin, Y., Song, S. & Lee, J. Rapid prototyping of multifunctional microfluidic cartridges for electrochemical biosensing platforms. *Sensors Actuators, B Chem.* **202**, 60–66 (2014).
6. Saharil, F., Carlborg, C. F., Haraldsson, T. & van der Wijngaart, W. Biocompatible “click” wafer bonding for microfluidic devices. *Lab Chip* **12**, 3032 (2012).
7. Diercks, A. H. *et al.* A microfluidic device for multiplexed protein detection in nano-liter volumes. *Anal. Biochem.* **386**, 30–35 (2009).
8. Eijkel, J. C. T. & van den Berg, A. Young 4ever—the use of capillarity for passive flow handling in lab on a chip devices. *Lab Chip* **6**, 1405–1408 (2006).
9. Delamarche, E., Juncker, D. & Schmid, H. Microfluidics for processing surfaces and miniaturizing biological assays. *Advanced Materials* **17**, 2911–2933 (2005).
10. Juncker, D. *et al.* Autonomous microfluidic capillary system. *Anal. Chem.* **74**, 6139–6144 (2002).
11. Gumuscu, B., Bomer, J. G., van den Berg, A. & Eijkel, J. C. T. Large scale patterning of hydrogel microarrays using capillary pinning. *Lab Chip* **15**, 664–667 (2015).
12. Yildirim, E. *et al.* Phaseguides as tunable passive microvalves for liquid routing in complex microfluidic networks. *Lab Chip* **14**, 3334 (2014).
13. Man, P. F., Mastrangelo, C. H., Burns, M. A. & Burke, D. T. Microfabricated capillarity-driven stop valve and sample injector. *Proc. MEMS 98. IEEE. Elev. Annu. Int. Work. Micro Electro Mech. Syst. An Investig. Micro Struct. Sensors, Actuators, Mach. Syst. (Cat. No.98CH36176)* 45–50 (1998). doi:10.1109/MEMSYS.1998.659727
14. Casavant, B. P. *et al.* Suspended microfluidics. *Proc. Natl. Acad. Sci.* **110**, 10111–10116 (2013).
15. Leu, T. S. & Chang, P. Y. Pressure barrier of capillary stop valves in micro sample separators. in *Sensors and Actuators, A: Physical* **115**, 508–515 (2004).
16. Hagemeyer, B., Zechnall, F. & Stelzle, M. Towards plug and play filling of

- microfluidic devices by utilizing networks of capillary stop valves. *Biomicrofluidics* **8**, (2014).
17. Berthier, J., Brakke, K. A. & Berthier, E. *Open Microfluidics*. (Scrivener Publishing, 2016).
 18. Weibel, D. B., DiLuzio, W. R. & Whitesides, G. M. Microfabrication meets microbiology. *Nat. Rev. Microbiol.* **5**, 209–218 (2007).
 19. Cao, H., Amador, C., Jia, X. & Ding, Y. Capillary Dynamics of Water/Ethanol Mixtures. *Ind. Eng. Chem. Res.* **54**, 12196–12203 (2015).
 20. Mishra, H. *et al.* Time-Dependent Wetting Behavior of PDMS Surfaces with Bioinspired, Hierarchical Structures. *ACS Appl. Mater. Interfaces* **8**, 8168–8174 (2016).
 21. Mata, A., Fleischman, A. J. & Roy, S. Fabrication of multi-layer SU-8 microstructures. *J. Micromechanics Microengineering* **16**, 276–284 (2006).

Chapter 4

Continuous Focusing, Fractionation and Extraction of Anionic Analytes in a Microfluidic Chip

Electrokinetic focusing and separation methods, specifically ion concentration polarization focusing (ICPF) provide a very powerful and easy to use analytical tool that can be used in several scientific fields. Nevertheless, the concentrated and separated analytes are effectively trapped inside the chip in picoliter volumes, complicating further processing. In this chapter we propose an ICPF device that allows continuous and selective extraction of the focused analytes. A theoretical background is presented to understand the dynamics of the system and an 1D model was developed that describes the general behaviour of the system. We demonstrate the selective extraction of three fluorescent model anionic analytes and we report selective extraction of the analytes at a 300-fold increased concentration.

This chapter is based on the publication: Vasileios A. Papadimitriou, Loes I. Segerink and Jan C. T. Eijkel. "Continuous Focusing, Fractionation and Extraction of Anionic Analytes in a Microfluidic Chip. " Lab-on-Chip 2019, <https://doi.org/10.1039/c9lc00434c>

4.1| Introduction

Electrokinetic separation methods are powerful tools that have found application in a wide range of fields, from biological/chemical research to food industry and forensics. Since the early days of microfluidics many electrokinetic separation methods have been translated to lab-on-chip systems. A special class of electrokinetic techniques combines *separation* and *focusing* such as isoelectric focusing (IEF), electric field gradient focusing (EFGF) and isotachopheresis (ITP). These techniques require an application-specific electrolyte preparation which can be a tedious process and significantly reduce their usability for point-of-care systems. For example, ITP requires a leading and trailing electrolyte with electrophoretic mobilities higher and lower than the target analyte. In recent years ion concentration polarization focusing (ICPF) was introduced, which is capable of concentrating and separating analytes without the use of specific electrolytes. ICPF focuses analytes in the electric field gradient created by the phenomenon of ion concentration polarization (ICP).

ICPF was introduced by Wang et al¹ more than a decade ago and it was capable of concentration factors of proteins and peptides in the order of millions. Since its introduction vast amount of research has been performed with this technique, where Quist et al.² demonstrated that apart from concentration also separation occurred³⁻⁷. Though the technique offers a very powerful and simple analytical tool, a disadvantage is that the focused and separated analytes are “trapped” inside the chip in picoliter volumes. Further analysis, for example by mass spectrometry, thus is impossible. Attempts to extract the preconcentrated analytes have been reported, but they require the use of Quake valves⁸ or magnetically actuated valves⁹. Continuous extraction of the concentrated biomolecules and cells in non-selective fashion has been demonstrated by Kwak et al¹⁰. In this article we propose an ICPF device modified to selectively and continuously extract the fractionated and concentrated analytes from their complex background, allowing further downstream analysis.

Figure 4.1 - Device outline (a) and concept of our ICPF device for extraction (b). (a) A potential is applied in the upstream (V_u) and downstream (V_d) reservoir with V_u>V_d. A low negative pressure is applied in the extraction channels marked with green. The side channels are filled with a buffer and they are grounded. A depletion zone (shown in white(b)) is formed due to ICP when an E-field is applied across an exclusion zone (Nafion) (b,c). At the interface between dz and the bulk (shown in orange) the concentration gradient (c) creates an E-field gradient zone when a second E-field is applied across it. All ions move towards the dz with a constant net flow (v_{conv}) but due to their difference in electrophoretic mobility (μ_{eph}) they experience different **electrophoretic velocity** (v_{eph}) in the E-field gradient zone resulting in separation. The analytes will start focusing at the position in the E-field that electrophoretic (v_{eph}) and bulk flow velocity (v_{conv}) are equal and opposite (d). Due to non-uniformities of the electro-osmotic flow (EOF) an induced pressure (P_{ind}) is created at the focusing location (e). 1D area averaged flow velocities. The focused analytes can be placed at the extraction channel and will be extracted under low negative pressure, which needs to be lower than the induced pressure (P_{ext}<P_{ind}) Note: On figure (e) the EOF arrow accounts for both the primary and secondary EOF due to the extended space charge close to the Nafion membrane¹¹.

4.2| Theory

4.2.1| Concentration Polarization and Establishment of a Depletion Zone

In order to understand the dynamics of the device we will first briefly describe the process of ICPF. For a more extensive theoretical description of ICPF the reader is referred to the recent report by Ouyang et al¹¹. In addition the feasibility of extraction of concentrated (cationic) analytes via ICPF was reported via numerical simulations of similar systems^{12,13}. ICPF is based on differential ionic migration in an electric field gradient. The electrical field gradient is created by applying a steady potential difference over a microchannel which contains a region in the axial direction with a salt concentration gradient. As the current density must be equal in the entire system, an electric field gradient results, which can be formulated as

$$E(x) = J \cdot \rho(x) \quad (4.1)$$

with $J[A/m^2]$ the current density, $\rho[\Omega m]$ the electrical resistivity of the solution and x the axial coordinate. In order to form the concentration gradient in ICPF, the phenomenon of ICP is used¹⁴. A typical configuration to generate an ICP is by connecting the microchannel considered to one or two other microchannels via a “cation-permselective zone” (Figure 4.1a)⁵. The term “cation-permselective zone” indicates an area where predominantly cations are able to enter and pass through, and the anion transport is greatly reduced. This cation-permselective zone, typically a nanochannel⁹ or a cation-permselective membrane such as Nafion⁴, creates a flux gradient of the anions and cations in the direction of the electric field. This flux gradient removes cations and anions from the anodic side of the barrier resulting in a zone with low concentration of all ionic species, called the **depletion zone**.

Figure 4.1a shows the separation channel connected to two buffer channels via a Nafion membrane, which was patterned by capillarity¹⁵ in a manner previously reported⁵. The buffer channels are grounded while two different potentials are applied at the ends of the separation channel (V^u at upstream and V^d at downstream reservoir with $V^u > V^d$). This configuration will create a depletion zone in the separation channel and simultaneously apply an axial electrical field. At the interface between the depletion zone and the bulk solution an E-field gradient is generated, where anionic analytes will be focused (see below).

The novelty of our device is, that to perform continuous extraction, we added two extraction channels to this configuration, intersecting the separation channel perpendicularly (Figure 4.1b). The focused analytes are extracted by applying a small negative pressure (P_{ext}) in these extraction channels. The system variables relevant for the extraction process are the analyte position, analyte extraction rate and analyte concentration rate. The two reservoir potentials (V^u and V^d) and the extraction pressure (P_{ext}) all influence these variables and their effects are coupled. To describe this complex system an approximative one-dimensional (1D) model was created. It consists of two coupled parts: a model for the electrical currents (Figure 4.2, blue) and a model for the hydrodynamic fluxes in the system (Figure

4.2, green). The model is limited in its scope as it does not provide a description of the formation of the different analyte zones in the E-field gradient zone. However, it serves as a model to understand the coupling of the electrical and hydrodynamic phenomena of the device.

Figure 4.2 - Schematic of the 1D model for our ICPF extraction device. Each resistance and current is a function of the parameters stated in the brackets next to it. The **electric** model describes the electric response of the system and the growth of the depletion zone ($\frac{dl_e}{dt}$) due to ICP. The inputs for the electric model are the actuation potentials and some system parameters such as dimensions, conductivities and concentrations. The outputs, which are $\frac{dl_e}{dt}$ and all the potentials (in each node V_i) between bulk and depletion zone interfaces, are fed to the **fluidic** model. The **fluidic** model with the use of the potentials and zone sizes (provided by the electric model) calculates the E-fields and EOFs (represented as current sources) in each zone. The unequal current sources induce a secondary current (representing induced pressure-driven flow) through the hydraulic resistors (R_f^i). The total current ($\frac{dl_f}{dt}$) (i.e. bulk flow = EOF+PDF+PDF_{ind}) is calculated and updates the zone sizes which is fed back to electric circuit. The process is repeated until convergence and the converged solution for focusing position (l^u), bulk flow in the separation channel (concentration rate) and extraction flow for each time step is exported.

4.2.2| Electric model (Figure 4.2)

As mentioned above, the cation-permselective Nafion membrane creates a local gradient of the cation and anion fluxes, creating the depletion zone in the separation channel. For simplicity of the model we assume that the current is carried exclusively by the background electrolyte (not by the analytes) and that

the cation and anion transport numbers in the bulk solution are equal. We also assume that the membrane is perfectly cation selective. We denote the salt concentration in the depletion zone as C_{dz} . Under these conditions, the growth rate of the depletion zone length in the channel, dl_e/dt [$m s^{-1}$], depends on the current running through the Nafion membrane as

$$\frac{dl_e}{dt} = \frac{I}{2(C_b - C_{dz})FA_c} \quad (4.2)$$

where $I[A]$ is the electric current through the membrane, $F[C mol^{-1}]$ is the Faraday constant, $C_b[mol m^{-3}]$ is the bulk ion concentration and $A_c[m^2]$ is the cross-sectional area of the separation channel. The growth rate of the depletion zone thus scales linearly with the electric current through the Nafion membrane. The conductivity in the depletion zone is generally measured to be several orders of magnitude lower than in the bulk⁴, and hence the total resistance of the system increases when the depletion zone grows and occupies an increasing part of the channel. Since constant potentials are applied to the reservoirs, the current through the channel and the Nafion membrane decreases as the depletion zone grows, resulting in a reduced growth rate of this zone as time proceeds. The electric model shown in Figure 4.2 was created to calculate at any moment in time the size of each zone (bulk, depletion zone) both upstream and downstream from the Nafion membrane, as well as the various currents and the potentials at each interface between the zones.

4.2.3| Fluidic model (Figure 4.2)

The fluxes of the analyte ions i , $J_i[mol m^{-2}s^{-1}]$ are given by the Nernst-Planck equation. We formulate the fluxes as a function of axial position x as:

$$J_i(x) = J_{i,diff}(x) + J_{i,conv}(x) + J_{i,eph}(x) \quad (4.3)$$

Here $J_{i,diff}$, $J_{i,conv}$ and $J_{i,eph}$ are the flux contributions of diffusion, convection and electrophoresis of analyte ions i , respectively. In our initial analysis we neglect diffusion for reasons of simplicity ($J_{i,diff}(x)=0$).

We will now discuss the separate contributions to the flux of analyte i in equation (4.3) in more detail.

The contribution by convection is

$$J_{i,conv}(x) = v_{conv}C_i(x) \quad (4.4)$$

Here $C_i[mol m^{-3}]$ is the concentration of the species i and $v_{conv}[m s^{-1}]$ the linear convective liquid velocity assuming constant channel cross section. It has been demonstrated that the area-averaged bulk flow velocity in a channel can be obtained by a linear combination of pressure-driven ($v_{PDF}[m s^{-1}]$) and electroosmotic flow ($v_{EOF}[m s^{-1}]$).¹⁶ In our channel a pressure distribution is created by the suction that is applied at the extraction channels, as well as by the

axial variation of EOF stemming from the conductivity gradient, that by the requirement of mass conservation locally generates a restoring pressure-driven flow. Below we will briefly treat both contributions.

Electroosmotic flow – The EOF magnitude varies along the channel length, as it is determined by the local electric field, which results from the potential difference between upstream (V^u) and downstream (V^d) reservoirs and the local resistivity (equation (4.1)). At any location along the channel the magnitude of the EOF follows from the Helmholtz-Smoluchowski equation:

$$v_{EOF}(x) = \frac{\varepsilon \varepsilon_0 \zeta}{\eta} E(x) \quad (4.5)$$

where $\eta[kgm^{-1}s^{-1}]$ is the viscosity of the liquid, $\zeta[V]$ is the zeta potential (assumed constant in the model) and $\varepsilon, \varepsilon_0[Fm^{-1}]$ are the relative and vacuum permittivity. In our system EOF generally is the dominant convective velocity so the net convective velocity vector follows the EOF direction. Since we have a negative zeta potential and $V^u > V^d$ the bulk solution flows from the upstream to the downstream reservoir. In the depletion zone of the separation channel, the high E-field results in a high EOF velocity while in the remainder of the channel the low E-field results in a low EOF velocity. EOF is also significantly affected by the zeta potential (ζ) which is directly influenced by the pH. Mogi et al.¹⁷ reports a significant change of the pH close the depletion zone. Here we will neglect this effect.

EOF-induced pressure driven flow – Since aqueous electrolytes are non-compressible and because of mass conservation, a pressure-driven flow is induced towards the interface between the bulk and the depletion zone, where a negative pressure is generated. An EOF-induced pressure is for example also reported by Herr et al.¹⁶ in the case of channels with a non-uniform zeta potential.

In addition, close to the membrane a space charge region exists due to ICP^{18–22}. The space charge region has a large net positive charge, so the action of the electrical field in the bulk is to move it to the cathodic reservoir (same direction as the main EOF). Because this EOF (usually named electroosmosis of the second kind¹¹) is so much larger than anywhere else in the channel, we get the PDF back-flow vortices. A small part of the extra ‘push’ on the solution is translated to a PDF towards the cathode. Summarizing, the space charge region at the Nafion acts as a small and strong pump.

The device is operated in the over-limiting current regime¹⁹ where these EOF induced vortices have a strong contribution to the local 2D flow velocity profile. The 2D flow velocity profile that will result from the combination of all PDF and EOF contributions is a rich scientific topic^{4,11,23,24}, which for simplicity we here reduce to an area-averaged 1D flow velocity (Figure 4.1e).

Adding both contributions to the bulk flow velocity ($v_{conv} = v_{EOF}(x) + v_{PDF}(x)$), we can write the convective flux as:

$$J_{i,conv}(x) = v_{EOF}(x)C_i(x) + v_{PDF}(x)C_i(x) \quad (4.6)$$

Extraction pressure driven flow – The extraction channels are electrically floating; hence they have no contribution of EOF. We extract the analytes by applying an external pressure at the extraction channel intersections with the separation channel (P_{ext}), which pressure must be lower than the local EOF-induced negative pressure ($P_{ext} < P_{ind}$). It must be noted that without an applied extraction pressure, or when the applied pressure is lower than the induced pressure (P_{ind}), the flow is directed from the extraction channels towards the separation channel. In our system this effect can however be neglected, as the thin and long extraction channels have high hydrodynamic resistance and the induced and applied external pressures result in minute volume flows, approximately two orders of magnitude smaller than the EOF volume flow.

Analyte electrophoresis and focusing – Anions migrate in the opposite direction of the convective flow with an electrophoretic velocity ($v_{i,eph}$) which scales linearly with the local electric field ($E(x)[V\ m^{-1}]$).

$$v_{i,eph}(x) = \mu_{i,eph}E(x) \quad (4.7)$$

Here $\mu_{i,eph}[m^2s^{-1}V^{-1}]$ is the electrophoretic mobility. At the interface between the depletion zone and the bulk a region exists with a concentration and thus E-field gradient. The further the analytes move up the electric field in this zone, the higher their electrophoretic velocity. Within a certain mobility window, each ionic species will have a specific point in the gradient where its electrophoretic velocity is equal and opposite to the convective flow velocity, at which point it will be focused (Figure 4.1d)². The analytes will thus be separated and create focused bands, sorting themselves out based on their electrophoretic mobilities with the lowest mobility ion closest to the depletion zone, where the E-field is highest.

Analyte extraction - By tuning the focusing location of a specific analyte by the applied potentials to the intersection point of separation channel and extraction channels, and by applying a low negative pressure at the extraction channels, we will be able to *selectively* extract the focused analytes whose mobilities fall within a specific electrophoretic mobility window. This mobility window will depend on the electric field gradient and the width of the extraction channel.

Fluidic model – The fluidic model (figure 4.2) derives the convective bulk flow in the main channel. An electric equivalent of the fluidic system is used where the volumetric flows, pressures and hydraulic resistances are represented by currents, potentials and electric resistances, respectively. Similar approaches have been reported before^{25–29}, but in our system the local magnitude of the EOF (generated by the local E-field) is provided by the coupled electric model. The EOF of the second kind can be accounted in the model via the use of high zeta potential in the upstream depletion zone. The EOF in each section of the channel (bulk, depletion zone) is modelled as a current source with a current magnitude that is calculated from the linear velocity (equation 4.4) multiplied by the cross-sectional area. The length of each zone, and the potential differences applied across it are provided by the coupled electric model. The zone lengths are denoted as l^u and l^d

for the depletion zone, $L - l^u$ and $L - l^d$ for the bulk solution located upstream and downstream, where L is the distance from reservoir to the Nafion membrane (Figure 4.2). In addition to the EOF, the model derives the induced hydrodynamic pressure by introducing feedback hydraulic resistances based on the length of each zone and the channel cross-sectional geometry. The feedback current that is induced through the resistors to equalize the difference between the current sources, results in a feedback voltage over the hydraulic resistances, which represents the induced hydrodynamic pressure. Finally, the extraction pressure and PDF are simulated via a potential source at the end of the extraction channel (extraction resistance, R_f^{ext}). The resulting current through the separation and extraction channel corresponds to the sum of the convective flows (EOF, PDF) described by equation 4.5.

The basic principle of the model is shown in Figure 4.2. An in-depth analysis is presented in the Appendix B along with a description of the effect of the downstream and up-stream potential on the size of the depletion zone (i.e. focusing location), on the concentration rate and on the maximum induced negative pressure. In the Appendix B the model results are compared and explained based on previous theoretical and experimental works¹⁶⁻²¹. The fitting parameters of the model are the zeta potential in the bulk and in the depletion zone, and the salt concentration in the depletion zone. For the latter we used the parameter “depletion factor” which describes how many times the average concentration in the depletion zone is lower than the bulk. An estimate for the depletion factor was taken from literature.²⁴

4.2.4| Separation and extraction resolution

To determine the separation resolution of the system, we need to distinguish between two operational modes, namely *peak* mode and *plateau* mode, as can be found also in other focusing techniques such as ITP^{2,35}. A schematic of the two modes is shown in figure 4.3.

Operation in peak mode – In this mode (figure 4.3a) the analytes are in very low concentration compared to the bulk electrolyte so that we can assume that they do not contribute to the conductivity and the local E-field in the E-field gradient zone. This is the most common mode for typical applications. In our experiments for example the transport number of the analyte (Bodipy) is approximately $2 \cdot 10^{-6}$ making its contribution to the electric field negligible. In the peak mode the concentrating analytes form a Gaussian concentration profile. Since the early days of separation sciences^{36,37} the shape of the concentrated peak has been investigated. In our analysis we follow the approach from J.C. Giddings³⁸ where a focusing influence (in our case an electric field gradient) works against a defocusing influence (i.e. diffusion). We also assume a constant electric field gradient ($\frac{d^2E}{dx^2} = 0$). This approach results in the concentration profile:

$$C_i(x) = C_{i,0} \exp \left(- \frac{\left(x - \frac{v_{conv} - E_0 \mu_i}{\frac{dE}{dx} \mu_i} \right)^2}{2 \frac{V_T}{z_i \frac{dE}{dx}}} \right) \quad (4.8)$$

Figure 4.3 - a) Peak mode accumulation in the E-field gradient zone. The analytes are in low concentration, so they do not affect the local electric field (green concentration peaks not in scale). The analytes are focused at the E-field magnitude (E_1, E_2) where they acquire a zero net velocity b) Plateau mode. The analyte reaches the maximum concentration that satisfies the Kohlrausch regulation function (KRF) and forms a plateau at its concentration and the local electric field. c) Using a plateau mode analyte as an electrophoretic spacer. The plateau mode analyte pushes the peak mode analytes further apart. The peak mode analytes focus at the same E_1, E_2 values as in (a).

where z_i is the valence of the analyte i , C_0 [mol/m^3] is the maximum concentration of the focused analyte, x [m] is the direction along the separation channel with $x=0$ denoting the location between bulk and depletion zone where the E-field gradient starts and E_0 the electric field in the bulk solution. Furthermore V_T [V] is the thermal potential ($V_T = k_b T / e$ with T [K] the temperature and k_b [J K^{-1}] Boltzmann's constant). Equation 4.8 describes a Gaussian profile with mean

$$x_{eq,i} = \frac{v_{conv} - E_0 \mu_{i,eph}}{\frac{dE}{dx} \mu_{i,eph}} \quad (4.9)$$

and variance σ^2 [m^2]

$$\sigma_i^2 = \frac{V_T}{z_i \frac{dE}{dx}} \quad (4.10),$$

The derivation of equations (4.8) and (4.9) is presented in the ESI. The focusing location of species i is given by equation 4.9. In peak mode we then obtain the resolution R_s

$$R_s = \frac{\Delta x}{2(\sigma_1 + \sigma_2)} \quad (4.11)$$

as

$$R_s = \frac{v_{conv}}{2 \sqrt{\frac{dE}{dx} V_T}} \cdot \frac{\left(\frac{1}{\mu_1} - \frac{1}{\mu_2} \right)}{\left(\frac{1}{\sqrt{z_1}} + \frac{1}{\sqrt{z_2}} \right)} \quad (4.12)$$

In equation 4.12 the first term is device- and actuation potential-dependent while the second term depends on analyte properties. As shown in equation 4.9 the focusing location is inversely proportional to the mobility. Analytes with low electrophoretic mobility will thus focus closer to the depletion zone where the E-field is high. It follows from equation 4.12 that the resolution of such slower analytes, for constant $\Delta\mu = \mu_1 - \mu_2$, will be better than for the faster analytes that focus at a location with lower E-field.

If the analytes are in peak mode, the mobilities of the analytes that are extracted from their focusing position by an extraction channel of determined width lie in a mobility window that can be calculated by equating Δx to the extraction channel width. If the mobility difference between two analytes in peak mode is smaller than that mobility window for a specific extraction channel width, then the extraction of a single analyte is impossible, and adjacent analyte(s) will be extracted along at varying concentration.

Finally, only analytes within a specific mobility window will focus in the device, which window is given by the maximum and minimum electric field and the convective flow velocity. As the analytes require an electrophoretic velocity equal and opposite to the convective flow hence this mobility window (assuming that the analyte i is peak mode and does not contribute to the local conductivity and electric field) is given by

$$\frac{v_{conv}}{E_0} > \mu_i > \frac{v_{conv}}{E_{dz}} \quad (4.13)$$

Operation in plateau mode – If the concentration of an analyte approaches the background electrolyte concentration, it will significantly contribute to the conductivity and its effect on the electric field cannot be neglected. In this case the analyte will concentrate no further and instead of a Gaussian peak a plateau will be formed at the maximum concentration (Figure 4.3b), which will widen in time. At the location of the plateau the E-field will be constant ($dE/dx = 0$). The maximum concentration for a specific analyte can be calculated from the Kohlrausch regulation function (KRF [mol V s m^{-5}])³⁹

$$KRF = \sum_i \frac{z_i C_i}{\mu_i} \quad (4.14)$$

A conservation law can be derived that requires that the KRF value remains constant across all zones in a capillary (i.e. the bulk zone and any plateau formed from an analyte) on application of an electrical field. The E-field gradient is not affected on either side of the plateau hence other less abundant analytes will still be focusing there in peak mode. A known substance can be added to the solution with an electrophoretic mobility intermediate to the two analytes to push them apart (Figure 4.3c). Such a compound is usually named electrophoretic spacer which has been previously reported in ICPF^{3,40}.

4.3| Experimental

In order to test the proposed system and procedure, polydimethyl siloxane (PDMS, DOWSIL™ 184 Silicone Elastomer kit)(1:10 crosslinker to polymer ratio) chips were fabricated. A silicon wafer was spin coated with 35µm of MicroChem® SU-8 2050 negative photoresist and patterned with photolithography mask of the pattern of figure 4.1a. The supplier's instructions for exposure and development were followed to create the SU-8 soft lithography mould. The mould was used for standard soft lithography of PDMS chips⁴¹ which were bonded after O₂ plasma treatment to microscopy glass slides.

A droplet of Nafion® perfluorinated resin solution (20wt. % - Sigma-Aldrich) was introduced in the two reservoirs marked with blue in Figure 4.1a. The Nafion solution filled and pinned in the channel via capillary forces. The Nafion solution was dried at 60°C for 30 minutes to create the solid cation selective Nafion membrane. During the drying process Nafion experiences a significant shrinkage. Because of the shrinkage occasionally Nafion detaches from the PDMS and gaps

are formed that allow undesired flow from the separation to the buffer channels. To eliminate this flow, the buffer channels were filled with 2% wt. UltraPure™ Agarose (Invitrogen) in 1x phosphate buffered saline (PBS) (Sigma-Aldrich). For the fluorescent microscopy an Olympus IX51 was used and images/videos were captured with FLIR Grasshopper®3 color camera. As model cation analytes BODIPY™ 492/515 Disulfonate (BDP) (Invitrogen), Alexa Fluor™ 647 Carboxylic Acid, tris(triethylammonium) (AF647) (Invitrogen) salt, and Cascade Blue™ hydrazide trisodium salt (CB) (Invitrogen) were chosen and diluted in 1x PBS or 0.1x PBS which served as a background electrolyte buffered at pH 7.4. A calibration curve between fluorescent analyte concentration and fluorescent intensity for each analyte was prepared for the specific microscope and camera settings used in the experiments. The concentration factors were then calculated using this curve. The electric potentials were applied by two Keithley 2410 sourcemeter power supplies and the extraction pressure via a Fluigent MFCS-EZ.

Figure 4.4 - Fluorescent microscopy images demonstrating focusing, band formation, control and extraction (1.5μM BDP in 0.1x PBS). a) Focusing of the analyte away from the extraction channel. The concentration of the dye in the extraction channel is similar to the bulk. b) Movement of the focused analyte towards the extraction channel and partial release. c) Focusing and simultaneous extraction. d) Focusing at the other side of extraction channel. If a second slower analyte was present it could be extracted. Scale bar - 100μm.

4.4| Results and discussion

4.4.1| Analyte position control

As described in the model, the analyte focusing position is regulated by regulating the size of the depletion zone, which scales with the ratio of the upstream over downstream potential. An example of the analyte position control is shown in figure 4.4 where the potential control is used to locate the focused analyte band at the intersection with the two extraction channels. The device could subsequently successfully be used for prolonged extraction of a single fluorescent concentrated analyte. In our devices we achieved reproducible and stable extraction for up to 20

minutes with the limit being only posed by the small size of our reservoirs. Longer extractions require larger reservoirs in order to avoid hydrostatic pressure changes and pH changes due to electrolysis.

In figure 4.5 the focusing position is plotted against the ratio of upstream (V^u) and downstream (V^d) potential. The upstream potential was kept steady at 110V and the downstream potential was varied from 110V to 10V and back to 110V with steps of 10V over a period of 35 minutes. The blue points denote the measured position of the analyte over time, while the red line connects the average values for each potential ratio (red bars: standard deviation of the focusing location over time). The instabilities in the position mainly stem from electroconvective vortices and instabilities in the depletion zone^{24,31}. The higher the flow rate (higher $V^u : V^d$) the smaller the deviation from the mean focusing value (standard deviation of $9\mu\text{m}$ at $V^u : V^d$ of 11), while for lower flow rates the standard deviation increases ($19\mu\text{m}$ for $V^u : V^d$ of 1.22).

Figure 4.5 - Analyte position vs upstream over downstream potential ratio. The blue points correspond to the distance of the analyte (BDP in 1x PBS) from the Nafion membrane. The red line connects the average value for each potential ratio and the red bars correspond to the standard deviation. The black line shows the behaviour predicted by our model.

4.4.2| Analyte selection control

We also investigated the use of the analyte positioning control for the selection of focused analyte to be extracted. In figure 4.6 the selection between two negatively charged analytes, namely BDP and AF647 is shown. The electrophoretic mobilities of the two analytes as determined by on-chip electrophoresis were $\mu_{\text{BDP}} = 2.11 \cdot 10^{-8} \text{ m}^2\text{V}^{-1}\text{s}^{-1}$ (a mobility of $1.76 \cdot 10^{-8} \text{ m}^2\text{V}^{-1}\text{s}^{-1}$ is reported in the literature⁴²) and $\mu_{\text{AF647}} = 1.58 \cdot 10^{-8} \text{ m}^2\text{V}^{-1}\text{s}^{-1}$. The slower analyte (i.e. the red AF647) is expected to focus closer to the depletion zone at the right of the figure where the E-field is higher, while the green BDP will focus closer to the bulk solution on the left of the figure, at the lower E-field. By tuning the actuation potentials (V^u, V^d) we could select which of the focused analytes positionally overlaps with the extraction channel and will be extracted.

As shown in experiment A of figure 4.6, in the extraction channels only the fluorescence of the targeted analyte (BDP) is present, while the fluorescence of the “interfering” analyte (AF647) remains below the limit of detection of our microscope. A similar result is shown for experiment B but now with AF647 as target analyte and BDP as “interfering” analyte. The lack of fluorescence of the interfering species in the extraction channel demonstrates that our method in this case could be used for selective extraction.

Figure 4.6 - Separation and extraction of single analytes from a mixture (BDP (green) and AF647 (red)) in 0.1x PBS). Red filter column indicates the AF647 concentration, Green filter column the BDP and Red+Green the composite image. We focus and create bands of both analytes for approximately 15s and then by changing the potentials we release BDP (A) or AF647 (B). The extraction channels remain dark in the red filter (A) and green filter (B) which indicates that only the targeted analyte is extracted. In both experiments an extraction pressure of -3mBar was applied at T=20sec(A) and T=30sec(B). Before the application of the extraction pressure the extraction channels contain bulk liquid. Note: A and B are two separate experiments and the time values are not related. Actuation potentials during extraction (A): $V_u=60V$ and $V_d=30V$, (B) $V_u=60V$ and $V_d=55V$. Scale Bars - 100µm.

As shown in figure 4.6 there is a clear difference in the resolution between experiments A and B before the extraction. This difference is caused by the difference in potential difference applied in the two experiments (30V in A and 5V

in B). As described by equation 4.12 the resolution improves with a lower electric field gradient (i.e. lower potential difference) at the cost of the concentration rate. The poor resolution results in the substantial overlap between the concentrated analytes seen in figure 4.6A. A selective extraction of analyte in that case is still possible but requires a small width of the extraction channel relative to the width of the desired concentrated analyte band.

The extraction of *fluorescent* analytes is a straightforward, reproducible and robust process, since we can monitor our analyte of interest until its position overlaps with the extraction channel. Extraction of non-fluorescent analytes would be a more cumbersome process, since the electrophoretic mobility of the analyte of interest must be known with respect to the electrophoretic mobilities to the other species in the solution. A possible experimental solution is to use a fluorescent substance with a mobility close to analyte of interest as a marker, placing it adjacent to the extraction channel.

Figure 4.7 - Concentration factor as (concentration)/([bulk concentration]) of analytes in the extraction channel versus time. i) At $t=0$ s the device is turned on with actuation potentials of $V^u=80$ V and $V^d=20$ V and an extraction pressure of -15mBar. The analytes are focusing at a location that does not overlap with the extraction channel hence the concentration at the extraction channel does not change. ii) At $t=60$ s potentials are changed to $V^u=80$ V and $V^d=45$ V which moves the focused analytes to the extraction channel. The extraction pressure of -15mBar creates an extraction flux that is lower than the incoming flux in the separation channel hence a constant increase in the concentration is seen. iii) At $t=160$ s the actuation potentials remain constant and the pressure is reduced to -13mBar hence an even lower extraction flux results in a higher concentration increase in the extraction channel. iv) At $t=200$ s the actuation potentials remain constant and the pressure is increased back to -15mBar. It was expected that the original concentration increase rate (slope between ii and iii) will be restored, but that only occurred after approximately 40s. Electrolyte: 1xPBS. Analytes: 100nM BDP, 100nM AF647.

4.4.3| Higher concentration factors

The factor with which the extracted analyte can be concentrated is tuneable. A steady extracted concentration factor is achieved when the extracted analyte flux matches the arriving analyte flux through the main channel towards the extraction location. A typical operational scheme for this purpose is the following: i) The process is initiated with actuation potentials such that the focusing location of the analyte is not overlapping the extraction channel; ii) A sufficient waiting time (typically a concentration rate is 1 times the bulk concentration per second) ensures that the desired concentration factor is achieved; iii) The potentials are adjusted to move the focused analyte band to the extraction channel; iv) A negative pressure is applied at the extraction channel to create an extraction flux that approximately matches the incoming analyte flux. An example of an extraction attempting to follow this scheme is shown in figure 4.7. We obtained an average concentration factor of about 200 in the continuously extracted analyte over several minutes. During the experiments (as also can be seen in figure 4.7) a slow response time of the pressure-driven flow was noticed varying between 5 to 40 seconds. We attribute this to instabilities of the pressure controller which was operated at its resolution limit. In addition, as can be seen in figure 4.7, the change of only 2mBar in extraction pressure introduced at moment iii has a strong influence on the extraction rate. We conclude that a better controllability of the extraction process is needed In future devices, which can be implemented e.g. by increasing the hydraulic resistance of the extraction channel.

Despite the high concentration factor of AF647 as seen in figure 4.7, in this experiment we obtained low selectivity since also BDP was extracted (at a concentration factor approximately 2/3 of AF647). Similar to figure 4.6A this was due to the poor separation resolution caused by the high potential difference.

As described in the theory section the separation resolution can be improved using an electrophoretic spacer. In figure 4.8 an example of the use of a spacer is shown. A third fluorescent marker (CB) was added with a mobility higher than BDP and the added phosphate of the buffer, causing the phosphate (H_2PO_4^-) to reach its plateau concentration and act as a spacer, while AF647 and BDP remained in peak mode and at their initial position.

Figure 4.8 - Normalised concentration profile of three focused fluorescent analytes in peak mode. a) $t=10s$. The concentration of the electrophoretic spacer is still low comparable to the background electrolyte hence also the spacer is still in peak mode. b) $t=150s$. The concentration of the spacer has increased hence now it is in plateau mode pushing CB peak away from AF647 and BDP. The concentration was normalized based on the maximum fluorescent intensity for each fluorescent analyte independently. Electrolyte: 1xPBS. Analytes: 100nM BDP, 100nM AF647. $V^u=60V$ and $V^d=35V$.

4.4.4| Comparison to the theoretical model

In the experiments characterizing the analyte positioning (Figure 4.4) a single fluorescent analyte was used and the focusing position (i.e. depletion zone length) was found to scale, as predicted by our model, with the ratio of upstream over downstream potential. We found experimentally that the baseline width (4σ) of the focused analyte varied between $57\mu m$ (for $V^u=60V$, $V^d=0V$) and $141\mu m$ (for $V^u=60V$, $V^d=55V$). Equation 4.10 allows us to derive the local E-field gradients from these measured peak widths. As the model provides us with the electric field in the bulk section of the channel and in the depletion zone at the applied potentials, the length of the E-field gradient zone can now be estimated assuming a constant electric field gradient. With this approach we derived an E-field gradient zone length of approximately $500\mu m$. Since the extraction channels have a width of $20\mu m$, this allows us safe overlap and a steady extraction of an analyte even in the case of a slight variation in the position of the focused analyte over time (standard deviation $19\mu m$ in the focusing position as calculated from Figure 4.5).

Figure 4.9 - Maximum concentration factor of three fluorescent analytes over time in the separation channel (a) and the extraction channel (b). a) Concentration factor of analytes in the separation channel. All analytes are concentrating with the same rate till $t=150$ s when the extraction pressure of -17 mBar is applied. Once the extraction starts then the maximum concentration of AF647 and BDP drops in the separation channel while the concentration increase of CB is unaffected. b) Concentration factor of analytes in the extraction channel. Before the application of extraction pressure at $t=150$ s no enrichment in the separation channel can be seen. Once the pressure is applied only AF647 and BDP are observed in the extraction channel.

The σ of the Gaussian (green and red) peaks in the experiments at higher concentration factors (figure 4.8b) is approximately $26\mu\text{m}$ indicating an electric field gradient of $1.849 \cdot 10^6 \text{ V/m}^2$ (based on equation 4.10). At this field gradient our model predicts a spacing between the peaks of BDP and AF647 of $23\mu\text{m}$ comparing well to the experimentally observed spacing of $19\mu\text{m}$. Interestingly it was found that the σ of the blue peak (CB) increased from $19\mu\text{m}$ (Figure 4.8a) to $31\mu\text{m}$ (figure 4.8b) during the experiment indicating that the electric field gradient is less steep further away from the depletion zone. Figure 9 shows the maximum concentration factor of the three analytes over time in the separation channel (Figure 4.9a) and in the extraction channel (4.9b). Our model predicts a concentration rate of 2.7 times the bulk concentration per second while an average concentration rate of 2.1 can be seen in figure 4.9a. Before the extraction pressure was applied ($t < 150$ s) all three analytes focussed with approximately the same concentration rate. Once the extraction pressure was applied, AF647 was extracted together with a lower concentration of BDP, similarly to figure 4.7. However, no detectable amount of the CB was extracted as it was pushed away from the extraction channel by the electrophoretic spacer.

In figure 4.7 and 4.9b a strong variation can be seen in the maximum concentration of the extracted analytes. This can be attributed to hydrodynamic instabilities in the focusing location at high potentials in ICPF, causing variations in the spatial overlap between the focused analyte band and the extraction channel.

Summarizing, the high electric field gradients that result in narrowly focused and highly concentrated bands, also drastically reduce the resolution of the method as can be seen from the denominator in Equation 4.12. The resolution of the system will thus be superior for lower potential differences between upstream and

downstream reservoirs. This is further theoretically described in the Appendix B and can also be seen in figure 4.6B. There thus exists a trade-off between high resolution and high concentration rate. This conundrum can be solved by increasing the value of the numerator in Equation 4.12 by a method independent of EOF. This can be done e.g. by additional PDF. The addition of a PDF will also shift the mobility window of analytes that will be focused in the device. We can thus envision two potential future uses of this method. If the main interest is to obtain extracted analytes at enhanced concentration in continuous flow, the default operation (i.e. without the addition of spacers and/or added convective flow) of the device can be used, if needed in combination with pressure-driven flow. If the main interest is the purity of the extract, electrophoretic spacers can be used (if the mobility of the analyte is known) or an external pressure driven flow can be added for improved separation resolution.

4.5| Conclusions and outlook

We demonstrated a device capable of selective extraction and concentration of anionic analytes out of a complex background solution. The maximum concentration factor of the extracted analytes found was above 300, as measured by an increased fluorescence intensity. In order to investigate the dynamics of the system and deepen our understanding of the phenomena at play, a simple two-part one-dimensional model (i.e. an electric and a fluidic) was developed that describes the input-output relations of the system (applied potentials, extraction pressure – focusing position, concentration rate, extraction rate) to a level that allowed prediction of the system behaviour. Different future modes of operation are described based on the model and the experiments.

4.6| References

1. Wang, Y. C., Stevens, A. L. & Han, J. Million-fold preconcentration of proteins and peptides by nanofluidic filter. *Anal. Chem.* (2005). doi:10.1021/ac050321z
2. Quist, J., Janssen, K. G. H., Vulto, P., Hankemeier, T. & Van Der Linden, H. J. Single-electrolyte isotachophoresis using a nanochannel-induced depletion zone. *Anal. Chem.* **83**, 7910–7915 (2011).
3. Quist, J., Vulto, P., Van Der Linden, H. & Hankemeier, T. Tunable ionic mobility filter for depletion zone isotachophoresis. *Anal. Chem.* **84**, 9065–9071 (2012).
4. Kim, S. J., Li, L. D. & Han, J. Amplified electrokinetic response by concentration polarization near nanofluidic channel. *Langmuir* **25**, 7759–7765 (2009).
5. Liu, V., Song, Y.-A. & Han, J. Capillary-valve-based fabrication of ion-selective membrane junction for electrokinetic sample preconcentration in PDMS chip. *Lab Chip* **10**, 1485 (2010).
6. Khandurina, J., Jacobson, S. C., Waters, L. C., Foote, R. S. & Ramsey, J. M. Microfabricated porous membrane structure for sample concentration and electrophoretic analysis. *Anal. Chem.* **71**, 1815–1819 (1999).
7. Ko, S. H. *et al.* Nanofluidic preconcentration device in a straight

- microchannel using ion concentration polarization. *Lab Chip* **12**, 4472 (2012).
8. Choi, J. *et al.* Selective preconcentration and online collection of charged molecules using ion concentration polarization. *RSC Adv.* **5**, 66178–66184 (2015).
 9. Chen, Y. Y., Chiu, P. H., Weng, C. H. & Yang, R. J. Preconcentration of diluted mixed-species samples following separation and collection in a micro-nanofluidic device. *Biomicrofluidics* **10**, (2016).
 10. Kwak, R., Kim, S. J. & Han, J. Continuous-flow biomolecule and cell concentrator by ion concentration polarization. *Anal. Chem.* (2011). doi:10.1021/ac2012619
 11. Ouyang, W., Ye, X., Li, Z. & Han, J. Deciphering ion concentration polarization-based electrokinetic molecular concentration at the micro-nanofluidic interface: theoretical limits and scaling laws. *Nanoscale* (2018). doi:10.1039/c8nr02170h
 12. Gong, L., Ouyang, W., Li, Z. & Han, J. Direct numerical simulation of continuous lithium extraction from high Mg²⁺/Li⁺ ratio brines using microfluidic channels with ion concentration polarization. *J. Memb. Sci.* (2018). doi:10.1016/j.memsci.2018.03.078
 13. Gong, L., Li, Z. & Han, J. Numerical simulation of continuous extraction of highly concentrated Li⁺ from high Mg²⁺/Li⁺ ratio brines in an ion concentration polarization-based microfluidic system. *Sep. Purif. Technol.* (2019). doi:10.1016/j.seppur.2019.01.036
 14. Pu, Q., Yun, J., Temkin, H. & Liu, S. Ion-Enrichment and Ion-Depletion Effect of Nanochannel Structures. *Nano Lett.* **4**, 1099–1103 (2004).
 15. Papadimitriou, V. A., Segerink, L. I., van den Berg, A. & Eijkel, J. C. T. 3D capillary stop valves for versatile patterning inside microfluidic chips. *Anal. Chim. Acta* (2017). doi:10.1016/j.aca.2017.11.055
 16. Herr, A. E. *et al.* Electroosmotic capillary flow with nonuniform zeta potential. *Anal. Chem.* (2000). doi:10.1021/ac990489i
 17. Mogi, K. A visualization technique of a unique pH distribution around an ion depletion zone in a microchannel by using a dual-excitation ratiometric method. *Micromachines* **9**, (2018).
 18. Dukhin, S. S. Electrokinetic phenomena of the second kind and their applications. *Adv. Colloid Interface Sci.* (1991). doi:10.1016/0001-8686(91)80022-C
 19. Rubinstein, S. M. *et al.* Direct observation of a nonequilibrium electro-osmotic instability. *Phys. Rev. Lett.* (2008). doi:10.1103/PhysRevLett.101.236101
 20. Rubinstein, I., Zaltzman, B. & Lerman, I. Electroconvective instability in concentration polarization and nonequilibrium electro-osmotic slip. *Phys. Rev. E - Stat. Nonlinear, Soft Matter Phys.* (2005). doi:10.1103/PhysRevE.72.011505
 21. Rubinstein, I. & Zaltzman, B. Electro-osmotic slip of the second kind and instability in concentration polarization at electrodialysis membranes. *Math. Model. Methods Appl. Sci.* (2003). doi:10.1142/s0218202501000866

22. Rubinstein, I. & Zaltzman, B. Electro-osmotically induced convection at a permselective membrane. *Phys. Rev. E - Stat. Physics, Plasmas, Fluids, Relat. Interdiscip. Top.* (2000). doi:10.1103/PhysRevE.62.2238
23. Leinweber, F. C. & Tallarek, U. Nonequilibrium electrokinetic effects in beds of ion-permselective particles. *Langmuir* (2004). doi:10.1021/la048408n
24. Kim, S. J., Wang, Y. C., Lee, J. H., Jang, H. & Han, J. Concentration polarization and nonlinear electrokinetic flow near a nanofluidic channel. *Phys. Rev. Lett.* **99**, (2007).
25. Plecis, A. & Chen, Y. Microfluidic analogy of the Wheatstone Bridge for systematic investigations of electro-osmotic flows. *Anal. Chem.* (2008). doi:10.1021/ac800186c
26. Xuan, X. & Li, D. Analysis of electrokinetic flow in microfluidic networks. *J. Micromechanics Microengineering* (2004). doi:10.1088/0960-1317/14/2/018
27. Ajdari, A. Steady flows in networks of microfluidic channels: Building on the analogy with electrical circuits. *Comptes Rendus Phys.* (2004). doi:10.1016/j.crhy.2004.02.012
28. Glawdel, T., Elbuken, C., Lee, L. E. J. & Ren, C. L. Microfluidic system with integrated electroosmotic pumps, concentration gradient generator and fish cell line (RTgill-W1)-towards water toxicity testing. *Lab Chip* (2009). doi:10.1039/b911412m
29. Oh, K. W., Lee, K., Ahn, B. & Furlani, E. P. Design of pressure-driven microfluidic networks using electric circuit analogy. *Lab on a Chip* (2012). doi:10.1039/c2lc20799k
30. Zangle, T. A., Mani, A. & Santiago, J. G. Effects of constant voltage on time evolution of propagating concentration polarization. *Anal. Chem.* **82**, 3114–3117 (2010).
31. De Valença, J. C., Wagterveld, R. M., Lammertink, R. G. H. & Tsai, P. A. Dynamics of microvortices induced by ion concentration polarization. *Phys. Rev. E - Stat. Nonlinear, Soft Matter Phys.* **92**, (2015).
32. Kirby, B. J. & Hasselbrink, E. F. Zeta potential of microfluidic substrates: 1. Theory, experimental techniques, and effects on separations. *Electrophoresis* **25**, 187–202 (2004).
33. Kirby, B. J. & Hasselbrink, E. F. Zeta potential of microfluidic substrates: 2. Data for polymers. *Electrophoresis* **25**, 203–213 (2004).
34. Sung, J. K. & Han, J. Self-sealed vertical polymeric nanoporous-junctions for high-throughput nanofluidic applications. *Anal. Chem.* **80**, 3507–3511 (2008).
35. Rubin, S., Schwartz, O. & Bercovici, M. Sample distribution in peak mode isotachopheresis. *Phys. Fluids* (2014). doi:10.1063/1.4861399
36. MacInnes, D. A. & Longworth, L. G. Transference Numbers by the Method of Moving Boundaries. *Chem. Rev.* **11**, 171–230 (1932).
37. Tiselius, A. A new apparatus for electrophoretic analysis of colloidal mixtures. *Trans. Faraday Soc.* **33**, 524–531 (1937).
38. Giddings, J. C. *Unified Separation Science*. (John Wiley & Sons, 1991).
39. Kohlrausch, R. Theorie des elektrischen Rückstandes in der Leidener Flasche. *Ann. Phys.* **167**, 179–214 (1854).

40. Cheow, L. F., Sarkar, A., Kolitz, S., Lauffenburger, D. & Han, J. Detecting kinase activities from single cell lysate using concentration-enhanced mobility shift assay. *Anal. Chem.* (2014). doi:10.1021/ac502185v
41. Weibel, D. B., DiLuzio, W. R. & Whitesides, G. M. Microfabrication meets microbiology. *Nat. Rev. Microbiol.* **5**, 209–218 (2007).
42. Splawn, B. G. & Lytle, F. E. On-chip absorption measurements using an integrated waveguide. *Anal. Bioanal. Chem.* (2002). doi:10.1007/s00216-002-1316-9

Chapter 5

Free Flow Ion Concentration Polarization Focusing (FF-ICPF)

Electrokinetic separation techniques in microfluidics are a powerful analytical chemistry tool, although an inherent limitation of microfluidics is their low sample throughput. In this chapter we report a free-flow variant of an electrokinetic focusing method, namely ion concentration polarization focusing (ICPF). The analytes flow continuously through the system via pressure driven flow while they separate and concentrate perpendicularly to the flow by ICPF. We demonstrate free-flow ion concentration polarization focusing (FF-ICPF) in two operating modes, namely peak and plateau modes. Additionally, we showed the separation resolution could be improved by the use of an electrophoretic spacer. We report a concentration factor of 10 in human blood plasma in continuous flow at a flow rate of $15\mu\text{l min}^{-1}$.

This chapter is submitted for publication as: Vasileios A. Papadimitriou, Loes I. Segerink and Jan C. T. Eijkel. "Free Flow Ion Concentration Polarization Focusing (FF-ICPF)

5.1| Introduction

Lab-on-chip (LOC) systems provide an appealing platform for electrophoretic separations due to their high controllability of fluid flow and electric field at the micrometer scale. A subclass of electrophoretic separation methods combines separation and focusing such as electric field gradient focusing ¹, isoelectric focusing (IEF) and isotachopheresis (ITP). Also, ion concentration polarization focusing (ICPF) belongs to this special class of techniques. In contrast to other techniques of the same class (*e.g.* ITP and IEF) ICPF does not require any sample preparation or specific electrolytes that can prove to be a tedious process.

Wang *et al* ² specifically introduced ICPF as a method capable of achieving focusing. They demonstrated extremely high concentration factors in the order of millions. Later Quist *et al* ³ also demonstrated separation of anionic analytes in a similar system. Since its introduction, additional research has been performed with this technique ³⁻⁸. Though ICPF offers a very powerful analytical tool, an inherent disadvantage of miniaturizing any separation technique in LOC systems is the low throughput of sample. Additionally, in many cases the separated analytes are effectively trapped in chip, thereby prohibiting any downstream analysis such as by mass spectrometry.

In order to overcome this limitation, a “free flow” variant of a separation method can be used. The term “free flow” refers to methods where the separation direction is perpendicular to the flow direction allowing continuous high-throughput separation and extraction. Several electrophoretic separation methods have been adapted and demonstrated to free-flow variants ^{9,10} including focusing techniques such as ITP ¹¹ and IEF ^{12,13}, as reviewed by Kohlheyer *et al* ¹⁴. Also attempts to extract preconcentrated analytes have been reported, but the use of Quake valves ¹⁵ or magnetically actuated valves ¹⁶ makes the extraction non-continuous and low throughput (*i.e.* flow rates in the nl min^{-1} range¹⁷. ICPF has been used in high throughput applications for separation particles ($1\mu\text{l min}^{-1}$) ¹⁸, bacterial lysis ($>1\text{ml min}^{-1}$) ¹⁹ and desalination ($<20\mu\text{l min}^{-1}$) ²⁰. The required flow rate (throughput) is dependent on the specific application. Specifically the throughput is determined by the sensitivity of the detection method and the concentration of the analyte of interest present in the sample ²¹. In this article we propose a setup for continuous high throughput concentration and separation of anionic analytes based on free-flow ICPF (FF-ICPF).

5.2| Theory

A schematic of the FF-ICPF process is shown in figure 5.1. The microfluidic device consists of a chamber where the separation takes place, which is connected via a Nafion patterned region to a microchannel. An electric field is applied in the y-direction and a pressure-driven flow (PDF) perpendicular to the electric field (x-direction, figure 5.1). We will first give a short description of ICPF in order to understand the dynamics of our system. ICPF is a concentration and separation method of ionic species based on their differential migration in an electric field gradient. In ICPF the electric field gradient is created via a constant electric potential across a background electrolyte concentration gradient. The concentration gradient is thereby created via the phenomenon of ion

concentration polarization (ICP) ²². When a potential is applied across a cation perm-selective membrane, the biggest fraction of the current is carried by the cations. The flux imbalance between cations and anions through the perm-selective region removes anions from the anodic side resulting in a zone with low concentration of all species known as the depletion zone. Such a cation perm-selective zone can be a nanochannel ²² or a cation perm-selective polymer (e.g. Nafion [®]).

Figure 5.1 - a) Design of the device and a typical actuation scheme (Scale bar-1mm). b) Schematic of operation principle of FF-ICPF. The sample enters and flows across the separation chamber by PDF (main contribution to $v_{conv}(x)$) and an E-field is applied perpendicular to the flow (in contrast to simple ICPF where the E-field and flow have the same direction). The analytes focus at the position where the EOF (main contribution to $v_{conv}(y)$) and electrophoretic flow ($v_{eph}(y)$) are equal and opposite. A different analyte with a different electrophoretic mobility requires a different electric field to acquire the same $v_{eph}(y)$ hence it will focus at a different position in the E-field gradient (present between depletion zone and bulk solution).

The requirement of a constant current density in all regions (due to charge conservation) dictates that the application of a constant potential across the separation chamber will result in a high electric field in the depletion zone (low conductivity), a low electric field in the bulk region (high conductivity) and an electric field gradient in between. The fluxes of ions are described via the Nernst-Planck equation as the sum of the diffusive, convective and electrophoretic flux. If we neglect diffusion for simplicity, we can write the total flux of analyte ion i , $J_i [mol m^{-2} s^{-1}]$ as follows:

$$J_i = J_{i,conv} + J_{i,eph} \quad (5.1)$$

$$J_i = v_{conv}C_i + v_{i,eph}C_i \quad (5.2)$$

Here $J_{i,conv}$ and $J_{i,eph}$ are the convective and electrophoretic flux, v_{conv} [$m s^{-1}$] the linear convective bulk velocity, $v_{i,eph}$ [$m s^{-1}$] and C_i [$mol m^{-3}$] the electrophoretic velocity and concentration of species i respectively.

We are now going to investigate the velocity contributions separately in the x- and y-direction (see figure 5.1).

5.2.1| Convection

The convective velocity is a combination of a PDF and electroosmotic flow (EOF). The PDF is applied via two syringe pumps; one is pushing liquid through the inlet and the other is sucking liquid from the outlet with the same flow rate. The use of two syringe pumps in combination with the high hydraulic resistance of the channels connected to the chamber in the vertical direction ensures a uniform horizontal PDF ($v_{conv,x} = constant$). The equivalent hydraulic resistance of all the vertical channels is approximately 5 times higher than the total resistance of the chamber in the x-direction.

The electroosmotic velocity follows the electric field according to the Helmholtz-Smoluchowski equation:

$$v_{EOF} = \frac{\varepsilon \varepsilon_0 \zeta}{\eta} \mathbf{E} \quad (5.3)$$

Here η [$kg m^{-1} s^{-1}$] is the viscosity of the liquid, ζ [V] is the zeta potential, $\varepsilon, \varepsilon_0$ [$F m^{-1}$] are the relative and vacuum permittivity and $\mathbf{E}$ [$V m^{-1}$] is the electric field. A high positive potential is applied to the top reservoir (figure 5.1) and the bottom reservoirs are grounded. The high electric resistance (12 times higher) of the channel array connecting the left- and right-hand reservoirs to the chamber (in the horizontal direction in figure 5.1) ensures that only a small fraction of the current will flow through them. Hence, we assume that the electric field direction points along the y-direction from top to bottom in the separation chamber ($E_x = 0$). The magnitude of the electric field is not uniform along the y-direction due to the depletion zone that forms as described above. As a result, as described by equation 5.3, the electroosmotic velocity in the y-direction is not uniform. Due to the incompressibility of aqueous electrolytes and because of mass conservation, a negative pressure is induced at the location of the electric field gradient¹⁷. The hereby induced PDF creates a constant and uniform flow in the y-direction ($v_{conv,y} = constant$). EOF-induced pressures have been previously reported at electric field gradients²³⁻²⁵ or at channels with non-uniform zeta potential²⁶. It is worth mentioning that the Nafion membrane does not hydrodynamically close the system, since it does not completely block the channel. The Nafion membrane thus resembles the one in the system reported by Ko *et al*⁷, where they demonstrated ICPF in a microchannel where only the bottom was patterned with a strip of Nafion. Despite the convective flow on top of the Nafion, the cationic flux through

the Nafion was much higher than in the bulk and sufficient to create the ICP phenomenon⁷.

5.2.2| Analyte electrophoresis

Anions will migrate in the direction opposite to the electric field and the electrophoretic velocity ($v_{i,eph}$) of anion i scales linearly with the electric field,

$$v_{i,eph} = \mu_i E \quad (5.4)$$

where $\mu_i [m^2 s^{-1} V^{-1}]$ is the electrophoretic mobility of species i . As described earlier we assume no electric field in the x direction, hence no electrophoresis in that direction.

5.2.3| Analyte focusing

We first summarize the velocities in the x and y direction for an anionic species i .

$$v_{x,i} = v_{x,conv} + v_{x,i,eph} \quad v_{y,i} = v_{y,conv} + v_{y,i,eph} \quad (5.5)$$

$$v_{x,conv} = \text{constant}, v_{x,i,eph} = 0 \quad v_{y,conv} = \text{constant}, v_{y,i,eph} = \mu_i E_y \quad (5.6)$$

An anion will be transported in the x -direction with a constant velocity in the separation chamber, as is used for the continuous extraction of the focused analytes. The focusing of the analytes occurs in the y -direction. In the y -direction the velocity of the anion is the sum of a constant convective velocity and an opposite, electric field-dependent electrophoretic velocity. As the field is non-uniform in the y -direction, the total velocity depends on the location in the electric field gradient. If the anion is far away from the depletion zone (the buffer zone in figure 5.1) the electric field is low and $v_{y,conv}$ is the dominant contribution, moving the anion towards the depletion zone. If the anion is in the depletion zone where the electric field is the highest, electrophoresis dominates and migrates the anion upwards towards the buffer zone. At some location in the electric field gradient between bulk and depletion zone, the y -contributions of convective and electrophoretic velocities are equal and opposite resulting in a zero net y -direction velocity and hence focusing of the anion. A different anion with a different electrophoretic mobility requires a different electric field to acquire a zero net velocity, and hence will focus at a different location in the electric field gradient.

5.2.4| Operation modes

In many focusing techniques, such as ITP^{3,27} two distinct operation modes can be found, namely peak mode and plateau mode. In **peak mode** the analytes are in very low concentration compared to the background electrolyte so that we assume they do not contribute to the local conductivity of the solution. Hence the analytes do not affect the local electric field and the concentration process. This is the most common operation mode of focusing methods where the main goal is the concentration of low abundant species. In peak mode the analytes are concentrating and forming a Gaussian concentration profile (in the separation direction). The concentration profile of analytes in separation sciences is a long

and well investigated topic²⁸⁻³⁰. As described in previous work¹⁷ the variance ($\sigma_i^2 [m^2]$) of the Gaussian profile of a species i is given by

$$\sigma_i^2 = \frac{V_T}{z_i \frac{dE_y}{dy}} (5.7),$$

where V_T [V] is the thermal potential ($V_T = k_b T / e$ with T [K] the temperature and k_b [J K⁻¹] Boltzmann's constant and e [C] the elementary charge) z_i the valence of the species i and dE/dx [V m⁻²] the electric field gradient between the bulk and depletion zone. We assume that the electric field gradient is constant. In addition, the separation resolution R_s for two species can be calculated as

$$R_s = \frac{d_x}{2(\sigma_1 + \sigma_2)} (5.8a)$$

$$R_s = \frac{v_{y,conv}}{2 \sqrt{\frac{dE}{dy}} V_T} \cdot \frac{\left(\frac{1}{\mu_1} - \frac{1}{\mu_2}\right)}{\left(\frac{1}{\sqrt{z_1}} + \frac{1}{\sqrt{z_2}}\right)} (5.8b)$$

Here σ_1 [m] and σ_2 [m] are the standard deviations of the analyte Gaussian peaks and d_x [m] is the distance between the peaks (i.e. the difference of the mean value). In equation 5.8b the first term is dependent on the applied potential and device geometry and the second term dependent on the analyte properties.

In contrast, if the concentrated analyte approaches the background electrolyte concentration, its contribution to the conductivity and electric field can no longer be neglected. In this case the analyte is in **plateau mode**. As indicated by the name, the analyte will concentrate until a maximum concentration is reached and a plateau is formed in the concentration profile which will then widen over time. The constant concentration of the plateau locally creates a constant electric field. A known analyte in plateau mode (of which the electrophoretic mobility is between two analytes of interest) can be used as an electrophoretic spacer to push these two analytes apart and thereby improving their separation resolution. Electrophoretic spacers have been reported before in various focusing techniques^{27,28,31}, including ICPF^{8,32}.

In standard ICPF, there is a continuous supply of analytes towards their focusing location. Therefore a theoretical infinite concentration factor can be achieved until the analyte reaches plateau mode. Quist *et al*⁸ report concentration factors up to 10⁷ using ICPF. In FF-ICPF there is no continuous supply of analyte in the separation direction, hence the maximum concentration is limited by the length of the chamber in the y -direction. As the analytes move along the chamber (in the x -direction), they are getting "squeezed" down to either a Gaussian profile in peak mode or a plateau in the plateau mode. When the analytes reach peak mode, the maximum concentration can be calculated by the ratio of the chamber width (W [m]) compared to the standard deviation of the Gaussian peak.

$$C_{max,peak} = \frac{W}{\sigma_i \sqrt{2\pi}} C_{bulk} \quad (5.9)$$

given that the area ($C_A [mol/m^2]$) under a Gaussian peak equals $C_A = C_{max,peak} \sigma_i \sqrt{2\pi}$. In the case of plateau mode, the plateau concentration can be calculated from the Kohlrausch regulation function (KRF) ³³. KRF is a conservation function or conservation law ³⁴ which requires the KRF value (equation 5.10) to be constant in all regions (bulk, depletion zone and any plateau mode zones).

$$KRF = \sum_i \frac{z_i C_i}{\mu_i} \quad (5.10)$$

5.3.5| Throughput

The throughput of the device is determined by the volumetric flow rate ($Q_s [m^3 s^{-1}]$) of the sample. If we assume that the PDF applied by the syringe pump is the only contribution for flow in the x -direction (*i.e.* throughput), it takes an analyte to cross the length of chamber ($L_x [m]$) a time ($t_x [s]$):

$$t_x = \frac{L_x L_y h}{Q_s} \quad (5.11)$$

where $L_y [m]$ is the length of the chamber in the y -direction and $h [m]$ is the height of the chamber. In order for the analytes to separate they need to travel to their focusing position. If we take the worst case where the focusing position is at the bottom of the chamber adjacent to the Nafion membrane and an analyte is at the top of the chamber, it needs to travel the entire length of the chamber in the y -direction (L_y). If for simplicity we assume that the only contribution to $v_{conv,y} [m s^{-1}]$ is the electroosmotic flow using equation 5.3 we can calculate the time ($t_y [s]$) that an analyte needs to travel through the chamber in the y -direction.

$$t_y = \frac{L_y \eta}{\varepsilon \varepsilon_0 \zeta E_y} \quad (5.12)$$

In all cases t_y should be smaller than t_x . If we equate the two, we can derive a relation between the two means of actuation (by pressure-driven flow and electric field) needed to satisfy the condition of proper focusing:

$$Q_s = \frac{\varepsilon \varepsilon_0 \zeta L_x h}{\eta} E_y \quad (5.13)$$

Once again assuming that there are no effects due to ICPF influencing the electric field, we can state $E_y = V/L_y$ where $V[V]$ is the applied potential across the chamber, and we obtain

$$Q_s = \frac{\varepsilon \varepsilon_0 \zeta L_x h}{\eta L_y} V (5.14)$$

In this simplified scaling law, the applied potential is linearly related to the throughput for a specific device. When it comes to device design parameters, the larger L_x and h , the higher the throughput for a specific potential, since these parameters increase t_x . In contrast, the larger L_y , the lower the throughput because of the increase in t_y . In Appendix C we furthermore calculate the effect of electric power on the stability of the system. A high electric power can affect the stability in two ways: (1) in the form of heat and; (2) in the form of changes in pH due to electrochemical reactions in the reservoirs.

5.3| Experimental

In order to characterize our proposed method, microfluidic chips were fabricated out of polydimethyl siloxane (PDMS, DOWSIL™ 184 Silicone Elastomer kit) (1:10 crosslinker to polymer ratio). A mould was used for standard soft lithography [34] of the PDMS chips, which were bonded on standard microscopy glass slides after 45 sec of O₂ plasma treatment (in a FemtoScience Cute device). The mould was made out of a silicon wafer and 35 µm of MicroChem® SU-8 2050 negative photoresist which was patterned using a photolithography mask. The supplier's instructions were followed for the exposure and development of the photoresist.

A small amount (approximately 5 µl) of Nafion® perfluorinated resin solution (20wt. % - Sigma-Aldrich) was introduced to one of the reservoirs (marked with yellow in figure 5.1). The Nafion solution was filled and patterned via capillary forces [5], [35]. Nafion was dried at 60°C for 30 minutes to form a solid permselective polymer. Nafion resin solution experiences significant shrinkage during the drying process due to solvent evaporation. The shrinkage causes the solid Nafion to detach from the channel walls creating gaps which allow hydrodynamic flow around the solid Nafion.

An O₂ plasma treatment preceded the testing of each chip to ensure high hydrophilicity of the PDMS walls to avoid any bubble formation during the filling process. The anodic and cathodic reservoirs of the microfluidic chip were filled with a buffer solution (dilutions of PBS (Sigma-Aldrich)). The inlet and outlet reservoirs were connected to a NEMESIS syringe pump (two 4605 dosing units, Cetoni GmbH). Platinum wires (Alfa Aesar 0.01inØ) were introduced to the anodic and cathodic reservoirs and connected to a Keithley 2410 source meter power supply. For the fluorescent microscopy, an Olympus IX51 was used and images/videos were captured with a FLIR Grasshopper®3 color camera. The syringe pump and power supply were operated via neMESYS UI (Cetoni GmbH) and an in-house made LabVIEW program respectively. The results were analysed with ImageJ (V. 1.51) and Matlab (R2016a).

As sample, PBS dilutions or human blood plasma spiked with fluorescent anionic markers were used. Whole human blood (with 3.2% sodium acetate) was provided by the Experimental Centre for Technical Medicine (ECTM, Technical Medical Centre, University of Twente). The whole blood was centrifuged (within 4 hours after donation) for 15 min at 500 g in an Allegra X-12R Centrifuge (Beckman

Coulter) and the blood plasma was extracted, aliquoted and stored at -80°C . As model anion analytes BODIPY[™] 492/515 Disulfonate (BDP) (Invitrogen), Alexa Fluor[™] 647 Carboxylic Acid, tris(triethylammonium) (AF647) (Invitrogen) salt, fluorescein sodium salt (Sigma-Aldrich) and Cascade Blue[™] hydrazide trisodium salt (CB) (Invitrogen) were chosen.

Figure 5.2 - a) Fluorescent microscopy image of FF-ICPF in 0.1xPBS. Focused streams of CB, BDP and AF647 can be seen ($5 \mu\text{L min}^{-1}$ at 200 V). Nafion is marked with the yellow box. b) Close-up fluorescent microscopy image of the extracted streams c) Normalized fluorescence intensity profiles of CB, BDP and AF647 (along the yellow line of image b with $y=0$ at the Nafion membrane), the maximum intensity is approximately 17 times higher than the bulk intensity for all three dyes. The fluorescent intensity is normalized independently for each color. Note: The contrast and color balance of microscopy images a and b have been altered for better visibility. The fluorescence intensity profiles have been extracted from the original images (which can be found in Appendix C).

5.4| Results and discussion

5.4.1| Peak mode

In peak mode the analytes are in very low concentration compared to the background electrolyte so their contribution to the conductivity can be neglected, and they will form a Gaussian concentration peak during the focusing. We prepared our model sample of 70 μM BDP, AF647 and CB in 0.1xPBS. Our model analytes are approximately in a three orders of magnitude lower concentration than the dominant ions (15.7 mM Na^+ and 14.0 mM Cl^-) in 0.1xPBS. Our sample was flown through the chip with a flow rate of 5 $\mu\text{L min}^{-1}$ and a potential of 200 V was applied. Fluorescent microscopy images were taken after approximately 3 minutes as shown in figure 5.2. A depletion zone was formed on the anodic side of the Nafion and the analytes were focused at the region between bulk and depletion zone as they flowed from left to right due to the PDF and from top to bottom due to EOF. As shown in figure 5.2c, the analytes formed focused streams with a Gaussian concentration profile in the y-direction. The added analyte CB has the highest electrophoretic mobility, followed by BDP and AF647 [36]. This means that AF647, with the lowest mobility, focused at a region of higher E-field (closer to the depletion zone) compared to BDP and CB. Similarly, the CB with the highest mobility focused at a lower E-field compared to BDP. Despite the high concentration of the focused analytes, a clear overlap of the three focused streams can be seen (Figure 5.2c). Due to the very high electric field gradients in the ICPF, an inherent disadvantage of the method is the poor resolution in peak mode (Equation 5.8a). In the example shown in figure 5.2c, the separation resolution between AF647 (red) and CB (blue) is 0.26 ($\sigma_{\text{AF647}} = 27 \mu\text{m}$, $\sigma_{\text{CB}} = 29 \mu\text{m}$ and distance between peaks was 30 μm as calculate from figure 5.2c).

5.4.2| Plateau Mode

In order to demonstrate the plateau mode, 0.1xPBS was spiked with 1mM of CB, AF647 and BDP. In this solution the analytes have approximately a 10 times lower concentration than the background electrolyte. As shown in figure 5.3, once the analytes concentrate to their maximum allowed concentrations (Equation 5.10), they form wide plateaus instead of Gaussian concentration profiles.

In figure 5.3 two different plateaus of blue can be seen. We attribute this to the fact that CB has a pKa at 7.3. [37] If a small pH gradient exists in the chip, both CB^{3-} and CB^{2-} will be present. AF647 is an acidic salt and the addition of 1mM in 0.1xPBS is expected to result in a sample pH of approximately 6.9, hence a pH gradient exists between the buffer in the anodic reservoir (0.1xPBS - 7.4pH) and the sample (6.9pH). The more mobile CB^{3-} then forms the right-hand peak in figure 5.3c, with the second and less bright band of blue corresponding to CB^{2-} .

In figure 5.4 the evolution of the focusing process can be seen. The analytes move with a constant velocity along the x-direction due to the PDF. Once the analytes enter the separation chamber, they will start moving in the y-direction towards their focusing location by a combination of convective flow (EOF) opposed by electrophoresis (Figure 5.4 - i). As the analytes flow in the x-direction, they are moving continuously towards their focusing location (Figure 5.4-i,ii,iii). Once they

form their plateaus the concentration profiles remain constant until they get extracted (Figure 5.4-iii,iv,vi).

Figure 5.3 - a) Fluorescent microscopy image of FF-ICPF in 0.1xPBS. Focused streams of CB, BDP and AF647 can be seen ($5 \mu\text{l min}^{-1}$ at 200 V). Nafion is marked with the yellow box. b) Close-up fluorescent microscopy image of the extracted streams c) Normalized fluorescence intensity profiles of CB, BDP and AF647 (along the yellow line of image b with $y=0$ at the Nafion membrane), the maximum intensity is approximately 4-5 times higher than the bulk intensity for all three dyes. Nevertheless, because of the high starting concentration of the fluorescent dyes the fluorescent intensity is no longer linearly related to concentration of the analyte due to self-quenching. The analytes create plateaus instead of Gaussian peaks. The fluorescent intensity is normalized independently for each color. Note: the contrast and color balance of microscopy images a and b has been altered for better visibility. The fluorescent intensity profiles have been extracted from the original images (which can be found in Appendix C).

Figure 5.4 – Evolution of concentration profiles along the x-direction. The profile projected on the y-z plane corresponds at the location just before the extraction channels ($y=300\ \mu\text{m}$).

5.4.3| Electrophoretic spacers

Analytes which are focused in their plateau mode can be used as electrophoretic spacers to improve the resolution of analytes in peak mode. In figure 5.5, CB and AF647 (spiked in $70\ \mu\text{M}$ to the bulk solution) are in peak mode and BDP (spiked in $1\ \text{mM}$ to the bulk solution) is in plateau mode. Since the electrophoretic mobility of BDP lies in between AF647 and CB, it acts as a spacer, improving the separation resolution of the two analytes of interest (in this case AF647 and CB). In this case the separation resolution between AF647 (red) and CB (blue) is 1.96 ($\sigma_{\text{AF647}} = 46\ \mu\text{m}$, $\sigma_{\text{CB}} = 36\ \mu\text{m}$ and the distance between peaks was $323\ \mu\text{m}$ as calculated from figure 5.5c) compared to a resolution 0.26 in peak mode. A higher starting concentration of BDP will result in a wider plateau further increasing the separation resolution.

Figure 5.5 - a) Fluorescent microscopy image of FF-ICPF in 0.1xPBS. Focused streams of **CB**, **BDP** and **AF647** can be seen ($5\mu\text{l min}^{-1}$ at 200 V). Nafion is marked with the yellow box. b) Close-up fluorescent microscopy image of the extracted streams. c) Normalized fluorescence intensity profiles of **CB**, **BDP** and **AF647** (along the yellow line of image b with $y=0$ at the Nafion membrane). **BDP** in plateau mode acts as an electrophoretic spacer between the **CB** and **AF647**. The fluorescent intensity is normalized independently for each color. Note: The contrast and color balance of microscopy images a and b has been altered for better visibility. The fluorescent intensity profiles have been extracted from the original images (which can be found in Appendix C).

5.4.4| Concentration rate and extraction position

Both the concentration of the focused analytes and the extraction position of the streams can be tuned by the applied potential and flow rate of the sample. We characterised the influence of both using human blood plasma spiked with a fluorescent analyte (BDP). The results are shown in figure 5.6. Since the analytes focus at the position in the electric field gradient where the convective and electrophoretic velocities cancel in the y-direction and where an electric field gradient exists between the depletion zone and the bulk, we can control the

extraction location of our focused streams of analytes in the y-direction by controlling the size of the depletion zone. The higher the applied potential the wider the depletion zone and the further away from the Nafion the analytes will focus (Figure 5.6c). In addition, the depletion zone grows over distance (x-direction) as the liquid flows from left to right. A faster flow rate allows less time for the depletion zone to grow, and therefore the analytes will focus closer to the Nafion membrane (Figure 5.6c). Finally, the analytes are brought to their focusing location by the convective flow in the y-direction. The dominant contribution of convective flow in that direction is EOF. The higher the EOF, the more analytes are brought to the focusing location and the higher the concentration factor (Figure 5.6b). A higher flow rate (in the x-direction) reduces the time that the analytes spend in the separation chamber, resulting in a lower amount of analyte reaching the focusing location and a lower concentration factor. As we mentioned, the maximum concentration factor is furthermore dependent on the operation mode.

Figure 5.6 - a) Fluorescent microscopy image of FF-ICPF of human blood plasma ($5 \mu\text{l min}^{-1}$ at 200 V). A highly concentrated stream of BDP can be seen to form. b) Concentration factor versus potential for two flow rates. Each point (*) corresponds to a different measurement of the same experiment at a different time over a duration of 100 seconds to demonstrate the stability of the system. The lines show a linear fit with R^2 of 0.9999 and 0.9934 and a slope of 0.0697 and 0.0337 V^{-1} for 5 and $10 \mu\text{l min}^{-1}$, respectively. c) Extraction position as distance from Nafion membrane (l_e in (a)) versus flow rate for different applied potentials. As extraction position the location of the maximum intensity of BDP was chosen. Each point (*) corresponds to a separate experiment with the same device and the lines connect the average values. For a flow rate of $1 \mu\text{l min}^{-1}$ the extraction position of 60 V and 90 V was outside the observation window.

The system was tested for stability over a period of 20 minutes with no significant change in the focusing location in 0.1xPBS at 150 V (data not shown). We report a maximum flow rate of $200 \mu\text{l min}^{-1}$ in 10x dilute blood plasma at 500 V, while still having separation and focusing. Nevertheless, after approximately 1 minute the formation of bubbles could be seen in the thin channels where the current density is the highest. We believe that these bubbles were the result of local heating that reduces the solubility of gas in water. We expect that a higher stable throughput can be achieved with the use of active cooling of the device, possible making the device suitable for sample preparation applications. A stable separation of non-dilute human blood plasma was achieved at a lower throughput ($15 \mu\text{l min}^{-1}$) at 120 V.

5.5| Conclusions and outlook

We have demonstrated the feasibility of the continuous separation and concentration of anionic analytes via free-flow ion concentration polarization focusing (FF-ICPF). The two different operation modes, namely peak and plateau mode, of the technique were investigated and demonstrated. In addition, analytes with known electrophoretic mobility in plateau mode could be used as electrophoretic spacers in order to improve the separation resolution, and a resolution of 7.5 was demonstrated. Finally, we investigated the tunability of the extraction location and concentration rate by the applied electric potential and the sample (human blood plasma) flow rate. We believe that FF-ICPF could be a promising candidate for sample preparation of biological samples and with the use of more heat conductive substrates or active cooling even higher throughputs can be achieved making it suitable for a wide variety of applications.

5.6| References

1. Hlushkou, D., Perdue, R. K., Dhopeswarkar, R., Crooks, R. M. & Tallarek, U. Electric field gradient focusing in microchannels with embedded bipolar electrode. *Lab Chip* (2009). doi:10.1039/b822404h
2. Wang, Y. C., Stevens, A. L. & Han, J. Million-fold preconcentration of proteins and peptides by nanofluidic filter. *Anal. Chem.* (2005). doi:10.1021/ac050321z
3. Quist, J., Janssen, K. G. H., Vulto, P., Hankemeier, T. & Van Der Linden, H. J. Single-electrolyte isotachopheresis using a nanochannel-induced depletion zone. *Anal. Chem.* **83**, 7910–7915 (2011).
4. Kim, S. J., Li, L. D. & Han, J. Amplified electrokinetic response by concentration polarization near nanofluidic channel. *Langmuir* **25**, 7759–7765 (2009).
5. Liu, V., Song, Y.-A. & Han, J. Capillary-valve-based fabrication of ion-selective membrane junction for electrokinetic sample preconcentration in PDMS chip. *Lab Chip* **10**, 1485 (2010).
6. Khandurina, J., Jacobson, S. C., Waters, L. C., Foote, R. S. & Ramsey, J. M. Microfabricated porous membrane structure for sample concentration and electrophoretic analysis. *Anal. Chem.* **71**, 1815–1819 (1999).
7. Ko, S. H. *et al.* Nanofluidic preconcentration device in a straight microchannel using ion concentration polarization. *Lab Chip* **12**, 4472 (2012).
8. Quist, J., Vulto, P., Van Der Linden, H. & Hankemeier, T. Tunable ionic mobility filter for depletion zone isotachopheresis. *Anal. Chem.* **84**, 9065–9071 (2012).
9. Pamme, N. Continuous flow separations in microfluidic devices. *Lab on a Chip* (2007). doi:10.1039/b712784g
10. Turgeon, R. T. & Bowser, M. T. Micro free-flow electrophoresis: Theory and applications. *Analytical and Bioanalytical Chemistry* (2009). doi:10.1007/s00216-009-2656-5
11. Janasek, D., Schilling, M., Franzke, J. & Manz, A. Isotachopheresis in free-flow using a miniaturized device. *Anal. Chem.* **78**, 3815–3819 (2006).

12. Poehler, E. *et al.* Label-free microfluidic free-flow isoelectric focusing, pH gradient sensing and near real-time isoelectric point determination of biomolecules and blood plasma fractions. *Analyst* (2015). doi:10.1039/c5an01345c
13. Herzog, C. *et al.* Continuous on-chip fluorescence labelling, free-flow isoelectric focusing and marker-free isoelectric point determination of proteins and peptides. *Lab Chip* (2016). doi:10.1039/c6lc00055j
14. Kohlheyer, D., Eijkel, J. C. T., van den Berg, A. & Schasfoort, R. B. M. Miniaturizing free-flow electrophoresis - A critical review. *Electrophoresis* **29**, 977–993 (2008).
15. Choi, J. *et al.* Selective preconcentration and online collection of charged molecules using ion concentration polarization. *RSC Adv.* **5**, 66178–66184 (2015).
16. Chen, Y. Y., Chiu, P. H., Weng, C. H. & Yang, R. J. Preconcentration of diluted mixed-species samples following separation and collection in a micro-nanofluidic device. *Biomicrofluidics* **10**, (2016).
17. V. A. Papadimitriou, L. I. Segerink. and J. C. T. Eijkel. Continuous Focusing, Fractionation and Extraction of Anionic Analytes in a Microfluidic Chip. *Lab Chip* (2019). doi:DOI:10.1039/c9lc00434c
18. Jeon, H., Lee, H., Kang, K. H. & Lim, G. Ion concentration polarization-based continuous separation device using electrical repulsion in the depletion region. *Sci. Rep.* (2013). doi:10.1038/srep03483
19. Kim, M., Wu, L., Kim, B., Hung, D. T. & Han, J. Continuous and High-Throughput Electromechanical Lysis of Bacterial Pathogens Using Ion Concentration Polarization. *Anal. Chem.* (2018). doi:10.1021/acs.analchem.7b03746
20. Kim, S. J., Ko, S. H., Kang, K. H. & Han, J. Direct seawater desalination by ion concentration polarization. *Nat. Nanotechnol.* (2010). doi:10.1038/nnano.2010.34
21. Sonker, M., Sahore, V. & Woolley, A. T. Recent advances in microfluidic sample preparation and separation techniques for molecular biomarker analysis: A critical review. *Analytica Chimica Acta* (2017). doi:10.1016/j.aca.2017.07.043
22. Pu, Q., Yun, J., Temkin, H. & Liu, S. Ion-Enrichment and Ion-Depletion Effect of Nanochannel Structures. *Nano Lett.* **4**, 1099–1103 (2004).
23. Kim, S. J., Wang, Y. C., Lee, J. H., Jang, H. & Han, J. Concentration polarization and nonlinear electrokinetic flow near a nanofluidic channel. *Phys. Rev. Lett.* **99**, (2007).
24. Ouyang, W., Ye, X., Li, Z. & Han, J. Deciphering ion concentration polarization-based electrokinetic molecular concentration at the micro-nanofluidic interface: theoretical limits and scaling laws. *Nanoscale* (2018). doi:10.1039/c8nr02170h
25. Gong, L., Ouyang, W., Li, Z. & Han, J. Direct numerical simulation of continuous lithium extraction from high Mg²⁺/Li⁺ ratio brines using microfluidic channels with ion concentration polarization. *J. Memb. Sci.* (2018). doi:10.1016/j.memsci.2018.03.078
26. Herr, A. E. *et al.* Electroosmotic capillary flow with nonuniform zeta

- potential. *Anal. Chem.* (2000). doi:10.1021/ac990489i
27. Rubin, S., Schwartz, O. & Bercovici, M. Sample distribution in peak mode isotachophoresis. *Phys. Fluids* (2014). doi:10.1063/1.4861399
28. Giddings, J. C. *Unified Separation Science*. (John Wiley & Sons, 1991).
29. MacInnes, D. A. & Longworth, L. G. Transference Numbers by the Method of Moving Boundaries. *Chem. Rev.* **11**, 171–230 (1932).
30. Tiselius, A. A new apparatus for electrophoretic analysis of colloidal mixtures. *Trans. Faraday Soc.* **33**, 524–531 (1937).
31. Karsenty, M., Rosenfeld, T., Gommed, K. & Bercovici, M. Current monitoring in a microchannel with repeated constrictions for accurate detection of sample location in isotachophoresis. *Anal. Chem.* (2015). doi:10.1021/ac5036346
32. Cheow, L. F., Sarkar, A., Kolitz, S., Lauffenburger, D. & Han, J. Detecting kinase activities from single cell lysate using concentration-enhanced mobility shift assay. *Anal. Chem.* (2014). doi:10.1021/ac502185v
33. Kohlrausch, R. Theorie des elektrischen Rückstandes in der Leidener Flasche. *Ann. Phys.* **167**, 179–214 (1854).
34. Hruška, V. & Gaš, B. Kohlrausch regulating function and other conservation laws in electrophoresis. *Electrophoresis* (2007). doi:10.1002/elps.200600513

Chapter 6

Continuous or on-Demand Droplet Generator for Extraction of Electrokinetically Focused Anionic Analytes on Chip

Similar to the two previous chapters, this chapter reports on our attempts to extract analytes that were concentrated and separated via ion concentration polarization focusing. As the analyte concentration factor is prone to reduction after extraction due to diffusion, we propose in this chapter the integration of a droplet generator with a ICPF device. The droplet generator should not interfere with the focusing technique and allow continuous concentration, separation and continuous, or on-demand “packaged” extraction of analytes. These properties will make it ideal for integration with a variety of electrokinetic separation techniques. We demonstrate extraction of droplets containing analytes concentrated by a factor of 100.

6.1| Introduction

In microfluidic systems electrokinetic focusing techniques can be used to separate, purify and increase the effective concentration of analytes, finding applications in various research and industry sectors. However, the focused analytes are trapped in the microchannel, making the integration of a detection system in a lab-on-a-chip device mandatory. This integration requirement significantly limits the detection methods and processes, namely to those that can be integrated on chip and that are compatible with the electrokinetic method. Powerful tools such as mass spectrometry cannot be used as they are impossible to be implemented on chip. Downstream processing increases the choice of detection methods, but requires the focused analytes to stay separated and concentrated while they are transported off chip. A typical method for transporting analytes is by the use of droplet microfluidics. Droplet microfluidics has been investigated over the years and has seen many versatile applications in research and industry areas such as for material science and biological/chemical platforms ¹. Droplet microfluidics is used to compartmentalize reactants into picolitre volumes ² and allows control over transport in space and time. The surface to volume ratio is high at this scale, facilitating shorter heat and mass transfer times, shorter diffusion distances, and faster reaction times making the droplets highly efficient microreactors. Moreover, droplet microfluidics allows the production of size-controlled and reproducible droplets, generated at high frequency, while having the ability to independently control each droplet. Also, droplets can be transported, sorted, merged and split ³⁻⁵. These characteristics make it a versatile technique and countless examples can be found in literature ^{1,2,4-7}.

The integration of a droplet generator with an electrokinetic separation technique has been demonstrated before, allowing the encapsulation of separated analytes while maintaining their spatial concentration profile. An example of this is given by Edgar *et al.* ⁸ where capillary electrophoresis was used to separate the analytes in bands and propagated these towards a flow focusing droplet generator. In another paper, Chen *et al.* ⁹ used ion concentration polarization focusing (ICPF) to accumulate biomolecules into a plug. Once a sufficient concentration factor was reached, the ICPF process was stopped and the plug was pushed towards the droplet generator where the analytes were encapsulated in droplets. Though the sample was concentrated a 100-fold, an increase in concentration of only 20-fold was measured in the droplets due to diffusion of the analytes before they were encapsulated in droplets⁹. While the first example mainly concerns separating the analytes, and the second example concentrating the sample, van Kooten *et al.* ¹⁰ used isotachopheresis (ITP) to separate and concentrate analytes, and selectively extract them by droplet microfluidics. Nevertheless, the droplet generator in that work disrupted the electrokinetic separation, not allowing continuous extraction. In this chapter we propose a droplet generator suitable for both continuous and on-demand droplet generation that does not disrupt the electrokinetic separation and concentration process. We demonstrate droplet generator functionality when integrating it with an ICPF chip.

Figure 6.1 - a) Outline of the ICPF device integrated with the droplet generator and a typical actuation scheme. The separation channel (dispersed phase - light blue) is filled with the sample. The green channels represent the continuous phase channels filled with oil. Nafion membrane is patterned in the grey channels. The dark blue channels are filled with buffer and are electrically grounded. b) Schematic of the ICPF process. The electric field across the Nafion creates a depletion zone (DZ). A second electric field across the concentration gradient creates an electric field gradient in the separation channel. All analytes approach the depletion zone with a constant convective velocity. Anions experience an opposite electrophoretic velocity which scales linearly with the electric field. The anions will focus at the location where their electrophoretic velocity is equal to the convective velocity. c) Principle of the proposed droplet on demand method. The pressure conditions for equilibrium and droplet formation are shown. P_{LP} is the oil-water interface Laplace pressure, P_d is the pressure in the disperse phase (arising from hydrostatic pressure and/or any induced pressure of the ICPF process) and P_c is the pressure at the interface resulting from the actuation pressures at the reservoirs (P_{in} and P_{out}).

6.2| Theory

6.2.1| Ion concentration polarization focusing

Electrokinetic focusing techniques are a powerful tool in analytical chemistry. ICPF is such a focusing technique and it was chosen for integration with the droplet

generator because of its ease of use compared to other focusing techniques such as isoelectric focusing or ITP that require application of specific electrolytes. ICPF was introduced by Wang *et al.*¹¹ who demonstrated concentration of biomolecules by a factor of 10^6 . Later Quist *et al.*¹² also showed separation of anionic analytes using ICPF. Since then a vast amount of research has been done in ion concentration polarization (ICP) and ICPF^{9,13–23}. We will give a short theoretical background of ICPF in order to define the requirements of the droplet generator. For a deeper theoretical background of ICPF the reader is referred to Chapter 4 or the work of Ouyang *et al.*²⁴ and the more recent work of Gong *et al.*^{25,26}.

ICPF is based on the differential migration of charged analytes in an electric field gradient. The electric field gradient is created via a salt concentration gradient caused by the phenomenon of ICP²⁷. When two microchannels are connected by an ion perm-selective zone and an electric potential is applied across it, the difference in flux between anion and cations creates ICP. In the case of a cation perm-selective region (in our case Nafion), the majority of the current through that region is carried by cations. The cations are being removed from the anodic side of the Nafion resulting in a local reduction of their concentration. The anions will migrate to the anode away from the Nafion so their concentration is also reduced on the anodic side. This results in a depletion zone: a region in the anodic side close to the perm-selective region (Nafion) where the concentration of all species is much lower than the bulk concentration. When subsequently a current is sent across the concentration gradient that arises between the bulk and the depletion zone, an electric field gradient is created along the channel (Figure 1b). When introducing analytes in the microchannel, they will move due to different influences. Firstly, all ions will move towards the depletion zone with a constant convective velocity towards the cathode, mainly due to the electroosmotic flow. Anionic analytes also experience an electrophoretic velocity in the opposite direction ($v_{i,eph}$ [m s^{-1}]) which scales linearly with the local electric field (E [V m^{-1}]) by:

$$v_{i,eph} = \mu_{i,eph} E \quad (6.1)$$

with $\mu_{i,eph}$ [$\text{m}^2 \text{s}^{-1} \text{V}^{-1}$] the electrophoretic mobility. As the anions move up the electric field gradient, the electrophoretic velocity increases until it matches their convective velocity. The position in the E-field gradient where the two velocities are equal is their focusing position. A different analyte with different electrophoretic mobility (and thus velocity) requires a different electric field to acquire the same velocity hence it will focus at a different location in the E-field gradient. The result is a separation of analytes based on their electrophoretic mobilities.

The convective flow in ICPF has multiple contributions. Firstly, the electric field across the separation channel creates an electroosmotic flow (EOF) which scales according to the Helmholtz-Smoluchowski equation:

$$v_{EOF} = \frac{\varepsilon \varepsilon_0 \zeta}{\eta} E \quad (6.2)$$

with η [$kg\ m^{-1}s^{-1}$] the viscosity of the liquid, ζ [V] is the zeta potential and ϵ, ϵ_0 [$F\ m^{-1}$] are the relative and vacuum permittivity. The EOF is of unequal magnitude in different parts of the separation channel. As mentioned earlier, there is an electric field gradient due to the concentration gradient in the depletion zone. The high electric field in the depletion zone results in a higher EOF in the depletion zone than in the bulk region. In addition to the depletion zone, there also is a space charge region close to the Nafion²⁸⁻³². This space charge region has a net positive charge creating a secondary EOF (a.k.a EOF of the second kind²⁴) with the same direction as the main EOF. This EOF of the second kind further increases the difference in EOF between the bulk and the depletion zone. Due to the incompressibility of the liquid, this EOF induces vortices and therefore a local negative pressure is created resulting in a complex 2D velocity profile^{29,33,34}. Analytes that are in low concentration compared to the bulk electrolyte will form a Gaussian peak when they concentrate with ICPF. In our previous work³⁵ we derived the variance σ_i^2 [m^2] of this Gaussian distribution as:

$$\sigma_i^2 = \frac{V_T}{z_i \frac{dE}{dx}} (6.3),$$

where z_i is the valence of the analyte i , V_T [V] thermal potential ($V_T = k_b T / e$ with T [K] the temperature and k_b [J K⁻¹] Boltzmann's constant). In the same work the peak width (4σ) of the focused analytes was experimentally determined and it was ranging from 57 μm to 141 μm depending on the actuation potentials applied in that work. In this chapter a similar design (and dimensions) and the same analytes are used hence a similar peak size is expected.

6.2.2| Droplet generator

After this short description of ICPF, the set of requirements for the droplet generator is now formulated:

- i. The continuous phase (oil) should not cross/fill the separation channel, as the goal is to package the focused analytes without interrupting the ICPF process. ICPF requires an electric field (and hence a current) running through the whole separation channel. If the non-conductive oil protrudes in the separation channel, the electric current will be interrupted causing the focusing process to stop.
- ii. The pressure of the dispersed phase (applied to the separation channel reservoirs) should not be directly controlled. As described in Chapter 4, the separation and focusing of analytes is strongly affected by the convective flow. The addition of pressure in the separation channel can easily affect the convective flow with undesired results. Pressure control of the dispersed phase is feasible but not trivial and hence it will be avoided.
- iii. The droplet generator should allow both continuous and droplet-on-demand (DoD) operation. In the DoD operation the generator should be able to form a predetermined number of droplets (one or more). In the

continuous droplet formation operation, the volumetric flow rate of the dispersed phase should be smaller than the volumetric flow rate due to ICPF.

- iv. The droplet size should be smaller than the size of a concentrated analyte peak, as otherwise the analyte will be diluted in the volume of the droplet. Assuming the aforementioned peak size and considering the height (30 μm) and the width (50 μm) of our channel, we arrive at a focused analyte volume ranging from 42.8 pL to 105.8 pL for 2σ width of the Gaussian peak. Thus the droplets should be smaller than 42.8 pL.

There are many types and layouts of droplet microfluidic systems with different purposes, advantages and limitations. Generally, two or more immiscible fluids are injected in a microfluidic system to form stable interfaces in the form of droplets. Operationally, two categories can be distinguished in which either droplets are generated passively by means of hydrodynamics and capillary effects, or actively by integration of actuators into the devices³⁶. Passive droplet generators rely on fluid instabilities on introduction of an immiscible fluid (dispersed phase) into another liquid (continuous phase). No active elements are part of the chip and the flows of both phases are controlled outside of the microfluidic chip. In contrast, in active droplet generators active elements, such as valves, facilitate the droplet formation and increase the controllability of the formation process by modifying the force balance. This can be done by introducing additional forces, such as electrical, magnetic, and centrifugal forces, or by modifying locally intrinsic parameters such as flow velocity or material properties. Since active droplet generators increase the device complexity in both fabrication and operation, we propose a passive droplet generator.

In both the passive and active droplet microfluidic systems, five device geometries can be distinguished: i) cross flow (*e.g.* T-junction), ii) co-flow, iii) flow focusing, iv) step emulsification, and v) microchannel emulsification³⁷. To satisfy our first requirement (the continuous phase not crossing into the separation channel) we are limited to a T-junction geometry. T-junction droplet generators are extensively used in microfluidics and the droplet formation and break-up mechanisms have been investigated in numerous review papers^{3,37–39}. The T-junction is characterized by two immiscible flows meeting at an angle to produce monodispersed droplets in the carrier phase. The standard T-junction was first reported by Thorsen *et al.*⁴⁰ who used pressure-induced flow to form droplets by shearing one phase by a second immiscible one.

Thorsen stated that the droplet formation in this case is the result of the competition between interfacial tension and shear forces. Generally, three break-up modes are distinguished for T-junctions: squeezing, dripping, and jetting³⁷, of which the latter two are shear-driven. For a precise control over droplet formation in DoD systems (our third requirement) the break-up should be in the squeezing regime⁴¹. The pressure balance between the dispersed and carrier phase interface at the junction dominates the droplet formation in the squeezing regime.

The capillary number can be used to determine in which mode the device operates. The capillary number (Ca) is defined as

$$Ca = \frac{\eta v}{\gamma} \quad (6.4)$$

where v [m/s] is the linear velocity and γ [N/m] is the surface tension. The capillary number compares the capillary to the viscous forces. De Menech *et al.*³⁹ define a critical value of $Ca > 0.015$ for the transition of squeezing to dripping regime.

In short, the droplet formation mechanism in the squeezing regime can be described as follows. At the orifice, the two immiscible phases form an interface. As the dispersed phase penetrates into the continuous phase channel, the shear stress exerted by the continuous phase is not enough to break off the droplet and the dispersed phase penetrates deeper into the continuous channel until it fills its cross-section. This leaves only a thin wetting film of continuous phase on the walls, giving rise to an increased pressure at the interface. The resulting pressure force pushes the droplet in the downstream direction and a neck is formed connecting the emerging droplet with the bulk dispersed phase. The neck thins as the droplet elongates in the downstream direction. As the neck approaches the downstream edge of the orifice, it breaks off and a droplet is formed inside the carrier channel. The droplet is transported downstream by the carrier phase, while the dispersed phase stream retracts into the orifice.

Presently, not many examples are known in literature in which a **passive** (i.e. without any active elements on chip such as valves) **DoD** is used, and even less in combination with a **T-junction** geometry. Vanapalli *et al.*⁴², and in a similar setup Hamidovic *et al.*⁴¹, used simple pressure actuation to form a single water droplet in oil in a T-junction. In this case, the oil phase was driven by hydrostatic heads. A droplet was created by using short pressure pulses on the dispersed phase to squeeze a small volume of water into the oil channel. Churski *et al.*⁴³ in another approach used external valves coupled to the dispersed and continuous phase to demonstrate DoD in a T-junction setup. In both cases the pressure of the *dispersed phase* was actively controlled. Teo *et al.*⁴⁴ used negative pressure to produce DoD in a flow-focusing configuration. The water pressure and oil pressure were first balanced to form a stable interface. By applying a negative pressure on *the continuous phase* at the outlet, a droplet was formed.

Our proposed passive droplet generator (capable of both DoD and continuous actuation) is shown in figure 1c. A continuous phase (oil) channel intercepts a dispersed phase via a small sampling channel. The sampling channel is connected perpendicularly to the separation channel. An oil-water interface is established at the orifice of the sampling channel with the continuous phase channel. Three pressures act on this oil-water interface, namely Laplace pressure (P_{LP}), continuous phase pressure (P_c) and dispersed phase pressure (P_d).

A number of factors contribute to the P_d at the water-oil interface. The reservoirs of the dispersed phase channel (separation channel) are open to the atmospheric pressure and the pressure is not actively controlled. Based on the height of the liquid in the reservoirs there is a small hydrostatic pressure contribution and in addition there is also small pressure created due to ICPF (see Chapter 4). All these factors contribute to the P_d at the water-oil interface.

The two reservoirs of the continuous phase are connected to two pressure controllers. A positive pressure is applied to the P_{in} reservoir and a negative pressure to the P_{out} reservoir, resulting in a net pressure driven flow from P_{in} to P_{out} . Due to the flow there is a pressure drop along the oil channel. The pressure at the oil-water interface will range between P_{in} and P_{out} ($P_{in} > P_c > P_{out}$), depending on the hydraulic resistance of channel from the inlet (where P_{in} is applied) to the droplet generator and the resistance from the droplet generator to the outlet (where P_{out} is applied).

The Laplace pressure at the oil-water interface equals (Chapter 3⁴⁵):

$$P_{LP} = -\gamma \left(2 \cos \theta \frac{h + w}{wh} \right) \quad (6.5)$$

where θ is the water-solid contact angle and $h[m]$, $w[m]$ are the height and width of the channel, respectively. Note that equation 6.5 does not take into account the curvature of the meniscus. Since the chip material is hydrophobic ($\theta > 90^\circ$), the Laplace pressure is positive resulting in a normal force to the interface pointing from the oil side to the water side.

An electric equivalent circuit can be used for the calculation of the pressures and of their sum in the system as shown in figure 6.2. It is common to represent a (complex) microfluidic network by an electric network [41]. All the pressure sources are thereby represented as voltage sources, the hydraulic resistances as electric resistances and the volumetric flow as electric current.

If the sum of all the pressures at the interface is zero then the system is at an equilibrium state, the meniscus remains stagnant at the site of the droplet generator and no droplets are created.

$$P_{LP} + P_d + P_c = 0 \quad (6.6)$$

Note that P_{LP} and P_c have the opposite sign of P_d . Once the system is in the equilibrium state, the ICPF process can concentrate and separate the analytes unhindered. If the sum of all the pressure is smaller than zero, the dispersed phase is pushed in the continuous phase and the squeezing-regime droplet formation and break up will take place.

$$P_{LP} + P_d + P_c < 0 \quad (6.7)$$

Figure 6.2 - Electric network equivalent of the microfluidic network. Where V_d represent the pressure at the reservoirs of the disperse phase. V_{in} and V_{out} represent the pressure applied at the P_{in} and P_{out} reservoirs (Figure 6.1a). V_c is the pressure at the oil-water interface due to the V_{in} and V_{out} . V_{LP} represent the Laplace pressure at the oil-water interface. $R_{d,1}$ and $R_{d,2}$ represent the hydraulic resistance from the disperse phase reservoirs to the oil-water interface. R_1 represents the hydraulic resistance from the P_{in} reservoir to the oil water interface and R_2 represents the hydraulic resistance from the P_{out} reservoir to the oil water interface.

The condition expressed in equation 6.7 can be created in the following way. By applying a short negative pressure pulse of P_{out} (Figure 3) the pressure equilibrium is temporarily disturbed, creating (a) droplet(s) sampling the highly concentrated focused analytes without interrupting the ICPF process. Once the droplet(s) is formed the pressure equilibrium is regained. The length of the pressure pulse determines the number of droplets created by the droplet generator. If a continuous negative step pressure is applied instead of a pulse, then equation 6.7 will continuously be satisfied and droplets will continuously be formed.

4.3| Experimental

A 30 μm layer of Microchem SU-8 2050 photoresist was spin-coated on a silicon wafer and the instructions of the manufacturer were followed for exposure and development. Polydimethyl siloxane (PDMS) and curing agent (10:1 ratio) were mixed and PDMS chips were fabricated using standard soft lithography⁴⁶ with the prepared silicon wafer as a mold. The chips were bonded to standard microscopy glass slides after O_2 plasma treatment.

Figure 6.3 - Schematic of the setup and a typical pressure actuation scheme for a single droplet generation (DoD).

A droplet of Nafion perfluorinated resin solution (20wt%) (Sigma-Aldrich) was introduced at their dedicated reservoirs (Figure 6.1a) and the solution was patterned via capillary forces⁴⁷ followed by a drying step of 30min at 60°C. During the drying process Nafion occasionally lost a considerable fraction of its volume, creating microchannels/-gaps between the separation and buffer channels. For this reason, a solution of 2wt% agarose (Sigma-Aldrich) in 1x phosphate buffered saline (PBS, Sigma-Aldrich) was later added in the buffer channels (Figure 6.1a) to seal the gaps in the Nafion and prevent any convective flow from the separation channel into the buffer channels.

The aqueous sample used is 1x PBS spiked with the fluorescent markers Bodipy 492/515 Disulfonate (BDP, Invitrogen) and Alexa Fluor 647 (AF647, Invitrogen). This aqueous sample was added in the separation channel followed by filling the continuous phase, mineral oil (GE Healthcare Life Sciences). To prevent coalescence of the droplets, surfactant Span80 (Sigma-Aldrich) was added to the oil in 3 wt% percent.

The continuous phase inlet and outlet were connected to a Fluigent MFCS-EZ pressure controller which was operated via the MAESFLO software. Platinum wires (Alfa Aesar 0.01inØ) were introduced in the other six reservoirs (buffer channels and separation channel) and were connected to two Keithley 2410 SourceMeters (Figure 6.3). The power supplies were operated and the current

recorded via in-house built LabVIEW software. The formation of droplets and focusing of analytes was optically captured via an Olympus IX51 microscope and a FLIR Grasshopper3 color camera. The droplet size and frequency were analysed with Droplet morphometry and velocimetry (DMV) software provided by Basu ⁴⁸. The fluorescent image analysis was done via ImageJ and Matlab(R2016a).

6.4| Results and discussion

6.4.1| Equilibrium state

Initially the droplet generator was evaluated without the use of ICPF to test several designs. The main variations were applied at the channel widths of the disperse and continuous (small sampling channel) phase (three of these are shown in figure 6.4). The initial aim was to determine the equilibrium pressures P_{in} and P_{out} (i.e. a stable meniscus and no visible droplet formation) for each design, starting from the expected values based on the dimensions shown in the Appendix D. For all designs, we noticed a difference between the theoretical and experimental equilibrium pressures of -2.8 ± 5.1 mBar. We ascribe this difference to inaccuracies in the calculation of the hydrostatic pressure at the reservoirs of the separation channel (P_d) and in the measurement of the contact angle for the calculation of the Laplace pressure (P_{LP}). In addition, the pressure applied by the pressure controller (P_{in} and P_{out}) was fluctuating by ± 1 mBar. Considering all these errors we believe that our model reasonably fits the system's behavior.

Figure 6.4 - Three examples of variations of the droplet generator geometries of the ICPF/droplet extraction chips

6.4.2| Droplet on demand

Once the equilibrium state was achieved a small negative pressure pulse was applied to P_{in} or a negative pressure pulse on P_{in} and on P_{out} . Note that P_{out} is a negative pressure hence a negative pulse will result in a higher flow towards P_{out} . P_{in} is a positive pressure hence a negative pulse results in a lower pressure. In both cases a negative pulse at P_{in} and/or P_{out} tilts the pressure balance towards the same

direction (equation 6.7). For the formation of a single droplet, the duration and magnitude of the pulse was found to be dependent on the design. Typically, the pulse duration ranged between 3 and 5 s for a step size between 5 and 20 mbar. A possible DoD pressure scheme is shown in figure 6.5 and in figure 6.6 the formation of the droplet over time is shown.

In addition, we investigated the success rate of the DoD generators. Either a single or five droplets were requested of each design and the success rate established. If the generator created more or less droplets than the requested number, the attempt was counted as a fail. In figure 6.7 the percentage of success per design for a single droplet is shown. On average in 77% of the cases, a successful single droplet was produced. For 12% of the cases, no droplet was created and in 11% of the cases two droplets were created. Taking into account also the multiple (5) droplets requests out of the total 213 requests (for all the designs) on average 74% of cases were successful.

Figure 6.5 - Pressure actuation schemes (a. and b.) for a single DoD with P_{in} (purple) and P_{out} (black). The dotted line indicates the pressure command that was given, and the solid line is the actual pressure measured by the pump. The volumetric flow was also measured (red). Note that P_{out} is a negative value, but it is given here as an absolute value. a) a single DoD by decreasing P_{in} for 5 seconds. b) a single DoD by decreasing P_{in} and increasing P_{out} for 4 seconds. Note that P_{out} is a negative value, but it is given here as an absolute value. The system was returned to the equilibrium state after the application of the pulse.

Figure 6.6 - Formation of a droplet in design 6. At $t = 0$ s the DoD was started. The aqueous slug penetrated the oil channel and grew until it blocked the channel. The slug was then pushed downstream by the pressure built up at the rear end and the neck thinned. At some point the droplet broke off and the aqueous slug retreated into the orifice to regain its equilibrium. The droplet size is approximately 13.7 pL.

Figure 6.7 - The percentage of success of DoD formation. The designs with 0% success were not capable of forming a stable equilibrium. In the table, the design number, the number of attempts and the success rate is given. The success of a single DoD was 77% and the overall success was 74%.

6.4.3| Droplet size

As previously mentioned, a critical requirement for the droplet generator is the droplet volume which is required to be smaller than the volume of the focused analyte plug. In figure 6.8 the droplet volume for each design is shown. For every design, 80% of the droplets are smaller than 20 pL with the largest droplet being 27 pL which is well below the required 42.8 pL for 2σ of the smallest Gaussian of a focused analyte in ICPF in the present structures. Figure 6.8 also shows the volumetric flow rate of the continuous phase. Although there is no significant correlation between flow rate and droplet size, in all cases the capillary number is below 0.001 which indicates that the device is in the desired squeezing regime. The droplet size is mainly determined by the geometry of the T-junction and more specifically the size (width) of the continuous phase channel. For designs 1,2,12,15 and 16 the width of the continuous phase channel is 20 μm compared to 10 μm for the remainder of the designs. From figure 6.8, it is clear that the 20 μm wide designs produce on average larger droplets.

Figure 6.8 - The average volume of droplets and the volumetric flow rate of the continuous phase for each design in the same pressure range. The error bars represent the standard deviation (the number of tests N per design is shown at the table on the right). Droplets were generally smaller than 20 pL.

6.4.4| Integration of DoD and ICPF

Some initial experiments were performed with the integrated DoD generator and ICPF process. An example of the proposed experimental process is shown in figure 6.9. First the aqueous sample (dispersed phase – 2 μM BDP and 8 μM AF647 in 1xPBS) was introduced in the separation channel, followed by the filling of the continuous phase channels with mineral oil. The equilibrium state was established by tuning the P_{in} and P_{out} (Figure 6.9-1). The ICPF process started by applying suitable potentials to the two reservoirs of the separation channel to have the analytes focusing at a location that did not overlap with the droplet generator (Figure 6.9-2). By allowing sufficient time for the ICPF, the desired concentration of analyte was reached. The focusing location can be tuned by the actuation potentials as shown in Chapter 4. By subsequently tuning the potentials, the focusing location could be moved to the droplet generator (Figure 6.9-3). Once the analytes properly overlapped the droplet generator, the pressure scheme was applied and droplets with highly concentrated analyte were formed and extracted. In addition, we found that the droplet formation did not affect the ICPF process, which continued concentrating the analytes.

Continuous or on-Demand Droplet Generator for Extraction of Electrokinetically Focused Anionic Analytes on Chip

Figure 6.9 - Sequence of ICPF and DoD. Microscopy image - left, Fluorescent intensity profile - right 1) The initial condition 2) A potential difference is applied, and the analytes are focused, with BDP in green and AF647 in red. The concentration of the focused analytes is so high that the camera sensor is saturated making the distinction between colors (analytes) difficult. 3) Adjusting the potential difference enables the control of the focusing location. 4) Once the focused plug has settled in front of the droplet generator, DoDs are created.

In order to investigate the concentration recovery (i.e. ratio of the droplet concentration to the concentration of the focused analyte) of the droplet generator setup in continuous mode, the analyte (1 μM BDP in 1xPBS) was focused in a location that does not intercept with the droplet generator. In contrast to the previous DoD approach, now the droplet generator was set to continuous droplet generation. Once the focused analyte plug by voltage tuning was moved to the location of the droplet generator, pressures were changed such that the analyte plug became continuously “packaged” and extracted in a stream of droplets. A video of this process was recorded, and the concentration of the newly formed droplet was compared to the concentration in the separation channel (at the intercept with the droplet generator averaged over the separation channel width) of the same video frame (Figure 6.10). We report an average concentration recovery of 84% with a minimum of 62% and a maximum of 100%. Since the droplet and focused concentration are compared in the same frame, in some cases the droplet concentration was found to be higher than the concentration in the separation channel. In addition, a relative high exposure time was required for the microscopy images which results in non-sharp images of the fast-moving droplets which may cause underestimation of their fluorescent intensity. Despite the low accuracy of this method for evaluating the concentration recovery, we believe it

gives a good estimate of the process. In the future a downstream processing method can be used for a more accurate droplet concentration quantification.

Figure 6.10 - Example of a video analysis for concentration recovery evaluation. a) A frame of the actual video of the separation channel. Two droplets can be identified left of the separation channel. b) Spatiotemporal intensity profile of the separation channel along the x-axis of figure a. c) Spatiotemporal intensity profile of the oil channel. The vertical lines represent droplets that move through the channel along the x-axis defined in a. A zoom-in is given for frame number 7000-8500. d) The mean intensity in the separation channel (black) and oil channel (red). Every red peak represents a droplet. The intensity recovery is given in the histogram for the droplets produced between frame number 6750-8000. In total 91 droplets were analyzed with an average recovery of 84%

High concentration droplet extraction – Using one of our devices we allowed a single low concentration analyte, namely 100nM of BDP in 0.1xPBS, to concentrate via ICPF for approximately 15 minutes. Subsequently, several (19) highly concentrated single droplets were extracted on demand (DoD). The concentration of the droplets was calculated via a calibration curve and ranged between 84.7μM

and $100.3\mu\text{M}$ (corresponding to a concentration factor ranging from **847** to **1003**). The variation in the concentration of the extracted droplets can arise from various factors: i) Since the focused analytes are in peak mode (i.e. have Gaussian concentration profile), the positioning of the focused analytes with respect to the orifice of the droplet generator determines the extracted concentration. ii) Since the ICPF process is not interrupted during the droplet generation, the analyte in the separation channel continuously concentrates hence droplet extraction at different times results in different droplet concentrations. iii) The extraction of a droplet removes some of the concentrated analyte from the separation channel reducing its concentration hence the time interval between droplets also affects the concentration of the extracted droplets.

Continuous or DoD extraction of separated analytes - In order to demonstrate the extraction of separated droplets, $0.1\times\text{PBS}$ was spiked with 1mM of Cascade blue(CB), 1mM of Alexa Fluor 647(AF647) and 1mM of BDP. Because of the relatively high concentration of analytes compared to the background electrolyte, the ICPF will be in plateau mode as described in chapter 4³⁵. The analytes are allowed to focus and separate into wide plateaus for approximate 1 minute. By tuning the actuation potentials the plateau can then be moved to overlap with the orifice of the droplet generator. In figure 6.11 we demonstrate this process for DoD generation.

Figure 6.11 – Extraction of separated droplets on demand. i) Initial condition. ii) Start of ICPF process ($t\sim 1\text{s}$). iii) After approximately 1 minute the AF647 plateau (red) is moved to the droplet generator by tuning the actuation potentials and a command for a single droplet is given to the droplet generator. iv) The BDP plateau is moved to the droplet generator and a droplet is generated. v) Similarly a single drop of CB is extracted. vi) An array of droplets created over a duration of 5 minutes. Note that image vi corresponds to a different experiment than i-v.

In figure 6.12 another instance of multiple DoD droplets is shown and the purity of each droplet is investigated. Depending on the placement of the plateaus with respect to the droplet generator orifice either pure droplets or a mixture between adjacent plateaus is extracted. For example, the droplet (i) in figure 6.12 contains a mixture of AF647 and BDP and droplet (ii) contains a mixture of BDP and CB. In figures 6.11 and 6.12 the diameter of all the extracted droplets ranged between $20\mu\text{m}$ and $22\mu\text{m}$.

Figure 6.12 – DoD extraction of separated analytes. Top: fluorescent microscopy image of the extracted droplets. The image aspect ratio and contrast have been altered for improved readability. Below: the red (AF647), green (BDP) and blue (CB) fluorescent intensities are plotted.

In addition to the droplet on demand operation, the same device can be used for continuous droplet generation. Two examples of continuous droplet extraction are shown in figure 6.13. As shown in the two examples of figures 6.12 and 6.13, pure and variously mixed droplets can be extracted. Since in ICPF analytes sort themselves based on their mobility, a possible application of continuous droplet extraction could be as follows: The analytes of a complex sample (e.g. proteins in human serum) are separated and allowed sufficient time to concentrate via ICPF. The longer the focusing time the, higher the concentration of low abundance analytes, while the concentration of the highly abundant analytes is limited by their plateau concentration. After the desired focusing time, a continuous droplet generation begins while the actuation potentials are tuned so the sample is “swept” across the droplet generator’s orifice. The resulting droplets then contain highly concentrated analytes and they are sorted based on their electrophoretic mobility, creating in a sense an electrophoretic mobility “memory” of the sample.

6.6| Conclusion and outlook

We have demonstrated a versatile droplet generator that is capable of either DoD (an average success rate of 77%) or continuous droplet generation without the need of any active elements on chip or external valves. We have demonstrated that the generator can be successfully integrated with ICPF. The droplet generator did not affect the ICPF process, which was able to continuously concentrate analytes while highly concentrated analyte droplets could be extracted on demand. We report droplets with concentration of up to 1000 times the original concentration. In case the ICPF duration for concentrating analytes is prolonged, we expect that a much higher concentration factor would still be possible. The recovery of the concentration of our system (84%) improved the results earlier reported by Chen *et al.*⁹ (20%) and van Kooten *et al.*¹⁰ (60%). In addition to the improved recovery, our device does not interrupt or affect the ICPF process compared to the

aforementioned works, making it suitable for integration with a plethora of electrokinetic separation techniques.

Figure 6.13 - Continuous droplet extraction of separated analytes. i) Initial condition. ii) After approximately 1 minute a continuous generation of droplets begins and the AF647 plateau (red) is moved to the droplet generator by tuning the actuation potentials iii) The BDP plateau is moved to the droplet generator iv) The plateau of CB is moved to the droplet generator. v-vi) Examples of the extracted droplets as the sample is swept across the droplet generator. The droplet diameters were 20 μm and 25 μm in v and vi, respectively.

We demonstrated separation and selective the droplet extraction in a simple sample with three analytes. We showed selective droplet extraction either in DoD or continuous droplet generation. A possible application of the continuous droplet generation mode, since analytes focus in bands based on their electrophoretic mobility, could be the focusing via ICPF of a complex sample such as human serum followed by sequential extraction of all analytes in concentrated form, creating in a sense an electrophoretic mobility “memory” of the sample, with the analytes spatially sorted by electrophoretic mobility in the droplets.

6.6| References

1. Guo, M. T., Rotem, A., Heyman, J. A. & Weitz, D. A. Droplet microfluidics for high-throughput biological assays. *Lab on a Chip* (2012). doi:10.1039/c2lc21147e
2. Kaminski, T. S., Scheler, O. & Garstecki, P. Droplet microfluidics for microbiology: Techniques, applications and challenges. *Lab on a Chip* (2016). doi:10.1039/c6lc00367b
3. Pit, A. M., Duits, M. H. G. & Mugele, F. Droplet manipulations in two phase flow microfluidics. *Micromachines* (2015). doi:10.3390/mi6111455
4. Teh, S.-Y., Lin, R., Hung, L.-H. & Lee, A. P. Droplet microfluidics. *Lab Chip* (2008). doi:10.1039/b715524g
5. Van Den Brink, F. T. G. *et al.* A miniaturized push-pull-perfusion probe for few-second sampling of neurotransmitters in the mouse brain. *Lab Chip* (2019). doi:10.1039/c8lc01137k

6. Shang, L., Cheng, Y. & Zhao, Y. Emerging Droplet Microfluidics. *Chemical Reviews* (2017). doi:10.1021/acs.chemrev.6b00848
7. Hindson, B. J. *et al.* High-throughput droplet digital PCR system for absolute quantitation of DNA copy number. *Anal. Chem.* (2011). doi:10.1021/ac202028g
8. Edgar, J. S. *et al.* Compartmentalization of chemically separated components into droplets. *Angew. Chemie - Int. Ed.* (2009). doi:10.1002/anie.200805396
9. Chen, C. H. *et al.* Enhancing protease activity assay in droplet-based microfluidics using a biomolecule concentrator. *J. Am. Chem. Soc.* (2011). doi:10.1021/ja2036628
10. Van Kooten, X. F., Bercovici, M. & Kaigala, G. V. Extraction of electrokinetically separated analytes with on-demand encapsulation. *Lab Chip* (2018). doi:10.1039/c8lc00912k
11. Wang, Y. C., Stevens, A. L. & Han, J. Million-fold preconcentration of proteins and peptides by nanofluidic filter. *Anal. Chem.* (2005). doi:10.1021/ac050321z
12. Quist, J., Janssen, K. G. H., Vulto, P., Hankemeier, T. & Van Der Linden, H. J. Single-electrolyte isotachopheresis using a nanochannel-induced depletion zone. *Anal. Chem.* **83**, 7910–7915 (2011).
13. Cheow, L. F., Sarkar, A., Kolitz, S., Lauffenburger, D. & Han, J. Detecting kinase activities from single cell lysate using concentration-enhanced mobility shift assay. *Anal. Chem.* (2014). doi:10.1021/ac502185v
14. Jeong, H. L., Chung, S., Sung, J. K. & Han, J. Poly(dimethylsiloxane)-based protein preconcentration using a nanogap generated by junction gap breakdown. *Anal. Chem.* (2007). doi:10.1021/ac071162h
15. Liu, V., Song, Y.-A. & Han, J. Capillary-valve-based fabrication of ion-selective membrane junction for electrokinetic sample preconcentration in PDMS chip. *Lab Chip* **10**, 1485 (2010).
16. Ko, S. H. *et al.* Nanofluidic preconcentration device in a straight microchannel using ion concentration polarization. *Lab Chip* **12**, 4472 (2012).
17. Lee, J. H., Song, Y. A. & Han, J. Multiplexed proteomic sample preconcentration device using surface-patterned ion-selective membrane. *Lab Chip* (2008). doi:10.1039/b717900f
18. Kwak, R., Kim, S. J. & Han, J. Continuous-flow biomolecule and cell concentrator by ion concentration polarization. *Anal. Chem.* (2011). doi:10.1021/ac2012619
19. Kim, S. J., Wang, Y. C., Lee, J. H., Jang, H. & Han, J. Concentration polarization and nonlinear electrokinetic flow near a nanofluidic channel. *Phys. Rev. Lett.* **99**, (2007).
20. Quist, J., Vulto, P., Van Der Linden, H. & Hankemeier, T. Tunable ionic mobility filter for depletion zone isotachopheresis. *Anal. Chem.* **84**, 9065–9071 (2012).
21. Wang, Y. C. & Han, J. Pre-binding dynamic range and sensitivity enhancement for immuno-sensors using nanofluidic preconcentrator. *Lab Chip* (2008). doi:10.1039/b717220f

22. Kim, S. J., Ko, S. H., Kang, K. H. & Han, J. Direct seawater desalination by ion concentration polarization. *Nat. Nanotechnol.* (2010). doi:10.1038/nnano.2010.34
23. Sung, J. K. & Han, J. Self-sealed vertical polymeric nanoporous-junctions for high-throughput nanofluidic applications. *Anal. Chem.* **80**, 3507–3511 (2008).
24. Ouyang, W., Ye, X., Li, Z. & Han, J. Deciphering ion concentration polarization-based electrokinetic molecular concentration at the micro-nanofluidic interface: theoretical limits and scaling laws. *Nanoscale* (2018). doi:10.1039/c8nr02170h
25. Gong, L., Ouyang, W., Li, Z. & Han, J. Direct numerical simulation of continuous lithium extraction from high Mg^{2+}/Li^{+} ratio brines using microfluidic channels with ion concentration polarization. *J. Memb. Sci.* (2018). doi:10.1016/j.memsci.2018.03.078
26. Gong, L., Li, Z. & Han, J. Numerical simulation of continuous extraction of highly concentrated Li^{+} from high Mg^{2+}/Li^{+} ratio brines in an ion concentration polarization-based microfluidic system. *Sep. Purif. Technol.* (2019). doi:10.1016/j.seppur.2019.01.036
27. Pu, Q., Yun, J., Temkin, H. & Liu, S. Ion-Enrichment and Ion-Depletion Effect of Nanochannel Structures. *Nano Lett.* **4**, 1099–1103 (2004).
28. Dukhin, S. S. Electrokinetic phenomena of the second kind and their applications. *Adv. Colloid Interface Sci.* (1991). doi:10.1016/0001-8686(91)80022-C
29. Rubinstein, S. M. *et al.* Direct observation of a nonequilibrium electro-osmotic instability. *Phys. Rev. Lett.* (2008). doi:10.1103/PhysRevLett.101.236101
30. RUBINSTEIN, I. & ZALTZMAN, B. ELECTRO-OSMOTIC SLIP OF THE SECOND KIND AND INSTABILITY IN CONCENTRATION POLARIZATION AT ELECTRODIALYSIS MEMBRANES. *Math. Model. Methods Appl. Sci.* (2003). doi:10.1142/s0218202501000866
31. Rubinstein, I. & Zaltzman, B. Electro-osmotically induced convection at a permselective membrane. *Phys. Rev. E - Stat. Physics, Plasmas, Fluids, Relat. Interdiscip. Top.* (2000). doi:10.1103/PhysRevE.62.2238
32. Rubinstein, I., Zaltzman, B. & Lerman, I. Electroconvective instability in concentration polarization and nonequilibrium electro-osmotic slip. *Phys. Rev. E - Stat. Nonlinear, Soft Matter Phys.* (2005). doi:10.1103/PhysRevE.72.011505
33. Kim, S. J., Li, L. D. & Han, J. Amplified electrokinetic response by concentration polarization near nanofluidic channel. *Langmuir* **25**, 7759–7765 (2009).
34. Leinweber, F. C. & Tallarek, U. Nonequilibrium electrokinetic effects in beds of ion-permselective particles. *Langmuir* (2004). doi:10.1021/la048408n
35. Vasileios A. Papadimitriou, L. I. S. and J. C. T. E. Continuous Focusing, Fractionation and Extraction of Anionic Analytes in a Microfluidic Chip. *Lab Chip* (2019). doi:DOI:10.1039/c9lc00434c
36. Schindler, M. & Ajdari, A. Droplet traffic in microfluidic networks: A simple model for understanding and designing. *Phys. Rev. Lett.* (2008).

- doi:10.1103/PhysRevLett.100.044501
37. Zhu, P. & Wang, L. Passive and active droplet generation with microfluidics: a review. *Lab Chip* (2017). doi:10.1039/C6LC01018K
 38. Zhao, C. X. & Middelberg, A. P. J. Two-phase microfluidic flows. *Chem. Eng. Sci.* (2011). doi:10.1016/j.ces.2010.08.038
 39. De menezes, M., Garstecki, P., Jousse, F. & Stone, H. A. Transition from squeezing to dripping in a microfluidic T-shaped junction. *J. Fluid Mech.* (2008). doi:10.1017/S0022211200700910X
 40. Thorsen, T., Roberts, R. W., Arnold, F. H. & Quake, S. R. Dynamic Pattern Formation in a Vesicle-Generating Microfluidic Device. *Phys. Rev. Lett.* (2001). doi:10.1103/physrevlett.86.4163
 41. Hamidović, M., Haselmayr, W., Grimmer, A., Wille, R. & Springer, A. Passive droplet control in microfluidic networks: A survey and new perspectives on their practical realization. *Nano Communication Networks* (2019). doi:10.1016/j.nancom.2018.10.002
 42. Vanapalli, S. A., Banpurkar, A. G., Van Den Ende, D., Duits, M. H. G. & Mugele, F. Hydrodynamic resistance of single confined moving drops in rectangular microchannels. *Lab Chip* (2009). doi:10.1039/b815002h
 43. Churski, K., Korczyk, P. & Garstecki, P. High-throughput automated droplet microfluidic system for screening of reaction conditions. *Lab Chip* (2010). doi:10.1039/b925500a
 44. Teo, A. J. T. *et al.* Negative Pressure Induced Droplet Generation in a Microfluidic Flow-Focusing Device. *Anal. Chem.* (2017). doi:10.1021/acs.analchem.6b05053
 45. Papadimitriou, V. A., Segerink, L. I., van den Berg, A. & Eijkel, J. C. T. 3D capillary stop valves for versatile patterning inside microfluidic chips. *Anal. Chim. Acta* (2018). doi:10.1016/j.aca.2017.11.055
 46. Weibel, D. B., DiLuzio, W. R. & Whitesides, G. M. Microfabrication meets microbiology. *Nat. Rev. Microbiol.* **5**, 209–218 (2007).
 47. Liu, V., Song, Y. A. & Han, J. Capillary-valve-based fabrication of ion-selective membrane junction for electrokinetic sample preconcentration in PDMS chip. *Lab Chip* (2010). doi:10.1039/b923214a
 48. Basu, A. S. Droplet morphometry and velocimetry (DMV): A video processing software for time-resolved, label-free tracking of droplet parameters. *Lab Chip* (2013). doi:10.1039/c3lc50074h

Chapter 7

Current Monitoring for Fluorescence-free Analyte Extraction Control in Ion Concentration Polarization Focusing

In all our experiments and most of the reported work in literature the ion concentration polarization focusing process is monitored by microscopy of fluorescent analytes. This approach allows the direct observation of the focusing location of the analytes of interest, nevertheless it is not applicable in most cases in an industry environment. In this chapter we propose a method to control and predict the focusing location of analytes in the chip by monitoring the electric current through the microfluidic system. Current monitoring has been used in other electrokinetic methods and is highly integrable and suitable for automation of the ICPF process.

7.1| Introduction

As described in earlier chapters, electrokinetic separation techniques have found extensive applications in lab-on-chip systems. A subset of electrokinetic techniques combines separation with focusing (such as isoelectric focusing (IEF) and isotachopheresis (ITP)), locally increasing the concentration of analytes. These focusing techniques have attracted a lot of attention in research in microfluidic systems for more than a decade. Ion concentration polarization focusing (ICPF) is such a focusing technique which is capable of concentration factors in the order of millions¹.

ICPF has been intensively investigated and various applications have been reported since its introduction²⁻¹². The popularity of ICPF is a result of its ease of use and its versatility. Where other focusing techniques such as ITP or IEF require the preparation of application-specific electrolytes, this is not the case for ICPF. A wide variety of focused analytes have been focused with this technique ranging from fluorescent anions¹³ to biomolecules¹⁴. Furthermore ICPF can be applied for cells⁴ and enhanced antigen-antibody binding¹⁵. The focusing location of the analytes can be tuned by the actuation potentials², making it an easy-to-tune process. Despite of all these advantages, most of the research has been demonstrated with the use of fluorescently labeled analytes and the focusing location was investigated via fluorescent microscopy. In this chapter we propose a method to determine the focusing location without the need for optical monitoring.

7.2| Theory

As described in chapter 3 and 4, at the start of the ICPF process the analytes start focusing in the electric field gradient between two regions with different conductivities: the depletion zone with low conductivity (low salt concentration) and the bulk liquid with high conductivity (high salt concentration) (Figure 7.1). The ion concentration is the determining factor for the conductivity of a microchannel (κ), specifically:

$$\kappa = F \sum_i \mu_i c_i \quad (7.1)$$

where $F[C \text{ mol}^{-1}]$ is the Faraday constant, and $\mu_i[m^2 V^{-1} s^{-1}]$ and $c_i[mol m^{-3}]$ are the electrophoretic mobility and average concentration of the ionic species i . The resulting electric resistance of the channel (or a zone) j is:

$$R_j = \frac{l_j}{A\kappa} \quad (7.2)$$

where $l_j[m]$ is the length of the channel (or zone) j and $A[m^2]$ the cross-sectional area of the channel. Since there is a conductivity difference between depletion zone and bulk zone, our separation channel can be electrically represented as two resistors in series, namely one for the depletion zone (R_{DZ}) and one for the bulk

zone (R_{Bulk}) with $\kappa_{DZ} \ll \kappa_{Bulk}$ their respective conductivities (Figure 7.1c). We assume that all the focused analytes are in peak mode; hence they do not contribute significantly to the concentration, conductivity and electric field in the E-field gradient. In the simple case of two resistors, the electric current running through the channel equals:

$$I = \frac{V^u - V^m}{R_{DZ} + R_{Bulk}} \quad (7.3)$$

Here V^u is the upstream potential and V^m the potential at the location of the Nafion membrane (Figure 7.1). Note that the potential at the membrane position will depend on the resistances of all other zones (including the buffer channels) and the upstream (V^u) and downstream (V^d) potentials. As shown in equation 7.2 and 3, the total current in the separation channel will depend on the length (l_j) of each zone. Thus a longer depletion zone will result in a lower current, which can be easily monitored and used for determination of the analyte peak position. A similar current monitoring approach was reported by Karsenty *et al.*¹⁶ for another electrokinetic focusing technique, namely ITP. According to Quist *et al.*², the size of the depletion zone can be tuned by the two actuation potentials at the upstream and downstream reservoir. Since the analytes are focusing in the interface between the depletion zone and bulk zone, knowing the size of the depletion zone results in a known location of focused analytes. A linear relationship is predicted between depletion zone size and current, as calculated by equations 7.2 and 7.3; hence, monitoring the current (I^u) sourced by V^u correlates to the length of the depletion zone and can therefore predict the location of the concentrated analytes.

Nevertheless, variations between chips and between sample conductivities may shift or change the slope of the relation between current and depletion zone size while maintaining the linearity. Simply put, a specific current value will not always correspond to the same depletion zone size and focused analyte position. In order to overcome this limitation, we decided to use another variable from equation 7.2. The resistance of each zone also depends on the cross-sectional area of the channel. Since all the fluidic chip channels have the same height in our devices, the cross-sectional area can be modified by modifying the channel width. By varying the channel width at a specific location in the channel we will vary the linear relation between depletion zone size and current once the depletion zone grows over the channel part with the width variation¹⁶. The (non-linear) current response now is coupled to a specific location of the channel rather than to the sample conductivity.

Starting from this idea, various channel variations were designed and tested. We strongly recommend Appendix E to the reader where the reasoning behind the design of the channel variations along with the applicability of the same reasoning for a variety of microfluidic applications (*e.g.* Coulter counters) is presented.

Figure 7.1 - a) Schematic representation of the setup for ICPF. A separation channel is connected to two buffer channels via an ion permselective membrane (Nafion®). A potential is applied to the upstream (V^u) and downstream (V^d) reservoirs and the buffers channels are grounded. Due to ion concentration polarization a depletion zone is formed in the separation channel with a locally very low salt concentration compared to the bulk salt concentration. b) Schematic of ICPF with a width variation in the separation channel at a specific location. c) A simple electric equivalent of the separation channel from the upstream reservoir to the Nafion® membrane, with V^m the potential at the location of the membrane. d) Schematic of current (I^u) vs depletion zone length (l_{DZ}). In the first case (a) there is a linear relation between the depletion zone length and the current. In the second case (b) the resistance of the depletion zone will increase non-linearly when the depletion zone overlaps the width variation in the channel and the linearity between the current and the depletion zone size will be broken.

7.3| Experimental

The chip fabrication and preparation are similar to those given in the previous chapters. In short, polydimethyl siloxane (PDMS) chips were prepared by soft lithography¹⁷. The soft lithography molds were made by 30 μm thick MicroChem® SU-8 2050 features patterned with photolithography on silicon wafers. The outline of the photolithography mask is shown in figure 7.2. The Nafion® perfluorinated resin solution (20wt. % - Sigma-Aldrich) was filled and patterned via capillary forces^{18,19}. Nafion was dried at 60°C for 30 minutes to form a solid permselective polymer. 2% wt. UltraPure™ Agarose (Invitrogen) in 1x phosphate buffered saline (PBS) (Sigma-Aldrich) was introduced in the buffer channels to

prevent bulk liquid flow between separation and buffer channel due to gaps formed in the Nafion channel during its drying process.

BODIPY™ 492/515 Disulfonate (BDP) (Invitrogen) was chosen as a model anionic analyte and it was used as a tracer for the focusing location. 1xPBS was chosen as a background electrolyte for its biological relevant properties and applications. For the fluorescent microscopy an Olympus IX51 was used and images/videos were captured with a FLIR Grasshopper®3 color camera. The videos were analysed via Matlab (R2016a). Platinum wires (Alfa Aesar 0.01in diameter) were introduced in the separation and buffer channels reservoirs as electrodes to which electric potentials were applied and the current measured by two Keithley 2410 sourcemeter power supplies controlled by an in-house made LabVIEW program. The 2D simulations were performed in Comsol (Multiphysics 5.3) using the *transport of dilute species*, *electrostatics* and *laminar flow* physics modules which were coupled via *flow coupling*, *space charge density coupling* and *potential coupling* multiphysics.

Figure 7.2 - Overview of the ICPF design with some typical actuation potentials. Various width variations were fabricated in the separation channel. Three examples are shown (red scale bars – 200 µm).

7.4| Results and discussion

In a PDMS device with a separation channel with no variations (constant cross-sectional area) we tested the assumption that the current (I^u) sourced by V^u correlates to the size of the depletion zone and hence to the concentrated analyte location. One of the actuation potentials (V^u) was kept constant at 110 V and the other one (V^d) varied from 0 to 110 V and back while the location of the concentrated analyte and the current was recorded. The location of the maximum

concentration of the focused analyte was taken as the focusing position. Since there is a single analyte in our system, it will focus at the gradient between depletion zone and bulk (in the electric field gradient) hence the focusing position can be correlated to the depletion zone size (assuming that the concentration and electric field gradient have a constant length). The results are shown in Figure 7.3. A linear relation between current and depletion zone length can be seen in figure 7.3b as indeed expected from equation 7.2 and 7.3. The electric current (measured by the power supply) and the focusing position (measured via microscopy) were sampled with the same sampling frequency, as a mismatch in time and frequency between the two devices could result in an error matching the current to the focusing position. Nevertheless, the instabilities in the focusing location due to electroconvective vortices which cause variations faster than the sampling rate of 10 Hz, and the non-perfectly stable sampling rate of the power supply (ranging from 9-11Hz) introduces an error in matching the current samples to the microscopy frames. We conclude that despite this error, monitoring the current can predict the size of the depletion zone and hence the focusing location.

Figure 7.3 - a) Focusing position versus time and potential difference ($V^u - V^d$) versus time. b) Current (I^u) versus focusing position. A linear relation with a R^2 value of 0.87 can be seen between current and focusing position x . The focusing position is taken as the distance from the Nafion membrane.

As we mentioned in the theory section, differences in the conductivity between samples along with fabrication variations between chips may change the slope or shift the current-position curve of figure 7.3b. To overcome this limitation, varying the channel cross section was proposed. Various designs of channels with varying cross section were first investigated in Comsol. For this purpose, a front of low concentration was flown across the channel variation to simulate a depletion zone of increasing length, and the current running through the entire channel was simulated (Figure 7.4). A clear disruption of the linear relationship between the current and the length of the low concentration front can be seen. As seen in figure 7.4 the concentration profile is disturbed as it passes the channel expansion-constriction stemming from the non-uniform flow velocity through them (for more information see Appendix E).

In the simulations a concentration of 100mM and 1mM was used for the high and low concentration of a monovalent symmetric electrolyte with a diffusion

coefficient of $10^{-9} \text{ m}^2\text{s}^{-1}$ for both species. The front was flown by pressure driven flow (slip boundary condition on the walls) with a linear velocity of $1000 \mu\text{m/s}$. The channel width was $100 \mu\text{m}$ and length to $800 \mu\text{m}$ resulting in a Peclet number of 800.

Figure 7.4 - Comsol simulations of the two designs shown at the top of the figure. A front of low concentration (blue color) flows across a channel expansion and constriction while the current is monitored.

The designs with the most promising simulation results in terms of disturbance to the concentration profile and fabrication feasibility were fabricated in PDMS and integrated in an ICPF device shown in figure 7.2. Two of the experimental results are shown in figure 7.5. Similar to the previous results, the high potential (V^u) was kept constant at 100 V and V^d was varied from 0 to 100 V and back while the current (I^u) and the maximum concentration location were measured. The maximum concentration location was measured in the middle of the channel, averaged over the yellow area shown in figure 7.5. As can be seen in the current versus focusing position graph, the linear relation between the two is broken at the locations of the expansion and constriction features. As a result, a distinct drop in the current can be observed when the channel feature is crossed, and thus the current response can be related to a specific location in the channel as was our aim. In figure 7.6 the concentration profile (averaged over the red area) for each video frame is shown in a spatiotemporal graph. From that graph one can see that not only the current but also the focusing position has distinct “jumps”, *i.e.* the analytes focus at the expansion location rather than in the constriction. Once the depletion

zone is large enough, the focusing location will “jump” to the next expansion. We believe that this is an effect of the expansion and constriction features, influencing the convective flow velocity in the channel. The analytes are focusing at the location where the electrophoretic velocity is equal and opposite to the convective flow velocity. In the constriction the convective flow velocity is much higher than in the expansion, hence it is possible that the focusing condition of equal electrophoretic and convective velocities is locally not met. An additional contribution can be provided by the electroconvective vortices. Ouyang *et al.*¹⁰ demonstrated the importance of the electroconvective vortices in the focusing mechanism during ICPF. We expect that these vortices are altered or suppressed in the constriction due to its high hydraulic resistance. Further experimental and theoretical research is required for the investigation of the distinct jumps in the focusing position. Nevertheless, our assumption that variation in the channel width will result in a non-linear relation between current and focusing location clearly holds. Compared to the case of the straight microchannel, the current response in this case is coupled to the location of the expansion/constriction. An electrolyte with different conductivity will result in different absolute values of current but a distinct change in the current will be noticed once the depletion zone expands across the channel feature.

Figure 7.5 - Effect of the channel width on the current versus peak position response. (top) Fluorescence microscopy image of the channel. (bottom) Peak position versus current plotted with blue dots. The channel width is shown as a black line.

Figure 7.6 - a) Fluorescent microscopy image of ICPF with channel variations at $t=50s$ (Scale bar $200\ \mu m$) b) Spatiotemporal concentration graph. The concentration profiles were taken by averaging the fluorescent intensity over the red region in (a). c) Applied potential in the downstream reservoir versus time. b) and c) share the same time axis. The current response of this experiment is shown in figure 7.5a.

7.5| Conclusions and outlook

We demonstrated that current monitoring can be used in ICPF as an indication for the focusing position of analytes. In the typical case of ICPF where a simple straight channel is used for separation, the focusing position scales linearly with the current running through the system. Although current monitoring in a straight channel thus is a good qualitative method for estimating the focusing position, sample and chip variations make an absolute location determination challenging. To eliminate this challenge, we introduced one or multiple channel width variations close to the focusing location that will disrupt the linear dependence of current on focusing location. We showed that the current response can be used as a fingerprint to determine the exact focusing location in the channel. In addition, we observed that the focusing location is also affected by channel constrictions and expansions. This is a rich theoretical and experimental research topic and worthy of further investigation. We believe that our approach can help ICPF escape the research environment by allowing full electrical control, and in this manner find more industry applications.

7.6| References

1. Wang, Y. C., Stevens, A. L. & Han, J. Million-fold preconcentration of proteins and peptides by nanofluidic filter. *Anal. Chem.* (2005). doi:10.1021/ac050321z
2. Quist, J., Janssen, K. G. H., Vulto, P., Hankemeier, T. & Van Der Linden, H. J. Single-electrolyte isotachophoresis using a nanochannel-induced depletion zone. *Anal. Chem.* **83**, 7910–7915 (2011).
3. Rubinstein, I. & Zaltzman, B. Electro-osmotically induced convection at a permselective membrane. *Phys. Rev. E - Stat. Physics, Plasmas, Fluids, Relat. Interdiscip. Top.* (2000). doi:10.1103/PhysRevE.62.2238
4. Kwak, R., Kim, S. J. & Han, J. Continuous-flow biomolecule and cell concentrator by ion concentration polarization. *Anal. Chem.* (2011). doi:10.1021/ac2012619
5. Kim, S. J., Wang, Y. C., Lee, J. H., Jang, H. & Han, J. Concentration polarization and nonlinear electrokinetic flow near a nanofluidic channel. *Phys. Rev. Lett.* **99**, (2007).
6. Choi, J. *et al.* Selective preconcentration and online collection of charged molecules using ion concentration polarization. *RSC Adv.* **5**, 66178–66184 (2015).
7. RUBINSTEIN, I. & ZALTZMAN, B. ELECTRO-OSMOTIC SLIP OF THE SECOND KIND AND INSTABILITY IN CONCENTRATION POLARIZATION AT ELECTRODIALYSIS MEMBRANES. *Math. Model. Methods Appl. Sci.* (2003). doi:10.1142/s0218202501000866
8. Zangle, T. A., Mani, A. & Santiago, J. G. Theory and experiments of concentration polarization and ion focusing at microchannel and nanochannel interfaces. *Chemical Society Reviews* **39**, 1014–1035 (2010).
9. Gong, L., Li, Z. & Han, J. Numerical simulation of continuous extraction of highly concentrated Li⁺ from high Mg²⁺/Li⁺ ratio brines in an ion concentration polarization-based microfluidic system. *Sep. Purif. Technol.* (2019). doi:10.1016/j.seppur.2019.01.036
10. Ouyang, W., Ye, X., Li, Z. & Han, J. Deciphering ion concentration polarization-based electrokinetic molecular concentration at the micro-nanofluidic interface: theoretical limits and scaling laws. *Nanoscale* (2018). doi:10.1039/c8nr02170h
11. Kim, S. J., Li, L. D. & Han, J. Amplified electrokinetic response by concentration polarization near nanofluidic channel. *Langmuir* **25**, 7759–7765 (2009).
12. Kim, S. J., Ko, S. H., Kang, K. H. & Han, J. Direct seawater desalination by ion concentration polarization. *Nat. Nanotechnol.* (2010). doi:10.1038/nnano.2010.34
13. Quist, J., Vulto, P., Van Der Linden, H. & Hankemeier, T. Tunable ionic mobility filter for depletion zone isotachophoresis. *Anal. Chem.* **84**, 9065–9071 (2012).
14. Cheow, L. F., Sarkar, A., Kolitz, S., Lauffenburger, D. & Han, J. Detecting kinase activities from single cell lysate using concentration-enhanced

- mobility shift assay. *Anal. Chem.* (2014). doi:10.1021/ac502185v
15. Wang, Y. C. & Han, J. Pre-binding dynamic range and sensitivity enhancement for immuno-sensors using nanofluidic preconcentrator. *Lab Chip* (2008). doi:10.1039/b717220f
 16. Karsenty, M., Rosenfeld, T., Gommed, K. & Bercovici, M. Current monitoring in a microchannel with repeated constrictions for accurate detection of sample location in isotachophoresis. *Anal. Chem.* (2015). doi:10.1021/ac5036346
 17. Weibel, D. B., DiLuzio, W. R. & Whitesides, G. M. Microfabrication meets microbiology. *Nat. Rev. Microbiol.* **5**, 209–218 (2007).
 18. Liu, V., Song, Y.-A. & Han, J. Capillary-valve-based fabrication of ion-selective membrane junction for electrokinetic sample preconcentration in PDMS chip. *Lab Chip* **10**, 1485 (2010).
 19. Papadimitriou, V. A., Van Den Berg, A. & Eijkel, J. C. T. 3D capillary valves for versatile capillary patterning of channel walls. in *20th International Conference on Miniaturized Systems for Chemistry and Life Sciences, MicroTAS 2016* (2016).

Chapter 8

Summary and Recommendations for Further Work

In this chapter a short summary and recommendations for further work per chapter are presented.

8.1| Summary and recommendations

The research work presented in this thesis was aimed at developing a microfluidic system capable of separating and concentrating specific biomarkers out of human blood for early diagnosis of cardiovascular diseases (CVD) in a point of care testing (POCT) device. The thesis also includes novel techniques that were developed to reach this aim, and spin-offs of the applied techniques for other applications. Since research and technology is a never-ending process, recommendations for future work will here be combined with the chapter-by-chapter summary.

Porous particles find a wide variety of applications in research and industry, specifically catalytic particles used in the oil industry are of great importance. The catalytic properties of such particles are greatly dependent to their porosity and pore size. A quick, inexpensive and easy to use tool for porosity characterization at the single particle level could provide valuable information to the catalysis industry. In **chapter 2** we demonstrated the use of the ion concentration polarization (ICP) phenomenon as a tool for differentiating mesoporous particles based on their porosity. The one-dimensional analytical model of the process we developed was sufficient to predict the general behavior of the system. Nevertheless, we believe that a two- or three-dimensional numerical model would significantly improve our understanding of the process and help us determine the relations between the physical properties of the particles (*e.g.* pore size, pore shape) and ICP. Once these relations are determined, ICP can evolve from a porosity differentiation tool to a porosity quantification tool.

Antibody patterning is of great importance for medical Lab-on-a-chip devices. In such device typically antibodies are patterned on a flat chip with standard and well-established methods, such as micro-contact printing. After the patterning, a second chip containing the required fluidic features is aligned and bonded to the antibody patterned chip. This approach has two disadvantages; i) It requires precise alignment during bonding. ii) Any bonding methods tools that can harm the antibodies, such as UV or Plasma treatment, are prohibited. In **chapter 3** we demonstrated the use of capillary forces for patterning liquids inside a closed microfluidic chip. The proposed geometry is using a combination of capillary stop valves and open microfluidics. We demonstrated antibody patterning followed by immunodetection of a cardiac biomarker. We derived a simple theoretical model that can be used as a design tool for tailoring three dimensional valves for various applications, solutions and materials as long as the contact angle and surface tension are known. In the future we would like to demonstrate the functionality of our design for different application *e.g.* for patterning hydrogels, patterning phase change materials (such as Nafion resin) and local surface functionalization. **Appendix A** provides supplementary information for this chapter.

Ion concentration polarization focusing (ICPF) has been proven a very powerful electrokinetic separation and concentration technique. Nevertheless, the separated and concentrated analytes become effectively trapped in the microchannel in picoliter volumes, making mandatory the integration of a sensor

for the analysis of the sample. Another solution to this problem could be the extraction of the concentrated and separated analytes out the chip. In **chapter 4** we demonstrated selective extraction of concentrated and separated anionic analytes by pressure application. The analytes were separated and concentrated by ICPF. The analytes were concentrated by a factor of 300 and were extracted with a low throughput in the range of nl min^{-1} . In the future we would like to demonstrate the selective extraction of concentrated proteins out of human blood serum. In addition, the purity of the extracted analytes could in future be investigated by integrating the chip with a downstream processing method such as mass spectrometry. **Appendix B** provides supplementary information on this chapter.

For some applications, such as sample preparation, the throughput of our proposed device in chapter 4 is too low. In **chapter 5** high-throughput (up to sample flows in the $\mu\text{l min}^{-1}$ range) selective extraction and concentration of anionic analytes was shown with the use of a novel method, namely free-flow ion concentration polarization focusing (FF-ICPF). We demonstrated two operating modes, namely peak and plateau mode. In addition, an analyte in plateau mode was used as an electrophoretic spacer improving the separation resolution between two analytes in peak mode. Finally, we characterized the device in human blood serum showing the applicability of the method for sample preparation applications. In the future we expect that the fabrication of the device from more heat conductive materials (such as silicon) in combination with active cooling will result in significant improvement in the throughput, widening the range of potential applications of FF-ICPF. **Appendix C** provides supplementary information on this chapter.

Notwithstanding their merits, in both approaches presented in the chapters 4 and 5 the analytes are prone to diffusion and mixing after extraction. A solution to this problem can be a selective “packaging” and extraction of the focused analytes. In **chapter 6** we developed a droplet generator suitable for integration with electrokinetic separations, capable of droplet-on-demand or continuous droplet generation without interfering with the separation process. We demonstrate the “packaging” and extraction of highly concentrated (by a factor of 100) droplets in ICPF without interrupting the separation and concentration process. In the future we would like to investigate the purity of the extracted droplets and demonstrate a selective droplet extraction in real sample (human blood serum). **Appendix D** provides supplementary information on this chapter.

Despite the power of ICPF, to our current knowledge there are not many (if any) commercial products that use the method. Currently in research on ICPF (including this thesis) fluorescent analytes are monitored via microscopy. This approach requires the labelling of the analytes with fluorescent markers and the use of a bulky microscope limiting ICPF’s applicability outside a research environment. In **chapter 7** we investigated how the electric current running through the separation channel is related to the focusing position in ICPF. The combination of current monitoring with a channel cross-section variation can be

used for predicting the exact focusing location during the separation process. In the future we would like to demonstrate a fully automated ICPF process by monitoring and adjusting the current, making it suitable for integration in a POCT device. Such a device would represent a significant advance compared to the present situation where fluorescent analytes and optical detection must be employed.

Finally, in **Appendix E** we try to deepen our understanding of the phenomena of chapter 7. We propose that the electric current response of a microchannel can be described by a convolution between the conductivity profile and the channel cross-section. This hypothesis can find a wide range of application from ICPF control to tailoring Coulter counters for specific particle shapes. Comsol modeling was used to prove our hypothesis. In the future we would like to also experimentally prove this hypothesis.

Appendix A
Supplementary Information for
Chapter 3

A.1| Capillary stop valves

During operation, capillary stop valves can be analyzed in three stages, namely pinning, pivoting and “breaking”¹, which are shown in figure A.1 As described in the article the capillary pressure can be calculated by the following formula.

$$P = \frac{dU_t}{dV} = -\gamma_{lg} \left(\cos\theta \frac{dA_{sl}}{dV} - \frac{dA_{lg}}{dV} \right) \quad (\text{A. 1})$$

At the channel expansion, A_{lg} increases more strongly than A_{sl} for a given volume change, and thus creates a positive pressure. This positive pressure barrier forces the liquid to stop and to become pinned at the expansion site (pinning region). Such valves can be broken when external pressure/energy is applied (i.e. increase of V) to the pinned liquid. In such a case the curvature of the meniscus will change from concave to convex (pivoting region). This results in a geometrical change of A_{lg} upon which the pressure barrier depends. If the volume of the liquid further increases, the meniscus angle will become equal to the equilibrium contact angle (θ_c) at the walls of the widened part and the liquid will proceed filling the channel. Meeting the equilibrium contact angle at the walls of the widened section is the condition for “breaking” the geometric stop valve. During the normal operation of our device the capillary valve should not break, since no external pressure is applied. The pressure barrier of the valve equals the external pressure that needs to be applied for the valve to break.

Figure A.1 - Three stages of capillary valve operation. i) Pinning of the meniscus at the abrupt opening. ii) Pivoting of the meniscus curvature from concave to convex. iii) When the meniscus meets the new equilibrium contact angle the valve “breaks” and the liquid advances.

A.2| Flow velocity calculation

A.2.1| Capillary filling

The equation describing the capillary pressure in a rectangular channel is given in section 3.2.1:

$$P = -\gamma_{lg} \left(2\cos\theta \frac{h+w}{wh} \right) \quad (\text{A. 2})$$

Using a contact angle(θ) of 38° and a surface tension(γ_{lg}) of $24.87\text{e-}3^{2,3}$, a width(w) of $10\mu\text{m}$ and a height(h) of $70\mu\text{m}$ results in a capillary pressure of -4.47kPa . The hydraulic resistance, R_h is given by:

$$R_h = \frac{8\mu L}{\pi R^4} \quad (\text{A. 3})$$

Where R is the hydraulic radius, $\mu(8.9\text{e-}4\text{Pa s})$ is the viscosity, $L(400\mu\text{m})$ the length of the channel and R the hydraulic radius. An equivalent hydraulic radius can be calculated for rectangular channels. This results in a hydraulic resistance of $2.47\text{e}15 \text{ Pa s m}^{-3}$.

The volumetric pressure driven flow (Q) is given by:

$$Q = \frac{P}{R_h} \quad (\text{A. 4})$$

And the linear velocity(v) of the liquid front:

$$v = \frac{P}{R_h A} \quad (\text{A. 5})$$

Where A is the cross-sectional area. Using the results of pressure and hydraulic resistance we can calculate the linear velocity which equals to 2.6mm/s .

A.2.2| Open microfluidics

As described in the article the capillary pressure in a rectangular open microfluidic structure is given by:

$$P = -\gamma_{lg} \left(\cos\theta \frac{2h+w}{wh} - \frac{1}{h} \right) \quad (\text{A. 6})$$

If we use the same values for surface tension, contact angle, and width as before and a height of $35\mu\text{m}$ we get a capillary pressure of -3.80kPa .

Equation A.2 for the hydraulic resistance also holds for open microfluidic structures and an equivalent hydraulic radius can be acquired for arbitrary geometries by⁴:

$$R = 4 \frac{A}{p_{sl}} \quad (\text{A. 7})$$

Where A is the channel cross-sectional area and p_{sl} the wetted perimeter. The hydraulic resistance of an open microfluidic feature is lower since it has one less solid liquid interface compared to a closed channel. For examples a typical

open microfluidic feature (100 μm long, 10 μm wide, and 45 μm deep) results in a hydraulic resistance of 5.5e-14Pa s m⁻³.

Using equation A.4 for calculating the linear velocity in the open microfluidic structure we calculate a velocity of 15.3mm/s.

As it can be seen also in the attached video the velocity of the filling liquid is high enough to fill the whole device in less than a second and the time depended flow velocity that is typical in capillary systems it can be neglected.

A.3| References

1. Man, P. F., Mastrangelo, C. H., Burns, M. A. & Burke, D. T. Microfabricated capillarity-driven stop valve and sample injector. *Proc. MEMS 98. IEEE. Elev. Annu. Int. Work. Micro Electro Mech. Syst. An Investig. Micro Struct. Sensors, Actuators, Mach. Syst. (Cat. No.98CH36176)* 45–50 (1998). doi:10.1109/MEMSYS.1998.659727
2. Mishra, H. *et al.* Time-Dependent Wetting Behavior of PDMS Surfaces with Bioinspired, Hierarchical Structures. *ACS Appl. Mater. Interfaces* **8**, 8168–8174 (2016).
3. Cao, H., Amador, C., Jia, X. & Ding, Y. Capillary Dynamics of Water/Ethanol Mixtures. *Ind. Eng. Chem. Res.* **54**, 12196–12203 (2015).
4. Berthier, J., Brakke, K. A. & Berthier, E. *Open Microfluidics*. (Scrivener Publishing, 2016).

Appendix B
Supplementary Information for
Chapter 4

B.1| Ion concentration polarization focusing (ICPF) model

In order to extract the analytes, the focused analyte peaks must be precisely placed at the location where the extraction channels intersect the sample channel. Since different analytes are focused in different locations in the E-field gradient, the gradient needs to be moved so that the concentrated band of the analyte of interest overlaps with the location of the extraction channel and it can be selectively extracted. In order to change the position of the E-field gradient we need to regulate the length of depletion zone(dz).

The length of the dz, l^u , can be regulated by two phenomena that have an opposite effect, namely ICP and the linear convective flow which is dominated by EOF. Both phenomena are driven by an E-field; ICP by the E-field across the Nafion membrane and EOF by the E-field between up- and downstream reservoirs. The EOF velocity scales linearly with the potential difference between up- and downstream reservoirs as shown in Helmholtz-Smoluchowski equation (equation (4.5) of the Chapter 4). In this way the electric and the fluidic model are coupled. The simulation is performed in incremental time steps. For each time step the electric model calculates the expansion of dz due to ICP($\frac{dl_e}{dt}$) equation 4.2 of the Chapter 4). The volumetric flow and linear flow velocity ($\frac{dl_f}{dt}$) are then calculated by the fluidic model and fed back to the electric model.

As described in literature¹ and as also follows from our model, the length of dz due to ICP under a no-flow condition (no EOF or PDF, $V^u = V^d, \frac{dl_f}{dt} = 0$), grows with the square root of time under constant voltage actuation (Figure B.1).

$$l^u = -l^d = \beta t^{\frac{1}{2}} \text{ (B. 1)}$$

$$\frac{dl^u}{dt} = \frac{1}{2} \beta t^{-1/2} \text{ (B. 2)}$$

The scaling factor β depends on various parameters of the system, i.e. applied potentials, channel dimensions, Nafion properties, bulk and depletion zone conductivity, bulk and depletion zone concentrations.

When EOF from upstream to downstream reservoir ($V^u > V^d$) is introduced, upstream from the Nafion the flow opposes the growth of dz and $\frac{dl_f}{dt}$, $\frac{dl_e}{dt}$ are opposite and the iteration process will result in a stable depletion zone length (l^u).

In contrast, downstream from the Nafion $\frac{dl_f}{dt}$ and $\frac{dl_e}{dt}$ have the same sign and the depletion zone (l^d) will grow until the downstream reservoir is reached. The focusing position depends on l^u (i.e. scaling factor β) and the zeta potential in the bulk and the depletion zone.

Figure B.1 - Depletion zone length upstream (l^u) and downstream (l^d) vs time under no convective flow condition ($V^u = V^d = 30V$) following from the model. The expected square root of time behavior can be seen.

The focusing position of the analytes can be regulated by adjusting the reservoir potentials. As shown in figure B.2 the smaller the difference between upstream and downstream potential the further away the stable focusing position will become located from the Nafion interface. If the reservoir potentials are changed in magnitude but the ratio between both remains constant, then the focusing position is constant. In contrast the concentration rate and the induced pressure scale directly with the magnitude of the applied potential difference between upstream and downstream (Figure B.3, B.4). A typical approach to increase the preconcentration rate in standard ICPF devices is to apply an extra PDF between the upstream and downstream reservoir². This behavior can also be described by our model by applying the corresponding potentials (pressures) on the now grounded reservoir nodes of the fluidic model. Though the model can describe the general behaviour of the system, exact prediction is a challenging process since some parameters of the system are unknown. Specifically, the concentration, conductivity and zeta potential in the depletion zone are unknown. We used an estimate of the concentration based on experimental results of similar devices. Kim et al[4] report a 33-fold increase in the E-field in the depletion zone compared to bulk E-field, which translates to a 33-fold decreased conductivity in the depletion zone compared to the bulk buffer (1mM phosphate (dibasic sodium phosphate)). Nevertheless, in depletion zone systems electroconvective vortices enhance the conductivity in the depletion zone by introducing extra charge carriers^{3,4} hence only an approximation of the average concentration can be obtained from the conductivity. The low salt concentration in the depletion zone is expected also to locally increase the zeta potential. The zeta potential is also greatly influenced by the pH^{5,6} which is reported⁷ to be more acidic close to the depletion zone. Finally, our model neglects the effect of diffusion between bulk and depletion zone.

Figure B.2 - Focusing position (l^u) shown in color map (as distance from Nafion in meters) vs actuation potentials (V^u, V^d) at $t=5s$ (Note: the position is constant over time after $t \sim 3s$). The smaller the potential difference, the further the focusing position from the Nafion (i.e. the bigger the depletion zone). The response of the focusing position versus potential difference is shown in the inset figure. In case that the $V^u < V^d$ the depletion zone will reach a stable size towards the downstream reservoir and it will grow all the way to upstream reservoir. If the ratio between potentials is kept constant, a constant focusing position is achieved.

The preconcentration rate describes the local increase of concentration of analyte over time and is expressed as the number of times increase of the analyte relative to its starting/bulk concentration per unit of time. We assume all the anions that arrive at the interface between depletion zone are focused as described in the main article, hence the preconcentration rate simply scales with the flux (J_i) of each species in the separation channel arriving to the depletion zone.

$$J_i = v_{conv} C_i^b \quad (B.3)$$

Here v_{conv} is the convective flow and C_i^b is the bulk concentration of species i . The preconcentration rate thus simply scales with the bulk volumetric flow, as bulk flow brings analytes to their focusing position in the E-field gradient between bulk liquid and depletion zone. The higher the flow, the higher the number of analytes arriving at the location at the E-field gradient where they have zero-net velocity, and the highest the preconcentration rate.

Figure B.3 - Induced negative pressure vs actuation potentials (V^u, V^d) at $t=5\text{sec}$. The induced pressure scales linearly with the potential difference between V^u and V^d as shown by the inset figure.

Figure B.4 - Preconcentration rate (number of times the bulk concentration (C_b) per second) vs actuation potentials (V^u, V^d) at $t=5\text{sec}$ assuming a focused analyte plug of $125\mu\text{m}$ in width. The preconcentration rate scales approximately linearly with the potential difference between V^u and V^d as shown by the inset figure.

B.2| Derivation of focused analyte peak size and distribution

We will follow the approach of J.C. Gidding⁸ for focusing techniques. Neglecting the incoming flux of analyte, the peak profile follows from the opposing electrical and diffusional fluxes. For steady state we can write:

$$J_{i,0} = v_i C_i(x) - D_i \frac{dC_i}{dx} = 0 \quad (\text{B. 4})$$

Here v_i is the linear analyte velocity, C_i is concentration and D_i the diffusion coefficient of species i . From this we can write the differential equation

$$\frac{1}{C_i} \frac{dC_i}{dx} = \frac{v_i(x)}{D_i} \quad (\text{B. 5})$$

The velocity v_i of anion i equals

$$\begin{aligned} v_i(x) &= v_{conv} + v_{eph}(x) \\ v_i(x) &= v_{conv} - \mu_i E(x) = v_{conv} - \mu_i \left(E_0 + \frac{dE}{dx} x \right) \end{aligned} \quad (\text{B. 6})$$

Here E_0 is the electric field in the bulk and μ_i the electrophoretic mobility. Substitution in equation (B.4) gives

$$\frac{1}{C_i} \frac{dC_i}{dx} = \frac{v_{conv} - \mu_i \left(E_0 + \frac{dE}{dx} x \right)}{D_i} \quad (\text{B. 7})$$

From this we can write the integral

$$\int_{C_{i,0}}^{C_{i,x}} \frac{1}{C_i} dC_i = \int_0^x \frac{v_{conv} - \mu_i \left(E_0 + \frac{dE}{dx} x \right)}{D_i} dx \quad (\text{B. 8})$$

Assuming a constant E-field gradient $\frac{dE}{dx}$ we obtain

$$\ln \left(\frac{C_{i,x}}{C_{i,0}} \right) = \frac{(v_{conv} - \mu_i E_0)x - \frac{1}{2} \frac{dE}{dx} \mu_i x^2 + \beta}{D_i} \quad (\text{B. 9})$$

We thus obtain the expression for the concentration profile of an analyte in peak mode,

$$C_i(x) = C_{i,0} \exp\left(\frac{(v_{conv} - \mu_i E_0)x - \frac{1}{2} \frac{dE}{dx} \mu_i x^2 + \beta}{D_i}\right) \quad (\text{B.10})$$

The constant β can be calculated via the known value of $C_i(x_{eq}) = C_{i,0}$. The focusing position x_{eq} where the electrophoretic and convective flow are equal and opposite, and where the anion has zero net velocity (i.e. where Equation B.6 equals to 0) is

$$x_{eq,i} = \frac{v_{conv} - E_0 \mu_i}{\frac{dE}{dx} \mu_i} \quad (\text{B.11})$$

The focusing location x_{eq} is shown in figure B.5 as a function of electrophoretic mobility for a typical actuation potential ($V^u - V^d = 60V$).

Figure B.5 - Focusing location vs electrophoretic mobility.

After calculating β we can rewrite equation B.10 in its final form:

$$C_i(x) = C_{i,0} \exp\left(-\frac{\left(x - \frac{v_{conv} - E_0 \mu_i}{\frac{dE}{dx} \mu_i}\right)^2}{2 \frac{D_i}{\mu_i \frac{dE}{dx}}}\right) \quad (\text{B.12})$$

Equation B.12 describes a Gaussian distribution with a mean equal to x_{eq} (Equation B.11) At x_{eq} the analyte will focus and create a Gaussian peak with a variance of

$$\sigma^2 = \frac{D_i}{\mu_i \frac{dE}{dx}} \quad (\text{B. 13})$$

Since the diffusion coefficients and electrophoretic mobilities are related via Einstein's relation,

$$D_i = \frac{k_b T}{q_i} \mu_i = \frac{V_T}{z_i} \mu_i \quad (\text{B. 14})$$

(with k_b is the Boltzmann constant, T the temperature, V_T the thermal voltage and z_i the valence of the ion), we can rewrite the variance in a simpler form,

$$\sigma^2 = \frac{V_T}{z_i \frac{dE}{dx}} \quad (\text{B. 15})$$

Equation B.15 might appear counterintuitive since it is independent of electrophoretic mobility and diffusion coefficient of a specific analyte, but since at the focusing location the ion has zero net velocity any size-dependent variables drop out. Simply put, the ionic thermal energy (V_T) increases the variance while the electric field gradient reduces it.

Resolution

As shown in equation 4.12 of the chapter 4 the resolution of the separation method equals to:

$$R_s = \frac{v_{conv}}{2 \sqrt{\frac{dE}{dx}} V_T} \cdot \frac{\left(\frac{1}{\mu_1} - \frac{1}{\mu_2} \right)}{\left(\frac{1}{\sqrt{z_1}} + \frac{1}{\sqrt{z_2}} \right)} \quad (\text{B. 16})$$

Our model allow us to calculate the total convective flow in the separation channel along with the electric field in the bulk (E_B) and depletion zone (E_{dz}) and the electric field difference ($\Delta E = E_{dz} - E_B$). One still unknown variable is the size of the concentration gradient between bulk and depletion zone (electric field gradient size). According to Mani et al.⁹ the size of such gradient (l_{grad}) scales with the average diffusion coefficient (D) and the characteristic velocity of the system in our case the convective velocity.

$$l_{grad} \sim \frac{D}{v_{conv}} \quad (\text{B. 17})$$

Intuitively equation B.17 describes that diffusion acts towards a flatter gradient while the opposing flow act towards a steeper gradient assuming constant concentration in the depletion zone and in the bulk. Using equation B.17 and assuming a constant electric field gradient we can write

$$\frac{dE}{dx} = \frac{\Delta E}{l_{grad}} \quad (\text{B. 18})$$

On figure B.6 the resolution for separation of Bodipy ($\mu_{BDP}=1.76\cdot 10^{-8} \text{ m}^2\text{V}^{-1}\text{s}^{-1}$) and Alexa fluor 647 ($\mu_{AF647} = 1.58\cdot 10^{-8} \text{ m}^2\text{V}^{-1}\text{s}^{-1}$). As it can be seen for low potential difference the resolution is drastically improved compared to high potential difference where poor and constant resolution can be seen. Nevertheless, the improved resolution comes at a cost of concentration rate since as it shown on figure B.4 the lower the potential difference the lower the concentration rate.

Figure B.6 - Resolution vs potential difference ($V^u = 60\text{V}$, and V^d ranged from 0 to 59V).

B.3| References

1. Zangle, T. A., Mani, A. & Santiago, J. G. Effects of constant voltage on time evolution of propagating concentration polarization. *Anal. Chem.* **82**, 3114–3117 (2010).
2. Sung, J. K. & Han, J. Self-sealed vertical polymeric nanoporous-junctions for high-throughput nanofluidic applications. *Anal. Chem.* **80**, 3507–3511 (2008).
3. De Valença, J. C., Wagterveld, R. M., Lammertink, R. G. H. & Tsai, P. A. Dynamics of microvortices induced by ion concentration polarization. *Phys. Rev. E - Stat. Nonlinear, Soft Matter Phys.* **92**, (2015).
4. Kim, S. J., Wang, Y. C., Lee, J. H., Jang, H. & Han, J. Concentration polarization and nonlinear electrokinetic flow near a nanofluidic channel. *Phys. Rev. Lett.* **99**, (2007).
5. Kirby, B. J. & Hasselbrink, E. F. Zeta potential of microfluidic substrates: 1. Theory, experimental techniques, and effects on separations. *Electrophoresis* **25**, 187–202 (2004).
6. Kirby, B. J. & Hasselbrink, E. F. Zeta potential of microfluidic substrates: 2. Data for polymers. *Electrophoresis* **25**, 203–213 (2004).
7. Mogi, K. A visualization technique of a unique pH distribution around an ion depletion zone in a microchannel by using a dual-excitation ratiometric

- method. *Micromachines* **9**, (2018).
8. Giddings, J. C. *Unified Separation Science*. (John Wiley & Sons, 1991).
 9. Mani, A., Zangle, T. A. & Santiago, J. G. On the propagation of concentration polarization from microchannel - nanochannel interfaces Part I: Analytical model and characteristic analysis. *Langmuir* **25**, 3898–3908 (2009).

Appendix C
Supplementary Information for
Chapter 5

C.1| Effect of high electric power to the stability of the system

A high throughput of the device requires high velocities in the separation direction and hence a high electric field generating high electric power. The high electric power can affect the stability in two ways: (1) in the form of heat and; (2) in the form of changes in pH due to electrochemical reactions.

C.1.1| Heat analysis

The electric current running through the system results in Ohmic heating. In the typical experiments we performed, the maximal applied voltage is approximately 100 V, resulting in approximately 100 μ A of current (in 0.1xPBS) and a dissipated power in the order of magnitude of 0.1 W. The heat can be dissipated in the system via water cooling due to the flow of the sample through the chip or via heat transfer to the environment. The water cooling power (P_w [W]) can be calculated via:

$$P_w = Q_f \rho C_p \Delta T \quad (\text{C. 1})$$

where Q_f [$\text{m}^3 \text{s}^{-1}$] is the volumetric flow of the liquid, ρ [kg m^{-3}] the liquid density, C_p [$\text{J K}^{-1} \text{kg}^{-1}$] is the specific heat capacity of the liquid and ΔT [K] is the temperature difference between inlet and outlet. Using the heat capacity of water (4.19 kJ $\text{K}^{-1} \text{kg}^{-1}$) and a flow rate of 10 $\mu\text{l min}^{-1}$, we calculate a water cooling power of approximately 0.7 mW which is almost three orders of magnitude lower than the applied electric heat power. Hence the cooling of the device due to the liquid flow can be neglected.

Heat can also be dissipated from the separation chamber by conduction through the glass at the bottom of the device to the environment. The heat transfer power (P_T [W]) can be calculated as:

$$P_T = \kappa_T A \frac{\Delta T}{x} \quad (\text{C. 2})$$

where κ_T [$\text{W m}^{-1} \text{K}^{-1}$] is the thermal conductivity, A [m^2] is the total area of that heat flows through, in our case the size of the separation chamber, x [m] is the heat transfer distance (*i.e.* glass thickness) and ΔT [K] is the temperature difference between the two sides of the glass. If we equate the Ohmic heating power to the heat transfer power and assume that the temperature of the side of the glass to the environment is constant we calculate a temperature increase in the liquid of 0.95 K compared to the environment (using $\kappa_{T, \text{SiO}_2} = 1.05 \text{ W m}^{-1} \text{K}^{-1}$), proving that passive cooling of the device is sufficient for typical operation potentials. Nevertheless, higher throughputs in combination with highly conductive samples may require active cooling or the use of materials with higher thermal conductivity compared to glass such as silicon.

C.1.2| Electrochemical reactions

The electric current applied to the system is transformed to an ionic current via electrochemical reactions on the surface of the electrodes, whereby gaseous products can be formed (O_2 , Cl_2 , H_2). Water electrolysis thereby changes the pH of the solution. The rate of formation of H^+ and OH^- (assuming water electrolysis is the only reaction taking place) (j [$mol\ s^{-1}$]) can be simply calculated via Faraday's law:

$$j = \frac{I}{Fz_i} \quad (C.3)$$

where I [A] is the electric current and F [$C\ mol^{-1}$] is the Faraday's constant. A current of $100\ \mu A$ will add approximately $1\ nmol\ s^{-1}$ of H^+ to the anodic reservoir. The smaller the reservoir, the stronger the effect of the added acid on the local pH. In our device we therefore used large reservoirs of 1 ml. The application of $100\ \mu A$ for 1000 s will cause a pH reduction of 0.81 and 0.19 in 0.1xPBS and 1xPBS, respectively.

C.2| Original microscopy images

In the following figures the original fluorescent microscopy images are shown upon which the analysis of Chapter 5 is based.

Figure C.1 - Unedited fluorescent microscopy images upon which the analysis for peak mode was based for Chapter 5, Figure 5.2.

Figure C.2 - Unedited fluorescent microscopy images upon which the analysis for plateau mode was based for Chapter 5, Figure 5.3.

Figure C.3 - Unedited fluorescent microscopy images upon which the analysis for the electrophoretic spacers was based for Chapter 5, Figure 5.5.

Appendix D
Supplementary Information for
Chapter 6

D.1| Chip designs and dimensions

On figure D.1 all the different droplet-on-demand(DoD) generator designs that were tested are shown.

Figure D.1 – Representation of the designs tested for the DoD generator. The dimensions were kept the same for the integrated designs with the ICPF chips, where the sample channel (marked with “Sample Inlet” at the reservoirs) was used as the separation channel a) Full design. The red square indicates the location of the droplet generator. b) individual designs. The sample channel is 50 μm wide and orifice and oil channel widths range between 10-40 μm .

D.2| Equilibrium pressure calculations and observations

Based on the droplet generator dimensions the expected pressures in order to achieve equilibrium were calculated for every design shown in table D.1. The experimentally observed pressures that were required for the pressure equilibrium are shown in table D.2

Table D.1 – Expected theoretical pressures in mbar for P_{in} and P_{out} resulting in P_c , and the expected P_{LP} at the oil water interface. The hydrostatic pressure P_d is assumed to be 2mbar for all designs. The sum of pressure equals to zero (equilibrium state)

Design	1	2	6	10	12	15	16	17	19	24
P_{in}	43.8	38.0	36.4	50.2	37.5	39.0	37.1	37.1	43.0	43.0
P_{out}	-60	-60	-60	-60	-60	-60	-60	-60	-60	-60
P_c	-3.4	-6.6	-6.5	-4.4	-6.5	-3.3	-4.4	-4.4	-2.4	-3.4
P_{LP}	5.3	8.5	8.5	6.4	8.5	5.3	6.4	6.4	4.3	5.3

Table D.2 – Observed pressures in mbar for P_{in} and P_{out} resulting in zero pressure at the interface. The hydrostatic pressure P_d and Laplace pressure are assumed to be the same as in the expected theoretical pressures case. The sum of pressure equals to zero (equilibrium state). P_{diff} indicates the pressure difference at the interface between observed and the theoretically expected values

Design	1	2	6	10	12	15	16	17	19	24
P_{in}	34	41	31	40	27	37	30	38	30	55
P_{out}	-60	-60	-60	-36	-70	-60	-69	-70	-59	-70
P_{diff}	-5.4	1.6	-3.0	-6.7	-10.3	-1.1	-7.9	-3.8	-6.9	2.1

Appendix E

Convolution in Microfluidics

E.1| Introduction

In chapter 7 we described how the current can be monitored for determination of the focusing location in ion concentration polarization focusing (ICPF). In this appendix we will attempt to provide a more general framework to explain how the current response of the system changes with the cross-sectional area of a microfluidic channel. From Ohm's law we can write for the electric current (I [A]):

$$I = GV \text{ (E. 1)}$$

where G [S] is the electric conductance and V [V] is the applied potential difference. The electric current in liquids is not carried by electrons but by the charged species present in the electrolyte (i.e. ions). The electrolyte conductivity (κ [S m⁻¹]) of a solution equals:

$$\kappa = F \sum_i \mu_i c_i \text{ (E. 2)}$$

where F [C mol⁻¹] is the Faraday constant μ_i [m² s⁻¹ V⁻¹] and c_i [mol m⁻³] are the electrophoretic mobility and average concentration of the ionic species i , respectively. As shown in equation E.2 the dominant factor for the conductivity is the concentration of the charged species. We will investigate the case where a current is sent through a solution with a non-uniform concentration in the x-direction (1D approach), so that the concentration profile and the conductivity will be a function of x ($\kappa(x) = f(x)$).

The conductance (G [S]) of a liquid-filled channel in microfluidic chip can be described by

$$G(x) = \frac{A}{l} \kappa(x) \text{ (E. 3)}$$

Here A [m²] and l [m] are the channel cross-sectional area and channel length respectively. In the case where there is a variation of the cross-sectional area along the x-axis, A will also be a function of x , ($A(x) = g(x)$).

When there is a conductivity (i.e. concentration) profile moving through a channel with varying cross-sectional area, we can write the conductance for every offset position (χ) of the conductivity profile as (Figure E.1):

$$G(\chi) = \frac{1}{l} \int_0^l A(x) \kappa(x + \chi) dx \text{ (E. 4)}$$

Figure E.1 - Schematic of a conductivity gradient moving towards a channel expansion and symbol definition.

The integral of equation E.4 represents a cross-correlation function in the space domain. **Convolution** is a similar function but requires the reversal of one of the functions. However, for symmetric functions (that we will investigate in this chapter) or if the conductivity profile moves in the opposite direction of the cross-sectional variation, convolution and cross-correlation produce the same result. In such a case, we can write the current as the convolution ($\otimes$) of the cross-sectional area with the conductivity profile, as a function of the position of the conductivity profile.

$$I(\chi) = \frac{V}{l} (A \otimes \kappa) \quad (\text{E. 5})$$

E.2| Convolution

A very short introduction to convolution will be given in this section, the reader is referred to the book of Smith (Chapter 13 - Convolution)¹ for a deeper look. Convolution is a mathematical operation between two functions (f and g) (typically in the time domain(t) for 1D functions) and it is defined as:

$$(f \otimes g)(t) \triangleq \int_{-\infty}^{\infty} f(\tau)g(t - \tau)d\tau \quad (\text{E. 6})$$

Where τ is a dummy variable. Convolution describes how the shape of one functions is altered by the other one. "The convolution formula can be described as a weighted average of the function $f(\tau)$ at the moment t where the weighting is given by $g(-\tau)$ simply shifted by amount t . As t changes, the weighting function emphasizes different parts of the input function."¹

The neutral element in convolution is the Dirac delta function ($\delta(t)$), $f \otimes \delta(t) = f(t)$. Dirac delta functions ($\delta(t)$) is defined as

$$\delta(t) = \begin{cases} +\infty & \text{or } 1 & t = 0 \\ 0 & & t \neq 0 \end{cases} \quad (\text{E. 7})$$

The convolution of a function $f(t)$ with a function $k(t)$ consisting of positive Dirac delta function and negative Dirac delta function spaced dt apart results at $\frac{df}{dt}$.

$$k(t) = \begin{cases} 1 & t = 0 \\ -1 & t = dt \\ 0 & t \neq 0 \text{ and } t \neq dt \end{cases} \quad (\text{E.8})$$

$$(f \otimes k)(t) = \frac{df}{dt} \quad (\text{E.9})$$

Finally the convolution theorem states that:

$$\mathcal{F}\{f \otimes g\} = k \cdot \mathcal{F}\{f\} \cdot \mathcal{F}\{g\} \quad (\text{E.10})$$

where $\mathcal{F}\{f\}$ is the Fourier transform of f and k is a constant.

E.3| Application of convolution

In order to test our hypothesis that the current response of a conductivity profile moving through a channel with varying cross-sectional area is a convolution between the conductivity profile and the cross-sectional area (Equation E.5), we can try to replicate the results of the above convolution in a microfluidic equivalent constructed by Comsol simulation. In all simulations the “*Transport of diluted species (tds)*”, “*Electrostatics (es)*” and “*Laminar flow (lf)*” physics modules were used, which were coupled by “*Space charge density coupling (tds → es)*”, “*Potential coupling (es → tds)*” and “*flow coupling (lf → tds)*” multiphysics modules. A symmetric monovalent electrolyte was used with diffusion coefficient of $1\text{e-}9\text{m}^2\text{s}^{-1}$ for both species. The current was measured as the flux of charged species through the inlet (left side of the channel Figure E.2d). We assumed a constant channel height, hence the cross-sectional area changes of the channel simply translated to changes in the channel width.

The neutral element in the convolution function is the Dirac delta function. Since fabricating a Dirac function in the width of the channel is impossible, we used a square channel expansion instead (Figure E.2a). A high-concentration plug was flown across the expansion and the current response was simulated and compared to the result of a convolution of a square step function with a concentration profile (Figure E.2b). The maximum concentration was 100mM while the lowest was 1mM. The profile was flown by pressure driven flow (slip boundary condition) with a linear velocity of $1000\mu\text{m/s}$ (Peclet number of 1000). As shown in Figure E.2d the 2D concentration distribution profile is affected after it passes through the expansion of the channel, which also affects the current response shown in figure E.1e, altering it from the convolution result show in Figure E.2c. The origin of this disturbance is the non-uniform velocity profile along the channel.

Figure E.2 - a,b,c) Direct convolution of channel width (a) with the concentration profile (b) $a \otimes b = c$. d) Three instances of the Comsol simulation at different times. The colormap indicates the concentration magnitude. The concentration plug is flowing from left to right. The red lines indicate the boundary on which the current was measured. e) The normalized current response obtained in the simulation.

Figure E.3 - a,b,c) Direct convolution of channel width (a) with the concentration profile (b) $a \otimes b = c$. d) Three instances of the Comsol simulation at different times. The colormap indicates the concentration magnitude. The concentration plug is flowing from left to right. e) The normalized current response obtained in the simulation.

As mentioned earlier a convolution of a function with two opposite-in-sign Dirac functions results in the gradient of the original function. Once again, instead of a Dirac function, we used a square channel expansion and constriction in Comsol and the results of the Comsol simulation are compared to a direct convolution of

the two functions (Figure E.3). Also in this case we see that the concentration profile is affected by the channel expansion and constriction due to the non-uniform flow velocity along the channel.

The same principle of convolution can be used for the more widely used case of Coulter counters. In this case we used a uniform concentration profile (100mM) and calculated the current response created during the movement of a particle through a channel with a varying cross-section as a convolution of the channel cross-sectional area minus the particle cross-sectional area, with the local channel cross-sectional area (Equation E.4) (assuming a non-conducting particle and neglecting surface conduction effects). The particle area locally “modulates” the total channel area as it moves through it. We used a capsule-shaped particle and assumed that the particle is an ideal dielectric. The particle was moved by steps of $2\mu\text{m}$ and the simulation was allowed enough time (2 seconds) till a steady a current value was reached for each particle movement step. We assume that the particle flows in the center-line of the channel. Similar to the previous example, we can compare the convolution results with the simulation results. In figure E.4 the results are presented for a channel with a semicircular constriction and in figure E.5 the results for a channel with a semicircular constriction and semicircular expansion.

Figure E.4 - a,b,c) Direct convolution of the channel width (a) with the particle width (b) $a \otimes b = c$. d) Three instances of the Comsol simulation at different times. The colormap indicates the electric field magnitude. The particle is moving from left to right. e) The normalized current response of the simulation

Figure E.5 - a,b,c) Direct convolution of the channel width (a) with the effect of particle in the channel width (b). $a \otimes b = c$. d) Three instances of the Comsol simulation at different times. The colormap indicates the electric field magnitude. The particle is moving from left to right. e) The normalized current response obtained in the Comsol simulation.

As can be seen in figure E.5e, the response is not symmetrical between the expansion and the constriction, with the channel expansion resulting in a smaller change in the current. We believe this is due to electric field lines not following perfectly the channel profile. Since the electric current follows the path of least resistance, a sharp and wide expansion in the channel cross-sectional area will not contribute linearly to the local conductance as described by equation E.3.

E.4| Applications of deconvolution

Notwithstanding the limitations and non-idealities brought out by the Comsol simulations, based on the aforementioned results we believe that convolution can reasonably describe the current response of a microfluidic channel when a concentration/conductivity gradient or a particle moves through a local channel cross-sectional area variation. Therefore we can use deconvolution ($\otimes^{-1}$) to tailor a current response for a specific input. For example, we might want to design a Coulter counter that produces a specific current response when a capsule-shape particle passes (similar to the previous experiments). The capsule shape (input) and the requested current response (output) are shown in figure E.6a and E.6b respectively. The desired current response was thereby chosen arbitrarily. If we deconvolute the specific current response with the specific particle shape, we get the required channel shape (Figure E.6c) which should be unique for the specific particle shape. Since deconvolution is not always possible, the correct result of the deconvolution can be verified if we convolute it with the particle shape (Figure E.6d-f) and compare it to the requested response (Figure E.6a and Figure E.6f).

Figure E.6 - a) Arbitrary requested current response. b) Effect of particle in channel width. c) The deconvolution of a and b. $a \otimes b = c$. d,e,f) Verification of the deconvolution. $d \otimes e = f$.

Obviously, the shape shown in figure E.6c is impossible to fabricate. In figure E.6a we plot the spatial frequency of this shape. We can now apply a low pass filter in order to get a shape with smooth changes which should be suitable for fabrication. In this case we applied a low pass filter with a cut off spatial frequency of $0.06 \mu\text{m}^{-1}$ (Figure E.7b). This frequency indicates we can have a periodic change with a length of $16.7 \mu\text{m}$. The filtered result is shown in figure E.7c.

Figure E.7 - a) Spatial frequency spectrum of the original deconvolution shown in figure E.5c. b) Spatial frequency spectrum of the filtered deconvolution. c) The filtered deconvolution in the space domain.

Figure E.8 - a,b,c) Direct convolution of the channel width(a) with the effect of particle in the channel width(b). $a \otimes b = c$. d) Three instances of the simulation at different times. The colormap indicates the electric field magnitude. The particle is moving from left to right. e) The normalized current response of the simulation.

Once again, we test the convolution response (shown in figure E.8a-c) to the Comsol simulation response. We created a channel with the width variation shown in figure E.7c, imported it in Comsol and simulated a Coulter counter experiment for the capsule shaped particle that it was designed for. The results are shown in Figure E.8d-e.

The simulation current response Figure E.8e creates a much wider peak than the expected result of the convolution. We believe once again this is a result of the unequal contribution between expansions and constrictions in the local conductivity. Furthermore, in order to check the uniqueness of the response to the specific particle shape we also simulated three more Coulter counter experiments in the channel shape provided in Figure E.8d. We compared the responses to three different particles: a sphere, a capsule of the length it was designed for and a 25% longer capsule. All of the particles have the same width. The results are shown in figure E.9.

Despite the fact that current response does not precisely match the results of the convolution, the current response is clearly different for the different particles and easily can be used to differentiate between the shapes. Finally, the particle that the channel was designed for (capsule) creates a clear symmetric peak as it crosses this complicatedly shaped channel.

Figure E.9 - i) The Comsol mesh of the simulation showing the differences in the shape of the three particles. ii) The normalized current responses obtained in the Comsol simulations. iii) The convolution results between the particle and the channel width. **Box a)** Results for the longer capsule particle. **Box b)** Results of the capsule particle that the channel was designed for. **Box c)** Results of a spherical particle.

E.5| Conclusion and outlook

We proposed that the current response when a conductivity profile moves through a channel with a non-constant cross-sectional area can be reasonably match the result of a convolution of the conductivity profile to the cross-sectional area. The convolution is applicable when the conductivity profile arises from a concentration profile or from a dielectric particle (Coulter counter). We demonstrated the use of deconvolution for tailoring Coulter counters that can differentiate between particle shapes. In the future we would like to experimentally confirm the simulation results.

E.6| References

1. Smith, S. W. Convolution. *Sci. Eng. Guid. to Digit. Signal Process.* (1999).

Publication List

Peer - reviewed journal publications

1. **Vasileios A. Papadimitriou**, Loes I. Segerink, Albert v.d. Berg and Jan C. T. Eijkel. "3D capillary stop valves for versatile patterning inside microfluidic chips" *Analytica Chimica Acta* 2018 1000, pp 232-238, <https://doi.org/10.1016/j.aca.2017.11.055>
 2. Miguel Solsona⁺, **Vasileios A. Papadimitriou**⁺, Wouter Olthuis, Albert v.d. Berg and Jan C. T. Eijkel. "Ion Concentration Polarization for MicroParticle Mesoporosity Differentiation." *Langmuir* 2019, <https://doi.org/10.1021/acs.langmuir.9b00802>.
+ Both authors contributed equally
 3. **Vasileios A. Papadimitriou**, Loes I. Segerink and Jan C. T. Eijkel. "Continuous Focusing, Fractionation and Extraction of Anionic Analytes in a Microfluidic Chip." *Lab-on-Chip* 2019, DOI:10.1039/c9lc00434c
- Chapter 5 is **submitted** for publication as: **Vasileios A. Papadimitriou**, Loes I. Segerink and Jan C. T. Eijkel. "Free Flow Ion Concentration Polarization Focusing (FF-ICPF)".
 - Chapter 6 is **in preparation** for publication as: **Vasileios A. Papadimitriou**, Stella A. Kruit, Loes I. Segerink and Jan C. T. Eijkel. "Continuous or on-Demand Droplet Generator for Extraction of Electrokinetically Focused Anionic Analytes on Chip".

Conference Contributions

1. **Vasileios A. Papadimitriou**, Albert v. d. Berg, and Jan C. T. Eijkel.. (2016). "3D capillary valves for versatile capillary patterning of channel walls." In 20th International conference on Miniaturized Systems for Chemistry and Life Sciences (pp. 1649-1650). (**MicroTAS 2016**), Dublin, Ireland. (Poster Presentation)
2. **Vasileios A. Papadimitriou**, Y.Abbas, Johan G. Bomer, Albert v. d. Berg, and Wouter Olthuis, (2016). "Membrane templated activated carbon for electric double layer supercapacitors." 42nd International conference on Micro and Nano Engineering, (**MNE 2016**), Vienna, Austria. (Oral Presentation)
3. Miguel Solsona, Jan C.T. Eijkel, Wouter Olthuis, **Vasileios A. Papadimitriou**, Albert van den Berg, Leon Abelmann, Bert M. Weckhuysen, A. E. Nieuwelink (2017) "Concentration Polarization to Measure Nano-pore Accessibility" In

- 21st International conference on Miniaturized Systems for Chemistry and Life Sciences (pp. 1497-1499). (**MicroTAS 2017**), Savannah , USA. (Poster Presentation)
4. **Vasileios A. Papadimitriou**, Loes I. Segerink, Albert v. d. Berg, and Jan C. T. Eijkel.. (2017). "Continuous Extraction Depletion Zone Isotachophoresis (Edz-ITP)." In 21st International conference on Miniaturized Systems for Chemistry and Life Sciences. (**MicroTAS 2017**), Savannah , USA. (Oral Presentation)
 5. **Vasileios A. Papadimitriou**, Albert v. d. Berg, and Jan C. T. Eijkel. (2017) "Closed-chip capillary patterning of antibodies." In **Flow17** conference. Paris, France (Poster Presentation)
 6. **Vasileios A. Papadimitriou**, Roelof v. Zwol, Loes I. Segerink and Jan C. T. Eijkel. (2018) "Free-flow depletion zone isotachophoresis (FF-dzITP)" In 22nd International conference on Miniaturized Systems for Chemistry and Life Sciences (pp. 2013-2015). (**MicroTAS 2018**), Kaohsiung , Taiwan. (Poster Presentation)
 7. **Vasileios A. Papadimitriou**, Stella A. Kruit, Loes I. Segerink and Jan C. T. Eijkel. (2019) " On-demand droplet generator for extraction of electrokinetically focused analytes" In 23rd International conference on Miniaturized Systems for Chemistry and Life Sciences (**MicroTAS 2019**), Basel, Switzerland (Poster Presentation)
 8. **Vasileios A. Papadimitriou**, Miguel Solsona, Albert v. d. Berg, Wouter Olthuis and Jan C. T. Eijkel. (2019) "Ion Concentration Polarization for MicroParticle Mesoporosity Differentiation." In 23rd International conference on Miniaturized Systems for Chemistry and Life Sciences (**MicroTAS 2019**), Basel, Switzerland (Poster Presentation)

Samenvatting

Het onderzoek dat beschreven wordt in dit proefschrift had als doel het ontwikkelen van een microfluidisch systeem dat in staat is om specifieke biomarkers uit humaan bloed te scheiden en concentreren voor de vroege diagnostiek van cardiovasculaire ziektes in een point of care testing (POCT) apparaat. Dit proefschrift bevat nieuwe technieken die zijn ontwikkeld om dit doel te bereiken en variaties van de toegepaste techniek voor andere toepassingen. Omdat onderzoek en technologie een eindeloos proces is, worden aanbevelingen voor toekomstig onderzoek hier gecombineerd met een samenvatting van elk hoofdstuk.

Poreuze deeltjes hebben veel mogelijke toepassingen in onderzoek en industrie. Met name katalytische deeltjes gebruikt in de olie industrie zijn van groot belang. De katalytische eigenschappen van zulke deeltjes zijn erg afhankelijk van hun porositeit en porie grootte. Een snelle, goedkope en makkelijke manier voor porositeit karakterisatie op het niveau van een enkel deeltje zou waardevolle informatie geven voor de katalysator industrie. In **hoofdstuk 2** tonen we het gebruik van het ion concentratie polarisatie (ICP) fenomeen als gereedschap voor het differentiëren van mesoporeuze deeltjes op basis van hun porositeit. Het één-dimensionele analytische model van het proces dat we ontwikkeld hebben was voldoende om het algemene gedrag van het systeem te voorspellen. Desalniettemin, we denken dat een twee- of drie-dimensioneel numeriek model het begrip van het proces significant zou verbeteren, en het ons kan helpen in het bepalen van de relaties tussen de fysische eigenschappen van de deeltjes (bijv. porie grootte, porie vorm) en ICP. Wanneer deze relaties zijn bepaald, kan ICP ontwikkelen van een porositeit differentiatie method naar een porositeit kwantificatie gereedschap.

Antibody patterning (het maken van patronen van antilichamen op een oppervlak) is erg belangrijk voor medische Lab-on-a-chip apparaten. Vaak wordt in zulke apparaten een patroon van antilichamen gemaakt op een platte chip met standaard methoden, zoals micro-contact printen. Na het maken van het patroon, wordt een tweede chip met de benodigde vloeistof eigenschappen uitgelijnd en gebonden op de chip met het antilichaam patroon. Deze aanpak heeft twee nadelen; i) het vereist precieze uitlijning tijdens het binden. ii) Methodes voor het binden die de antilichamen kunnen beschadigen, zoals UV of plasma behandeling, kunnen niet worden gebruikt. In **hoofdstuk 3** demonstreren we het gebruik van capillaire krachten voor het maken van vloeistof patronen in een microfluidische chip. De voorgestelde geometrie maakt gebruik van de combinatie van capillaire stop kleppen en open microfluidica. We hebben de antibody patterning, gevolgd door de immunodetectie van een cardiac biomarker aangetoond. We hebben een simpel theoretisch model afgeleid dat kan worden gebruikt als een design tool voor het ontwerpen van drie dimensionale kleppen voor verschillende applicaties, oplossingen en materialen, zolang de contact hoek en oppervlaktespanning bekend zijn. In de toekomst willen we graag de functionaliteit van ons ontwerp voor verschillende toepassingen aantonen, bijvoorbeeld voor hydrogel patterning, fase veranderende materialen (zoals Nafion resin) patterning, en lokale oppervlakte functionalisering. **Appendix A** bevat aanvullende informatie voor dit hoofdstuk.

Ion concentratie polarisatie focussen (ICPF) is bewezen een erg krachtige elektrokinetische scheidings- en concentratie techniek te zijn. Echter, worden de gescheiden en geconcentreerde biomarkers effectief gevangen in het microkanaal in picoliter volume, waardoor de integratie van een sensor voor de analyse van het monster vereist wordt. Een andere oplossing voor dit probleem zou de extractie van de geconcentreerde en gescheiden biomarkers uit de chip zijn. In **hoofdstuk 4** tonen we de selectieve extractie van geconcentreerde en gescheiden anionische biomarkers aan door het toepassen van druk. The biomarkers zijn gescheiden en geconcentreerd door ICPF. De biomarkers zijn geconcentreerd met een factor 300 en zijn geëxtraheerd met een lage throughput in de orde van nl min^{-1} . In de toekomst zouden we graag de selectieve extractie van geconcentreerde eiwitten uit humaan bloed serum laten zien. Daarnaast, zou in de toekomst de zuiverheid van de geëxtraheerde biomarkers kunnen worden onderzocht door het integreren van een verwerkingsmethode als massa spectrometrie gekoppeld aan de chip. **Appendix B** bevat aanvullende informatie voor dit hoofdstuk.

Voor sommige toepassingen, zoals de voorbereiding van een monster, is het debiet van het door ons voorgestelde apparaat in hoofdstuk 4 te laag. **Hoofdstuk 5** laat een hoog debiet (met monster vloeistofsnelheden in de orde van $\mu\text{l min}^{-1}$) selectieve extractie en concentratie of anionische biomarkers zien met behulp van een nieuwe methode genaamd free-flow ion concentratie polarisatie focussing (FF-ICPF). We laten twee werkzame manieren zien genaamd de piek en plateau manier. Daarnaast werd een biomarkers in de plateau manier gebruikt als een elektroforetische tussenlaag, wat de scheidingsresolutie tussen twee biomarkers in piek modus verbetert. Ten slotte hebben we het apparaat gekarakteriseerd met

humaan bloed serum, wat de toepasbaarheid laat zien van de methode voor het voorbereiden van monsters. In de toekomst verwachten we dat de fabricatie van het apparaat uit meer warmtegeleidende materialen (zoals silicium) in combinatie met actieve koeling zal resulteren in een significante verbetering van het debiet, waardoor FF-ICPF meer mogelijke toepassingen krijgt. **Appendix C** bevat aanvullende informatie over dit hoofdstuk.

Ondanks hun verdiensten zijn beide aanpakken genoemd in de hoofdstukken 4 en 5 gevoelig voor diffusie en menging na extractie. Een oplossing voor dit probleem kan een selectieve ‘verpakking’ en extractie van het geconcentreerde biomarker zijn. In **hoofdstuk 6** hebben we een druppelgenerator ontwikkeld die geschikt voor het combineren met elektrokinetische scheidingen, geschikt voor druppel-op-aanvraag of continue druppelvorming zonder het scheidingsproces te verstoren. We laten het ‘verpakken’ en het extraheren van sterk geconcentreerde (met een factor 100) druppels in ICPF zonder het scheidings- en concentratieproces te verstoren zien. In de toekomst willen we de zuiverheid van de geëxtraheerde druppels onderzoeken en een selectieve druppel extractie in een echt monster (humaan bloed serum) laten zien. **Appendix D** bevat aanvullende informatie over dit hoofdstuk.

Ondanks de kracht van ICPF zijn er naar onze huidige kennis niet veel commerciële producten die deze methode gebruiken. Momenteel worden in onderzoeken naar ICPF (inclusief dit proefschrift) fluorescente biomarkers gebruikt die worden geobserveerd met behulp van een microscoop. Deze aanpak vereist het labelen van de biomarkers met fluorescente markers en het gebruik van een grote microscoop die de toepasbaarheid van ICPF buiten een onderzoeksomgeving beperkt. In **hoofdstuk 7** hebben we onderzocht hoe de elektrische stroom die door het scheidingskanaal stroomt gerelateerd is aan de focuspositie in ICPF. De combinatie van stroommetingen in een kanaal met variërende dwarsdoorsnede kan worden gebruikt om de exacte focus locatie tijdens het scheidingsproces te voorspellen. In de toekomst zouden we graag een compleet geautomatiseerd ICPF proces laten zien door het meten en aanpassen van de stroom, wat het geschikt maakt voor de integratie in een POCT apparaat. Een apparaat als deze zou een significante vooruitgang betekenen in vergelijking met de huidige situatie waarin fluorescente biomarkers en optische detectie moeten worden gebruikt.

Ten slotte hebben we geprobeerd ons begrip van de fenomenen beschreven in hoofdstuk 7 te verdiepen, beschreven in **Appendix E**. We stellen voor dat de elektrische stroomreactie van een microkanaal kan worden beschreven door een convolutie tussen het geleidbaarheidsprofiel en de kanaaldoorsnede. Deze hypothese kan een breed toepassingsgebied vinden, van ICPF besturing tot het aanpassen van Coulter-tellers voor specifieke deeltjes vormen. Comsol modellering werd gebruikt om onze hypothese te bewijzen. In de toekomst willen we deze hypothese ook experimenteel bewijzen.

Funding and Contributions

Funding

The research work presented in this thesis was supported by the Horizon 2020 Framework Programme of the European Union under the project H2020-PHC-634013 (PHOCNOSIS) which was funded by the European Commission.

Contributions

The researched described in this thesis is a result of collaboration of several people. Specifically Prof. dr. Jan C. T. Eijkel and Prof. dr. Loes I. Segerink contributed in **all of the chapters** presented in the thesis both directly via reviewing the thesis and the published articles and indirectly via fruitful weekly discussions and supervision. Prof. dr. ir. Albert van den Berg provided input and critical evaluation on **chapter 2** and **chapter 3**.

Chapter 2 was based on a publication which was co-authored by dr. Miguel Solsona who undertaken the experimental work along with writing of a big part of the published article. In the same chapter and publication Prof. dr. ir. Wouter Olthuis provided a critical review.

Two students, Timon Daniels and Roelof van Zwol received their bachelor and masters diplomas, respectively, on their work on free flow ion concentration polarization focusing presented on **chapter 5**.

Kamilo Ijsper and Stella Kruit received their bachelor and masters diplomas, respectively, on their work on the droplet generator suitable ion concentration polarization focusing presented on **chapter 6**.

Finally I would like to acknowledge the contribution of all the Phocnosis consortium members who helped via regular meetings and discussions throughout the whole duration of this project.

Acknowledgements

Congratulations for making it to the last pages of my thesis! Along with you I would like to thank a not so few people that helped me those last 4 years.

First, I would like to thank **Wouter Olthuis** who was the first BIOS member I met 6 years ago when I started my master in the university of Twente and he was one of the reasons I decided to stay for PhD in the BIOS group.

The biggest acknowledgment must rightfully go to my promotor **Jan Eijkel**. I remember 4 years ago during our first meeting you had the project proposal in a single line of text, it was something like: "Separating and concentrating biomarkers 1000 times in 10 minutes from a droplet of blood sample". Now this line has turned into 200 pages thanks to you. I learned a lot from you. I greatly enjoyed the time we spent together, no matter if it was a weekly meeting talking about the project or 3 hours of driving through Germany for another Phocnosis meeting talking about history, religion and politics. Even when things were not going as planned or there was something wrong you were patient, polite and very discrete about it. Next I want to thank my co-promotor **Loes Segerink**. Despite that you joined a bit later, I was lucky to have a co-promotor that is pretty much the opposite/complementary to my promotor. With you two combined I had the perfect supervisor. Whenever our weekly meeting conversations with Jan was spiraling down to irrelevant topics you were there to pull us back up to the right track. Your directness, your clear view of the important things and your attention to detail made me a better writer and scientist in total.

I want to thank **Albert van den Berg** for making me feel a part of the BIOS family since the first days and for his very insightful comments during meetings and my Monday morning presentations.

I would like to thank **Mathieu Odijk** for the co-supervision of a master student. I always enjoyed our conversations (scientific or not) and I admire your engineering skills that's why you were my number one person to talk about my engineering problems.

I also want to thank **Hermine** for fulfilling all my request, from providing office supplies to booking meeting rooms and a vast amount flights. I want to thank **Paul ter Braak** for being a good friend and all his help in the lab and in ordering all kind of chemicals and stuff. I also would like to thank the other technical stuff for

their open door policy and their willingness to help, **Johan** for his cleanroom work for me and his advices, **Hans** for his chipholders fabrications and **Jan** (van Nieukastelle) for his help regarding my setup.

Next I would like the students that chose me and my topic as a graduation assignment: **Kamilo Ijspeert**, **Stella Kruit**, **Tim van Schagen**, **Timon Daniels**, **Roelof van Zwol**, **Ymke van Zwet**, and a bit of **Douwe de Bruijn**. I hope you enjoyed it and learned as much as I did during your supervision.

I would like to thank **Hai** and **Elsbeth** for accepting to be my paranymphs and our discussions/trips scientific or not.

I want to thank my officemates **Miguel** and **Juan** for making the office work a bit more tolerable and much more smiley.

I also want to thank our 4th officemate **Itzik Frankel**. I learned a lot during our meetings and I greatly appreciate your effort and work you put in. I also want to thank you for your advices during traveling to Israel.

I want to thank **Corentin** and **Josh** for our discussions about the scientific problems during our time together. And I want to thank all the BIOS members in no particular order: **Christina**, **Esther**, **Jasper**, **Jeroen**, **Jorien**, **Rob**, **Edo**, **Lanhui**, **Masha**, **Eiko**, **Alessia**, **Luca**, **Alessandro**, **Martijn**, **Tania**, **Anke**, **Hugo**, **Rubben**, **Helen**, **Nienke**, **Dodo**, **Tina**, **Lisette**, **Pascal**, **Wesley** and the ones that I forgot to mention! I also want to thank the no longer BIOS members: **Yawar**, **Steffan**, **Allison**, **Floris**, **Burcu** and **Aura**, **JB** and **Rene** for our fun times during lunch breaks, especially the Friday ones.

I want to thank the **committee members** for accepting my invitation, they found some time for my defense. I also want to thank all the **Phocnosis** consortium members for the fun and interesting times during our meetings.

I also want to thank some people outside the academic environment that helped me keep my sanity. Starting from the people in Netherlands I want to thank, **Rosemarijn**, **Vasilis**, **Konstantinos**, **Nikki**, **Dimitris Bairaktaris**, **Lotte** (and **Daphne**), **Dimitris Katsaros**, **Dimitris Karampelas**, **Dimitris Nikoloutsopoulos**, **Alexandra**, **Giannis**, **Sofia**, **Afroditi**, **Stergios**, **Ingrid**, **Katerina**, **Savva**, **Danai**, **Eleutheria**, **Elmer**, **Vangelis**, **Alexandros**, **Angela**, **Marta**, **Alina**, and **Giorgos**.

I also want to thank my friends from Greece first **Alexia**, **Vasilis**, **Dimitris** and **Panagiotis** from my hometown and the guys from my studies: **Stathis**, **Christos**, **Giorgos**, **Leles**, **Dimos**, **Bouzouka**, **Manos** and **Bountouris**, thank you all for your friendship over so many years.

Then I want to greatly thank my family which I will do in Greek. Θα ήθελα να ευχαριστώ την οικογένεια μου: Τους γονείς μου για την υποστήριξη τους, οικονομική και ψυχολογική και την εμπιστοσύνη τους σε κάθε μου επιλογή και σε κάθε βήμα όλης μου της ζωής. Τον αδερφό μου Γιάννη που μου «κουβαλήθηκε» στην Ολλανδία και είναι ο καλύτερος συγκάτοικος που θα μπορούσα να έχω. Τον αδερφό μου Ηλία που έμεινε στην Ελλάδα για να κουβαλήσει το βάρος τις οικογένειας. Επίσης θέλω να ευχαριστήσω και την ευρύτερη οικογένεια μου, γιαγιάδες, θείους, θείες και τα ξαδέρφια μου για την υποστήριξη τους. Σας αγαπάω όλους.

Last but definitely not least I would like to thank the latest addition to my important people list, my girlfriend **Annelotte**. Thank you for all the great times

we had and the ones we are going to have and especially thank you for your understanding and support for the times close to the end of the writing of my thesis.

I want to sincerely thank all of you once more (especially the ones I forgot to mention) for all your support!

Vasilis
Enschede, 2019